

SECTION 26 08 00

APPARATUS INSPECTION AND TESTING

08/08, CHG 1: 02/15

PART 1 GENERAL

1.1 REFERENCES

The publications listed below form a part of this specification to the extent referenced. The publications are referred to within the text by the basic designation only.

INTERNATIONAL ELECTRICAL TESTING ASSOCIATION (NETA)

NETA ATS (2017; Errata 2017) Standard for Acceptance Testing Specifications for Electrical Power Equipment and Systems

1.2 RELATED REQUIREMENTS

Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM applies to this section with additions and modifications specified herein.

1.3 SUBMITTALS

Government approval is required for submittals with a "G" or "S" classification. Submittals not having a "G" or "S" classification are for Contractor Quality Control approval. Submit the following in accordance with Section 01 33 00 SUBMITTAL PROCEDURES:

SD-06 Test Reports

Acceptance tests and inspections; G

SD-07 Certificates

Qualifications of organization, and lead engineering technician; G

Acceptance test and inspections procedure; G

1.4 QUALITY ASSURANCE

1.4.1 Qualifications

Contractor shall engage the services of a qualified testing organization to provide inspection, testing, calibration, and adjustment of the electrical distribution system and generation equipment listed in paragraph entitled "Acceptance Tests and Inspections" herein.

Organization shall be independent of the supplier, manufacturer, and installer of the equipment. The organization shall be a first tier subcontractor. No work required by this section of the specification shall be performed by a second tier subcontractor.

- a. Submit name and qualifications of organization. Organization shall have been regularly engaged in the testing of electrical materials, devices, installations, and systems for a minimum of 5 years. The organization shall have a calibration program, and test instruments

used shall be calibrated in accordance with **NETA ATS**.

- b. Submit name and qualifications of the lead engineering technician performing the required testing services. Include a list of three comparable jobs performed by the technician with specific names and telephone numbers for reference. Testing, inspection, calibration, and adjustments shall be performed by an engineering technician, certified by NETA or the National Institute for Certification in Engineering Technologies (NICET) with a minimum of 5 years' experience inspecting, testing, and calibrating electrical distribution and generation equipment, systems, and devices.

1.4.2 Acceptance Tests and Inspections Reports

Submit certified copies of inspection reports and test reports. Reports shall include certification of compliance with specified requirements, identify deficiencies, and recommend corrective action when appropriate. Type and neatly bind test reports to form a part of the final record. Submit test reports documenting the results of each test not more than 10 days after test is completed.

1.4.3 Acceptance Test and Inspections Procedure

Submit test procedure reports for each item of equipment to be field tested at least 45 days prior to planned testing date. Do not perform testing until after test procedure has been approved.

PART 2 PRODUCTS

Not used.

PART 3 EXECUTION

3.1 ACCEPTANCE TESTS AND INSPECTIONS

Testing organization shall perform acceptance tests and inspections. Test methods, procedures, and test values shall be performed and evaluated in accordance with **NETA ATS**, the manufacturer's recommendations, and paragraph entitled "Field Quality Control" of each applicable specification section. Tests identified as optional in **NETA ATS** are not required unless otherwise specified. Equipment shall be placed in service only after completion of required tests and evaluation of the test results have been completed. Contractor shall supply to the testing organization complete sets of shop drawings, settings of adjustable devices, and other information necessary for an accurate test and inspection of the system prior to the performance of any final testing. Contracting Officer shall be notified at least 14 days in advance of when tests will be conducted by the testing organization. Perform acceptance tests and inspections on applicable equipment and systems specified in the following sections:

- a. Section **26 32 15.00** ENGINE-GENERATOR SET STATIONARY 15-2500 KW, WITH AUXILIARIES. Functional engine shutdown tests, vibration base-line test, and load bank test shall not be performed by the testing organization. These tests shall be performed by the start-up engineer.
- b. Section **26 12 19.10** THREE-PHASE, LIQUID-FILLED PAD-MOUNTED TRANSFORMERS
- d. Section **33 71 01** OVERHEAD TRANSMISSION AND DISTRIBUTION

- e. Section 33 71 02 UNDERGROUND ELECTRICAL DISTRIBUTION. Medium voltage cables and grounding systems only.
- i. Section 26 36 23 AUTOMATIC TRANSFER SWITCHES AND BY-PASS/ISOLATION SWITCH
- k. Section 26 24 13 SWITCHBOARDS

3.2 SYSTEM ACCEPTANCE

Final acceptance of the system is contingent upon satisfactory completion of acceptance tests and inspections.

3.3 PLACING EQUIPMENT IN SERVICE

A representative of the approved testing organization shall be present when equipment tested by the organization is initially energized and placed in service.

-- End of Section --

SECTION 26 12 19.10

THREE-PHASE, LIQUID-FILLED PAD-MOUNTED TRANSFORMERS

05/19

PART 1 GENERAL

1.1 REFERENCES

The publications listed below form a part of this specification to the extent referenced. The publications are referred to within the text by the basic designation only.

ASTM INTERNATIONAL (ASTM)

- ASTM A240/A240M (2020) Standard Specification for Chromium and Chromium-Nickel Stainless Steel Plate, Sheet, and Strip for Pressure Vessels and for General Applications
- ASTM C260/C260M (2010a; R 2016) Standard Specification for Air-Entraining Admixtures for Concrete
- ASTM D92 (2012a) Standard Test Method for Flash and Fire Points by Cleveland Open Cup Tester
- ASTM D97 (2017b) Standard Test Method for Pour Point of Petroleum Products
- ASTM D877/D877M (2019) Standard Test Method for Dielectric Breakdown Voltage of Insulating Liquids Using Disk Electrodes
- ASTM D1535 (2014; R 2018) Standard Practice for Specifying Color by the Munsell System

FM GLOBAL (FM)

- FM APP GUIDE (updated on-line) Approval Guide
<http://www.approvalguide.com/>

INSTITUTE OF ELECTRICAL AND ELECTRONICS ENGINEERS (IEEE)

- IEEE 386 (2016) Separable Insulated Connector Systems for Power Distribution Systems Rated 2.5 kV through 35 kV
- IEEE C2 (2017; Errata 1-2 2017; INT 1 2017) National Electrical Safety Code
- IEEE C37.47 (2011) Standard for High Voltage Distribution Class Current-Limiting Type Fuses and Fuse Disconnecting Switches
- IEEE C57.12.00 (2015) General Requirements for Liquid-Immersed Distribution, Power, and Regulating Transformers

IEEE C57.12.28 (2014) Standard for Pad-Mounted Equipment - Enclosure Integrity

IEEE C57.12.34 (2015) Standard Requirements for Pad-Mounted, Compartmental-Type, Self-Cooled, Three-Phase Distribution Transformers, 10 MVA and Smaller; High Voltage, 34.5 kV Nominal System Voltage and Below; Low Voltage, 15 kV Nominal System Voltage and Below

IEEE C57.12.80 (2010) Standard Terminology for Power and Distribution Transformers

IEEE C57.12.90 (2015; Corr 2017) Test Code for Liquid-Immersed Distribution, Power, and Regulating Transformers

IEEE C57.98 (2011) Guide for Transformer Impulse Tests

IEEE C62.11 (2020) Standard for Metal-Oxide Surge Arresters for Alternating Current Power Circuits (>1kV)

IEEE Stds Dictionary (2009) IEEE Standards Dictionary: Glossary of Terms & Definitions

INTERNATIONAL ELECTRICAL TESTING ASSOCIATION (NETA)

NETA ATS (2017; Errata 2017) Standard for Acceptance Testing Specifications for Electrical Power Equipment and Systems

NATIONAL ELECTRICAL MANUFACTURERS ASSOCIATION (NEMA)

NEMA 260 (1996; R 2004) Safety Labels for Pad-Mounted Switchgear and Transformers Sited in Public Areas

NEMA Z535.4 (2011; R 2017) Product Safety Signs and Labels

NATIONAL FIRE PROTECTION ASSOCIATION (NFPA)

NFPA 70 (2020; ERTA 20-1 2020; ERTA 20-2 2020; TIA 20-1; TIA 20-2; TIA 20-3; TIA 20-4) National Electrical Code

ORGANISATION FOR ECONOMIC CO-OPERATION AND DEVELOPMENT (OECD)

OECD Test 203 (1992) Fish Acute Toxicity Test

U.S. ENVIRONMENTAL PROTECTION AGENCY (EPA)

EPA 712-C-98-075 (1998) Fate, Transport and Transformation Test Guidelines - OPPTS 835.3100- "Aerobic Aquatic Biodegradation"

EPA 821-R-02-012 (2002) Methods for Measuring the Acute

Toxicity of Effluents and Receiving Waters
to Freshwater and Marine Organisms

U.S. NATIONAL ARCHIVES AND RECORDS ADMINISTRATION (NARA)

10 CFR 431

Energy Efficiency Program for Certain
Commercial and Industrial Equipment

UNDERWRITERS LABORATORIES (UL)

UL 467

(2013; Reprint Jun 2017) UL Standard for
Safety Grounding and Bonding Equipment

1.2 RELATED REQUIREMENTS

Section 26 08 00 APPARATUS INSPECTION AND TESTING applies to this section,
with the additions and modifications specified herein.

1.3 DEFINITIONS

Unless otherwise specified or indicated, electrical and electronics terms
used in these specifications, and on the drawings, are as defined in
IEEE Stds Dictionary.

1.4 SUBMITTALS

Government approval is required for submittals with a "G" designation;
submittals not having a "G" designation are for Contractor Quality Control
approval. Submittals with an "S" are for inclusion in the Sustainability
eNotebook, in conformance with Section 01 33 29 SUSTAINABILITY REPORTING.
Submit the following in accordance with Section 01 33 00 SUBMITTAL
PROCEDURES:

SD-02 Shop Drawings

Pad-mounted Transformer Drawings; G

SD-03 Product Data

Pad-mounted Transformers; G

SD-06 Test Reports

Acceptance Checks and Tests; G

SD-07 Certificates

Transformer Efficiencies; G

SD-09 Manufacturer's Field Reports

Transformer Test Schedule; G

Pad-mounted Transformer Design Tests; G

Pad-mounted Transformer Routine and Other Tests; G

SD-10 Operation and Maintenance Data

Transformer(s), Data Package 5; G

1.4.1 Reduced Submittal Requirements

Transformers designed and manufactured by ABB in Jefferson City, MO; by Eaton's Cooper Power Series Transformers in Waukesha, WI; by ERMCO in Dyersburg, TN; or by Howard Industries in Laurel, MS need not submit the entire submittal package requirements of this contract. Instead, submit the following items:

- a. A certification, signed by the manufacturer, stating that the manufacturer will meet the technical requirements of this specification.
- b. An outline drawing of the transformer with devices identified (paragraph PAD-MOUNTED TRANSFORMER DRAWINGS, item a).
- c. ANSI nameplate data of the transformer (paragraph PAD-MOUNTED TRANSFORMER DRAWINGS, item b).
- d. Manufacturer's published time-current curves in PDF format and in electronic format suitable for import or updating into the EasyPower computer program of the transformer high side fuses (paragraph PAD-MOUNTED TRANSFORMER DRAWINGS, item e).
- e. Provide transformer test schedule and routine and other tests required by submittal item "SD-09 Manufacturer's Field Reports".
- f. Provide acceptance test reports required by submittal item "SD-06 Test Reports".
- g. Provide operation and maintenance manuals required by submittal item "SD-10 Operation and Maintenance Data".

1.5 QUALITY ASSURANCE

1.5.1 Pad-Mounted Transformer Drawings

Include the following as a minimum:

- a. An outline drawing, including front, top, and side views.
- b. IEEE nameplate data.
- c. Elementary diagrams and wiring diagrams.
- d. One-line diagram, including switch(es).
- e. Manufacturer's published time-current curves in PDF format and in electronic format suitable for import or updating into the EasyPower computer program of the transformer high side fuses.

1.5.2 Regulatory Requirements

In each of the publications referred to herein, consider the advisory provisions to be mandatory, except of [NFPA 70](#) when more stringent requirements are specified or indicated, as though the word "must" had been substituted for "should" wherever it appears. Interpret references in these publications to the "authority having jurisdiction," or words of

similar meaning, to mean the Contracting Officer. Provide equipment, materials, installation, and workmanship in accordance with NFPA 70 unless more stringent requirements are specified or indicated.

1.5.3 Standard Products

Provide materials and equipment that are products of manufacturers regularly engaged in the production of such products which are of equal material, design and workmanship, and:

- a. Have been in satisfactory commercial or industrial use for 2 years prior to bid opening including applications of equipment and materials under similar circumstances and of similar size.
- b. Have been on sale on the commercial market through advertisements, manufacturers' catalogs, or brochures during the 2-year period.
- c. Where two or more items of the same class of equipment are required, provide products of a single manufacturer; however, the component parts of the item need not be the products of the same manufacturer unless stated in this section.

1.5.3.1 Alternative Qualifications

Products having less than a 2-year field service record will be acceptable if a certified record of satisfactory field operation for not less than 6000 hours, exclusive of the manufacturers' factory or laboratory tests, is furnished.

1.5.3.2 Material and Equipment Manufacturing Date

Products manufactured more than 3 years prior to date of delivery to site are not acceptable.

1.6 MAINTENANCE

1.6.1 Additions to Operation and Maintenance Data

Submit operation and maintenance data in accordance with Section 01 78 23 OPERATION AND MAINTENANCE DATA and as specified herein. In addition to requirements of Data Package 5, include the following on the actual transformer(s) provided:

- a. An instruction manual with pertinent items and information highlighted
- b. An outline drawing, front, top, and side views
- c. Prices for spare parts and supply list
- d. Routine and field acceptance test reports
- e. Fuse curves for primary fuses
- g. Actual nameplate diagram
- h. Date of purchase

PART 2 PRODUCTS

2.1 PRODUCT COORDINATION

Products and materials not considered to be pad-mounted transformers and related accessories are specified in Section 33 71 01 OVERHEAD TRANSMISSION AND DISTRIBUTION, Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM, and Section 33 71 02 UNDERGROUND ELECTRICAL DISTRIBUTION.

2.2 THREE-PHASE PAD-MOUNTED TRANSFORMERS

IEEE C57.12.34, IEEE C57.12.28 and as specified herein. Submit manufacturer's information for each component, device, insulating fluid, and accessory provided with the transformer.

2.2.1 Compartments

Provide high- and low-voltage compartments separated by steel isolating barriers extending the full height and depth of the compartments. Compartment doors: hinged lift-off type with stop in open position and three-point latching.

2.2.1.1 High Voltage, Dead-Front

High-voltage compartment contains: the incoming line, insulated high-voltage load-break connectors, bushing well inserts, six high-voltage bushing wells configured for loop feed application, load-break switch handle(s), access to oil-immersed bayonet fuses, dead-front surge arresters, tap changer handle, connector parking stands with insulated standoff bushings, protective caps, and ground pad.

Minimum high-voltage compartment dimensions: IEEE C57.12.34, Figures 16 and 17.

- a. Insulated high-voltage load-break connectors: IEEE 386, rated 15 kV, 95 kV BIL. Current rating: 200 amperes rms continuous. Short time rating: 10,000 amperes rms symmetrical for a time duration of 0.17 seconds. Connector must have a steel reinforced hook-stick eye, grounding eye, test point, and arc-quenching contact material.

- c. Bushing well inserts: IEEE 386, 200 amperes, 15 kV Class. Provide a bushing well insert for each bushing well unless indicated otherwise.

- e. Load-break switch

Loop feed sectionalizer switches: Provide three, two-position, oil-immersed type switches to permit closed transition loop feed and sectionalizing. Each switch must be rated at 15 kV, 95 kV BIL, with a continuous current rating and load-break rating of 200 amperes, and a make-and-latch rating of 12,000 rms amperes symmetrical. Locate the switch handles in the high-voltage compartment. Operation of switches must be as follows:

ARRANGEMENT NO.	DESCRIPTION OF SWITCH ARRANGEMENT	SWITCH POSITION					
		LINE A SW.		LINE B SW		XFMR. SW	
		OPEN	CLOSE	OPEN	CLOSE	OPEN	CLOSE
1	Line A connected to Line B and both lines connected to transformer		X		X		X
2	Transformer connected to Line A only		X	X			X
3	Transformer connected to Line Bonly	X			X		X
4	Transformer open and loop closed		X		X	X	
5	Transformer open and loop open	X		X		X	

f. Provide bayonet oil-immersed, expulsion fuses in series with oil-immersed, partial-range, current-limiting fuses. The bayonet fuse links sense both high currents and high oil temperature in order to provide thermal protection to the transformer. Coordinate transformer protection with expulsion fuse clearing low-current faults and current-limiting fuse clearing high-current faults beyond the interrupting rating of the expulsion fuse. Include an oil retention valve inside the bayonet assembly housing, which closes when the fuse holder is removed, and an external drip shield to minimize oil spills. Display a warning label adjacent to the bayonet fuse(s) cautioning against removing or inserting fuses unless the transformer has been de-energized and the tank pressure has been released.

Bayonet fuse assembly: 150 kV BIL.

Oil-immersed current-limiting fuses: IEEE C37.47; 50,000 rms amperes symmetrical interrupting rating at the system voltage specified.

- g. Surge arresters: IEEE C62.11, rated 10 kV, fully shielded, dead-front, metal-oxide-varistor, elbow type with resistance-graded gap. Provide three arresters for loop feed circuits.
- h. Parking stands: Provide a parking stand near each bushing. Provide insulated standoff bushings for parking of energized high-voltage connectors on parking stands.
- i. Protective caps: IEEE 386, 200 amperes, 15 kV Class. Provide insulated protective caps (not shipping caps) for insulating and sealing out moisture from unused bushings.

2.2.1.2 Low Voltage

Low-voltage compartment contains: low-voltage bushings with NEMA spade

terminals, accessories, metering, stainless steel or laser-etched anodized aluminum diagrammatic transformer nameplate, and ground pad.

- a. Include the following accessories: drain valve with sampler device, fill plug, pressure relief device, liquid level gage, pressure-vacuum gage, and dial type thermometer with maximum temperature indicator.
- b. Metering: Provide as specified in Section 26 27 14.00 20 ELECTRICITY METERING.

2.2.2 Transformer

- a. Less-flammable liquid-insulated, two winding, 60 hertz, 65 degrees C rise above a 30 degrees C average ambient, self-cooled type.
- b. Transformer rated (as indicated in design documents) kVA.
- c. Transformer voltage ratings: 12470 V Delta - 480Y/277 V or 208Y/120 V, as indicated on the plans.
- d. Tap changer: externally operated, manual type for changing tap setting when the transformer is de-energized. Provide four 2.5 percent full capacity taps, two above and two below rated primary voltage. Indicate which tap setting is in use, clearly visible when the compartment is opened.
- e. Minimum tested percent impedance at 85 degrees C:
 - 2.50 for units rated 75kVA and below
 - 2.87 for units rated 112.5kVA to 300kVA
 - 4.03 for 500kVA rated units
 - 5.32 for units rated 750kVA and above
- f. Comply with the following audible sound level limits:

kVA	DECIBELS (MAX)
75	51
112.5	55
150	55
225	55
300	55
500	56
750	57
1000	58
1500	60

2000	61
2500	62

g. Include:

- (1) Lifting lugs and provisions for jacking under base, with base construction suitable for using rollers or skidding in any direction.
- (2) An insulated low-voltage neutral bushing with NEMA spade terminal, and with removable ground strap.
- (3) Provide transformer top with an access handhole.
- (4) kVA rating conspicuously displayed using 3 inch high yellow letters on its enclosure.

2.2.2.1 Specified **Transformer Efficiencies**

Provide transformer efficiency calculations utilizing the actual no-load and load loss values obtained during the routine tests performed on the actual transformer(s) prepared for this project. Reference no-load losses (NLL) at 20 degrees C. Reference load losses (LL) at 55 degrees C and at 50 percent of the nameplate load. The transformer is not acceptable if the calculated transformer efficiency is less than the efficiency indicated in the "KVA / Efficiency" table below. The table is based on requirements contained within 10 CFR 431, Subpart K. Submit certification, including supporting calculations, from the manufacturer indicating conformance.

<u>kVA</u>	<u>EFFICIENCY</u> <u>(percent)</u>
15	98.65
30	98.83
45	98.92
75	99.03
112.5	99.11
150	99.16
225	99.23
300	99.27
500	99.35
750	99.40

1000	99.43
1500	99.48
2000	99.51
2500	99.53
above 2500	99.54

2.2.3 Insulating Liquid

- a. Less-flammable transformer liquids: [NFPA 70](#) and [FM APP GUIDE](#) for less-flammable liquids having a fire point not less than 300 degrees C tested per [ASTM D92](#) and a dielectric strength not less than 33 kV tested per [ASTM D877/D877M](#). Provide identification of transformer as "non-PCB" and "manufacturer's name and type of fluid" on the nameplate.

Provide a fluid that is a biodegradable, electrical insulating, and cooling liquid classified by UL and approved by FM as "less flammable" with the following properties:

- (1) Pour point: [ASTM D97](#), less than -15 degree C
- (2) Aquatic biodegradation: [EPA 712-C-98-075](#), ultimately biodegradable as designated by EPA.
- (3) Trout toxicity: [OECD Test 203](#), zero mortality of [EPA 821-R-02-012](#), pass

2.2.3.1 Liquid-Filled Transformer Nameplates

Provide nameplate information in accordance with [IEEE C57.12.00](#) and as modified or supplemented by this section.

2.2.4 Corrosion Protection

Provide entire transformer assembly, including tank and radiator, base, enclosure, and metering enclosure fabricated of stainless steel conforming to [ASTM A240/A240M](#), Type 304 or 304L. Form enclosure of stainless steel sheets. The optional use of aluminum is permitted for the metering enclosure.

Paint entire transformer assembly Munsell 7GY3.29/1.5 green, with paint coating system complying with [IEEE C57.12.28](#) regardless of base, cabinet, and tank material. The Munsell color notation is specified in [ASTM D1535](#).

2.3 WARNING SIGNS AND LABELS

Provide warning signs for the enclosures of pad-mounted transformers having a nominal rating exceeding 600 volts in accordance with [NEMA Z535.4](#) and [NEMA 260](#).

- a. When the enclosure integrity of such equipment is specified to be in accordance with [IEEE C57.12.28](#), such as for pad-mounted transformers, provide self-adhesive warning labels on the outside of the high voltage compartment door(s) with nominal dimensions of 7 by 10 inches with the legend "WARNING HIGH VOLTAGE" printed in two lines of nominal

2 inch high letters. Include the work "WARNING" in white letters on an orange background and the words "HIGH VOLTAGE" in black letters on a white background.

- b. When such equipment is guarded by a fence, mount signs on the fence. Provide metal signs having nominal dimensions of 14 by 10 inches with the legend "WARNING HIGH VOLTAGE KEEP OUT" printed in three lines of nominal 3 inch high white letters on an orange and black field.

2.4 ARC FLASH WARNING LABEL

Provide arc flash warning label for the enclosure of pad-mounted transformers. Locate this self-adhesive warning label on the outside of the high voltage compartment door warning of potential electrical arc flash hazards and appropriate PPE required. Provide label format as indicated.

2.5 GROUNDING AND BONDING

UL 467. Provide grounding and bonding as specified in Section 33 71 02 UNDERGROUND ELECTRICAL DISTRIBUTION.

2.6 PADLOCKS

Provide padlocks for pad-mounted equipment and for each fence gate, keyed as directed by the Contracting Officer. Comply with Section 08 71 00 DOOR HARDWARE.

2.7 CAST-IN-PLACE CONCRETE

Provide concrete associated with electrical work for other than encasement of underground ducts rated for 4000 psi minimum 28-day compressive strength unless specified otherwise. Conform to the requirements of Section 03 30 00 CAST-IN-PLACE CONCRETE.

Provide concrete associated with electrical work as follows:

- a. Composed of fine aggregate, coarse aggregate, portland cement, and water so proportioned and mixed as to produce a plastic, workable mixture.
- b. Fine aggregate: hard, dense, durable, clean, and uncoated sand.
- c. Coarse aggregate: reasonably well graded from 3/16 inch to 1 inch.
- d. Fine and coarse aggregates: free from injurious amounts of dirt, vegetable matter, soft fragments or other deleterious substances.
- e. Water: fresh, clean, and free from salts, alkali, organic matter, and other impurities.
- f. Concrete associated with electrical work for other than encasement of underground ducts: 4000 psi minimum 28-day compressive strength unless specified otherwise.
- g. Slump: Less than 4 inches. Retempering of concrete will not be permitted.
- h. Exposed, unformed concrete surfaces: smooth, wood float finish.

- i. Concrete must be cured for a period of not less than 7 days, and concrete made with high early strength portland cement must be repaired by patching honeycombed or otherwise defective areas with cement mortar as directed by the Contracting Officer.
- j. Air entrain concrete exposed to weather using an air-entraining admixture conforming to **ASTM C260/C260M**.
- k. Air content: between 4 and 6 percent.

2.8 SOURCE QUALITY CONTROL

2.8.1 Transformer Test Schedule

The Government reserves the right to witness tests. Provide transformer test schedule for tests to be performed at the manufacturer's test facility. Submit required test schedule and location, and notify the Contracting Officer 30 calendar days before scheduled test date. Notify Contracting Officer 15 calendar days in advance of changes to scheduled date.

a. Test Instrument Calibration

- (1) Provide a calibration program which assures that all applicable test instruments are maintained within rated accuracy.
- (2) Accuracy: Traceable to the National Institute of Standards and Technology.
- (3) Instrument calibration frequency schedule: less than or equal to 12 months for both test floor instruments and leased specialty equipment.
- (4) Dated calibration labels: visible on all test equipment.
- (5) Calibrating standard: higher accuracy than that of the instrument tested.
- (6) Keep up-to-date records that indicate dates and test results of instruments calibrated or tested. For instruments calibrated by the manufacturer on a routine basis, in lieu of third party calibration, include the following:
 - (a) Maintain up-to-date instrument calibration instructions and procedures for each test instrument.
 - (b) Identify the third party/laboratory calibrated instrument to verify that calibrating standard is met.

2.8.2 Design Tests

IEEE C57.12.00, and **IEEE C57.12.90**. Section 5.1.2 in **IEEE C57.12.80** states that "design tests are made only on representative apparatus of basically the same design." Submit design test reports (complete with test data, explanations, formulas, and results), in the same submittal package as the catalog data and drawings for the specified transformer(s), with design tests performed prior to the award of this contract.

- a. Tests: certified and signed by a registered professional engineer.
- b. Temperature rise: "Basically the same design" for the temperature rise test means a pad-mounted transformer with the same coil construction (such as wire wound primary and sheet wound secondary), the same kVA, the same cooling type (KNAN), the same temperature rise rating, and the same insulating liquid as the transformer specified.
- c. Lightning impulse: "Basically the same design" for the lightning impulse dielectric test means a pad-mounted transformer with the same BIL, the same coil construction (such as wire wound primary and sheet wound secondary), and a tap changer, if specified. Design lightning impulse tests includes the primary windings only of that transformer.
 - (1) IEEE C57.12.90, paragraph 10.3 entitled "Lightning Impulse Test Procedures," and IEEE C57.98.
 - (2) State test voltage levels.
 - (3) Provide photographs of oscilloscope display waveforms or plots of digitized waveforms with test report.
- d. Lifting and moving devices: "Basically the same design" requirement for the lifting and moving devices test means a test report confirming that the lifting device being used is capable of handling the weight of the specified transformer in accordance with IEEE C57.12.34.
- e. Pressure: "Basically the same design" for the pressure test means a pad-mounted transformer with a tank volume within 30 percent of the tank volume of the transformer specified.
- f. Short circuit: "Basically the same design" for the short circuit test means a pad-mounted transformer with the same kVA as the transformer specified.

2.8.3 Routine and Other Tests

IEEE C57.12.00. Routine and other tests: performed in accordance with IEEE C57.12.90 by the manufacturer on the actual transformer(s) prepared for this project to ensure that the design performance is maintained in production. Submit test reports, by serial number and receive approval before delivery of equipment to the project site. Required tests and testing sequence as follows:

- a. Phase relation
- b. Ratio
- c. No-load losses (NLL) and excitation current
- d. Load losses (LL) and impedance voltage
- e. Dielectric
 - (1) Impulse
 - (2) Applied voltage
 - (3) Induced voltage

f. Leak

PART 3 EXECUTION

3.1 INSTALLATION

Conform to IEEE C2, NFPA 70, and to the requirements specified herein. Provide new equipment and materials unless indicated or specified otherwise.

3.2 GROUNDING

NFPA 70 and IEEE C2, except provide grounding systems with a resistance to solid earth ground not exceeding 5 ohms.

3.2.1 Grounding Electrodes

Provide driven ground rods as specified in Section 33 71 02 UNDERGROUND ELECTRICAL DISTRIBUTION. Connect ground conductors to the upper end of ground rods by exothermic weld or compression connector. Provide compression connectors at equipment end of ground conductors.

3.2.2 Pad-Mounted Transformer Grounding

Provide a ground ring around the transformer with 4/0 AWG bare copper. Provide four ground rods in the ground ring, one per corner. Install the ground rods at least 10 feet apart from each other. Provide separate copper grounding conductors and connect them to the ground loop as indicated. When work in addition to that indicated or specified is required to obtain the specified ground resistance, the provision of the contract covering "Changes" applies.

3.2.3 Connections

Make joints in grounding conductors and loops by exothermic weld or compression connector. Install exothermic welds and compression connectors as specified in Section 33 71 02 UNDERGROUND ELECTRICAL DISTRIBUTION.

3.2.4 Grounding and Bonding Equipment

UL 467, except as indicated or specified otherwise.

3.3 INSTALLATION OF EQUIPMENT AND ASSEMBLIES

Install and connect pad-mounted transformers furnished under this section as indicated on project drawings, the approved shop drawings, and as specified herein.

3.4 FIELD APPLIED PAINTING

Where field painting of enclosures is required to correct damage to the manufacturer's factory applied coatings, provide manufacturer's recommended coatings and apply in accordance with manufacturer's instructions.

3.5 WARNING SIGN MOUNTING

Provide the number of signs required to be readable from each accessible side, but space the signs a maximum of 30 feet apart.

3.6 FOUNDATION FOR EQUIPMENT AND ASSEMBLIES

Mount transformer on prefabricated concrete support as indicated on the drawings as follows:

- a. Place prefabricated concrete support on a 6 inch thick, well-compacted gravel base.
- b. Install prefabricated concrete support such that top of support is approximately 12 inches above the finished grade with gradual slope for drainage.
- c. Provide support of adequate size to project at least 8 inches beyond the equipment.

Stub up conduits, with bushings, 2 inches into cable wells in the prefabricated concrete support. Coordinate dimensions of cable wells with transformer cable training areas.

3.6.1 Cast-In-Place Concrete

Provide cast-in-place concrete work in accordance with the requirements of Section 03 30 00 CAST-IN-PLACE CONCRETE.

3.6.2 Sealing

When the installation is complete, seal all entries into the equipment enclosure with an approved sealing method. Provide seals of sufficient strength and durability to protect all energized live parts of the equipment from rodents, insects, or other foreign matter.

3.7 FIELD QUALITY CONTROL

3.7.1 Performance of Acceptance Checks and Tests

Perform in accordance with the manufacturer's recommendations and include the following visual and mechanical inspections and electrical tests, performed in accordance with NETA ATS. Submit reports, including acceptance criteria and limits for each test in accordance with NETA ATS "Test Values".

3.7.1.1 Pad-Mounted Transformers

- a. Visual and mechanical inspection
 - (1) Compare equipment nameplate data with specifications and approved shop drawings.
 - (2) Inspect physical and mechanical condition. Check for damaged or cracked insulators and leaks.
 - (3) Inspect anchorage, alignment, and grounding.
 - (4) Verify the presence of PCB content labeling.

- (5) Verify the bushings and transformer interiors are clean.
- (6) Inspect all bolted electrical connections for high resistance using low-resistance ohmmeter, verifying tightness of accessible bolted electrical connections by calibrated torque-wrench method, or performing thermographic survey.
- (7) Verify correct liquid level in tanks and bushings.
- (8) Verify that positive pressure is maintained on gas-blanketed transformers.
- (9) Perform specific inspections and mechanical tests as recommended by manufacturer.
- (10) Verify de-energized tap changer position is left as specified.
- (11) Verify the presence of transformer surge arresters.

b. Electrical tests

- (1) Perform resistance measurements through all bolted connections with low-resistance ohmmeter.
- (2) Verify proper secondary voltage phase-to-phase and phase-to-neutral after energization and prior to loading.

3.7.1.2 Grounding System

a. Visual and mechanical inspection

- (1) Inspect ground system for compliance with contract plans and specifications.

b. Electrical tests

- (1) Perform ground-impedance measurements utilizing the fall-of-potential method. On systems consisting of interconnected ground rods, perform tests after interconnections are complete. On systems consisting of a single ground rod perform tests before any wire is connected. Take measurements in normally dry weather, not less than 48 hours after rainfall. Use a portable ground resistance tester in accordance with manufacturer's instructions to test each ground or group of grounds. Use an instrument equipped with a meter reading directly in ohms or fractions thereof to indicate the ground value of the ground rod or grounding systems under test.
- (2) Submit the measured ground resistance of each ground rod and grounding system, indicating the location of the rod and grounding system. Include the test method and test setup (i.e., pin location) used to determine ground resistance and soil conditions at the time the measurements were made.

3.7.1.3 Surge Arresters, Medium- and High-Voltage

a. Visual and mechanical inspection

- (1) Compare equipment nameplate data with specifications and approved shop drawings.
- (2) Inspect physical and mechanical condition.
- (3) Inspect anchorage, alignment, grounding, and clearances.
- (4) Verify the arresters are clean.
- (5) Inspect all bolted electrical connections for high resistance using low-resistance ohmmeter, verifying tightness of accessible bolted electrical connections by calibrated torque-wrench method, or performing thermographic survey.
- (6) Verify that the ground lead on each device is individually attached to a ground bus or ground electrode.

b. Electrical tests

- (1) Perform resistance measurements through all bolted connections with low-resistance ohmmeter, if applicable.
- (2) Perform an insulation-resistance test on each arrester, phase terminal-to-ground.
- (3) Test grounding connection.

3.7.2 Follow-Up Verification

Upon completion of acceptance checks and tests, show by demonstration in service that circuits and devices are in good operating condition and properly performing the intended function. As an exception to requirements stated elsewhere in the contract, notify the Contracting Officer 5 working days in advance of the dates and times of checking and testing.

-- End of Section --

SECTION 26 20 00

INTERIOR DISTRIBUTION SYSTEM

08/19

PART 1 GENERAL

1.1 REFERENCES

The publications listed below form a part of this specification to the extent referenced. The publications are referred to within the text by the basic designation only.

ASTM INTERNATIONAL (ASTM)

- ASTM B1 (2013) Standard Specification for Hard-Drawn Copper Wire
- ASTM B8 (2011; R 2017) Standard Specification for Concentric-Lay-Stranded Copper Conductors, Hard, Medium-Hard, or Soft
- ASTM D709 (2017) Standard Specification for Laminated Thermosetting Materials

INSTITUTE OF ELECTRICAL AND ELECTRONICS ENGINEERS (IEEE)

- IEEE 81 (2012) Guide for Measuring Earth Resistivity, Ground Impedance, and Earth Surface Potentials of a Ground System
- IEEE 100 (2000; Archived) The Authoritative Dictionary of IEEE Standards Terms
- IEEE C2 (2017; Errata 1-2 2017; INT 1 2017) National Electrical Safety Code

INTERNATIONAL ELECTRICAL TESTING ASSOCIATION (NETA)

- NETA ATS (2017; Errata 2017) Standard for Acceptance Testing Specifications for Electrical Power Equipment and Systems

NATIONAL ELECTRICAL MANUFACTURERS ASSOCIATION (NEMA)

- ANSI C80.1 (2005) American National Standard for Electrical Rigid Steel Conduit (ERSC)
- ANSI C80.3 (2015) American National Standard for Electrical Metallic Tubing (EMT)
- ANSI C80.5 (2015) American National Standard for Electrical Rigid Aluminum Conduit
- NEMA 250 (2018) Enclosures for Electrical Equipment (1000 Volts Maximum)
- NEMA FU 1 (2012) Low Voltage Cartridge Fuses

NEMA ICS 1 (2000; R 2015) Standard for Industrial Control and Systems: General Requirements

NEMA ICS 2 (2000; R 2005; Errata 2008) Industrial Control and Systems Controllers, Contactors, and Overload Relays Rated 600 V

NEMA ICS 4 (2015) Application Guideline for Terminal Blocks

NEMA ICS 6 (1993; R 2016) Industrial Control and Systems: Enclosures

NEMA KS 1 (2013) Enclosed and Miscellaneous Distribution Equipment Switches (600 V Maximum)

NEMA MG 1 (2018) Motors and Generators

NEMA MG 10 (2017) Energy Management Guide for Selection and Use of Fixed Frequency Medium AC Squirrel-Cage Polyphase Induction Motors

NEMA MG 11 (1977; R 2012) Energy Management Guide for Selection and Use of Single Phase Motors

NEMA RN 1 (2005; R 2013) Polyvinyl-Chloride (PVC) Externally Coated Galvanized Rigid Steel Conduit and Intermediate Metal Conduit

NEMA ST 20 (2014) Dry-Type Transformers for General Applications

NEMA TC 2 (2020) Standard for Electrical Polyvinyl Chloride (PVC) Conduit

NEMA TC 3 (2016) Polyvinyl Chloride (PVC) Fittings for Use With Rigid PVC Conduit and Tubing

NEMA VE 1 (2017) Metal Cable Tray Systems

NEMA WD 1 (1999; R 2015) Standard for General Color Requirements for Wiring Devices

NEMA WD 6 (2016) Wiring Devices Dimensions Specifications

NEMA Z535.4 (2011; R 2017) Product Safety Signs and Labels

NATIONAL FIRE PROTECTION ASSOCIATION (NFPA)

NFPA 70 (2020; ERTA 20-1 2020; ERTA 20-2 2020; TIA 20-1; TIA 20-2; TIA 20-3; TIA 20-4) National Electrical Code

NFPA 70E (2021) Standard for Electrical Safety in

the Workplace

NFPA 780 (2017) Standard for the Installation of Lightning Protection Systems

TELECOMMUNICATIONS INDUSTRY ASSOCIATION (TIA)

TIA-568-C.1 (2009; Add 2 2011; Add 1 2012) Commercial Building Telecommunications Cabling Standard

TIA-569 (2015d) Commercial Building Standard for Telecommunications Pathways and Spaces

TIA-607 (2015c; Addendum 1 2017) Generic Telecommunications Bonding and Grounding (Earthing) for Customer Premises

U.S. NATIONAL ARCHIVES AND RECORDS ADMINISTRATION (NARA)

10 CFR 431 Energy Efficiency Program for Certain Commercial and Industrial Equipment

29 CFR 1910.147 The Control of Hazardous Energy (Lock Out/Tag Out)

29 CFR 1910.303 Electrical, General

UNDERWRITERS LABORATORIES (UL)

UL 1 (2005; Reprint Jan 2020) UL Standard for Safety Flexible Metal Conduit

UL 5 (2016; Reprint Aug 2020) UL Standard for Safety Surface Metal Raceways and Fittings

UL 5A (2015; Reprint Aug 2020) Nonmetallic Surface Raceways and Fittings

UL 6 (2007; Reprint Sep 2019) UL Standard for Safety Electrical Rigid Metal Conduit-Steel

UL 6A (2008; Reprint Sep 2019) UL Standard for Safety Electrical Rigid Metal Conduit - Aluminum, Red Brass, and Stainless Steel

UL 20 (2010; Reprint Feb 2012) General-Use Snap Switches

UL 44 (2018) UL Standard for Safety Thermoset-Insulated Wires and Cables

UL 50 (2015) UL Standard for Safety Enclosures for Electrical Equipment, Non-Environmental Considerations

UL 67 (2018; Reprint Jul 2020) UL Standard for Safety Panelboards

- UL 83 (2017; Reprint Mar 2020) UL Standard for Safety Thermoplastic-Insulated Wires and Cables
- UL 198M (2018) UL Standard for Mine-Duty Fuses
- UL 360 (2013; Reprint Nov 2018) UL Standard for Safety Liquid-Tight Flexible Metal Conduit
- UL 467 (2013; Reprint Jun 2017) UL Standard for Safety Grounding and Bonding Equipment
- UL 486A-486B (2018) UL Standard for Safety Wire Connectors
- UL 486C (2019) UL Standard for Safety Splicing Wire Connectors
- UL 489 (2016) UL Standard for Safety Molded-Case Circuit Breakers, Molded-Case Switches and Circuit-Breaker Enclosures
- UL 498 (2017; Reprint Aug 2020) UL Standard for Safety Attachment Plugs and Receptacles
- UL 506 (2017) UL Standard for Safety Specialty Transformers
- UL 508 (2018) UL Standard for Safety Industrial Control Equipment
- UL 510 (2020) UL Standard for Safety Polyvinyl Chloride, Polyethylene and Rubber Insulating Tape
- UL 514A (2013; Reprint Aug 2017) UL Standard for Safety Metallic Outlet Boxes
- UL 514B (2012; Reprint May 2020) Conduit, Tubing and Cable Fittings
- UL 514C (2014; Reprint Feb 2020) UL Standard for Safety Nonmetallic Outlet Boxes, Flush-Device Boxes, and Covers
- UL 651 (2011; Reprint Mar 2020) UL Standard for Safety Schedule 40, 80, Type EB and A Rigid PVC Conduit and Fittings
- UL 674 (2011; Reprint Nov 2018) UL Standard for Safety Electric Motors and Generators for Use in Hazardous (Classified) Locations
- UL 797 (2007; Reprint Mar 2017) UL Standard for Safety Electrical Metallic Tubing -- Steel
- UL 869A (2006; Reprint Jun 2020) Reference Standard for Service Equipment

- UL 943 (2016; Reprint Feb 2018) UL Standard for Safety Ground-Fault Circuit-Interrupters
- UL 984 (1996; Reprint Sep 2005) Hermetic Refrigerant Motor-Compressors
- UL 1063 (2017) UL Standard for Safety Machine-Tool Wires and Cables
- UL 1203 (2013; Reprint Jan 2020) UL Standard for Safety Explosion-Proof and Dust-Ignition-Proof Electrical Equipment for Use in Hazardous (Classified) Locations
- UL 1242 (2006; Reprint Aug 2020) Standard for Electrical Intermediate Metal Conduit -- Steel
- UL 1449 (2014; Reprint Jul 2017) UL Standard for Safety Surge Protective Devices
- UL 1561 (2011; Reprint Jun 2015) Dry-Type General Purpose and Power Transformers
- UL 1660 (2019) Liquid-Tight Flexible Nonmetallic Conduit
- UL 1699 (2017) UL Standard for Safety Arc-Fault Circuit-Interrupters
- UL 4248-1 (2017) UL Standard for Safety Fuseholders - Part 1: General Requirements
- UL 4248-12 (2018) UL Standard for Safety Fuseholders - Part 12: Class R

1.2 DEFINITIONS

Unless otherwise specified or indicated, electrical and electronics terms used in these specifications, and on the drawings, are as defined in IEEE 100.

1.3 SUBMITTALS

Government approval is required for submittals with a "G" designation; submittals not having a "G" designation are for Contractor Quality Control approval. Submittals with an "S" are for inclusion in the Sustainability eNotebook, in conformance with Section 01 33 29 SUSTAINABILITY REPORTING. Submit the following in accordance with Section 01 33 00 SUBMITTAL PROCEDURES:

SD-02 Shop Drawings

Panelboards; G

Transformers; G

Cable Trays; G

Modular Power Distribution System; G

Marking Strips Drawings; G

SD-03 Product Data

Receptacles; G

Circuit Breakers; G

Switches; G

Transformers; G

Enclosed Circuit Breakers; G

Motor Controllers; G

Manual Motor Starters; G

CATV Outlets; G

Telecommunications Grounding Busbar; G

Surge Protective Devices; G

SD-06 Test Reports

600-volt Wiring Test; G

Grounding System Test; G

Transformer Tests; G

Ground-fault Receptacle Test; G

SD-07 Certificates

Fuses; G

SD-09 Manufacturer's Field Reports

Transformer Factory Tests

SD-10 Operation and Maintenance Data

Electrical Systems, Data Package 5; G

1.4 QUALITY ASSURANCE

1.4.1 Fuses

Submit coordination data as specified in paragraph, FUSES of this section.

1.4.2 Regulatory Requirements

In each of the publications referred to herein, consider the advisory provisions to be mandatory, as though the word, "shall" or "must" had been substituted for "should" wherever it appears. Interpret references in these publications to the "authority having jurisdiction," or words of similar meaning, to mean the Contracting Officer. Provide equipment, materials, installation, and workmanship in accordance with NFPA 70 unless more stringent requirements are specified or indicated.

1.4.3 Standard Products

Provide materials and equipment that are products of manufacturers regularly engaged in the production of such products which are of equal material, design and workmanship and:

- a. Have been in satisfactory commercial or industrial use for 2 years prior to bid opening including applications of equipment and materials under similar circumstances and of similar size.
- b. Have been on sale on the commercial market through advertisements, manufacturers' catalogs, or brochures during the 2-year period.
- c. Where two or more items of the same class of equipment are required, provide products of a single manufacturer; however, the component parts of the item need not be the products of the same manufacturer unless stated in this section.

1.4.3.1 Alternative Qualifications

Products having less than a 2-year field service record will be acceptable if a certified record of satisfactory field operation for not less than 6000 hours, exclusive of the manufacturers' factory or laboratory tests, is furnished.

1.4.3.2 Material and Equipment Manufacturing Date

Products manufactured more than 3 years prior to date of delivery to site are not acceptable.

1.5 MAINTENANCE

1.6 WARRANTY

Provide equipment items supported by service organizations that are reasonably convenient to the equipment installation in order to render satisfactory service to the equipment on a regular and emergency basis during the warranty period of the contract.

PART 2 PRODUCTS

2.1 MATERIALS AND EQUIPMENT

As a minimum, meet requirements of UL, where UL standards are established for those items, and requirements of NFPA 70 for all materials, equipment, and devices.

2.2 CONDUIT AND FITTINGS

Conform to the following:

2.2.1 Rigid Metallic Conduit

2.2.1.1 Rigid, Threaded Zinc-Coated Steel Conduit

ANSI C80.1, UL 6.

2.2.1.2 Rigid Aluminum Conduit

ANSI C80.5, UL 6A.

2.2.2 Rigid Nonmetallic Conduit

PVC Type EPC-40 in accordance with NEMA TC 2, UL 651.

2.2.3 Intermediate Metal Conduit (IMC)

UL 1242, zinc-coated steel only.

2.2.4 Electrical, Zinc-Coated Steel Metallic Tubing (EMT)

UL 797, ANSI C80.3.

2.2.5 Plastic-Coated Rigid Steel and IMC Conduit

NEMA RN 1, Type 40 (40 mils thick).

2.2.6 Flexible Metal Conduit

UL 1.

2.2.6.1 Liquid-Tight Flexible Metal Conduit, Steel

UL 360.

2.2.7 Fittings for Metal Conduit, EMT, and Flexible Metal Conduit

UL 514B. Ferrous fittings: cadmium- or zinc-coated in accordance with UL 514B.

2.2.7.1 Fittings for Rigid Metal Conduit and IMC

Threaded-type. Split couplings unacceptable.

2.2.7.2 Fittings for EMT

Steel compression type.

2.2.8 Fittings for Rigid Nonmetallic Conduit

NEMA TC 3 for PVC, and UL 514B.

2.2.9 Liquid-Tight Flexible Nonmetallic Conduit

UL 1660.

2.3 SURFACE RACEWAY

2.3.1 Surface Metal Raceway

UL 5, two-piece painted steel, totally enclosed, snap-cover type. Provide multiple outlet-type raceway with grounding-type receptacle where indicated. Provide receptacles as specified herein, spaced a minimum of one every **18 inches**. Wire alternate receptacles on different circuits.

2.3.2 Surface Nonmetallic Raceway

UL 5A, nonmetallic totally enclosed, snap-cover type. Provide multiple outlet-type raceway with grounding-type receptacle where indicated. Provide receptacles as specified herein, spaced a minimum of one every **18 inches**. Wire alternate receptacles on different circuits.

2.4 CABLE TRAYS

NEMA VE 1. Provide the following:

- a. Cable trays: form a wireway system, with a nominal **4 inch** depth as indicated.
- b. Cable trays: constructed of steel that has been zinc-coated after fabrication.
- c. Cable trays: include splice and end plates, dropouts, and miscellaneous hardware.
- d. Edges, fittings, and hardware: finished free from burrs and sharp edges.
- e. Fittings: ensure not less than load-carrying ability of straight tray sections and have manufacturer's minimum standard radius.
- f. Radius of bends: as indicated.

2.4.1 Basket-Type Cable Trays

Provide of nominal **18, inch** width and **4 inch** depth with maximum wire mesh spacing of **2 by 4 inch**.

2.5 OUTLET BOXES AND COVERS

UL 514A, cadmium- or zinc-coated, if ferrous metal. **UL 514C**, if nonmetallic.

2.5.1 Floor Outlet Boxes

Provide the following:

- a. Boxes: nonadjustable and concrete tight.
- b. Each outlet: consisting of cast-metal body with threaded openings, for conduits, brass flange ring, and cover plate with **1 1/4 inch** threaded plug.
- c. Telecommunications outlets: consisting of flush, aluminum or stainless steel housing with a receptacle as specified and **3/4 inch**

top opening.

- d. Receptacle outlets: consisting of flush aluminum or stainless steel housing with duplex-type receptacle as specified herein.
- e. Provide gaskets where necessary to ensure watertight installation.

2.5.2 Outlet Boxes for Telecommunications System

Provide the following:

- a. Standard type 4 11/16 inches square by 2 1/8 inches deep.
- b. Outlet boxes for wall-mounted telecommunications outlets: 4 by 2 1/8 by 2 1/8 inches deep.
- c. Depth of boxes: large enough to allow manufacturers' recommended conductor bend radii.
- d. Outlet boxes for fiber optic telecommunication outlets: include a minimum 3/8 inch deep single or two gang plaster ring as shown and installed using a minimum one inch conduit system.

2.6 CABINETS, JUNCTION BOXES, AND PULL BOXES

UL 50; volume greater than 100 cubic inches, NEMA Type 1 enclosure; sheet steel, hot-dip, zinc-coated. Where exposed to wet, damp, or corrosive environments, NEMA Type 4X.

2.7 WIRES AND CABLES

Provide wires and cables in accordance applicable requirements of NFPA 70 and UL for type of insulation, jacket, and conductor specified or indicated. Do not use wires and cables manufactured more than 12 months prior to date of delivery to site.

2.7.1 Conductors

Provide the following:

- a. Conductor sizes and capacities shown are based on copper, unless indicated otherwise.
- b. Conductors No. 8 AWG and larger diameter: stranded.
- c. Conductors No. 10 AWG and smaller diameter: solid.
- d. Conductors for remote control, alarm, and signal circuits, classes 1, 2, and 3: stranded unless specifically indicated otherwise.
- e. All conductors: copper.

2.7.1.1 Minimum Conductor Sizes

Provide minimum conductor size in accordance with the following:

- a. Branch circuits: No. 12 AWG.
- b. Class 1 remote-control and signal circuits: No. 14 AWG.

- c. Class 2 low-energy, remote-control and signal circuits: No. 16 AWG.
- d. Class 3 low-energy, remote-control, alarm and signal circuits: No. 22 AWG.
- e. Digital low voltage lighting control (DLVLC) system at 24 Volts or less: Category 5 UTP cables in EMT conduit.

2.7.2 Color Coding

Provide color coding for service, feeder, branch, control, and signaling circuit conductors.

2.7.2.1 Ground and Neutral Conductors

Provide color coding of ground and neutral conductors as follows:

- a. Grounding conductors: Green.
- b. Neutral conductors: White.
- c. Exception, where neutrals of more than one system are installed in same raceway or box, other neutrals color coding: white with a different colored (not green) stripe for each.

2.7.2.2 Ungrounded Conductors

Provide color coding of ungrounded conductors in different voltage systems as follows:

- a. 208/120 volt, three-phase
 - (1) Phase A - black
 - (2) Phase B - red
 - (3) Phase C - blue
- b. 480/277 volt, three-phase
 - (1) Phase A - brown
 - (2) Phase B - orange
 - (3) Phase C - yellow
- c. 120/240 volt, single phase: Black and red

2.7.3 Insulation

Unless specified or indicated otherwise or required by NFPA 70, provide power and lighting wires rated for 600-volts, Type THWN/THHN conforming to UL 83 or Type XHHW conforming to UL 44, except that grounding wire may be type TW conforming to UL 83; remote-control and signal circuits: Type TW or TF, conforming to UL 83. Where lighting fixtures require 90-degree Centigrade (C) conductors, provide only conductors with 90-degree C insulation or better.

2.7.4 Bonding Conductors

ASTM B1, solid bare copper wire for sizes No. 8 AWG and smaller diameter; **ASTM B8**, Class B, stranded bare copper wire for sizes No. 6 AWG and larger diameter.

2.7.4.1 Telecommunications Bonding Backbone (TBB)

Provide a copper conductor TBB in accordance with **TIA-607** with No. 6 AWG minimum size, and sized at 2 kcmil per linear foot of conductor length up to a maximum size of 3/0 AWG.

2.7.4.2 Bonding Conductor for Telecommunications

Provide a copper conductor Bonding Conductor for Telecommunications between the telecommunications main grounding busbar (TMGB) and the electrical service ground in accordance with **TIA-607**. Size the bonding conductor for telecommunications the same as the TBB.

2.8 SPLICES AND TERMINATION COMPONENTS

UL 486A-486B for wire connectors and **UL 510** for insulating tapes. Connectors for No. 10 AWG and smaller diameter wires: insulated, pressure-type in accordance with **UL 486A-486B** or **UL 486C** (twist-on splicing connector). Provide solderless terminal lugs on stranded conductors.

2.9 DEVICE PLATES

Provide the following:

- a. UL listed, one-piece device plates for outlets to suit the devices installed.
- b. For metal outlet boxes, plates on unfinished walls: zinc-coated sheet steel or cast metal having round or beveled edges.
- c. For nonmetallic boxes and fittings, other suitable plates may be provided.
- d. Plates on finished walls: nylon or lexan, minimum 0.03 inch wall thickness and same color as receptacle or toggle switch with which they are mounted.
- f. Screws: machine-type with countersunk heads in color to match finish of plate.
- g. Sectional type device plates are not be permitted.
- h. Plates installed in wet locations: gasketed and UL listed for "wet locations."

2.10 SWITCHES

2.10.1 Toggle Switches

NEMA WD 1, **UL 20**, single pole, double pole, three-way, and four-way, totally enclosed with bodies of thermoplastic or thermoset plastic and mounting strap with grounding screw. Include the following:

- a. Handles: white thermoplastic.
- b. Wiring terminals: screw-type, side-wired.
- c. Contacts: silver-cadmium and contact arm - one-piece copper alloy.
- d. Switches: rated quiet-type ac only, 120/277 volts, with current rating and number of poles indicated.

2.10.2 Switch with Red Pilot Handle

NEMA WD 1. Provide the following:

- a. Pilot lights that are integrally constructed as a part of the switch's handle.
- b. Pilot light color: red and illuminate whenever the switch is closed or "on".
- c. Pilot lighted switch: rated 20 amps and 120 volts or 277 volts as indicated.
- d. The circuit's neutral conductor to each switch with a pilot light.

2.10.3 Breakers Used as Switches

For 120- and 277-Volt fluorescent fixtures, mark breakers "SWD" in accordance with **UL 489**.

2.10.4 Disconnect Switches

NEMA KS 1. Provide heavy duty-type switches where indicated, where switches are rated higher than 240 volts, and for double-throw switches. Utilize Class R fuseholders and fuses for fused switches, unless indicated otherwise. Provide horsepower rated for switches serving as the motor-disconnect means. Provide switches in NEMA 1 4X Type 304 stainless steel, enclosure as indicated per **NEMA ICS 6**.

2.11 FUSES

NEMA FU 1. Provide complete set of fuses for each fusible switch. Coordinate time-current characteristics curves of fuses serving motors or connected in series with circuit breakers or other circuit protective devices for proper operation. Submit coordination data for approval. Provide fuses with a voltage rating not less than circuit voltage.

2.11.1 Fuseholders

Provide in accordance with **UL 4248-1**.

2.11.2 Cartridge Fuses, Current Limiting Type (Class R)

UL 198M, Class RK-1. Provide only Class R associated fuseholders in accordance with **UL 4248-12**.

2.11.3 Cartridge Fuses, High-Interrupting Capacity, Current Limiting Type (Classes J, L, and CC)

UL 198M, Class J for zero to 600 amperes, Class L for 601 to 6,000 amperes, and Class CC for zero to 30 amperes.

2.11.4 Cartridge Fuses, Current Limiting Type (Class T)

UL 198M, Class T for zero to 1,200 amperes, 300 volts; and zero to 800 amperes, 600 volts.

2.12 RECEPTACLES

Provide the following:

- a. UL 498, general purpose specification grade, grounding-type. Residential grade receptacles are not acceptable.
- b. Ratings and configurations: as indicated.
- c. Bodies: white as per NEMA WD 1.
- d. Face and body: thermoplastic supported on a metal mounting strap.
- e. Dimensional requirements: per NEMA WD 6.
- f. Screw-type, side-wired wiring terminals or of the solderless pressure type having suitable conductor-release arrangement.
- g. Grounding pole connected to mounting strap.
- h. The receptacle: containing triple-wipe power contacts and double or triple-wipe ground contacts.

2.12.1 Split Duplex Receptacles

Provide separate terminals for each ungrounded pole. One receptacle must be controlled separately.

2.12.2 Weatherproof Receptacles

Provide receptacles, UL listed for use in "wet locations". Include cast metal box with gasketed, hinged, lockable and weatherproof while-in-use, polycarbonate, UV resistant/stabilized cover plate.

2.12.3 Ground-Fault Circuit Interrupter Receptacles

UL 943, duplex type for mounting in standard outlet box. Provide device capable of detecting current leak when the current to ground is 6 milliamperes or higher, and tripping per requirements of UL 943 for Class A ground-fault circuit interrupter devices. Provide screw-type, side-wired wiring terminals or pre-wired (pigtail) leads.

2.12.4 Special Purpose Receptacles

Receptacles serving telecommunication areas are special purpose. Provide in ratings indicated.

2.12.5 Tamper-Resistant Receptacles

Provide duplex receptacle with mechanical sliding shutters that prevent the insertion of small objects into its contact slots.

2.12.6 Receptacles in Hazardous (Classified) Locations

Provide in accordance with UL 1203. Receptacles shall be dead front interlocked, explosion proof, dust-ignition proof, raintight, and approved for wet locations. Receptacles shall be approved and certified for use in NEC Class 1 - Division 1 and 2 - Groups B, C, and D, Class 2 - Division 1 and 2 - Groups F and G, and Class 3 locations as indicated. Housing and plug body shall be die cast copper free aluminum with brass contacts, stainless steel cover hinge pin and spring, neoprene receptacle gasket and plug bushing, and copper free aluminum back boxes. Grounding requirements shall be in accordance with NEC Article 501. Receptacles shall be NEMA 5-20R, rated 20 amperes, 125/250 volts.

2.13 PANELBOARDS

Provide panelboards in accordance with the following:

- a. UL 67 and UL 50 having a short-circuit current rating as indicated .
- b. Panelboards for use as service disconnecting means: additionally conform to UL 869A.
- c. Panelboards: circuit breaker-equipped.
- d. Designed such that individual breakers can be removed without disturbing adjacent units or without loosening or removing supplemental insulation supplied as means of obtaining clearances as required by UL.
- e. "Specific breaker placement" is required in panelboards to match the breaker placement indicated in the panelboard schedule on the drawings.
- f. Use of "Subfeed Breakers" is not acceptable.
- g. Main breaker: "separately" mounted "above" or "below" branch breakers.
- h. Where "space only" is indicated, make provisions for future installation of breakers.
- i. Directories: indicate load served by each circuit in panelboard.
- j. Directories: indicate source of service to panelboard (e.g., Panel PA served from Panel MDP).
- l. Type directories and mount in holder behind transparent protective covering.
- m. Panelboards: listed and labeled for their intended use.
- n. Panelboard nameplates: provided in accordance with paragraph FIELD FABRICATED NAMEPLATES.

2.13.1 Enclosure

Provide panelboard enclosure in accordance with the following:

- a. UL 50.
- b. Cabinets mounted outdoors or flush-mounted: hot-dipped galvanized after fabrication .
- c. Cabinets: painted in accordance with paragraph PAINTING.
- d. Outdoor cabinets: NEMA 4x with a removable steel plate 1/4 inch thick in the bottom for field drilling for conduit connections.
- e. Front edges of cabinets: form-flanged or fitted with structural shapes welded or riveted to the sheet steel, for supporting the panelboard front.
- f. All cabinets: fabricated such that no part of any surface on the finished cabinet deviates from a true plane by more than 1/8 inch.
- g. Holes: provided in the back of indoor surface-mounted cabinets, with outside spacers and inside stiffeners, for mounting the cabinets with a 1/2 inch clear space between the back of the cabinet and the wall surface.
- h. Flush doors: mounted on hinges that expose only the hinge roll to view when the door is closed.
- i. Each door: fitted with a combined catch and lock latch.
- j. Keys: two provided with each lock, with all locks keyed alike.
- k. Finished-head cap screws: provided for mounting the panelboard fronts on the cabinets.

2.13.2 Panelboard Buses

Support bus bars on bases independent of circuit breakers. Design main buses and back pans so that breakers may be changed without machining, drilling, or tapping. Provide isolated neutral bus in each panel for connection of circuit neutral conductors. Provide separate ground bus identified as equipment grounding bus per UL 67 for connecting grounding conductors; bond to steel cabinet.

2.13.2.1 Panelboard Neutrals for Non-Linear Loads

Provide in accordance with the following:.

- a. UL listed, with panelboard type specifically UL heat rise tested for use on non-linear loads.
- b. Panelboard: heat rise tested in accordance with UL 67, except with the neutral assembly installed and carrying 200 percent of the phase bus current during testing.
- c. Verification of the testing procedure: provided upon request.
- d. Two neutral assemblies paralleled together with cable is not

acceptable.

- e. Nameplates for panelboard rated for use on non-linear loads: marked "SUITABLE FOR NON-LINEAR LOADS" and in accordance with paragraph FIELD FABRICATED NAMEPLATES.
- f. Provide a neutral label with instructions for wiring the neutral of panelboards rated for use on non-linear loads.

2.13.3 Circuit Breakers

UL 489, thermal magnetic-type having a minimum short-circuit current rating equal to the short-circuit current rating of the panelboard in which the circuit breaker will be mounted. Breaker terminals: UL listed as suitable for type of conductor provided. Where indicated on the drawings, provide circuit breakers with shunt trip devices. Series rated circuit breakers and plug-in circuit breakers are unacceptable.

2.13.3.1 Multipole Breakers

Provide common trip-type with single operating handle. Design breaker such that overload in one pole automatically causes all poles to open. Maintain phase sequence throughout each panel so that any three adjacent breaker poles are connected to Phases A, B, and C, respectively.

2.13.3.2 Circuit Breaker With Ground-Fault Circuit Interrupter

UL 943 and NFPA 70. Provide with auto-monitoring (self-test) and lockout features, "push-to-test" button, visible indication of tripped condition, and ability to detect and trip when current imbalance is 6 milliamperes or higher per requirements of UL 943 for Class A ground-fault circuit interrupter devices.

2.13.3.3 Arc-Fault Circuit Interrupters

UL 489, UL 1699 and NFPA 70. Molded case circuit breakers: rated as indicated. Provide with "push-to-test" button.

2.14 ENCLOSED CIRCUIT BREAKERS

UL 489. Individual molded case circuit breakers with voltage and continuous current ratings, number of poles, overload trip setting, and short circuit current interrupting rating as indicated. Enclosure type as indicated. Provide solid neutral.

2.15 MOTOR SHORT-CIRCUIT PROTECTOR (MSCP)

Motor short-circuit protectors, also called motor circuit protectors (MCPs): UL 508 and UL 489, and provided as shown. Provide MSCPs that consist of an adjustable instantaneous trip circuit breaker used only in conjunction with a combination motor controller which provides coordinated motor branch-circuit overload and short-circuit protection. Rate MSCPs in accordance with the requirements of NFPA 70.

2.16 TRANSFORMERS

Provide transformers in accordance with the following:

- a. NEMA ST 20, general purpose, dry-type, self-cooled, ventilated type in non-hazardous indoor locations and unventilated sealed type in outdoor or classified areas, as indicated.
- b. Provide transformers in NEMA 1 enclosure for indoor locations or NEMA 4X stainless steel enclosure for outdoor locations, as indicated.
- c. Taps for transformers 15 kVA and larger: Two 2.5 percent taps Full Capacity Above Nominal (FCAN) and two 2.5 percent taps Full Capacity Below Nominal (FCBN) .
- d. Transformer insulation system:
 - (1) 220 degrees C insulation system for transformers 15 kVA and greater, with temperature rise not exceeding 115 degrees C under full-rated load in maximum ambient of 40 degrees C.
 - (2) 180 degrees C insulation for transformers rated 10 kVA and less, with temperature rise not exceeding 80 degrees C under full-rated load in maximum ambient of 40 degrees C.
- e. Transformer of 150 degrees C temperature rise is not acceptable.
- f. Transformer of 115 degrees C temperature rise: capable of carrying continuously 115 percent of nameplate kVA without exceeding insulation rating.

2.16.1 Specified Transformer Efficiency

Transformers, indicated and specified with: 480V primary, 80 degrees C or 115 degrees C temperature rise, kVA ratings of 37.5 to 100 for single phase or 30 to 500 for three phase, energy efficient type. The transformer is not acceptable if the calculated transformer efficiency is less than the efficiency indicated in 10 CFR 431, Subpart K.

2.16.2 Transformers With Non-Linear Loads

Provide transformers for non-linear loads in accordance with the following:

- a. Transformer insulation: UL recognized 220 degrees C system. Neither the primary nor the secondary temperature is allowed to exceed 220 degrees C at any point in the coils while carrying their full rating of non-sinusoidal load.
- b. Transformers are to be UL listed and labeled for K-13 in accordance with UL 1561.
- c. Transformers evaluated by the UL K-Factor evaluation: listed for 115 degrees C average temperature rise only.
- d. Transformers with K-Factor ratings with temperature rise of 150 degrees C rise are not acceptable.
- e. K-Factor rated transformers impedance: allowed range of 3 percent to 5 percent, with a minimum reactance of 2 percent to prevent excessive neutral current when supplying loads with large amounts of third harmonic.

2.17 MOTORS

Provide motors in accordance with the following:

- a. NEMA MG 1 except provide fire pump motors as specified in Section 21 30 00 FIRE PUMPS.
- b. Hermetic-type sealed motor compressors: Also comply with UL 984.
- c. Provide the size in terms of HP, or kVA, or full-load current, or a combination of these characteristics, and other characteristics, of each motor as indicated or specified.
- d. Determine specific motor characteristics to ensure provision of correctly sized starters and overload heaters.
- e. Rate motors for operation on 208-volt, 3-phase circuits with a terminal voltage rating of 200 volts, and those for operation on 480-volt, 3-phase circuits with a terminal voltage rating of 460 volts.
- f. Use motors designed to operate at full capacity with voltage variation of plus or minus 10 percent of motor voltage rating.
- g. Unless otherwise indicated, use continuous duty type motors if rated 1 HP and above.
- h. Where fuse protection is specifically recommended by the equipment manufacturer, provide fused switches in lieu of non-fused switches indicated.
- i. Use Inverter-Rated motors designed to operate with adjustable speed drive (ASD).

2.17.1 High Efficiency Single-Phase Motors

Single-phase fractional-horsepower alternating-current motors: high efficiency types are not acceptable. In exception, for special purpose motors and motor-driven equipment with a minimum seasonal or overall efficiency rating, such as a SEER rating, provide equipment with motor to meet the overall system rating indicated.

2.17.2 Premium Efficiency Polyphase and Single-Phase Motors

Select polyphase and continuous-duty single phase motors based on high efficiency characteristics relative to typical characteristics and applications as listed in NEMA MG 10 and NEMA MG 11. In addition, continuous rated, polyphase squirrel-cage medium induction motors must meet the requirements for premium efficiency electric motors in accordance with NEMA MG 1, including the NEMA full load efficiency ratings. In exception, for motor-driven equipment with a minimum seasonal or overall efficiency rating, such as a SEER rating, provide equipment with motor to meet the overall system rating indicated.

2.17.3 Motor Sizes

Provide size for duty to be performed, not exceeding the full-load nameplate current rating when driven equipment is operated at specified capacity under most severe conditions likely to be encountered. When

motor size provided differs from size indicated or specified, make adjustments to wiring, disconnect devices, and branch circuit protection to accommodate equipment actually provided. Provide controllers for motors rated 1-hp and above with electronic phase-voltage monitors designed to protect motors from phase-loss, undervoltage, and overvoltage. Provide protection for motors from immediate restart by a time adjustable restart relay.

2.17.4 Wiring and Conduit

Provide internal wiring for components of packaged equipment as an integral part of the equipment. Provide power wiring and conduit for field-installed equipment using adjustable speed drive (ASD) manufacturer required wiring type and length as specified herein. Power wiring and conduit: conform to the requirements specified herein. Control wiring: provided under, and conform to, the requirements of the section specifying the associated equipment.

2.18 MOTOR CONTROLLERS

Provide motor controllers in accordance with the following:

- a. UL 508, NEMA ICS 1, and NEMA ICS 2, except fire pump controllers as specified in Section 21 30 00 FIRE PUMPS.
- b. Provide controllers with thermal overload protection in each phase, and one spare normally open auxiliary contact, and one spare normally closed auxiliary contact.
- c. Provide controllers for motors rated 1-hp and above with electronic phase-voltage monitors designed to protect motors from phase-loss, undervoltage, and overvoltage.
- d. Provide protection for motors from immediate restart by a time adjustable restart relay.
- e. When used with pressure, float, or similar automatic-type or maintained-contact switch, provide a hand/off/automatic selector switch with the controller.
- f. Connections to selector switch: wired such that only normal automatic regulatory control devices are bypassed when switch is in "hand" position.
- g. Safety control devices, such as low and high pressure cutouts, high temperature cutouts, and motor overload protective devices: connected in motor control circuit in "hand" and "automatic" positions.
- h. Control circuit connections to hand/off/automatic selector switch or to more than one automatic regulatory control device: made in accordance with indicated or manufacturer's approved wiring diagram.
- i. Provide selector switch with the means for locking in any position.
- j. Provide a disconnecting means, capable of being locked in the open position, for the motor that is located in sight from the motor location and the driven machinery location. As an alternative, provide a motor controller disconnect, capable of being locked in the open position, to serve as the disconnecting means for the motor if it

is in sight from the motor location and the driven machinery location.

- k. Overload protective devices: provide adequate protection to motor windings; be thermal inverse-time-limit type; and include manual reset-type pushbutton on outside of motor controller case.
- l. Cover of combination motor controller and manual switch or circuit breaker: interlocked with operating handle of switch or circuit breaker so that cover cannot be opened unless handle of switch or circuit breaker is in "off" position.
- m. Minimum short circuit withstand rating of combination motor controller: 10,000 rms symmetrical amperes.
- n. Provide controllers in hazardous locations with classifications as indicated.

2.18.1 Control Wiring

Provide control wiring in accordance with the following:

- a. All control wire: stranded tinned copper switchboard wire with 600-volt flame-retardant insulation Type SIS meeting UL 44, or Type MTW meeting UL 1063, and passing the VW-1 flame tests included in those standards.
- b. Hinge wire: Class K stranding.
- c. Current transformer secondary leads: not smaller than No. 10 AWG.
- d. Control wire minimum size: No. 14 AWG.
- e. Power wiring for 480-volt circuits and below: the same type as control wiring with No. 12 AWG minimum size.
- f. Provide wiring and terminal arrangement on the terminal blocks to permit the individual conductors of each external cable to be terminated on adjacent terminal points.

2.18.2 Control Circuit Terminal Blocks

Provide control circuit terminal blocks in accordance with the following:

- a. NEMA ICS 4.
- b. Control circuit terminal blocks for control wiring: molded or fabricated type with barriers, rated not less than 600 volts.
- c. Provide terminals with removable binding, fillister or washer head screw type, or of the stud type with contact and locking nuts.
- d. Terminals: not less than No. 10 in size with sufficient length and space for connecting at least two indented terminals for 10 AWG conductors to each terminal.
- e. Terminal arrangement: subject to the approval of the Contracting Officer with not less than four spare terminals or 10 percent, whichever is greater, provided on each block or group of blocks.

- f. Modular, pull apart, terminal blocks are acceptable provided they are of the channel or rail-mounted type.
- g. Submit data showing that any proposed alternate will accommodate the specified number of wires, are of adequate current-carrying capacity, and are constructed to assure positive contact between current-carrying parts.

2.18.2.1 Types of Terminal Blocks

- a. Short-Circuiting Type: Short-circuiting type terminal blocks: furnished for all current transformer secondary leads with provision for shorting together all leads from each current transformer without first opening any circuit. Terminal blocks: comply with the requirements of paragraph CONTROL CIRCUIT TERMINAL BLOCKS above.
- b. Load Type: Load terminal blocks rated not less than 600 volts and of adequate capacity: provided for the conductors for NEMA Size 3 and smaller motor controllers and for other power circuits, except those for feeder tap units. Provide terminals of either the stud type with contact nuts and locking nuts or of the removable screw type, having length and space for at least two indented terminals of the size required on the conductors to be terminated. For conductors rated more than 50 amperes, provide screws with hexagonal heads. Conducting parts between connected terminals must have adequate contact surface and cross-section to operate without overheating. Provide each connected terminal with the circuit designation or wire number placed on or near the terminal in permanent contrasting color.

2.18.3 Control Circuits

Control circuits: maximum voltage of 120 volts derived from control transformer in same enclosure. Transformers: conform to **UL 506**, as applicable. Transformers, other than transformers in bridge circuits: provide primaries wound for voltage available and secondaries wound for correct control circuit voltage. Size transformers so that 80 percent of rated capacity equals connected load. Provide disconnect switch on primary side. Provide fuses in each ungrounded primary feeder. Provide one fused secondary lead with the other lead grounded.

2.18.4 Enclosures for Motor Controllers

NEMA ICS 6.

2.18.5 Multiple-Speed Motor Controllers and Reversible Motor Controllers

Across-the-line-type, electrically and mechanically interlocked. Multiple-speed controllers: include compelling relays and multiple-button, station-type with pilot lights for each speed.

2.18.6 Pushbutton Stations

Provide with "start/stop" momentary contacts having one normally open and one normally closed set of contacts, and red lights to indicate when motor is running. Stations: heavy duty, oil-tight design.

2.18.7 Pilot and Indicating Lights

Provide LED cluster lamps.

2.19 **MANUAL MOTOR STARTERS** (MOTOR RATED SWITCHES)

Single or Double pole designed for surface mounting with overload protection and pilot lights, as indicated.

2.19.1 Pilot Lights

Provide yoke-mounted, seven element LED cluster light module. Color: in accordance with **NEMA ICS 2**.

2.20 **LOCKOUT REQUIREMENTS**

Provide circuit breakers, disconnecting means, and other devices that are electrical energy-isolating capable of being locked out for machines and other equipment to prevent unexpected startup or release of stored energy in accordance with **29 CFR 1910.147**, **NFPA 70E** and **29 CFR 1910.303**. Comply with requirements of Division 23, "Mechanical" for mechanical isolation of machines and other equipment.

2.21 **TELECOMMUNICATIONS SYSTEM**

Provide system of telecommunications wire-supporting structures (pathway), including: outlet boxes, conduits with pull wires, wireways, cable trays, and other accessories for telecommunications outlets and pathway in accordance with **TIA-569** and as specified herein. Additional telecommunications requirements are specified in Section **27 10 00 BUILDING TELECOMMUNICATIONS CABLING SYSTEM**.

2.22 **COMMUNITY ANTENNA TELEVISION (CATV) SYSTEM**

Additional CATV requirements are specified in Section **27 05 13.43 TELEVISION DISTRIBUTION SYSTEM**.

2.23 **GROUNDING AND BONDING EQUIPMENT**

2.23.1 Ground Rods

UL 467. Ground rods: cone pointed copper-clad steel, with minimum diameter of **3/4 inch** and minimum length **10 feet**. Sectional ground rods are permitted.

2.23.2 Ground Bus

Copper ground bus: provided in the electrical equipment rooms as indicated.

2.23.3 Telecommunications and CATV **Grounding Busbar**

Provide corrosion-resistant grounding busbar suitable for indoor installation in accordance with **TIA-607**. Busbars: plated for reduced contact resistance. If not plated, clean the busbar prior to fastening the conductors to the busbar and apply an anti-oxidant to the contact area to control corrosion and reduce contact resistance. Provide a telecommunications main grounding busbar (TMGB) in the telecommunications entrance facility and a (TGB) in all other telecommunications rooms and equipment rooms. The telecommunications main grounding busbar (TMGB) and the telecommunications grounding busbar (TGB): sized in accordance with the immediate application requirements and with consideration of future

growth. Provide telecommunications grounding busbars with the following:

- a. Predrilled copper busbar provided with holes for use with standard sized lugs,
- b. Minimum dimensions of 0.25 in thick by 4 in wide for the TMGB and 2 in wide for TGBs with length as indicated;
- c. Listed by a nationally recognized testing laboratory.

2.24 HAZARDOUS LOCATIONS

Electrical materials, equipment, and devices for installation in hazardous locations, as defined by NFPA 70: specifically approved by Underwriters' Laboratories, Inc., or Factory Mutual for particular "Class," "Division," and "Group" of hazardous locations involved. Boundaries and classifications of hazardous locations: as indicated. Equipment in hazardous locations: comply with UL 1203 for electrical equipment and industrial controls and UL 674 for motors.

2.25 MANUFACTURER'S NAMEPLATE

Provide on each item of equipment a nameplate bearing the manufacturer's name, address, model number, and serial number securely affixed in a conspicuous place; the nameplate of the distributing agent will not be acceptable.

2.26 FIELD FABRICATED NAMEPLATES

Provide field fabricated nameplates in accordance with the following:

- a. ASTM D709.
- b. Provide laminated plastic nameplates for each equipment enclosure, relay, switch, and device; as specified or as indicated on the drawings.
- c. Each nameplate inscription: identify the function and, when applicable, the position.
- d. Nameplates: melamine plastic, 0.125 inch thick, white with black center core.
- e. Provide red laminated plastic label with white center core where indicated.
- f. Surface: matte finish. Corners: square. Accurately align lettering and engrave into the core.
- g. Minimum size of nameplates: one by 2.5 inches.
- h. Lettering size and style: a minimum of 0.25 inch high normal block style.

2.27 WARNING SIGNS

Provide warning signs for flash protection in accordance with NFPA 70E and NEMA 2535.4 for switchboards, panelboards, industrial control panels, and motor control centers that are in other than dwelling occupancies and are

likely to require examination, adjustment, servicing, or maintenance while energized. Provide field installed signs to warn qualified persons of potential electric arc flash hazards when warning signs are not provided by the manufacturer. Provide marking that is clearly visible to qualified persons before examination, adjustment, servicing, or maintenance of the equipment.

2.28 FIRESTOPPING MATERIALS

Provide firestopping around electrical penetrations in accordance with Section 07 84 00 FIRESTOPPING.

2.29 MODULAR POWER DISTRIBUTION SYSTEM

The modular power distribution system shall consist of a modular wiring system, with quick connection of components, to provide a zone distribution of multiple circuits to raised access floor boxes. Component's wiring shall not be de-populated to impede future reconfigurations. System shall fit within a 1.75 inch tall cavity under a raised floor, minimum. The system shall be UL 183 listed and certified to CSA 22.2 No. 203-M. Connectors will be polarity keyed and shaped to prevent interconnection of electrically incompatible components. The modular power distribution system shall be in accordance with NEC Article 604 and all applicable UL standards. All components shall be labeled with both voltage ratings and installation information. The system shall be designed and keyed to prevent mismatching of different voltages. All devices and wiring shall be rated for 20 amperes, minimum. The connector-grounding pin on each modular assembly shall be designed so that the grounding connection is made, prior to the contact made within the current carrying conductors, per NEC Article 604.

Home Run Cable: The cable shall be metal clad cable consisting of multiple #10 AWG, THHN 90 C insulation. The cable type shall be UL listed and recognized as outlined in Article #334 of the latest edition of National Electrical Code.

Main Distribution Box: A Main Distribution Box (MDB) with multiple ports (as noted on the plans) shall provide general-purpose 3-phase, 120/208 volts power. The MDB shall include a home run as specified. Ground conductors shall be added as required by National Electrical Code (NEC). The MDB shall be UL-listed and identified accordingly. The MDB shall be suitable for use in environmental air-handling spaces (plenums) in accordance with NEC 300.22(c).

Extender Cables: Extender cables shall interface with the MDB and feed to the Secondary Distribution Boxes as indicated on the plans. Extender cables shall consist of 90 degree C insulated, #12 AWG solid copper conductors, with a #12 AWG solid copper ground conductor. The extender cable shall have line side (power out) and load side (power in) connectors. The connectors shall be capable of having 5 pins for the distribution of 3-phase, 4 wire, 120/208 volt general-purpose power.

Floor Box Modules: The Floor Box Modules shall be designed for use in the open office environment. It shall provide power and telecom outlets in a raised floor as shown on the plans. The Floor Box Module shall have a square shape to allow repositioning to any of four orientations without modification of the module or floor panel. The dual compartment enclosure shall be fitted with power receptacles and telecommunications jack arrangements as shown on the plans. The floor box shall be pre-wired with

the specified electrical devices at the factory and tested for continuity and highpot prior to installation.

2.30 SURGE PROTECTIVE DEVICES

Provide parallel type surge protective devices (SPD) which comply with **UL 1449** at the service entrance, load centers, panelboards, and switchboards. Provide surge protectors in a **NEMA 1 enclosure for indoor installations and NEMA 4X stainless steel enclosure for outdoor installations** per **NEMA ICS 6**. SPD must have the same short-circuit current rating as the protected equipment and shall not be installed at a point of system where the available fault current is in excess of that rating. Use Type 1 or Type 2 SPD and connect on the load side of a dedicated circuit breaker. Submit performance and characteristic curves.

Provide the following modes of protection:

FOR SINGLE PHASE AND THREE PHASE WYE CONNECTED SYSTEMS-
Phase to phase (L-L)
Each phase to neutral (L-N)
Neutral to ground (N-G)
Phase to ground (L-G)

SPDs at the service entrance: provide with a minimum surge current rating of 80,000 amperes for L-L mode minimum and 40,000 amperes for other modes (L-N, L-G, and N-G) and downstream SPDs rated 40,000 amperes for L-L mode minimum and 20,000 amperes for other modes (L-N, L-G, and N-G).

Provide SPDs per NFPA 780 for the lightning protection system.

Maximum L-N, and N-G Voltage Protection Rating:

600V for 120V, single phase system
600V for 208Y/120V, three phase system
1,200V for 480Y/277V, three phase system

Maximum L-G Protection Rating:

700V for 120V, single phase system
700V for 208Y/120V, three phase system
1,200V for 480Y/277V, three phase system

Maximum L-L Voltage Protection Rating:

1,200V for 208Y/120V, three phase system
1,800V for 480Y/277V, three phase system

The minimum MCOV (Maximum Continuous Operating Voltage) rating for L-N and L-G modes of operation: 120 percent of nominal voltage for 240 volts and below; 115 percent of nominal voltage above 240 volts to 480 volts.

2.31 FACTORY APPLIED FINISH

Provide factory-applied finish on electrical equipment in accordance with the following:

- a. **NEMA 250** corrosion-resistance test and the additional requirements as specified herein.

- b. Interior and exterior steel surfaces of equipment enclosures: thoroughly cleaned followed by a rust-inhibitive phosphatizing or equivalent treatment prior to painting.
- c. Exterior surfaces: free from holes, seams, dents, weld marks, loose scale or other imperfections.
- d. Interior surfaces: receive not less than one coat of corrosion-resisting paint in accordance with the manufacturer's standard practice.
- e. Exterior surfaces: primed, filled where necessary, and given not less than two coats baked enamel with semigloss finish.
- f. Equipment located indoors: ANSI Light Gray, and equipment located outdoors: ANSI Light Gray.
- g. Provide manufacturer's coatings for touch-up work and as specified in paragraph FIELD APPLIED PAINTING.

2.32 SOURCE QUALITY CONTROL

2.32.1 Transformer Factory Tests

Submittal: include routine NEMA ST 20 transformer test results on each transformer and also provide the results of NEMA "design" and "prototype" tests that were made on transformers electrically and mechanically equal to those specified.

2.33 COORDINATED POWER SYSTEM PROTECTION

Prepare analyses as specified in Section 26 28 01.00 10 COORDINATED POWER SYSTEM PROTECTION.

PART 3 EXECUTION

3.1 INSTALLATION

Electrical installations, including weatherproof and hazardous locations and ducts, plenums and other air-handling spaces: conform to requirements of NFPA 70 and IEEE C2 and to requirements specified herein.

3.1.1 Underground Service

Underground service conductors and associated conduit: continuous from service entrance equipment to outdoor power system connection.

3.1.2 Hazardous Locations

Perform work in hazardous locations, as defined by NFPA 70, in strict accordance with NFPA 70 for particular "Class," "Division," and "Group" of hazardous locations involved. Provide conduit and cable seals where required by NFPA 70. Provide conduit with tapered threads.

3.1.3 Service Entrance Identification

Service entrance disconnect devices, switches, and enclosures: labeled and identified as such.

3.1.3.1 Labels

Wherever work results in service entrance disconnect devices in more than one enclosure, as permitted by NFPA 70, label each enclosure, new and existing, as one of several enclosures containing service entrance disconnect devices. Label, at minimum: indicate number of service disconnect devices housed by enclosure and indicate total number of enclosures that contain service disconnect devices. Provide laminated plastic labels conforming to paragraph FIELD FABRICATED NAMEPLATES. Use lettering of at least 0.25 inch in height, and engrave on black-on-white matte finish. Service entrance disconnect devices in more than one enclosure: provided only as permitted by NFPA 70.

3.1.4 Wiring Methods

Provide insulated conductors installed in rigid steel conduit, IMC, rigid nonmetallic conduit, or EMT, except where specifically indicated or specified otherwise or required by NFPA 70 to be installed otherwise. Grounding conductor: separate from electrical system neutral conductor. Provide insulated green equipment grounding conductor for circuit(s) installed in conduit and raceways. Minimum conduit size: 1/2 inch in diameter for low voltage lighting and power circuits. Vertical distribution in multiple story buildings: made with metal conduit in fire-rated shafts, with metal conduit extending through shafts for minimum distance of 6 inches. Firestop conduit which penetrates fire-rated walls, fire-rated partitions, or fire-rated floors in accordance with Section 07 84 00 FIRESTOPPING.

3.1.4.1 Pull Wire

Install pull wires in empty conduits. Pull wire: plastic having minimum 200-pound force tensile strength. Leave minimum 36 inches of slack at each end of pull wire.

3.1.5 Conduit Installation

Unless indicated otherwise, conceal conduit under floor slabs and within finished walls, ceilings, and floors. Keep conduit minimum 6 inches away from parallel runs of flues and steam or hot water pipes. Install conduit parallel with or at right angles to ceilings, walls, and structural members where located above accessible ceilings and where conduit will be visible after completion of project.

3.1.5.1 Restrictions Applicable to Aluminum Conduit

- a. Do not install underground or encase in concrete or masonry.
- b. Do not use brass or bronze fittings.
- c. Do not use when the enclosed conductors must be shielded from the effects of High-altitude Electromagnetic Pulse (HEMP).

3.1.5.2 Restrictions Applicable to EMT

- a. Do not install underground.
- b. Do not encase in concrete, mortar, grout, or other cementitious materials.

- c. Do not use in areas subject to physical damage including but not limited to equipment rooms where moving or replacing equipment could physically damage the EMT.
- d. Do not use in hazardous areas.
- e. Do not use outdoors.
- f. Do not use in fire pump rooms.
- g. Do not use when the enclosed conductors must be shielded from the effects of High-altitude Electromagnetic Pulse (HEMP).

3.1.5.3 Restrictions Applicable to Nonmetallic Conduit

- a. PVC Schedule 40.
 - (1) Do not use where subject to physical damage, including but not limited to, mechanical equipment rooms, electrical equipment rooms, fire pump rooms, and where restrictions are applying to both PVC Schedule 40 and PVC Schedule 80.
 - (2) Do not use above grade, except where allowed in this section for rising through floor slab or indicated otherwise.
- b. PVC Schedule 40 and Schedule 80.
 - (1) Do not use where subject to physical damage, including but not limited to, hospitals, power plant, missile magazines, and other such areas.
 - (2) Do not use in hazardous (classified) areas.
 - (3) Do not use in penetrating fire-rated walls or partitions, or fire-rated floors.

-

3.1.5.4 Restrictions Applicable to Flexible Conduit

Use only as specified in paragraph FLEXIBLE CONNECTIONS. Do not use when the enclosed conductors must be shielded from the effects of High-altitude Electromagnetic Pulse (HEMP).

3.1.5.5 Underground Conduit

Plastic-coated rigid steel; plastic-coated steel IMC; PVC, Type EPC-40
Plastic coating: extend minimum 6 inches above floor.

3.1.5.6 Conduit Interior to Buildings for 400 Hz Circuits

Aluminum or nonmetallic. Where 400-Hz circuit runs underground or through concrete, provide PVC Schedule 40 conduit.

3.1.5.7 Conduit for Circuits Rated Greater Than 600 Volts

Rigid metal conduit or IMC only.

3.1.5.8 Conduit Installed Under Floor Slabs

Conduit run under floor slab: located a minimum of 12 inches below the vapor barrier. Seal around conduits at penetrations thru vapor barrier.

3.1.5.9 Conduit Through Floor Slabs

Where conduits rise through floor slabs, do not allow curved portion of bends to be visible above finished slab. Where conduit rises through slab-on grade, seal all electrical penetrations to address radon mitigation and prevent infiltration of air, insects, and vermin.

3.1.5.10 Conduit Installed in Concrete Floor Slabs

PVC, Type EPC-40, unless indicated otherwise. Locate so as not to adversely affect structural strength of slabs. Install conduit within middle one-third of concrete slab. Do not stack conduits. Space conduits horizontally not closer than three diameters, except at cabinet locations. Curved portions of bends must not be visible above finish slab. Increase slab thickness as necessary to provide minimum one inch cover over conduit. Where embedded conduits cross building expansion joints, provide suitable watertight expansion/deflection fittings and bonding jumpers. Expansion/deflection fittings must allow horizontal and vertical movement of raceway. Conduit larger than one inch trade size: installed parallel with or at right angles to main reinforcement; when at right angles to reinforcement, install conduit close to one of supports of slab. Where nonmetallic conduit is used, convert raceway to plastic coated rigid steel or plastic coated steel IMC before rising above floor, unless specifically indicated.

3.1.5.11 Stub-Ups

Provide conduits stubbed up through concrete floor for connection to free-standing equipment with adjustable top or coupling threaded inside for plugs, set flush with finished floor. Extend conductors to equipment in rigid steel conduit, except that flexible metal conduit may be used 6 inches above floor. Where no equipment connections are made, install screwdriver-operated threaded flush plugs in conduit end.

3.1.5.12 Conduit Support

Support conduit by pipe straps, wall brackets, threaded rod conduit hangers, or ceiling trapeze. Fasten by wood screws to wood; by toggle bolts on hollow masonry units; by concrete inserts or expansion bolts on concrete or brick; and by machine screws, welded threaded studs, or spring-tension clamps on steel work. Threaded C-clamps may be used on rigid steel conduit only. Do not weld conduits or pipe straps to steel structures. Do not exceed one-fourth proof test load for load applied to fasteners. Provide vibration resistant and shock-resistant fasteners attached to concrete ceiling. Do not cut main reinforcing bars for any holes cut to depth of more than 1 1/2 inches in reinforced concrete beams or to depth of more than 3/4 inch in concrete joints. Fill unused holes. In partitions of light steel construction, use sheet metal screws. In suspended-ceiling construction, run conduit above ceiling. Do not support conduit by ceiling support system. Conduit and box systems: supported independently of both (a) tie wires supporting ceiling grid system, and (b) ceiling grid system into which ceiling panels are placed. Do not share supporting means between electrical raceways and mechanical piping or ducts. Coordinate installation with above-ceiling mechanical systems

to assure maximum accessibility to all systems. Spring-steel fasteners may be used for lighting branch circuit conduit supports in suspended ceilings in dry locations. Where conduit crosses building expansion joints, provide suitable watertight expansion fitting that maintains conduit electrical continuity by bonding jumpers or other means. For conduits greater than 2 1/2 inches inside diameter, provide supports to resist forces of 0.5 times the equipment weight in any direction and 1.5 times the equipment weight in the downward direction.

3.1.5.13 Directional Changes in Conduit Runs

Make changes in direction of runs with symmetrical bends or cast-metal fittings. Make field-made bends and offsets with hickey or conduit-bending machine. Do not install crushed or deformed conduits. Avoid trapped conduits. Prevent plaster, dirt, or trash from lodging in conduits, boxes, fittings, and equipment during construction. Free clogged conduits of obstructions.

3.1.5.14 Locknuts and Bushings

Fasten conduits to sheet metal boxes and cabinets with two locknuts where required by NFPA 70, where insulated bushings are used, and where bushings cannot be brought into firm contact with the box; otherwise, use at least minimum single locknut and bushing. Provide locknuts with sharp edges for digging into wall of metal enclosures. Install bushings on ends of conduits, and provide insulating type where required by NFPA 70.

3.1.5.15 Flexible Connections

Provide flexible steel conduit between 3 and 6 feet in length for recessed and semirecessed lighting fixtures; for equipment subject to vibration, noise transmission, or movement; and for motors. Install flexible conduit to allow 20 percent slack. Minimum flexible steel conduit size: 1/2 inch diameter. Provide liquid tight flexible conduit in wet and damp locations and in fire pump rooms for equipment subject to vibration, noise transmission, movement or motors. Provide separate ground conductor across flexible connections.

3.1.5.16 Telecommunications and Signal System Pathway

Install telecommunications pathway in accordance with TIA-569.

- a. Horizontal Pathway: Telecommunications pathways from the work area to the telecommunications room: installed and cabling length requirements in accordance with TIA-568-C.1. Size conduits, wireways, and cable trays in accordance with TIA-569 and as indicated.
- b. Backbone Pathway: Telecommunication pathways from the telecommunications entrance facility to telecommunications rooms, and, telecommunications equipment rooms (backbone cabling): installed in accordance with TIA-569. Size conduits, wireways, and cable trays for telecommunications risers in accordance with TIA-569 and as indicated.

3.1.6 Busway Installation

Comply at minimum with NFPA 70. Install busways parallel with or at right angles to ceilings, walls, and structural members. Support busways at 5 foot maximum intervals, and brace to prevent lateral movement. Provide fixed type hinges on risers; spring-type are unacceptable. Provide

flanges where busway makes penetrations through walls and floors, and seal to maintain smoke and fire ratings. Provide waterproof curb where busway riser passes through floor. Seal gaps with fire-rated foam and caulk. Provide expansion joints, but only where bus duct crosses building expansion joints. Provide supports to resist forces of 0.5 times the equipment weight in any direction and 1.5 times the equipment weight in the downward direction.

3.1.7 Cable Tray Installation

Install cable trays parallel with or at right angles to ceilings, walls, and structural members. Support at maximum 6 foot intervals. In addition, install and ground telecommunications cable tray in accordance with TIA-569, and TIA-607 Ensure edges, fittings, and hardware are finished free from burrs and sharp edges. Provide No. 2 AWG bare copper wire throughout cable tray system, and bond to each section. Use No. 1/0 aluminum wire if cable tray is aluminum. Install conductors that run through smoke and fire partitions in 4 inch rigid steel conduits with grounding bushing, extending 12 inches beyond each side of partitions. Seal conduit on both ends to maintain smoke and fire ratings of partitions. Provide supports to resist forces of 0.5 times the equipment weight in any direction and 1.5 times the equipment weight in the downward direction.

3.1.8 Boxes, Outlets, and Supports

Provide boxes in wiring and raceway systems wherever required for pulling of wires, making connections, and mounting of devices or fixtures. Boxes for metallic raceways: cast-metal, hub-type when located in wet locations, when surface mounted on outside of exterior surfaces, when surface mounted on interior walls exposed up to 7 feet above floors and walkways, or when installed in hazardous areas and when specifically indicated. Boxes in other locations: sheet steel, except that aluminum boxes may be used with aluminum conduit, and nonmetallic boxes may be used with nonmetallic conduit system. Provide each box with volume required by NFPA 70 for number of conductors enclosed in box. Boxes for mounting lighting fixtures: minimum 4 inches square, or octagonal, except that smaller boxes may be installed as required by fixture configurations, as approved. Boxes for use in masonry-block or tile walls: square-cornered, tile-type, or standard boxes having square-cornered, tile-type covers. Provide gaskets for cast-metal boxes installed in wet locations and boxes installed flush with outside of exterior surfaces. Provide separate boxes for flush or recessed fixtures when required by fixture terminal operating temperature; provide readily removable fixtures for access to boxes unless ceiling access panels are provided. Support boxes and pendants for surface-mounted fixtures on suspended ceilings independently of ceiling supports. Fasten boxes and supports with wood screws on wood, with bolts and expansion shields on concrete or brick, with toggle bolts on hollow masonry units, and with machine screws or welded studs on steel. Threaded studs driven in by powder charge and provided with lock washers and nuts may be used in lieu of wood screws, expansion shields, or machine screws. In open overhead spaces, cast boxes threaded to raceways need not be separately supported except where used for fixture support; support sheet metal boxes directly from building structure or by bar hangers. Where bar hangers are used, attach bar to raceways on opposite sides of box, and support raceway with approved-type fastener maximum 24 inches from box. When penetrating reinforced concrete members, avoid cutting reinforcing steel.

3.1.8.1 Boxes

Boxes for use with raceway systems: minimum 1 1/2 inches deep, except where shallower boxes required by structural conditions are approved. Boxes for other than lighting fixture outlets: minimum 4 inches square, except that 4 by 2 inch boxes may be used where only one raceway enters outlet. Telecommunications outlets: a minimum of 5 inches square by 2 7/8 inches deep, except for wall mounted telephones and outlet boxes for handicap telephone stations. Mount outlet boxes flush in finished walls.

3.1.8.2 Pull Boxes

Construct of at least minimum size required by NFPA 70 of code-gauge aluminum or galvanized sheet steel, and compatible with nonmetallic raceway systems, except where cast-metal boxes are required in locations specified herein. Provide boxes with screw-fastened covers. Where several feeders pass through common pull box, tag feeders to indicate clearly electrical characteristics, circuit number, and panel designation.

3.1.9 Mounting Heights

Mount panelboards, enclosed circuit breakers, motor controller and disconnecting switches so height of operating handle at its highest position is maximum 78 inches above floor. Mount lighting switches 48 inches above finished floor. Mount receptacles and telecommunications outlets 18 inches above finished floor, unless otherwise indicated. Wall-mounted telecommunications outlets: mounted at height indicated. Mount other devices as indicated. Measure mounting heights of wiring devices and outlets in non-hazardous areas to center of device or outlet. Measure mounting heights of receptacle outlet boxes in the hazardous area to the bottom of the outlet box.

3.1.10 Conductor Identification

Provide conductor identification within each enclosure where tap, splice, or termination is made. For conductors No. 6 AWG and smaller diameter, provide color coding by factory-applied, color-impregnated insulation. For conductors No. 4 AWG and larger diameter, provide color coding by plastic-coated, self-sticking markers; colored nylon cable ties and plates; or heat shrink-type sleeves. Identify control circuit terminations in accordance with Section 23 09 00.00 22 INSTRUMENTATION AND CONTROL FOR HVAC. Provide telecommunications system conductor identification as specified in Section 27 10 00 BUILDING TELECOMMUNICATIONS CABLING SYSTEMS.

3.1.10.1 Marking Strips

Provide marking strips for identification of power distribution, control, data, and communications cables in accordance with the following:

- a. Provide white or other light-colored plastic marking strips, fastened by screws to each terminal block, for wire designations.
- b. Use permanent ink for the wire numbers
- c. Provide reversible marking strips to permit marking both sides, or provide two marking strips with each block.
- d. Size marking strips to accommodate the two sets of wire numbers.

- e. Assign a device designation in accordance with **NEMA ICS 1** to each device to which a connection is made. Mark each device terminal to which a connection is made with a distinct terminal marking corresponding to the wire designation used on the Contractor's schematic and connection diagrams.
- f. The wire (terminal point) designations used on the Contractor's wiring diagrams and printed on terminal block marking strips may be according to the Contractor's standard practice; however, provide additional wire and cable designations for identification of remote (external) circuits for the Government's wire designations.
- g. Prints of the **marking strips** drawings submitted for approval will be so marked and returned to the Contractor for addition of the designations to the terminal strips and tracings, along with any rearrangement of points required.

3.1.11 Splices

Make splices in accessible locations. Make splices in conductors No. 10 AWG and smaller diameter with insulated, pressure-type connector. Make splices in conductors No. 8 AWG and larger diameter with solderless connector, and cover with insulation material equivalent to conductor insulation.

3.1.11.1 Splices of Aluminum Conductors

Make with solderless circumferential compression-type, aluminum-bodied connectors UL listed for AL/CU. Remove surface oxides from aluminum conductors by wire brushing and immediately apply oxide-inhibiting joint compound and insert in connector. After joint is made, wipe away excess joint compound, and insulate splice.

3.1.12 Covers and Device Plates

Install with edges in continuous contact with finished wall surfaces without use of mats or similar devices. Plaster fillings are not permitted. Install plates with alignment tolerance of $1/16$ inch. Use of sectional-type device plates are not permitted. Provide gasket for plates installed in wet locations.

3.1.13 Electrical Penetrations

Seal openings around electrical penetrations through fire resistance-rated walls, partitions, floors, or ceilings in accordance with Section **07 84 00 FIRESTOPPING**.

3.1.14 Grounding and Bonding

Provide in accordance with **NFPA 70** and **NFPA 780**. Ground exposed, non-current-carrying metallic parts of electrical equipment, access flooring support system, metallic raceway systems, grounding conductor in metallic and nonmetallic raceways, telecommunications system grounds, and neutral conductor of wiring systems. Interconnect all grounding media in or on the structure to provide a common ground potential. This includes lightning protection, electrical service, telecommunications system grounds, as well as underground metallic piping systems. Make interconnection to the gas line on the customer's side of the meter. Use

main size lightning conductors for interconnecting these grounding systems to the lightning protection system. In addition to the requirements specified herein, provide telecommunications grounding in accordance with [TIA-607](#). Where ground fault protection is employed, ensure that connection of ground and neutral does not interfere with correct operation of fault protection.

3.1.14.1 Ground Rods

Provide ground rods and measure the resistance to ground using the fall-of-potential method described in [IEEE 81](#). Do not exceed 5 ohms under normally dry conditions for the maximum resistance of a driven ground. If the resultant resistance exceeds 5 ohms measured not less than 48 hours after rainfall, notify the Contracting Officer who will decide on the number of ground rods to add.

3.1.14.2 Grounding Connections

Make grounding connections which are buried or otherwise normally inaccessible, excepting specifically those connections for which access for periodic testing is required, by exothermic weld or high compression connector.

- a. Make exothermic welds strictly in accordance with the weld manufacturer's written recommendations. Welds which are "puffed up" or which show convex surfaces indicating improper cleaning are not acceptable. Mechanical connectors are not required at exothermic welds.
- b. Make high compression connections using a hydraulic or electric compression tool to provide the correct circumferential pressure. Provide tools and dies as recommended by the manufacturer. Use an embossing die code or other standard method to provide visible indication that a connector has been adequately compressed on the ground wire.

3.1.14.3 Ground Bus

Provide a copper ground bus in the electrical equipment rooms as indicated. Noncurrent-carrying metal parts of electrical equipment: effectively grounded by bonding to the ground bus. Bond the ground bus to both the entrance ground, and to a ground rod or rods as specified above having the upper ends terminating approximately 4 inches above the floor. Make connections and splices of the brazed, welded, bolted, or pressure-connector type, except use pressure connectors or bolted connections for connections to removable equipment.

3.1.14.4 Resistance

Maximum resistance-to-ground of grounding system: do not exceed 5 ohms under dry conditions. Where resistance obtained exceeds 5 ohms, contact Contracting Officer for further instructions.

3.1.14.5 Telecommunications System

Provide telecommunications grounding in accordance with the following:

- a. Telecommunications Grounding Busbars: Provide a telecommunications main grounding busbar (TMGB) in the telecommunications entrance

facility. Install the TMGB as close to the electrical service entrance grounding connection as practicable. Provide a telecommunications grounding busbar (TGB) in all other telecommunications rooms and telecommunications equipment rooms. Install the TGB as close to the telecommunications room panelboard as practicable, when equipped. Where a panelboard for telecommunications equipment is not installed in the telecommunications room, locate the TGB near the backbone cabling and associated terminations. In addition, locate the TGB to provide for the shortest and straightest routing of the grounding conductors. Where a panelboard for telecommunications equipment is located within the same room or space as a TGB, bond that panelboard's alternating current equipment ground (ACEG) bus (when equipped) or the panelboard enclosure to the TGB. Install telecommunications grounding busbars to maintain clearances as required by [NFPA 70](#) and insulated from its support. A minimum of [2 inches](#) separation from the wall is recommended to allow access to the rear of the busbar and adjust the mounting height to accommodate overhead or underfloor cable routing.

- b. Telecommunications Bonding Conductors: Provide main telecommunications service equipment ground consisting of separate bonding conductor for telecommunications, between the TMGB and readily accessible grounding connection of the electrical service. Grounding and bonding conductors should not be placed in ferrous metallic conduit. If it is necessary to place grounding and bonding conductors in ferrous metallic conduit that exceeds [3 feet](#) in length, bond the conductors to each end of the conduit using a grounding bushing or a No. 6 AWG conductor, minimum. Provide a telecommunications bonding backbone (TBB) that originates at the TMGB extends throughout the building using the telecommunications backbone pathways, and connects to the TGBs in all telecommunications rooms and equipment rooms. Install the TBB conductors such that they are protected from physical and mechanical damage. The TBB conductors should be installed without splices and routed in the shortest possible straight-line path. Make the bonding conductor between a TBB and a TGB continuous. Where splices are necessary, the number of splices should be a minimum. Make the splices accessible and located in telecommunications spaces. Connect joined segments of a TBB using exothermic welding, irreversible compression-type connectors, or equivalent. Install all joints to be adequately supported and protected from damage. Whenever two or more TBBs are used within a multistory building, bond the TBBs together with a grounding equalizer (GE) at the top floor and at a minimum of every third floor in between. Do not connect the TBB and GE to the pathway ground, except at the TMGB or the TGB.
- c. Telecommunications Grounding Connections: Telecommunications grounding connections to the TMGB or TGB: utilize listed compression two-hole lugs, exothermic welding, suitable and equivalent one hole non-twisting lugs, or other irreversible compression type connections. Bond all metallic pathways, cabinets, and racks for telecommunications cabling and interconnecting hardware located within the same room or space as the TMGB or TGB to the TMGB or TGB respectively. In a metal frame (structural steel) building, where the steel framework is readily accessible within the room; bond each TMGB and TGB to the vertical steel metal frame using a minimum No. 6 AWG conductor. Where the metal frame is external to the room and readily accessible, bond the metal frame to the TGB or TMGB with a minimum No. 6 AWG conductor. When practicable because of shorter distances and, where horizontal steel members are permanently electrically bonded to

vertical column members, the TGB may be bonded to these horizontal members in lieu of the vertical column members. All connectors used for bonding to the metal frame of a building must be listed for the intended purpose.

3.1.15 Equipment Connections

Provide power wiring for the connection of motors and control equipment under this section of the specification. Except as otherwise specifically noted or specified, automatic control wiring, control devices, and protective devices within the control circuitry are not included in this section of the specifications and are provided under the section specifying the associated equipment.

3.1.16 Elevator

Provide circuit to line terminals of elevator controller, and disconnect switch on line side of controller, outlet for control power, outlet receptacle and work light at midheight of elevator shaft, and work light and outlet receptacle in elevator pit.

3.1.17 Government-Furnished Equipment

Contractor rough-in for Government-furnished equipment to make equipment operate as intended, including providing miscellaneous items such as plugs, receptacles, wire, cable, conduit, flexible conduit, and outlet boxes or fittings.

3.1.18 Repair of Existing Work

Perform repair of existing work, demolition, and modification of existing electrical distribution systems as follows:

3.1.18.1 Workmanship

Lay out work in advance. Exercise care where cutting, channeling, chasing, or drilling of floors, walls, partitions, ceilings, or other surfaces is necessary for proper installation, support, or anchorage of conduit, raceways, or other electrical work. Repair damage to buildings, piping, and equipment using skilled craftsmen of trades involved.

3.1.18.2 Existing Concealed Wiring to be Removed

Disconnect existing concealed wiring to be removed from its source. Remove conductors; cut conduit flush with floor, underside of floor, and through walls; and seal openings.

3.1.18.3 Removal of Existing Electrical Distribution System

Removal of existing electrical distribution system equipment includes equipment's associated wiring, including conductors, cables, exposed conduit, surface metal raceways, boxes, and fittings, as indicated.

3.1.18.4 Continuation of Service

Maintain continuity of existing circuits of equipment to remain. Maintain existing circuits of equipment energized. Restore circuits wiring and power which are to remain but were disturbed during demolition back to original condition.

3.1.19 Surge Protective Devices

Connect the surge protective devices in parallel to the power source, keeping the conductors as short and straight as practically possible. Maximum allowed lead length is 3 feet avoiding 90 degree bends.

3.2 FIELD FABRICATED NAMEPLATE MOUNTING

Provide number, location, and letter designation of nameplates as indicated. Fasten nameplates to the device with a minimum of two sheet-metal screws or two rivets.

3.3 WARNING SIGN MOUNTING

Provide the number of signs required to be readable from each accessible side. Space the signs in accordance with NFPA 70E.

3.4 FIELD APPLIED PAINTING

Paint electrical equipment as required to match finish of adjacent surfaces or to meet the indicated or specified safety criteria. Painting: as specified in Section 09 90 00 PAINTS AND COATINGS.

3.5 FIELD QUALITY CONTROL

Furnish test equipment and personnel and submit written copies of test results. Give Contracting Officer 5 working days notice prior to each test.

3.5.1 Devices Subject to Manual Operation

Operate each device subject to manual operation at least five times, demonstrating satisfactory operation each time.

3.5.2 600-Volt Wiring Test

Test wiring rated 600 volt and less to verify that no short circuits or accidental grounds exist. Perform insulation resistance tests on wiring No. 6 AWG and larger diameter using instrument which applies voltage of 1,000 volts DC for 600 volt rated wiring and 500 volts DC for 300 volt rated wiring per NETA ATS to provide direct reading of resistance. All existing wiring to be reused shall also be tested.

3.5.3 Transformer Tests

Perform the standard, not optional, tests in accordance with the Inspection and Test Procedures for transformers, dry type, air-cooled, 600 volt and below; as specified in NETA ATS. Measure primary and secondary voltages for proper tap settings. Tests need not be performed by a recognized independent testing firm or independent electrical consulting firm.

3.5.4 Ground-Fault Receptacle Test

Test ground-fault receptacles with a "load" (such as a plug in light) to verify that the "line" and "load" leads are not reversed. Press the TEST button and then the RESET button to verify by LED status that the device is a self-test model as specified in UL 943.

3.5.5 Grounding System Test

Test grounding system to ensure continuity, and that resistance to ground is not excessive. Test each ground rod for resistance to ground before making connections to rod; tie grounding system together and test for resistance to ground. Make resistance measurements in dry weather, not earlier than 48 hours after rainfall. Submit written results of each test to Contracting Officer, and indicate location of rods as well as resistance and soil conditions at time measurements were made.

3.5.6 Phase Rotation Test

Perform phase rotation test to ensure proper rotation of service power prior to operation of new or reinstalled equipment using a phase rotation meter. Follow the meter manual directions performing the test.

-- End of Section --

SECTION 26 24 13

SWITCHBOARDS

05/15

PART 1 GENERAL

1.1 REFERENCES

The publications listed below form a part of this specification to the extent referenced. The publications are referred to in the text by the basic designation only.

AMERICAN NATIONAL STANDARDS INSTITUTE (ANSI)

ANSI C12.1 ((2014; Errata 2016) Electric Meters - Code for Electricity Metering

ASTM INTERNATIONAL (ASTM)

ASTM A123/A123M (2017) Standard Specification for Zinc (Hot-Dip Galvanized) Coatings on Iron and Steel Products

ASTM A153/A153M (2016a) Standard Specification for Zinc Coating (Hot-Dip) on Iron and Steel Hardware

ASTM A240/A240M (2020) Standard Specification for Chromium and Chromium-Nickel Stainless Steel Plate, Sheet, and Strip for Pressure Vessels and for General Applications

ASTM A653/A653M (2020) Standard Specification for Steel Sheet, Zinc-Coated (Galvanized) or Zinc-Iron Alloy-Coated (Galvannealed) by the Hot-Dip Process

ASTM A780/A780M (2020) Standard Practice for Repair of Damaged and Uncoated Areas of Hot-Dip Galvanized Coatings

ASTM D149 (2020) Dielectric Breakdown Voltage and Dielectric Strength of Solid Electrical Insulating Materials at Commercial Power Frequencies

ASTM D709 (2017) Standard Specification for Laminated Thermosetting Materials

ASTM D1535 (2014; R 2018) Standard Practice for Specifying Color by the Munsell System

INSTITUTE OF ELECTRICAL AND ELECTRONICS ENGINEERS (IEEE)

IEEE 81 (2012) Guide for Measuring Earth Resistivity, Ground Impedance, and Earth Surface Potentials of a Ground System

- IEEE 100 (2000; Archived) The Authoritative Dictionary of IEEE Standards Terms
- IEEE C2 (2017; Errata 1-2 2017; INT 1 2017) National Electrical Safety Code
- IEEE C37.90.1 (2013) Standard for Surge Withstand Capability (SWC) Tests for Relays and Relay Systems Associated with Electric Power Apparatus
- IEEE C57.12.28 (2014) Standard for Pad-Mounted Equipment - Enclosure Integrity
- IEEE C57.12.29 (2014) Standard for Pad-Mounted Equipment - Enclosure Integrity for Coastal Environments

INTERNATIONAL ELECTRICAL TESTING ASSOCIATION (NETA)

- NETA ATS (2017; Errata 2017) Standard for Acceptance Testing Specifications for Electrical Power Equipment and Systems

NATIONAL ELECTRICAL MANUFACTURERS ASSOCIATION (NEMA)

- ANSI/NEMA PB 2.1 (2013) General Instructions for Proper Handling, Installation, Operation and Maintenance of Deadfront Distribution Switchboards Rated 600 V or Less
- NEMA ICS 6 (1993; R 2016) Industrial Control and Systems: Enclosures
- NEMA PB 2 (2011) Deadfront Distribution Switchboards
- NEMA ST 20 (2014) Dry-Type Transformers for General Applications

NATIONAL FIRE PROTECTION ASSOCIATION (NFPA)

- NFPA 70 (2020; ERTA 20-1 2020; ERTA 20-2 2020; TIA 20-1; TIA 20-2; TIA 20-3; TIA 20-4) National Electrical Code

UNDERWRITERS LABORATORIES (UL)

- UL 467 (2013; Reprint Jun 2017) UL Standard for Safety Grounding and Bonding Equipment
- UL 489 (2016) UL Standard for Safety Molded-Case Circuit Breakers, Molded-Case Switches and Circuit-Breaker Enclosures
- UL 891 (2005; Reprint Oct 2012) Switchboards

1.2 RELATED REQUIREMENTS

Section 26 08 00 APPARATUS INSPECTION AND TESTING applies to this section, with the additions and modifications specified herein.

1.3 DEFINITIONS

Unless otherwise specified or indicated, electrical and electronics terms used in these specifications, and on the drawings, are as defined in IEEE 100.

1.4 SUBMITTALS

Government approval is required for submittals with a "G" designation; submittals not having a "G" designation are for Contractor QC approval. Submittals with an "S" are for inclusion in the Sustainability eNotebook, in conformance to Section 01 33 29, SUSTAINABILITY REPORTING. Submit the following in accordance with Section 01 33 00 SUBMITTAL PROCEDURES:

SD-02 Shop Drawings

Switchboard Drawings; G

SD-03 Product Data

Switchboard; G

SD-06 Test Reports

Switchboard Design Tests; G

Switchboard Production Tests; G

Acceptance Checks and Tests; G

SD-07 Certificates

Cybersecurity Equipment Certification; G

Submit certification indicating conformance with the paragraph CYBERSECURITY EQUIPMENT CERTIFICATION.

Cybersecurity Installation Certification; G

Submit certification indicating conformance with the paragraph CYBERSECURITY INSTALLATION CERTIFICATION.

SD-10 Operation and Maintenance Data

Switchboard Operation and Maintenance, Data Package 5; G

SD-11 Closeout Submittals

Assembled Operation and Maintenance Manuals; G

Equipment Test Schedule; G

Required Settings; G

Service Entrance Available Fault Current Label; G

1.5 QUALITY ASSURANCE

1.5.1 Product Data

Include manufacturer's information on each submittal for each component, device and accessory provided with the switchboard including:

- a. Circuit breaker type, interrupting rating, and trip devices, including available settings.
- b. Manufacturer's instruction manuals and published time-current curves (in electronic format) of the main secondary breaker and largest secondary feeder device.

1.5.2 Switchboard Drawings

Include wiring diagrams and installation details of equipment indicating proposed location, layout and arrangement, control panels, accessories, piping, ductwork, and other items that must be shown to ensure a coordinated installation. Identify circuit terminals on wiring diagrams and indicate the internal wiring for each item of equipment and the interconnection between each item of equipment. Indicate on the drawings adequate clearance for operation, maintenance, and replacement of operating equipment devices. Include the nameplate data, size, and capacity on submittal. Also include applicable federal, military, industry, and technical society publication references on submittals. Include the following:

- a. One-line diagram including breakers, fuses, current transformers, and meters.
- b. Outline drawings including front elevation, section views, footprint, and overall dimensions.
- c. Bus configuration including dimensions and ampere ratings of bus bars.
- d. Markings and NEMA nameplate data, including fuse information (manufacturer's name, catalog number, and ratings).
- e. Circuit breaker type, interrupting rating, and trip devices, including available settings.
- f. Wiring diagrams and elementary diagrams with terminals identified, and indicating prewired interconnections between items of equipment and the interconnection between the items.
- g. Manufacturer's instruction manuals and published time-current curves (in electronic format) of the main secondary breaker and largest secondary feeder device. Use this information (designer of record) to provide breaker settings that ensures protection and coordination are achieved. For Navy installations, provide electronic format curves using EasyPower device library format depending on installation modeling software requirements.

1.5.3 Regulatory Requirements

In each of the publications referred to herein, consider the advisory

provisions to be mandatory, as though the word, "shall" or "must" had been substituted for "should" wherever it appears. Interpret references in these publications to the "authority having jurisdiction," or words of similar meaning, to mean the Contracting Officer. Provide equipment, materials, installation, and workmanship in accordance with the mandatory and advisory provisions of NFPA 70 unless more stringent requirements are specified or indicated.

1.5.4 Standard Products

Provide materials and equipment that are products of manufacturers regularly engaged in the production of such products which are of equal material, design and workmanship, and:

- a. Have been in satisfactory commercial or industrial use for 2 years prior to bid opening including applications of equipment and materials under similar circumstances and of similar size.
- b. Have been on sale on the commercial market through advertisements, manufacturers' catalogs, or brochures during the 2-year period.
- c. Where two or more items of the same class of equipment are required, provide products of a single manufacturer; however, the component parts of the item need not be the products of the same manufacturer unless stated in this section.

1.5.4.1 Alternative Qualifications

Products having less than a 2-year field service record will be acceptable if a certified record of satisfactory field operation for not less than 6000 hours, exclusive of the manufacturers' factory or laboratory tests, is furnished.

1.5.4.2 Material and Equipment Manufacturing Date

Products manufactured more than 1 year prior to date of delivery to site are not acceptable.

1.6 MAINTENANCE

1.6.1 Switchboard Operation and Maintenance Data

Submit Operation and Maintenance Manuals in accordance with Section 01 78 23 OPERATION AND MAINTENANCE DATA.

1.6.2 Assembled Operation and Maintenance Manuals

Assemble and securely bind manuals in durable, hard covered, water resistant binders. Assemble and index the manuals in the following order with a table of contents:

- a. Manufacturer's O&M information required by the paragraph SD-10, OPERATION AND MAINTENANCE DATA.
- b. Catalog data required by the paragraph SD-03, PRODUCT DATA.
- c. Drawings required by the paragraph SD-02, SHOP DRAWINGS.
- d. Prices for spare parts and supply list.

- e. Information on metering.
- f. Design test reports.
- g. Production test reports.

1.7 WARRANTY

Provide equipment items that are supported by service organizations reasonably convenient to the equipment installation in order to render satisfactory service to the equipment on a regular and emergency basis during the warranty period of the contract.

PART 2 PRODUCTS

2.1 PRODUCT COORDINATION

Products and materials not considered to be switchboards and related accessories are specified in Section 33 71 02 UNDERGROUND ELECTRICAL DISTRIBUTION, and Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM.

2.2 SWITCHBOARD

NEMA PB 2 and UL 891.

2.2.1 Ratings

Provide equipment with the following ratings:

- a. Voltage rating: 480Y/277 volts AC, three-phase, 4-wire.
- b. Continuous current rating of the main bus: as indicated.
- c. Short-circuit current rating: as indicated.
- d. UL listed and labeled as service entrance equipment.

2.2.2 Construction

Provide the following:

- a. Switchboard: consisting of one or more vertical sections bolted together to form a rigid assembly and rear aligned as indicated.
- b. All circuit breakers: front accessible.
- c. Rear aligned switchboards: front accessible load connections.
- d. Where indicated, "space for future" or "space" means to include a vertical bus provided behind a blank front cover. Where indicated, "provision for future" means full hardware provided to mount a breaker suitable for the location.
- e. Completely factory engineered and assembled, including protective devices and equipment indicated with necessary interconnections, instrumentation, and control wiring.

2.2.2.1 Enclosure

Provide the following:

- a. Enclosure: NEMA ICS 6 Type 1 enclosure for indoor installation or NEMA 4X fabricated entirely of 12 gauge ASTM A240/A240M type 304 or 304L stainless steel for outdoor installation, as indicated on plans.
- b. Enclosure: bolted together with removable bolt-on side and rear covers.
- c. Front doors: provided with stainless steel padlockable vault handles with a three point catch.
- d. Bases, frames and channels of enclosure: corrosion resistant and fabricated of ASTM A240/A240M type 304 or 304L stainless steel for outdoor installation or galvanized steel for indoor installation.
- e. Base: includes any part of enclosure that is within 3 inches of concrete pad.
- f. Galvanized steel: ASTM A123/A123M, ASTM A653/A653M G90 coating, and ASTM A153/A153M, as applicable. Galvanize after fabrication where practicable.
- g. Paint color: ASTM D1535 light gray No. 61 or No. 49 over rust inhibitor.
- h. Paint coating system: comply with IEEE C57.12.28 for galvanized steel and IEEE C57.12.29 for stainless steel.

2.2.2.2 Bus Bars

Provide the following:

- a. Bus bars: copper with silver-plated contact surfaces.
 - (1) Phase bus bars: insulated with a tape wrap or insulating sleeve providing a minimum breakdown voltage of 16,000 volts per ASTM D149.
 - (2) Neutral bus: rated 100 percent of the main bus continuous current rating as indicated.
- b. Make bus connections and joints with hardened steel bolts.
- c. Main-bus (through bus): rated at the full ampacity of the main throughout the switchboard.
- d. Minimum one-quarter by 2 inch copper ground bus secured to each vertical section along the entire length of the switchboard.

2.2.2.3 Main Section

Provide the main section consisting of an individually mounted fixed air power circuit breaker or insulated-case circuit breaker, as indicated.

2.2.2.4 Distribution Sections

Provide the distribution sections consisting of individually mounted, insulated-case circuit breakers and/or molded-case circuit breakers as

indicated.

2.2.2.5 Auxiliary Sections

Provide auxiliary sections consisting of indicated metering equipment, control equipment, current transformer compartments as indicated.

2.2.2.6 Handles

Provide handles for individually mounted devices of the same design and method of external operation. Label handles prominently to indicate device ampere rating, color coded for device type. Identify ON-OFF indication by handle position and by prominent marking.

2.2.3 Protective Device

Provide main and branch protective devices as indicated.

2.2.3.1 Insulated-Case Breaker

Provide the following:

- a. **UL 489**. UL listed and labeled, 100 percent rated main breaker, manually operated, low voltage, insulated-case circuit breaker, with a short-circuit current rating as indicated at **480Y/277** volts.
- b. Breaker frame size: as indicated.
- c. Series rated circuit breakers are unacceptable.

2.2.3.2 Molded-Case Circuit Breaker

Provide the following:

- a. **UL 489**. UL listed and labeled, standard rated branch breakers, manually operated, low voltage molded-case circuit breaker, with a short-circuit current rating of as indicated at **480Y/277** volts.
- b. Breaker frame size: as indicated.
- c. Series rated circuit breakers are unacceptable.

2.2.4 Electronic Trip Units

Equip main and distribution breakers as indicated with a solid-state tripping system consisting of three current sensors and a microprocessor-based trip unit that provides true rms sensing adjustable time-current circuit protection. Include the following:

- a. Current sensors ampere rating: as indicated.
- b. Trip unit ampere rating: as indicated.
- c. Ground fault protection: as indicated.
- d. Electronic trip units: provide additional features as indicated:
 - (1) Indicated Breakers: include long delay pick-up and time settings, and LED indication of cause of circuit breaker trip.

- (2) Main breakers: include short delay pick-up and time settings and, instantaneous settings and ground fault settings as indicated.
- (3) Distribution breakers: include short delay pick-up and time settings, instantaneous settings as indicated.
- (8) For electronic trip units that are rated for or can be adjusted to 1,200 amperes or higher, provide arc energy reduction capability with an energy-reducing maintenance switch with local status indicator.

2.2.5 Metering

2.2.5.1 Digital Meters

IEEE C37.90.1 for surge withstand. Provide true rms, plus/minus one percent accuracy, programmable, microprocessor-based meter enclosed in a sealed case with the following features.

a. Display capability:

- (1) Multi-Function Meter: Display a selected phase to neutral voltage, phase to phase voltage, percent phase to neutral voltage THD, percent phase to phase voltage THD; a selected phase current, neutral current, percent phase current THD, percent neutral current; selected total PF, kW, KVA, kVAR, FREQ, kVAh, kWh. Detected alarm conditions include over/under current, over/under voltage, over/under KVA, over/under frequency, over/under selected PF/kVAR, voltage phase reversal, voltage imbalance, reverse power, over percent THD. Include a Form C KYZ pulse output relay on the meter.
- b. Design meters to accept input from standard 5A secondary instrument transformers and direct voltage monitoring range to 600 volts, phase to phase.
- c. Provide programming via a front panel display and a communication interface accessible by a computer.
- d. Provide password secured programming stored in non-volatile EEPROM memory.
- e. Provide digital communications in a Modbus RTU protocol via a RS485 serial port and an independently addressable RS485 serial port.
- f. Provide meter that calculates and stores average max/min demand values with time and date for all readings based on a user selectable sliding window averaging period.
- g. Provide meter with programmable hi/low set limits with two Form C dry contact relays when exceeding alarm conditions.
- h. Provide meter with a display of Total Harmonic Distortion (THD) measurement to a minimum of the thirty-first order.
- i. Include historical trend logging capability with the ability to store up to 100,000 data points with intervals of 1 second to 180 minutes. Provide a unit that can store and time stamp up to 1000 programmable

triggered conditions.

- j. Provide event waveform recording triggered by the rms of 2 cycles of voltage or current exceeding programmable set points. Store waveforms for all 6 channels of voltage and current for a minimum of 10 cycles prior to the event and 50 cycles past the event.

2.2.5.2 Electronic Watthour Meter

Provide as specified in Section 26 27 14.00 20 ELECTRICITY METERING.

2.2.6 Heaters

Provide 120-volt heaters in each switchboard section. Provide heaters of sufficient capacity to control moisture condensation in the section, 250 watts minimum, and controlled by a thermostat located in the section. Provide industrial type thermostat, high limit, to maintain sections within the range of 60 to 90 degrees F. Obtain supply voltage for the heaters from a control power transformer within the switchboard. If heater voltage is different than switchboard voltage, provide transformer rated to carry 125 percent of heater full load rating. Provide transformer with a 220 degrees C insulation system with a temperature rise not exceeding 115 degrees C and conforming to NEMA ST 20.

2.2.7 Terminal Boards

Provide with engraved plastic terminal strips and screw type terminals for external wiring between components and for internal wiring between removable assemblies. Provide short-circuiting type terminal boards associated with current transformer. Terminate conductors for current transformers with ring-tongue lugs. Provide terminal board identification that is identical in similar units. Provide color coded external wiring that is color coded consistently for similar terminal boards.

2.2.8 Wire Marking

Mark control and metering conductors at each end. Provide factory installed, white, plastic tubing, heat stamped with black block type letters on factory-installed wiring. On field-installed wiring, provide white, preprinted, polyvinyl chloride (PVC) sleeves, heat stamped with black block type letters. Provide a single letter or number on each sleeve, elliptically shaped to securely grip the wire, and keyed in such a manner to ensure alignment with adjacent sleeves. Provide specific wire markings using the appropriate combination of individual sleeves. Indicate on each wire marker the device or equipment, including specific terminal number to which the remote end of the wire is attached.

2.3 MANUFACTURER'S NAMEPLATE

Provide a nameplate on each item of equipment bearing the manufacturer's name, address, model number, and serial number securely affixed in a conspicuous place; the nameplate of the distributing agent is not acceptable. This nameplate and method of attachment may be the manufacturer's standard if it contains the required information.

2.4 FIELD FABRICATED NAMEPLATES

ASTM D709. Provide laminated plastic nameplates for each switchboard,

equipment enclosure, relay, switch, and device; as specified in this section or as indicated on the drawings. Identify on each nameplate inscription the function and, when applicable, the position. Provide nameplates of melamine plastic, 0.125 inch thick, white with black center core. Provide red laminated plastic label with white center core where indicated. Provide matte finish surface. Provide square corners. Accurately align lettering and engrave into the core. Provide nameplates with minimum size of one by 2.5 inches. Provide lettering that is a minimum of 0.25 inch high normal block style.

2.5 SOURCE QUALITY CONTROL

2.5.1 Equipment Test Schedule

The Government reserves the right to witness tests. Provide equipment test schedules for tests to be performed at the manufacturer's test facility. Submit required test schedule and location, and notify the Contracting Officer 30 calendar days before scheduled test date. Notify Contracting Officer 15 calendar days in advance of changes to scheduled date.

Provide the following as part of test equipment calibration:

- a. Provide a calibration program which assures that all applicable test instruments are maintained within rated accuracy.
- b. Accuracy: Traceable to the National Institute of Standards and Technology.
- c. Instrument calibration frequency schedule: less than or equal to 12 months for both test floor instruments and leased specialty equipment.
- d. Dated calibration labels: visible on all test equipment.
- e. Calibrating standard: higher accuracy than that of the instrument tested.
- f. Keep up-to-date records that indicate dates and test results of instruments calibrated or tested. For instruments calibrated by the manufacturer on a routine basis, in lieu of third party calibration, include the following:
 - (1) Maintain up-to-date instrument calibration instructions and procedures for each test instrument.
 - (2) Identify the third party/laboratory calibrated instrument to verify that calibrating standard is met.

2.5.2 Switchboard Design Tests

NEMA PB 2 and UL 891.

2.5.2.1 Design Tests

Furnish documentation showing the results of design tests on a product of the same series and rating as that provided by this specification.

- a. Short-circuit current test.

- b. Enclosure tests.
- c. Dielectric test.

2.5.3 Switchboard Production Tests

NEMA PB 2 and UL 891. Furnish reports which include results of production tests performed on the actual equipment for this project. These tests include:

- a. 60-hertz dielectric tests.
- b. Mechanical operation tests.
- c. Electrical operation and control wiring tests.
- d. Ground fault sensing equipment test.

2.5.4 Cybersecurity Equipment Certification

Furnish a certification that control systems are designed and tested in accordance with DoD Instruction 8500.01, DoD Instruction 8510.01, and as required by individual Service Implementation Policy.

2.6 COORDINATED POWER SYSTEM PROTECTION

Provide a power system study as specified in Section 26 28 01.00 10 COORDINATED POWER SYSTEM PROTECTION.

2.7 ARC FLASH WARNING LABEL

Provide warning label for switchboards. Locate this self-adhesive warning label on the outside of the enclosure warning of potential electrical arc flash hazards and appropriate PPE required. Provide label format as indicated.

2.8 SERVICE ENTRANCE AVAILABLE FAULT CURRENT LABEL

Provide label on exterior of switchboards used as service equipment listing the maximum available fault current at that location. Include on the label the date that the fault calculation was performed and the contact information for the organization that completed the calculation. Locate this self-adhesive warning label on the outside of the switchboard. Provide label format as indicated.

PART 3 EXECUTION

3.1 INSTALLATION

Conform to IEEE C2, NFPA 70, and to the requirements specified herein. Provide new equipment and materials unless indicated or specified otherwise.

3.2 GROUNDING

NFPA 70 and IEEE C2, except that grounds and grounding systems with a resistance to solid earth ground not exceeding 5 ohms.

3.2.1 Grounding Electrodes

Provide driven ground rods as specified in Section 33 71 02 UNDERGROUND ELECTRICAL DISTRIBUTION. Connect ground conductors to the upper end of the ground rods by exothermic weld or compression connector. Provide compression connectors at equipment end of ground conductors.

3.2.2 Equipment Grounding

Provide bare copper cable not smaller than No. 4/0 AWG not less than 24 inches below grade connecting to the indicated ground rods. When work in addition to that indicated or specified is directed to obtain the specified ground resistance, the provision of the contract covering "Changes" applies.

3.2.3 Connections

Make joints in grounding conductors and loops by exothermic weld or compression connector. Install exothermic welds and compression connectors as specified in Section 33 71 02 UNDERGROUND ELECTRICAL DISTRIBUTION.

3.2.4 Grounding and Bonding Equipment

UL 467, except as indicated or specified otherwise.

3.3 INSTALLATION OF EQUIPMENT AND ASSEMBLIES

Install and connect equipment furnished under this section as indicated on project drawings, the approved shop drawings, and as specified herein.

3.3.1 Switchboard

ANSI/NEMA PB 2.1.

3.3.2 Meters and Instrument Transformers

ANSI C12.1.

3.3.3 Field Applied Painting

Where field painting of enclosures is required to correct damage to the manufacturer's factory applied coatings, provide manufacturer's recommended coatings and apply in accordance with manufacturer's instructions.

3.3.4 Galvanizing Repair

Repair damage to galvanized coatings using ASTM A780/A780M, zinc rich paint, for galvanizing damaged by handling, transporting, cutting, welding, or bolting. Do not heat surfaces that repair paint has been applied to.

3.3.5 Field Fabricated Nameplate Mounting

Provide number, location, and letter designation of nameplates as indicated. Fasten nameplates to the device with a minimum of two sheet-metal screws or two rivets.

3.4 FOUNDATION FOR EQUIPMENT AND ASSEMBLIES

3.4.1 Exterior Location

Mount switchboard on concrete slab as follows:

- a. Unless otherwise indicated, provide the slab with dimensions at least **8 inches** thick, reinforced with a **6 by 6 inch** No. 6 mesh placed uniformly **4 inches** from the top of the slab.
- b. Place slab on a **6 inch** thick, well-compacted gravel base.
- c. Install slab such that the top of the concrete slab is approximately **4 inches** above the finished grade.
- d. Provide edges above grade **1/2 inch** chamfer.
- e. Provide slab of adequate size to project at least **8 inches** beyond the equipment.
- f. Provide conduit turnups and cable entrance space required by the equipment to be mounted.
- g. Seal voids around conduit openings in slab with water- and oil-resistant caulking or sealant.
- h. Cut off and bush conduits **3 inches** above slab surface.
- i. Provide concrete work as specified in Section **03 30 00** CAST-IN-PLACE CONCRETE.

3.4.2 Interior Location

Mount switchboard on concrete slab as follows:

- a. Unless otherwise indicated, provide the slab with dimensions at least **4 inches** thick.
- b. Install slab such that the top of the concrete slab is approximately **4 inches** above the finished grade.
- c. Provide edges above grade **1/2 inch** chamfer.
- d. Provide slab of adequate size to project at least **8 inches** beyond the equipment.
- e. Provide conduit turnups and cable entrance space required by the equipment to be mounted.
- f. Seal voids around conduit openings in slab with water- and oil-resistant caulking or sealant.
- g. Cut off and bush conduits **3 inches** above slab surface.
- h. Provide concrete work as specified in Section **03 30 00** CAST-IN-PLACE CONCRETE.

3.5 FIELD QUALITY CONTROL

Submit [Required Settings](#) of breakers to the Contracting Officer after approval of switchboard and at least 30 days in advance of their requirement.

3.5.1 Performance of [Acceptance Checks and Tests](#)

Perform in accordance with the manufacturer's recommendations and include the following visual and mechanical inspections and electrical tests, performed in accordance with [NETA ATS](#).

3.5.1.1 Switchboard Assemblies

a. Visual and Mechanical Inspection

- (1) Compare equipment nameplate data with specifications and approved shop drawings.
- (2) Inspect physical, electrical, and mechanical condition.
- (3) Verify appropriate anchorage, required area clearances, and correct alignment.
- (4) Clean switchboard and verify shipping bracing, loose parts, and documentation shipped inside cubicles have been removed.
- (5) Inspect all doors, panels, and sections for paint, dents, scratches, fit, and missing hardware.
- (6) Verify that circuit breaker sizes and types correspond to approved shop drawings as well as to the circuit breaker's address for microprocessor-communication packages.
- (7) Verify that current transformer ratios correspond to approved shop drawings.
- (8) Inspect all bolted electrical connections for high resistance using low-resistance ohmmeter, verifying tightness of accessible bolted electrical connections by calibrated torque-wrench method, or performing thermographic survey.
- (9) Confirm correct operation and sequencing of electrical and mechanical interlock systems.
- (10) Confirm correct application of manufacturer's recommended lubricants.
- (11) Inspect insulators for evidence of physical damage or contaminated surfaces.
- (12) Verify correct barrier installation and operation.
- (13) Exercise all active components.
- (14) Inspect all mechanical indicating devices for correct operation.
- (15) Verify that filters are in place and vents are clear.

(16) Test operation, alignment, and penetration of instrument transformer withdrawal disconnects.

(17) Inspect control power transformers.

b. Electrical Tests

(1) Perform insulation-resistance tests on each bus section.

(2) Perform dielectric withstand voltage tests.

(3) Perform insulation-resistance test on control wiring; Do not perform this test on wiring connected to solid-state components.

(4) Perform control wiring performance test.

(5) Perform primary current injection tests on the entire current circuit in each section of assembly.

(7) Verify operation of switchboard heaters.

3.5.1.2 Circuit Breakers

Low Voltage - Insulated-Case and Low Voltage Molded Case with Solid State Trips

a. Visual and Mechanical Inspection

(1) Compare nameplate data with specifications and approved shop drawings.

(2) Inspect circuit breaker for correct mounting.

(3) Operate circuit breaker to ensure smooth operation.

(4) Inspect case for cracks or other defects.

(5) Inspect all bolted electrical connections for high resistance using low resistance ohmmeter, verifying tightness of accessible bolted connections and/or cable connections by calibrated torque-wrench method, or performing thermographic survey.

(6) Inspect mechanism contacts and arc chutes in unsealed units.

b. Electrical Tests

(1) Perform contact-resistance tests.

(2) Perform insulation-resistance tests.

(3) Perform Breaker adjustments for final settings in accordance with Government provided settings.

(4) Perform long-time delay time-current characteristic tests

(5) Determine short-time pickup and delay by primary current injection.

(6) Determine ground-fault pickup and time delay by primary current injection.

- (7) Determine instantaneous pickup current by primary injection.
- (8) Verify correct operation of any auxiliary features such as trip and pickup indicators, zone interlocking, electrical close and trip operation, trip-free, and anti-pump function.

3.5.1.3 Current Transformers

a. Visual and Mechanical Inspection

- (1) Compare equipment nameplate data with specifications and approved shop drawings.
- (2) Inspect physical and mechanical condition.
- (3) Verify correct connection.
- (4) Verify that adequate clearances exist between primary and secondary circuit.
- (5) Inspect all bolted electrical connections for high resistance using low-resistance ohmmeter, verifying tightness of accessible bolted electrical connections by calibrated torque-wrench method, or performing thermographic survey.
- (6) Verify that all required grounding and shorting connections provide good contact.

b. Electrical Tests

- (1) Perform resistance measurements through all bolted connections with low-resistance ohmmeter, if applicable.
- (2) Perform insulation-resistance tests.
- (3) Perform polarity tests.
- (4) Perform ratio-verification tests.

3.5.1.4 Metering and Instrumentation

a. Visual and Mechanical Inspection

- (1) Compare equipment nameplate data with specifications and approved shop drawings.
- (2) Inspect physical and mechanical condition.
- (3) Verify tightness of electrical connections.

b. Electrical Tests

- (1) Determine accuracy of meters at 25, 50, 75, and 100 percent of full scale.
- (2) Calibrate watthour meters according to manufacturer's published data.

- (3) Verify all instrument multipliers.
- (4) Electrically confirm that current transformer and voltage transformer secondary circuits are intact.

3.5.1.5 Grounding System

a. Visual and Mechanical Inspection

- (1) Inspect ground system for compliance with contract plans and specifications.

b. Electrical Tests

- (1) **IEEE 81**. Perform ground-impedance measurements utilizing the fall-of-potential method. On systems consisting of interconnected ground rods, perform tests after interconnections are complete. On systems consisting of a single ground rod perform tests before any wire is connected. Take measurements in normally dry weather, not less than 48 hours after rainfall. Use a portable ground resistance tester in accordance with manufacturer's instructions to test each ground or group of grounds. Use an instrument equipped with a meter reading directly in ohms or fractions thereof to indicate the ground value of the ground rod or grounding systems under test.
- (2) Submit the measured ground resistance of each ground rod and grounding system, indicating the location of the rod and grounding system. Include the test method and test setup (i.e., pin location) used to determine ground resistance and soil conditions at the time the measurements were made.

3.5.1.6 [Cybersecurity Installation Certification](#)

Furnish a certification that control systems are installed in accordance with DoD Instruction 8500.01, DoD Instruction 8510.01, and as required by individual Service Implementation Policy.

3.5.2 Follow-Up Verification

Upon completion of acceptance checks, settings, and tests, show by demonstration in service that circuits and devices are in good operating condition and properly performing the intended function. Trip circuit breakers by operation of each protective device. Test each item to perform its function not less than three times. As an exception to requirements stated elsewhere in the contract, provide the Contracting Officer 5 working days advance notice of the dates and times for checks, settings, and tests.

-- End of Section --

SECTION 26 27 14.00 20

ELECTRICITY METERING

02/11

PART 1 GENERAL

1.1 REFERENCES

The publications listed below form a part of this specification to the extent referenced. The publications are referred to within the text by the basic designation only.

INSTITUTE OF ELECTRICAL AND ELECTRONICS ENGINEERS (IEEE)

- IEEE C2 (2017; Errata 1-2 2017; INT 1 2017)
National Electrical Safety Code
- IEEE C37.90.1 (2013) Standard for Surge Withstand
Capability (SWC) Tests for Relays and
Relay Systems Associated with Electric
Power Apparatus
- IEEE C57.13 (2016) Requirements for Instrument
Transformers
- IEEE Stds Dictionary (2009) IEEE Standards Dictionary: Glossary
of Terms & Definitions

INTERNATIONAL ELECTRICAL TESTING ASSOCIATION (NETA)

- NETA ATS (2017; Errata 2017) Standard for
Acceptance Testing Specifications for
Electrical Power Equipment and Systems

NATIONAL ELECTRICAL MANUFACTURERS ASSOCIATION (NEMA)

- ANSI C12.1 ((2014; Errata 2016) Electric Meters -
Code for Electricity Metering
- ANSI C12.18 (2006) Protocol Specification for ANSI
Type 2 Optical Port
- ANSI C12.20 (2015; E 2018) Electricity Meters - 0.1,
0.2, and 0.5 Accuracy Classes
- ANSI C12.7 (2005) Requirements for Watthour Meter
Sockets
- NEMA C12.19 (2008) Utility Industry End Device Data
Tables

NATIONAL FIRE PROTECTION ASSOCIATION (NFPA)

- NFPA 70 (2020; ERTA 20-1 2020; ERTA 20-2 2020; TIA
20-1; TIA 20-2; TIA 20-3; TIA 20-4)
National Electrical Code

1.2 DEFINITIONS

Unless otherwise specified or indicated, electrical and electronics terms used in these specifications, and on the drawings, shall be as defined in IEEE Stds Dictionary.

1.3 SUBMITTALS

Government approval is required for submittals with a "G" designation; submittals not having a "G" designation are for Contractor Quality Control approval.

Technical data packages consisting of technical data and computer software (meaning technical data which relates to computer software) which are specifically identified in this project and which may be defined/required in other specifications shall be delivered strictly in accordance with the CONTRACT CLAUSES and in accordance with the Contract Data Requirements List, DD Form 1423. Data delivered shall be identified by reference to the particular specification paragraph against which it is furnished. All submittals not specified as technical data packages are considered 'shop drawings' under the Federal Acquisition Regulation Supplement (FARS) and shall contain no proprietary information and be delivered with unrestricted rights.

Submittals with an "S" are for inclusion in the Sustainability eNotebook, in conformance to Section 01 33 29.05 20 SUSTAINABILITY REPORTING FOR DESIGN-BUILD. Submit the following in accordance with Section 01 33 00.05 20 CONSTRUCTION SUBMITTAL PROCEDURES:

SD-02 Shop Drawings

Installation Drawings; G, S

SD-03 Product Data

Electricity meters; G, S

The most recent meter product data shall be submitted as a Technical Data Package and shall be licensed to the project site. Any software shall be submitted on CD-ROM and 5 hard copies of the software user manual shall be submitted for each piece of software provided.

Current transformer; G

Potential transformer; G

External communications devices; G

Configuration Software; G

The most recent version of the configuration software for each type (manufacturer and model) shall be submitted as a Technical Data Package and shall be licensed to the project site. Software shall be submitted on CD-ROM and 5 hard copies of the software user manual shall be submitted for each piece of software provided.

SD-06 Test Reports

Acceptance checks and tests

System functional verification

Building meter installation sheet, per building

Completed meter installation schedule

Completed meter data schedule

Meter configuration template

Contractor shall fill in the meter configuration template and submit to the Activity for concurrence.

Meter configuration report; G

The meter configuration report shall be submitted as a Technical Data Package.

SD-10 Operation and Maintenance Data

Electricity Meters and Accessories, Data Package 5; G

Submit operation and maintenance data in accordance with Section 01 78 23 OPERATION AND MAINTENANCE DATA and as specified herein.

SD-11 Closeout Submittals

System functional verification

1.4 QUALITY ASSURANCE

1.4.1 Installation Drawings

Drawings shall be provided in hard-copy and electronic format, and shall include but not be limited to the following:

- a. Wiring diagrams with terminals identified of advanced meter, current transformers, potential transformers, protocol modules, communications interfaces, Ethernet connections, . For each typical meter installation, provide a diagram.
- b. One-line diagram, including meters, switch(es), current transformers, potential transformers, protocol modules, communications interfaces, Ethernet connections, telephone outlets, and fuses. For each typical meter installation, provide a diagram.

1.4.2 Standard Products

Provide materials and equipment that are products of manufacturers regularly engaged in the production of such products which are of equal material, design and workmanship. Products shall have been in satisfactory commercial or industrial use for 1 year prior to bid opening. The 1-year period shall include applications of equipment and materials under similar circumstances and of similar size. The product, or an earlier release of the product, shall have been on sale on the commercial market through advertisements, manufacturers catalogs, or brochures during the prior 1-year period. Where two or more items of the same class of

equipment are required, these items shall be products of a single manufacturer; however, the component parts of the item need not be the products of the same manufacturer unless stated in this section.

1.4.3 Material and Equipment Manufacturing Data

Products manufactured more than 1 year prior to date of delivery to site shall not be used, unless specified otherwise.

1.5 MAINTENANCE

1.5.1 Additions to Operation and Maintenance Data

In addition to requirements of Data Package 5, include the following on the actual **electricity meters and accessories** provided:

- a. A condensed description of how the system operates
- b. Block diagram indicating major assemblies
- c. Troubleshooting information
- d. Preventive maintenance
- e. Prices for spare parts and supply list

1.6 WARRANTY

The equipment items and software shall be supported by service organizations which are reasonably convenient to the equipment installation in order to render satisfactory service to the equipment and software on a regular and emergency basis during the warranty period of the contract.

1.7 SYSTEM DESCRIPTION

1.7.1 System Requirements

Electricity metering, consisting of meters and associated equipment, will be used to record the electricity consumption and other values as described in the requirements that follow and as shown on the drawings. Communication system requirements are contained in a separate specification section as identified in paragraph entitled "Communications Interfaces".

1.7.2 Selection Criteria

Metering components and software are part of a system that includes the physical meter, data recorder function and communications method. Every building site identified shall include sufficient metering components to measure the electrical parameters identified and to store and communicate the values as required.

Contractor shall verify that the electricity meter installed on any building site is compatible with the base-wide metering system with respect to the types of meters selected and the method used to program the meters for initial use. Software and meter programming tools are necessary to set up the meters described by this specification. New software tools different from the meter programming methods currently used by base

personnel will require separate approval for use.

The Base Wide Metering System is "ITRON_CENTRON" metering.

PART 2 PRODUCTS

2.1 ELECTRICITY METERS AND ACCESSORIES

Provide meter(s) and connect the meter(s) to the existing AMI DAS. The contractor shall use the existing government laptop computers to configure the meter using existing software loaded on the computer. The contractor will not be allowed to modify any software or add any additional software to the computer. Alternatively, the government will configure the meter(s), which must be compatible with the existing system, using existing software. Contract shall insure that the meter(s) will transmit the specified data to the DAS. The current meters being used by Camp Lejeune are: ITRON_CENTRON.

2.1.1 Physical and Common Requirements

- a. Provide metering system components in accordance with the Metering System Schedule shown in this specification. Provide Meter configuration template.
- b. Meter shall have NEMA 3R enclosure for surface mounting with bottom or rear penetrations.
- c. Surge withstand capability shall conform to IEEE C37.90.1.
- d. Use #12 SIS (XHHW, or equivalent) wiring with ring lugs for all meter connections. Color code and mark the conductors as follows:
 - (1) Red - Phase A CT - C1
 - (2) Orange - Phase B CT - C2
 - (3) Brown - Phase C CT - C3
 - (4) Gray with white stripe - neutral current return - C0
 - (5) Black - Phase A voltage - V1
 - (6) Yellow - Phase B voltage - V2
 - (7) Blue - Phase C voltage - V3
 - (8) White - Neutral voltage

2.1.2 Potential Transformer Requirements

- a. Meter shall be capable of connection to the service voltage phases and magnitude being monitored. If the meter is not rated for the service voltage, provide suitable potential transformers to send an acceptable voltage to the meter.
- b. Voltage input shall be optically isolated to 2500 volts DC from signal and communications outputs. Components shall meet or exceed IEEE C37.90.1.
- c. Provide one fuse per phase, Class RK type, to protect the voltage input to the meter. Size fuses as recommended by the meter manufacturer. Fusing shall either be inside the secondary compartment of the transformer or inside the same enclosure as the CT shorting device.

2.1.3 **Current Transformer** Requirements

- a. Current transformer shall be installed with a rating as shown in the schedule.
- b. Current transformers shall have an Accuracy Class of 0.3 (with a maximum error of plus/minus 0.3 percent at 5.0 amperes) when operating within the specified rating factor.
- c. Current transformers shall be solid-core, bracket-mounted for new installations using ring-tongue lugs for electrical connections. Current transformers shall be accessible and the associated wiring shall be installed in an organized and neat workmanship arrangement. Current transformers that are retrofitted onto existing switchgear busbar can be a busbar split-core design.
- d. Current transformers shall have:
 - (1) Insulation Class: All 600 volt and below current transformers shall be rated 10 KV BIL.
 - (2) Frequency: Nominal 60 Hz.
 - (3) Burden: Burden class shall be selected for the load.
 - (4) Phase Angle Range: 0 to 60 degrees.
- e. Meter shall accept current input from standard instrument transformers (5A secondary current transformers).
- f. Current inputs shall have a continuous rating in accordance with **IEEE C57.13**.
- g. Provide one single-ratio current transformer for each phase per power transformer with characteristics listed in the following table.

Single-Ratio Current Transformer Characteristics

kVA	Sec. Volt	CT Ratio	RF	Meter Acc. Class
1000	480Y/277	1200/5	1.33	0.3 thru B0.5
225	208Y/120	400/5	2.0	0.3 thru B0.2

2.1.4 **Meter** Requirements

Electricity meters shall include the following features:

- a. Meter shall comply with **ANSI C12.1**, **NEMA C12.19**, and **ANSI C12.20**.
- b. Meter sockets shall comply with **ANSI C12.7**.
- c. Provide socket-mounted meters.
- d. Meter shall be a Class 20, transformer rated design.
- e. Use Class 200 meters for direct current reading without current transformers for applications with an expected load less than 200 amperes, where indicated.

- f. Meter shall be rated for use at temperature from minus 40 degrees Centigrade to plus 85 degrees Centigrade.
- g. The meters shall have an electronic demand recording register and shall be secondary reading as indicated. The register shall be used to indicate maximum kilowatt demand as well as cumulative or continuously cumulative demand. Demand shall be measured on a block-interval basis and shall be capable of a 5 to 60 minute interval and initially set to a 15-minute interval. It shall have provisions to be programmed to calculate demand on a rolling interval basis. Meter readings shall be true RMS.
- h. The meter electronic register shall be of modular design with non-volatile data storage. Downloading meter stored data shall be capable via an optical port. Recording capability of data storage with a minimum capability of 89 days of 15 minute, 2 channel interval data. The meter shall be capable of providing at least 2 KYZ pulse outputs (dry contacts). Default initial configuration (unless identified otherwise by base personnel) shall be:
 - (1) First channel - kWh
 - (2) Second channel - kVARh
 - (3) KYZ output #1 - kWh
 - (4) KYZ output #2 - kVARh
- i. All meters shall have identical features available in accordance with this specification. The meter schedule identifies which features shall be activated at each meter location.
- j. Enable switches for Time of Use (TOU), pulse and load profile measurement module at the factory.
- k. Meter shall have an optical port on front of meter capable of speeds from 9600 to a minimum of 19.2k baud, and shall be initially set at 9600 baud. Optical device shall be compatible with ANSI C12.18.
- l. Meters shall be 120-480 volts auto ranging.
- m. Provide blank tag fixed to the meter faceplate for the addition of the meter multiplier, which will be the product of the current transformer ratio and will be filled in by base personnel on the job site. The meter's nameplate shall include:
 - (1) Meter ID number.
 - (2) Rated voltage.
 - (3) Current class.
 - (4) Metering form.
 - (5) Test amperes.
 - (6) Frequency.
 - (7) Catalog number.
 - (8) Manufacturing date.
- n. Meter covers shall be polycarbonate resins with an optical port and reset. Backup battery shall be easily accessible for change-out after removing the meter cover.
- o. The normal billing data scroll shall be fully programmable. Data scroll display shall include the following.

- (1) Number of demand resets.
 - (2) End-of-interval indication.
 - (3) Maximum demand.
 - (4) New maximum demand indication.
 - (5) Cumulative or continuously cumulative.
 - (6) Time remaining in interval.
 - (7) Kilowatt hours.
- p. The register shall incorporate a built-in test mode that allows it to be tested without the loss of any data or parameters. The following quantities shall be available for display in the test mode:
- (1) Present interval's accumulating demand.
 - (2) Maximum demand.
 - (3) Number of impulses being received by the register.
- q. Pulse module simple I/O board with programmable ratio selection.
- r. Meters shall be programmed after installation via an optical port. Optical display shall show TOU data, peak kWh, semi-peak kWh, off peak kWh, and phase angles.
- s. Self-monitoring to provide for:
- (1) Unprogrammed register.
 - (2) RAM checksum error.
 - (3) ROM checksum error.
 - (4) Hardware failure.
 - (5) Memory failure.
 - (6) EPROM error.
 - (7) Battery status (fault, condition, or time in service).
- t. Liquid crystal alphanumeric displays, 9 digits, blinking squares confirm register operation. 6 Large digits for data and smaller digits for display identifier.
- u. Display operations, programmable sequence with display identifiers. Display identifiers shall be selectable for each item. Continually sequence with time selectable for each item.
- v. The meters shall support three modes of registers: Normal Mode, Alternate Mode, and Test Mode. The meter also shall support a "Toolbox" or "Service Information" (accessible in the field) through an optocom port to a separate computer using the supplied software to allow access to instantaneous service information such as voltage, current, power factor, load demand, and the phase angle for individual phases.
- w. Meter shall have a standard 4-year warranty.
- 2.1.5 Disconnect Method
- a. Provide a 10-pole safety disconnect complete with isolation devices for the voltage and current transformer inputs, including a shorting means for the current transformers.

2.1.6 Installation Methods

- a. Stand Mounted Adjacent to Transformer ("STAND" in Metering Systems Schedule). Meter base shall be mounted on a structural steel pole approximately 4 feet from the transformer pad. This can be used for multiple meters associated with a single transformers.

2.2 COMMUNICATIONS INTERFACES

Meter shall be fully integrate into an existing Itron fixed network automatic meter reading system leveraging 900 MHz RF technology. Meter shall be equipped with a high powered RF 900 MHz electronic receiver transmitter communication modules. Meter shall provide standard consumption and interval data messages to an Itron fixed network repeater or collection station. Meter RF transmission shall include the unit identification number, unit type, energy usage, tamper status, and CRC check. Meter shall be based on a solid sate metering platform. Meter shall provide an accuracy of 0.3% or better. Meter shall provide a partial load profile including usage, demand, and power factor.

PART 3 EXECUTION

3.1 INSTALLATION

Electrical installations shall conform to IEEE C2, NFPA 70 (National Electrical Code), and to the requirements specified herein. Provide new equipment and materials unless indicated or specified otherwise.

3.1.1 Scheduling of Work and Outages

The Contract Clauses shall govern regarding permission for power outages, scheduling of work, coordination with Government personnel, and special working conditions.

3.1.2 Configuration Software

The standard meter shall include the latest available version of firmware and software. Meter shall either be programmed at the factory or shall be programmed in the field. Meters shall have a password that shall be provided to the contracting officer upon project completion. When field programming is performed, turn field programming device over to the Contracting Officer at completion of project. When interfacing software is used for a meter that is different than the existing meters in use at the Activity, turn the software over to the Contracting Officer at completion of the project.

3.2 FIELD QUALITY CONTROL

Perform the following acceptance checks and tests on all installed meters.

3.2.1 Performance of Acceptance Checks and Tests

Perform in accordance with the manufacturer's recommendations and include the following visual and mechanical inspections and electrical tests, performed in accordance with NETA ATS.

- a. Meter Assembly
 - (1) Visual and mechanical inspection.

- (a) Compare equipment nameplate data with specifications and approved shop drawings.
- (b) Inspect physical and mechanical condition. Confirm the meter is firmly seated in the socket, the socket is not abnormally heated, the display is visible, and the ring and seal on the cover are intact.
- (c) Inspect all electrical connections to ensure they are tight. For Class 200 services, verify tightness of the service conductor terminations for high resistance using low-resistance ohmmeter, or by verifying tightness of accessible bolted electrical connections by calibrated torque-wrench method.
- (d) Record model number, serial number, firmware revision, software revision, and rated control voltage.
- (e) Verify operation of display and indicating devices.
- (f) Record password and user log-in for each meter.
- (g) Verify grounding of metering enclosure.
- (h) Set all required parameters including instrument transformer ratios, system type, frequency, power demand methods/intervals, and communications requirements. Verify that the CT ratio and the PT ratio are properly included in the meter multiplier or the programming of the meter. Confirm that the multiplier is provided on the meter face or on the meter.
- (i) Provide [building meter installation sheet, per building](#) for each facility. See example Graphic E-S1.
- (j) Provide the [completed meter installation schedule](#) for the installation. See example Graphic E-S2.
- (k) Provide the [completed meter data schedule](#) for the installation. See example Graphic E-S3.

(2) Electrical tests.

- (a) Apply voltage or current as appropriate to each analog input and verify correct measurement and indication.
- (b) Confirm correct operation and setting of each auxiliary input/output feature including mechanical relay, digital, and analog.
- (c) After initial system energization, confirm measurements and indications are consistent with loads present.
- (d) Make note of, and report, any "Error-Code" or "Caution-Code" on the meter's display.

(3) Provide [meter configuration report](#).

b. Current Transformers

(1) Visual and mechanical inspection.

- (a) Compare equipment nameplate data with specification and approved shop drawings.
- (b) Inspect physical and mechanical condition.
- (c) Verify correct connection, including polarity.
- (d) Inspect all electrical connections to ensure they are tight.
- (e) Verify that required grounding and shorting connections provide good contact.

(2) Electrical Tests.

Verify proper operation by reviewing the meter configuration report.

3.2.2 System Functional Verification

Verify that the installed meters are working correctly in accordance with the meter configuration report:

- a. The correct meter form is installed.
- b. All voltage phases are present.
- c. Phase rotation is correct.
- d. Phase angles are correct.
- e. The new meter accurately measures power magnitude and direction, and can communicate as required by paragraph entitled "Communications Interfaces".

-- End of Section --

SECTION 26 28 01.00 10

COORDINATED POWER SYSTEM PROTECTION
10/07

PART 1 GENERAL

1.1 REFERENCES

The publications listed below form a part of this specification to the extent referenced. The publications are referred to within the text by the basic designation only.

INSTITUTE OF ELECTRICAL AND ELECTRONICS ENGINEERS (IEEE)

- IEEE 242 (2001; Errata 2003) Recommended Practice for Protection and Coordination of Industrial and Commercial Power Systems - Buff Book
- IEEE 399 (1997) Brown Book IEEE Recommended Practice for Power Systems Analysis
- IEEE C2 (2017; Errata 1-2 2017; INT 1 2017) National Electrical Safety Code
- IEEE C37.46 (2010) Standard for High Voltage Expulsion and Current-Limiting Type Power Class Fuses and Fuse Disconnecting Switches
- IEEE C57.13 (2016) Requirements for Instrument Transformers

NATIONAL ELECTRICAL MANUFACTURERS ASSOCIATION (NEMA)

- NEMA FU 1 (2012) Low Voltage Cartridge Fuses
- NEMA ICS 1 (2000; R 2015) Standard for Industrial Control and Systems: General Requirements
- NEMA ICS 2 (2000; R 2005; Errata 2008) Industrial Control and Systems Controllers, Contactors, and Overload Relays Rated 600 V
- NEMA ICS 3 (2005; R 2010) Medium-Voltage Controllers Rated 2001 to 7200 V AC
- NEMA ICS 6 (1993; R 2016) Industrial Control and Systems: Enclosures
- NEMA/ANSI C12.11 (2006; R 2019) Instrument Transformers for Revenue Metering, 10 kV BIL through 350 kV BIL (0.6 kV NSV through 69 kV NSV)

NATIONAL FIRE PROTECTION ASSOCIATION (NFPA)

- NFPA 70 (2020; ERTA 20-1 2020; ERTA 20-2 2020; TIA

20-1; TIA 20-2; TIA 20-3; TIA 20-4)
National Electrical Code

UNDERWRITERS LABORATORIES (UL)

- UL 198M (2018) UL Standard for Mine-Duty Fuses
- UL 486E (2015; Reprint Apr 2019) UL Standard for Safety Equipment Wiring Terminals for Use with Aluminum and/or Copper Conductors
- UL 489 (2016) UL Standard for Safety Molded-Case Circuit Breakers, Molded-Case Switches and Circuit-Breaker Enclosures
- UL 508 (2018) UL Standard for Safety Industrial Control Equipment
- UL 845 (2005; Reprint Oct 2018) UL Standard for Safety Motor Control Centers
- UL 1203 (2013; Reprint Jan 2020) UL Standard for Safety Explosion-Proof and Dust-Ignition-Proof Electrical Equipment for Use in Hazardous (Classified) Locations

1.2 SYSTEM DESCRIPTION

The power system covered by this specification consists of: 480Y/277V and 208Y/120V three-phase 4-wire services and power distribution to the P1338 II MEF Simulation/Training Center..

1.3 SUBMITTALS

Government approval is required for submittals with a "G" designation; submittals not having a "G" designation are for Contractor Quality Control approval. Submittals with an "S" are for inclusion in the Sustainability eNotebook, in conformance to Section 01 33 29 SUSTAINABILITY REPORTING. Submit the following in accordance with Section 01 33 00 SUBMITTAL PROCEDURES:

SD-03 Product Data

- Fault Current Analysis
- Protective Device Coordination Study
- Equipment
- System Coordinator
- Protective Relays
- Installation

SD-06 Test Reports

- Field Testing

SD-07 Certificates

- Devices and Equipment

1.4 QUALITY ASSURANCE

1.4.1 System Coordinator

System coordination, recommended ratings and settings of protective devices, and design analysis shall be accomplished by a registered professional electrical power engineer with a minimum of 3 years of current experience in the coordination of electrical power systems. Submit verification of experience and license number, of a registered Professional Engineer as specified above. Experience data shall include at least five references for work of a magnitude comparable to this contract, including points of contact, addresses and telephone numbers.

1.4.2 System Installer

Calibration, testing, adjustment, and placing into service of the protective devices shall be accomplished by a manufacturer's product field service engineer or independent testing company with a minimum of two years of current product experience in protective devices.

1.5 DELIVERY, STORAGE, AND HANDLING

Devices and equipment shall be visually inspected when received and prior to acceptance from conveyance. Protect stored items from the environment in accordance with the manufacturer's published instructions. Damaged items shall be replaced.

1.6 PROJECT/SITE CONDITIONS

Submit certificates attesting that all devices or equipment meet the requirements of the contract documents. **Devices and equipment** furnished under this section shall be suitable for the following site conditions. .

Altitude	26 feet
Ambient Temperature	73.8 degrees F
Frequency	60

PART 2 PRODUCTS

2.1 STANDARD PRODUCT

Provide protective devices and **equipment** which are the standard product of

a manufacturer regularly engaged in the manufacture of the product and that essentially duplicate items that have been in satisfactory utility type use for at least two years prior to bid opening. Submit data consisting of manufacturer's time-current characteristic curves for individual protective devices, recommended settings of adjustable protective devices, and recommended ratings of non-adjustable protective devices.

2.2 NAMEPLATES

Provide nameplates to identify all protective devices and equipment. Nameplate information shall be in accordance with [UL 489](#).

2.3 CORROSION PROTECTION

Metallic materials shall be protected against corrosion. Ferrous metal hardware shall be zinc or chrome-plated.

2.4 MOTOR CONTROLS

Motor controls shall be in accordance with [NEMA ICS 1](#), [NEMA ICS 2](#), [NEMA ICS 3](#) and [NEMA ICS 6](#), and [UL 508](#) and [UL 845](#).

2.4.1 Motor Starters

Provide combination starters with circuit breakers and fusible switches as indicated.

2.4.2 Thermal-Overload Protection

Each motor of $1/8$ hp or larger shall be provided with thermal-overload protection. Polyphase motors shall have overload protection in each ungrounded conductor. The overload-protection device shall be provided either integral with the motor or controller, or shall be mounted in a separate enclosure. Unless otherwise specified, the protective device shall be of the manually reset type. Single or double pole tumbler switches specifically designed for alternating-current operation only may be used as manual controllers for single-phase motors having a current rating not in excess of 80 percent of the switch rating.

2.4.3 Low-Voltage Motor Overload Relays

2.4.3.1 General

Thermal overload relays shall conform to [NEMA ICS 2](#) and [UL 508](#). Overload protection shall be provided either integral with the motor or controller, and shall be rated in accordance with the requirements of [NFPA 70](#). Standard units shall be used for motor starting times up to 7 second. Slow units shall be used for motor starting times from 8 to 12 seconds. Quick trip units shall be used on hermetically sealed, submersible pumps, and similar motors.

2.4.3.2 Construction

Manual reset type thermal relays shall be bimetallic construction. Automatic reset type relays shall be bimetallic construction. Magnetic current relays shall consist of a contact mechanism and a dash pot mounted on a common frame.

2.4.3.3 Ratings

Voltage ratings shall be not less than the applicable circuit voltage. Trip current ratings shall be established by selection of the replaceable overload device and shall not be adjustable. Where the controller is remotely-located or difficult to reach, an automatic reset, non-compensated overload relay shall be provided. Manual reset overload relays shall be provided otherwise, and at all locations where automatic starting is provided. Where the motor is located in a constant ambient temperature, and the thermal device is located in an ambient temperature that regularly varies by more than 14 degrees F, an ambient temperature-compensated overload relay shall be provided.

2.4.4 Automatic Control Devices

2.4.4.1 Direct Control

Automatic control devices (such as thermostats, float or pressure switches) which control the starting and stopping of motors directly shall be designed for that purpose and have an adequate horsepower rating.

2.4.4.2 Pilot-Relay Control

Where the automatic-control device does not have such a rating, a magnetic starter shall be used, with the automatic-control device actuating the pilot-control circuit.

2.4.4.3 Manual/Automatic Selection

- a. Where combination manual and automatic control is specified and the automatic-control device actuates the pilot control circuit of a magnetic starter, the magnetic starter shall be provided with a three-position selector switch marked MANUAL-OFF-AUTOMATIC.
- b. Connections to the selector switch shall only allow the normal automatic regulatory control devices to be bypassed when the switch is in the Manual position; all safety control devices, such as low-or high-pressure cutouts, high-temperature cutouts, and motor-overload protective devices, shall be connected in the motor-control circuit in both the Manual and the Automatic positions of the selector switch. Control circuit connections to any MANUAL-OFF-AUTOMATIC switch or to more than one automatic regulatory control device shall be made in accordance with wiring diagram approved by the contracting Officer unless such diagram is included on the drawings. All controls shall be 120 volts or less unless otherwise indicated.

2.5 LOW-VOLTAGE FUSES

2.5.1 General

Low-voltage fuses shall conform to NEMA FU 1. Time delay and nontime delay options shall be as specified. Equipment provided under this contract shall be provided with a complete set of properly rated fuses when the equipment manufacturer utilizes fuses in the manufacture of the equipment, or if current-limiting fuses are required to be installed to limit the ampere-interrupting capacity of circuit breakers or equipment to less than the maximum available fault current at the location of the equipment to be installed. Fuses shall have a voltage rating of not less than the phase-to-phase circuit voltage, and shall have the time-current

characteristics requires for effective power system coordination.

2.5.2 Cartridge Fuses; Noncurrent-Limiting Type

Cartridge fuses of the noncurrent-limiting type shall be Class H, nonrenewable, dual element, time lag type and shall have interrupting capacity of 10,000 amperes. Class H Fuses shall conform to [UL 198M](#). At 500 percent current, cartridge fuses shall not blow in less than 10 seconds. Cartridge fuses shall be used for circuits rated in excess of 30 amperes, 125 volts, except where current-limiting fuses are indicated.

2.5.3 Cartridge Fuses; Current-Limiting Type

Cartridge fuses, current-limiting type, Class RK1 RK5 shall have tested interrupting capacity not less than 100,000 amperes. Fuse holders shall be the type that will reject Class H fuses.

- a. Class G fuses shall conform to [UL 198M](#).
- b. Class K fuses shall conform to [UL 198M](#).
- c. Class R fuses shall conform to [UL 198M](#).
- d. Class T fuses shall conform to [UL 198M](#).

2.5.3.1 Continuous Current Ratings (600 amperes and smaller)

Service entrance and feeder circuit fuses (600 amperes and smaller) shall be Class RK1 RK5 , current-limiting, time-delay with 200,000 amperes interrupting capacity.

2.5.3.2 Continuous Current Ratings (greater than 600 amperes)

Service entrance and feeder circuit fuses (greater than 600 amperes) shall be Class L, current-limiting, time-delay with 200,000 amperes interrupting capacity.

2.5.3.3 Motor and Transformer Circuit Fuses

Motor, motor controller, transformer, and inductive circuit fuses shall be Class RK1 or RK5, current-limiting, time-delay with 200,000 amperes interrupting capacity.

2.6 MEDIUM-VOLTAGE AND HIGH-VOLTAGE FUSES

2.6.1 General

Medium-voltage and high-voltage fuses shall be distribution fuse cutouts or power fuses, E-rated, C-rated, or R-rated current-limiting fuses as shown.

2.6.2 Construction

Units shall be suitable for outdoor use. Fuses shall have integral blown-fuse indicators. All ratings shall be clearly visible.

2.6.3 Ratings

Voltage ratings shall be not less than the applicable circuit voltage.

Continuous-current ratings shall be as shown.

2.6.3.1 Fuse Cutouts

Medium-voltage fuses and cutouts shall be of the loadbreak type construction ratings and types indicated. Open-link cutouts are not acceptable. Fuses shall be either indicating or dropout type. Fuse ratings shall be as indicated. Fuses cutouts shall be equipped with mounting brackets suitable for the indicated installations.

2.6.3.2 Power Fuses

Expulsion-type power fuses shall have ratings in accordance with [IEEE C37.46](#) and as follows:

Nominal voltage	14.4 kV
Rated maximum voltage	15 kV
Maximum symmetrical interrupting capacity	16 kA
Rated continuous current	As indicated on plans
BIL	110 kV

2.6.3.3 E-Rated, Current-Limiting Power Fuses

E-rated, current-limiting, power fuses shall conform to [IEEE C37.46](#).

2.6.3.4 C-Rated, Current-Limiting Fuses

C-rated, current-limiting, power fuses shall open in 1000 seconds at currents between 170 and 240 percent of the C rating.

2.6.3.5 R-Rated, Current-Limiting Fuses

R-rated, current-limiting, fuses shall be used with medium-voltage motor controllers only. R-rated fuses shall conform to [IEEE C37.46](#).

2.7 MOTOR SHORT-CIRCUIT PROTECTOR (MSCP)

2.7.1 General

Motor short-circuit protectors shall conform to [UL 508](#) and shall be provided as shown. Protectors shall be used only as part of a combination motor controller which provides coordinated motor branch-circuit overload and short-circuit protection, and shall be rated in accordance with the requirements of [NFPA 70](#).

2.7.2 Construction

Motor short-circuit protector bodies shall be constructed of high temperature, dimensionally stable, long life, nonhygroscopic materials. Protectors shall fit special MSCP mounting clips and shall not be interchangeable with any commercially available fuses. Protectors shall have 100 percent one-way interchangeability within the A-Y letter designations. All ratings shall be clearly visible.

2.7.3 Ratings

Voltage ratings shall be not less than the applicable circuit voltage. Letter designations shall be A through Y for motor controller Sizes 0, 1, 2, 3, 4, and 5, with 100,000 amperes interrupting capacity rating. Letter designations shall correspond to controller sizes as follows:

CONTROLLER SIZE	MSCP DESIGNATION
NEMA 0	A-N
NEMA 1	A-P
NEMA 2	A-S
NEMA 3	A-U
NEMA 4	A-W
NEMA 5	A-Y

2.8 MOLDED-CASE CIRCUIT BREAKERS

2.8.1 General

Molded-case circuit breakers shall conform to [UL 489](#) and [UL 489](#). Circuit breakers may be installed in panelboards, switchboards, enclosures, motor control centers, or combination motor controllers. Circuit breakers and circuit breaker enclosures located in hazardous (classified) areas shall conform to [UL 1203](#).

2.8.2 Construction

Molded-case circuit breakers shall be assembled as an integral unit in a supporting and enclosing housing of glass reinforced insulating material providing high dielectric strength. Circuit breakers shall be suitable for mounting and operating in any position. Lugs shall be listed for copper conductors only in accordance with [UL 486E](#). Single-pole circuit breakers shall be full module size with not more than one pole per module. Multi-pole circuit breakers shall be of the common-trip type having a single operating handle such that an overload or short circuit on any one pole will result in all poles opening simultaneously. Sizes of 100 amperes or less may consist of single-pole breakers permanently factory assembled into a multi-pole unit having an internal, mechanical, nontamperable common-trip mechanism and external handle ties. All circuit breakers shall have a quick-make, quick-break overcenter toggle-type mechanism, and the handle mechanism shall be trip-free to prevent holding the contacts closed against a short-circuit or sustained overload. All circuit breaker handles shall assume a position between "ON" and "OFF" when tripped automatically. All ratings shall be clearly visible.

2.8.3 Ratings

Voltage ratings shall be not less than the applicable circuit voltage. The interrupting rating of the circuit breakers shall be at least equal to

the available short-circuit current at the line terminals of the circuit breaker and correspond to the UL listed integrated short-circuit current rating specified for the panelboards and switchboards. Molded-case circuit breakers shall have nominal voltage ratings, maximum continuous-current ratings, and maximum short-circuit interrupting ratings in accordance with [UL 489](#). Ratings shall be coordinated with system X/R ratio.

2.8.4 Cascade System Ratings

Circuit breakers used in series combinations shall be in accordance with [UL 489](#). Equipment, such as switchboards and panelboards, which house series-connected circuit breakers shall be clearly marked accordingly. Series combinations shall be listed in the UL Recognized Component Directory under "Circuit Breakers-Series Connected."

2.8.5 Thermal-Magnetic Trip Elements

Thermal magnetic circuit breakers shall be provided as shown. Automatic operation shall be obtained by means of thermal-magnetic tripping devices located in each pole providing inverse time delay and instantaneous circuit protection. The instantaneous magnetic trip shall be adjustable and accessible from the front of all circuit breakers on frame sizes above 150 amperes.

2.8.6 Solid-State Trip Elements

Solid-state circuit breakers shall be provided as shown. All electronics shall be self-contained and require no external relaying, power supply, or accessories. Printed circuit cards shall be treated to resist moisture absorption, fungus growth, and signal leakage. All electronics shall be housed in an enclosure which provides protection against arcs, magnetic interference, dust, and other contaminants. Solid-state sensing shall measure true RMS current with error less than one percent on systems with distortions through the 13th harmonic. Peak or average actuating devices are not acceptable. Current sensors shall be toroidal construction, encased in a plastic housing filled with epoxy to protect against damage and moisture and shall be integrally mounted on the breaker. Where indicated on the drawings, circuit breaker frames shall be rated for 100 percent continuous duty. Circuit breakers shall have tripping features as shown on the drawings and as described below:

- a. Long-time current pick-up, adjustable from 50 percent to 100 percent of continuous current rating.
- b. Adjustable long-time delay.
- c. Short-time current pick-up, adjustable from 1.5 to 9 times long-time current setting.
- d. Adjustable short-time delay.
- e. Short-time I^2t switch.
- f. Instantaneous current pick-up, adjustable from 1.5 to 9 times long-time current setting.
- g. Ground-fault pick-up, adjustable from 20 percent to 60 percent of sensor rating, but in no case greater than 1200 amperes. Sensing of

ground-fault current at the main bonding jumper or ground strap shall not be permitted.

- h. Adjustable ground-fault delay.
- i. Ground-fault I square times t switch.
- j. Overload and Short-circuit and Ground-fault trip indicators shall be provided.

2.8.7 Current-Limiting Circuit Breakers

Current-limiting circuit breakers shall be provided as shown. Current-limiting circuit breakers shall limit the let-through I square times t to a value less than the I square times t of one-half cycle of the symmetrical short-circuit current waveform. On fault currents below the threshold of limitation, breakers shall provide conventional overload and short-circuit protection. Integrally-fused circuit breakers shall not be used.

2.8.8 SWD Circuit Breakers

Circuit breakers rated 15 amperes or 20 amperes and intended to switch 277 volts or less fluorescent lighting loads shall be marked "SWD."

2.8.9 HACR Circuit Breakers

Circuit breakers 60 amperes or below, 240 volts, 1-pole or 2-pole, intended to protect multi-motor and combination-load installations involved in heating, air conditioning, and refrigerating equipment shall be marked "Listed HACR Type."

2.8.10 Motor Circuit Protectors (MCP)

Motor circuit protectors shall conform to [UL 489](#) and [UL 489](#) and shall be provided as shown. MCPs shall consist of an adjustable instantaneous trip circuit breaker in conjunction with a combination motor controller which provides coordinated motor circuit overload and short-circuit protection. Motor Circuit Protectors shall be rated in accordance with [NFPA 70](#).

2.9 INSTRUMENT TRANSFORMERS

2.9.1 General

Instrument transformers shall comply with [NEMA/ANSI C12.11](#) and [IEEE C57.13](#). Instrument transformers shall be configured for mounting in/on the device to which they are applied. Polarity marks on instrument transformers shall be visually evident and shown on the drawings.

2.9.2 Current Transformers

Unless otherwise indicated, bar, wound, or window-type transformers are acceptable; and except for window-type units installed over insulated buses, transformers shall have a BIL rating consistent with the rated BIL of the associated switchgear or electric power apparatus bushings, buses or conductors. Current transformers shall have the indicated ratios. The continuous thermal-current rating factor shall be not less than 1.2 . Other thermal and mechanical ratings of current transformers and their primary leads shall be coordinated with the design of the circuit breaker

and shall be not less than the momentary rating of the associated circuit breaker. Circuit protectors shall be provided across secondary leads of the current transformers to prevent the accidental open-circuiting of the transformers while energized. Each terminal of each current transformer shall be connected to a short-circuiting terminal block in the circuit interrupting mechanism cabinet, power transformer terminal cabinet, and in the associated instrument and relay cabinets.

2.9.2.1 For kW Hour and Demand Metering (Low Voltage)

Current transformers shall conform to [IEEE C57.13](#). Current transformers with a metering accuracy Class of 0.3 through [B0.9 for 1500 kVA and B-1.8 for 2000 kVA](#), with a minimum RF of [1.33 at 86 degrees F](#), with 600-volt insulation, and 10 kV BIL shall be provided. Butyl-molded, window-type current transformers mounted on the transformer low-voltage bushings shall be provided. Route current transformer leads in a location as remote as possible from the power transformer secondary cables to permit current measurements to be taken with hook-on-ammeters.

2.9.2.2 Voltage Transformers

Voltage transformers shall have indicated ratios. Units shall have an accuracy rating of [0.3](#). Voltage transformers shall be of the drawout type having current-limiting fuses in both primary and secondary circuits. Mechanical interlocks shall prevent removal of fuses, unless the associated voltage transformer is in a drawout position. Voltage transformer compartments shall have hinged doors.

2.10 COORDINATED POWER SYSTEM PROTECTION

Analyses shall be prepared to demonstrate that the equipment selected and system constructed meet the contract requirements for ratings, coordination, and protection. They shall include a load flow analysis, a [fault current analysis](#), and a [protective device coordination study](#). Submit the study along with protective device equipment submittals. No time extensions or similar contact modifications will be granted for work arising out of the requirements for this study. Approval of protective devices proposed will be based on recommendations of this study. The Government shall not be held responsible for any changes to equipment, device ratings, settings, or additional labor for installation of equipment or devices ordered and/or procured prior to approval of the study. The studies shall be performed by a registered professional engineer with demonstrated experience in power system coordination in the last 3 years. Provide a list of references complete with points of contact, addresses and telephone numbers. The selection of the engineer is subject to the approval of the Contracting Officer.

2.10.1 Scope of Analyses

The fault current analysis, and protective device coordination study shall begin at: the source bus and extend down to system buses where fault availability is 10,000 amperes (symmetrical) for building/facility 600 volt level distribution buses.

2.10.2 Determination of Facts

The time-current characteristics, features, and nameplate data for each existing protective device shall be determined and documented. Utilize the fault current availability indicated as a basis for fault current

studies.

2.10.3 Single Line Diagram

A single line diagram shall be prepared to show the electrical system buses, devices, transformation points, and all sources of fault current (including generator and motor contributions). A fault-impedance diagram or a computer analysis diagram may be provided. Each bus, device or transformation point shall have a unique identifier. If a fault-impedance diagram is provided, impedance data shall be shown. Location of switches, breakers, and circuit interrupting devices shall be shown on the diagram together with available fault data, and the device interrupting rating.

2.10.4 Fault Current Analysis

2.10.4.1 Method

The fault current analysis shall be performed in accordance with methods described in IEEE 242, and IEEE 399.

2.10.4.2 Data

Actual data shall be utilized in fault calculations. Bus characteristics and transformer impedance shall be those proposed. Data shall be documented in the report.

2.10.4.3 Fault Current Availability

Balanced three-phase fault, bolted line-to-line fault, and line-to-ground fault current values shall be provided at each voltage transformation point and at each power distribution bus. The maximum and minimum values of fault available at each location shall be shown in tabular form on the diagram or in the report.

2.10.5 Coordination Study

The study shall demonstrate that the maximum possible degree of selectivity has been obtained between devices specified, consistent with protection of equipment and conductors from damage from overloads and fault conditions. The study shall include a description of the coordination of the protective devices in this project. A written narrative shall be provided describing: which devices may operate in the event of a fault at each bus; the logic used to arrive at device ratings and settings; situations where system coordination is not achievable due to device limitations (an analysis of any device curves which overlap); coordination between upstream and downstream devices; and relay settings. Recommendations to improve or enhance system reliability, and detail where such changes would involve additions or modifications to the contract and cost damages (addition or reduction) shall be provided. Composite coordination plots shall be provided on log-log graph paper.

2.10.6 Study report

- a. The report shall include a narrative describing: the analyses performed; the bases and methods used; and the desired method of coordinated protection of the power system.
- b. The study shall include descriptive and technical data for existing devices and new protective devices proposed. The data shall include

manufacturers published data, nameplate data, and definition of the fixed or adjustable features of the existing or new protective devices.

- c. The report shall document existing power system data including time-current characteristic curves and protective device ratings and settings.
- d. The report shall contain fully coordinated composite time-current characteristics curves for each bus in the system, as required to ensure coordinated power system protection between protective devices or equipment. The report shall include recommended ratings and settings of all protective devices in tabulated form.
- e. The report shall provide the calculation performed for the analyses, including computer analysis programs utilized. The name of the software package, developer, and version number shall be provided.

PART 3 EXECUTION

3.1 EXAMINATION

After becoming familiar with details of the work, verify dimensions in the field, and advise the Contracting Officer of any discrepancy before performing any work.

3.2 INSTALLATION

Submit procedures including diagrams, instructions, and precautions required to properly install, adjust, calibrate, and test the devices and equipment. Install protective devices in accordance with the manufacturer's published instructions and in accordance with the requirements of [NFPA 70](#) and [IEEE C2](#).

3.3 FIELD TESTING

Prior to field tests, submit the proposed test plan consisting of complete field test procedure, tests to be performed, test equipment required, and tolerance limits, and complete testing and verification of the ground fault protection equipment, where used. Submit performance test reports in booklet form showing all field tests performed to adjust each component and all field tests performed to prove compliance with the specified performance criteria, upon completion and testing of the installed system. Each test report shall indicate the final position of controls.

3.3.1 General

Perform field testing in the presence of the Contracting Officer. Notify the Contracting Officer 30 days prior to conducting tests. Furnish all materials, labor, and equipment necessary to conduct field tests. Perform all tests and inspections recommended by the manufacturer unless specifically waived by the Contracting Officer. Maintain a written record of all tests which includes date, test performed, personnel involved, devices tested, serial number and name of test equipment, and test results.

3.3.2 Safety

Provide and use safety devices such as rubber gloves, protective barriers, and danger signs to protect and warn personnel in the test vicinity. Replace any devices or equipment which are damaged due to improper test

procedures or handling.

3.3.3 Molded-Case Circuit Breakers

Circuit breakers shall be visually inspected, operated manually, and connections checked for tightness. Current ratings shall be verified and adjustable settings incorporated in accordance with the coordination study.

3.3.4 Power Circuit Breakers

3.3.4.1 General

Visually inspect the circuit breaker and operate the circuit breaker manually; adjust and clean primary contacts in accordance with manufacturer's published instructions; check tolerances and clearances; check for proper lubrication; and ensure that all connections are tight. For electrically operated circuit breakers, verify operating voltages on closing and tripping coils. Verify fuse ratings in control circuits; electrically operate the breaker, where applicable; and implement settings in accordance with the coordination study.

-- End of Section --

SECTION 26 29 23

ADJUSTABLE SPEED DRIVE (ASD) SYSTEMS UNDER 600 VOLTS

02/20

PART 1 GENERAL

1.1 REFERENCES

The publications listed below form a part of this specification to the extent referenced. The publications are referred to within the text by the basic designation only.

EUROPEAN COMMITTEE FOR STANDARDIZATION (CEN/CENELEC)

EN 61800-3 (2017) Requirements for the Control of Electromagnetic Interference Characteristics of Subsystems and Equipment

INSTITUTE OF ELECTRICAL AND ELECTRONICS ENGINEERS (IEEE)

IEEE 519 (2014) Recommended Practices and Requirements for Harmonic Control in Electrical Power Systems

IEEE C62.41.1 (2002; R 2008) Guide on the Surges Environment in Low-Voltage (1000 V and Less) AC Power Circuits

IEEE C62.41.2 (2002) Recommended Practice on Characterization of Surges in Low-Voltage (1000 V and Less) AC Power Circuits

NATIONAL ELECTRICAL MANUFACTURERS ASSOCIATION (NEMA)

NEMA 250 (2018) Enclosures for Electrical Equipment (1000 Volts Maximum)

NEMA ICS 1 (2000; R 2015) Standard for Industrial Control and Systems: General Requirements

NEMA ICS 3.1 (2019) Guide for the Application, Handling, Storage, Installation and Maintenance of Medium-Voltage AC Contactors, Controllers and Control Centers

NEMA ICS 6 (1993; R 2016) Industrial Control and Systems: Enclosures

NEMA ICS 7 (2014) Adjustable-Speed Drives

NEMA ICS 7.2 (2015) Application Guide for AC Adjustable Speed Drive Systems

NEMA MG 1 (2018) Motors and Generators

NATIONAL FIRE PROTECTION ASSOCIATION (NFPA)

NFPA 70 (2020; ERTA 20-1 2020; ERTA 20-2 2020; TIA 20-1; TIA 20-2; TIA 20-3; TIA 20-4)
National Electrical Code

U.S. NATIONAL ARCHIVES AND RECORDS ADMINISTRATION (NARA)

47 CFR 15 Radio Frequency Devices

UNDERWRITERS LABORATORIES (UL)

UL 489 (2016) UL Standard for Safety Molded-Case Circuit Breakers, Molded-Case Switches and Circuit-Breaker Enclosures

UL 508C (2002; Reprint Nov 2010) Power Conversion Equipment

1.2 RELATED REQUIREMENTS

Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM applies to this section with additions and modifications specified herein.

1.3 SYSTEM DESCRIPTION

1.3.1 Performance Requirements

1.3.1.1 Electromagnetic Interference Suppression

Computing devices, as defined by 47 CFR 15 and EN 61800-3 rules and regulations, must be certified to comply with the requirements for class A computing devices and labeled.

1.3.1.2 Electromechanical and Electrical Components

Ensure electrical and electromechanical components of the Adjustable Speed Drive (ASD) do not cause electromagnetic interference to adjacent electrical or electromechanical equipment while in operation.

1.3.2 Electrical Requirements

1.3.2.1 Power Line Surge Protection

IEEE C62.41.1 and IEEE C62.41.2, IEEE 519 Control panel must have surge protection, included within the panel to protect the unit from damaging transient voltage surges. Surge protective device must be mounted near the incoming power source and properly wired to all three phases and ground. Fuses must not be used for surge protection.

1.3.2.2 Sensor and Control Wiring Surge Protection

I/O functions as specified must be protected against surges induced on control and sensor wiring installed outdoors and as shown. Test the inputs and outputs in both normal mode and common mode using the following two waveforms:

- a. A 10 microsecond by 1000 microsecond waveform with a peak voltage of 1500 volts and a peak current of 60 amperes.

- b. An 8 microsecond by 20 microsecond waveform with a peak voltage of 1000 volts and a peak current of 500 amperes.

1.4 SUBMITTALS

Government approval is required for submittals with a "G" designation; submittals not having a "G" designation are for Contractor Quality Control approval. Submittals with an "S" are for inclusion in the Sustainability eNotebook, in conformance with Section 01 33 29 SUSTAINABILITY REPORTING. Submit the following in accordance with Section 01 33 00 SUBMITTAL PROCEDURES:

SD-02 Shop Drawings

- Schematic Diagrams; G
- Interconnecting Diagrams; G
- Installation Drawings; G
- As-Built Drawings; G

SD-03 Product Data

- Adjustable Speed Drives; G
- Wires and Cables
- Equipment Schedule

SD-06 Test Reports

- ASD Test
- Performance Verification Tests
- Endurance Test

SD-08 Manufacturer's Instructions

- Installation instructions

SD-09 Manufacturer's Field Reports

- ASD Test Plan; G
- Standard Products

SD-10 Operation and Maintenance Data

- Adjustable Speed Drives, Data Package 4

1.5 QUALITY ASSURANCE

1.5.1 Schematic Diagrams

Submit diagrams showing circuits and device elements for each replaceable module. Schematic diagrams of printed circuit boards are permitted to

group functional assemblies as devices, provided that sufficient information is provided for government maintenance personnel to verify proper operation of the functional assemblies.

1.5.2 Interconnecting Diagrams

Show interconnections between equipment assemblies, and external interfaces, including power and signal conductors. Include for enclosures and external devices.

1.5.3 Installation Drawings

Show floor plan of each site, with ASD's and motors indicated. Indicate ventilation requirements, adequate clearances, and cable routes. Submit drawings for government approval prior to equipment construction or integration. Immediately record modifications to original drawings made during installation for inclusion into the **as-built drawings**.

1.5.4 Equipment Schedule

Provide schedule of equipment supplied. Schedule must provide a cross reference between manufacturer data and identifiers indicated in shop drawings. Schedule must include the total quantity of each item of equipment supplied and data indicating compatibility with motors being driven. For complete assemblies, such as ASD's, provide the serial numbers of each assembly, and a sub-schedule of components within the assembly. Provide recommended spare parts listing for each assembly or component.

1.5.5 Installation Instructions

Provide installation instructions issued by the manufacturer of the equipment, including notes and recommendations, prior to shipment to the site. Provide operation instructions prior to acceptance testing.

1.5.6 Standard Products

Provide materials and equipment that are products of manufacturers regularly engaged in the production of such products which are of equal material, design and workmanship and:

- a. Have been in satisfactory commercial or industrial use for 2 years prior to bid opening including applications of equipment and materials under similar circumstances and of similar size.
- b. Have been on sale on the commercial market through advertisements, manufacturers' catalogs, or brochures during the 2-year period.
- c. Where two or more items of the same class of equipment are required, provide products of a single manufacturer; however, the component parts of the item need not be the products of the same manufacturer unless stated in this section.

1.6 DELIVERY AND STORAGE

Store delivered equipment to protect from the weather, humidity and temperature variations, dirt and dust, or other contaminants.

1.7 WARRANTY

The complete system must be warranted by the manufacturer for a period of one year . Repair or replace any component failing to perform its function as specified and documented at no additional cost to the Government. Items repaired or replaced must be warranted for an additional period of at least one year from the date that it becomes functional again, as specified in FAR 52.246-21 Warranty of Construction.

1.8 MAINTENANCE

1.8.1 Operation and Maintenance Data

Provide in accordance with Section 01 78 23 OPERATION AND MAINTENANCE DATA. Provide service and maintenance information including preventive maintenance, assembly, and disassembly procedures. Include electrical drawings from electrical general sections. Provide additional information necessary to provide complete operation, repair, and maintenance information, detailed to the smallest replaceable unit. Include copies of as-built submittals. Provide routine preventative maintenance instructions, and equipment required. Provide instructions on how to modify program settings, and modify the control program. Provide instructions on drive adjustment, trouble-shooting, and configuration. Provide instructions on process tuning and system calibration.

1.8.2 Maintenance Support

During the warranty period, provide on-site, on-call maintenance services by drive manufacturer's personnel on the following basis: The service must be on a per-call basis with 36 hour response. Contractor is responsible for the maintenance of all hardware and software of the system during the warranty period. Various personnel of different expertise must be sent on-site depending on the nature of the maintenance service required. Costs must include travel, local transportation, living expenses, and labor rates of the service personnel while responding to the service request. The provisions of this Section are not in lieu of, nor relieve the Contractor of, warranty responsibilities covered in this specification. Should the result of the service request be the uncovering of a system defect covered under the warranty provisions, all costs for the call, including the labor necessary to identify the defect, must be borne by the Contractor.

1.8.3 Technical Support

Provide the ASDs with manufacturer's technical telephone support in English, readily available during normal working hours.

PART 2 PRODUCTS

2.1 ADJUSTABLE SPEED DRIVES (ASD)

Provide adjustable speed drive to control the speed of induction motor(s). The ASD must include the following minimum functions, features and ratings.

- a. Input circuit breaker per UL 489 with a minimum of 10,000 amps symmetrical interrupting capacity and door interlocked external operator.

- b. A converter stage per [UL 508C](#) must change fixed voltage, fixed frequency, ac line power to a fixed dc voltage. The converter must utilize a full wave bridge design incorporating diode rectifiers. Silicon Controlled Rectifiers (SCR) are not acceptable. The converter must be insensitive to three phase rotation of the ac line and must not cause displacement power factor of less than .95 lagging under any speed and load condition.
- c. An inverter stage must change fixed dc voltage to variable frequency, variable ac voltage for application to a standard [NEMA MG 1 Part 30](#) motor designed for use with adjustable frequency power supplies. Switch the inverter to produce a sine coded pulse width modulated (PWM) output waveform.
- d. The ASD shall be capable of supplying 120 percent of rated full load current for one minute at maximum ambient temperature.
- e. The ASD must be designed to operate from a 480 volt, plus or minus 10 percent, three phase, 60 Hz supply, and control motors with a corresponding voltage rating.
- f. Acceleration and deceleration time must be independently adjustable from one second to 60 seconds.

Required deceleration time may be achieved using not only dynamic braking resistor but with other methods described in [NEMA ICS 7.2-2015](#) paragraph 5.2.5.

- g. Adjustable full-time current limiting must limit the current to a preset value which must not exceed 110 percent of the controller rated current. The current limiting action must maintain the V/Hz ratio constant so that variable torque can be maintained. Short time starting override must allow starting current to reach 175 percent of controller rated current to maximum starting torque.
- h. The controllers must be capable of producing an output frequency over the range of 3 Hz to 60 Hz (20 to one speed range), without low speed cogging. Over frequency protection must be included such that a failure in the controller electronic circuitry must not cause frequency to exceed 110 percent of the maximum controller output frequency selected.
- i. Minimum and maximum output frequency must be adjustable over the following ranges: 1) Minimum frequency 3 Hz to 50 percent of maximum selected frequency; 2) Maximum frequency 40 Hz to 60 Hz.
- j. The controller efficiency at any speed must not be less than 96 percent.
- k. The controllers must be capable of being restarted into a motor coasting in the forward direction without tripping.
- l. Protection of power semiconductor components must be accomplished without the use of fast acting semiconductor output fuses. Subjecting the controllers to any of the following conditions must not result in component failure or the need for fuse replacement:

- (1) Short circuit at controller output

- (2) Ground fault at controller output
 - (3) Open circuit at controller output
 - (4) Input undervoltage
 - (5) Input overvoltage
 - (6) Loss of input phase
 - (7) AC line switching transients
 - (8) Instantaneous overload
 - (9) Sustained overload exceeding 115 percent of controller rated current
 - (10) Over temperature
 - (11) Phase reversal
- m. Solid state motor overload protection must have sensor in each phase, Class 10/20 selectable tripping characteristic selected to protect motor against voltage and current unbalance and single phasing, Class II ground-fault protection, with start and run delays to prevent nuisance trip on starting, NC isolated overload alarm contact, external overload, reset push button.
- n. Include slip compensation circuit that will sense changing motor load conditions and adjust output frequency to provide speed regulation of NEMA MG 1 Part 30 designed for use with adjustable frequency power supplies motors to within plus or minus 0.5 percent of maximum speed without the necessity of a tachometer generator.
- o. The ASD must be factory set for manual restart after the first protective circuit trip for malfunction (overcurrent, undervoltage, overvoltage or overtemperature) or an interruption of power. The ASD must be capable of being set for automatic restart after a selected time delay. If the drive faults again within a specified time period (adjustable 0-60 seconds), a manual restart will be required. Provide Bidirectional Autospeed Search capable of starting the ASD into rotating loads spinning in either direction and returning motor to set speed in proper direction, without causing damage to drive, motor, or load.
- p. The ASD must include external fault reset capability. All the necessary logic to accept an external fault reset contact must be included.
- q. Provide critical speed lockout circuitry to prevent operating at frequencies with critical harmonics that cause resonant vibrations. The ASD must have a minimum of three user selectable bandwidths.
- r. Provide properly sized NEMA rated by-pass and isolation contactors to enable operation of motor in the event of ASD failure and for safety transfers motor between power converter output and bypass circuit using a field-selectable automatic and manual bypass mode. Install mechanical and electrical interlocks between the by-pass and isolation contactors. Provide a selector switch and transfer delay timer.

Motor overload and short circuit protective features must remain in use during the bypass mode.

- s. Each individual ASD must meet the following Total Harmonic Distortion (THD) requirements at the input terminals to the factory assembly of the ASD or at the load disconnecting means serving the ASD and filter assembly. These measurements should be taken with the drive set at 90 percent frequency (rpms) and the motor under a minimum of 50 percent demand.
 - (1) The Voltage THD should not exceed 2.0 percent THD.
 - (2) The Current THD should not exceed 15.0 percent THD.
 - (3) If the standard factory ASD does not meet or exceed these requirements the factory must install appropriate equipment (Harmonic Traps, Filters, different Drive technology, etc.) to mitigate the distortion to assure performance of the VFD is within the limits.
 - (4) These tests should be performed at the Manufacturers Laboratory facilities and submitted as part of the Product Data Submittals, in order to prevent the necessity of adding mitigation equipment in the field. If the requirements listed above are met, [IEEE 519](#) will also be met.
- t. Minimum Operating Conditions. Designed and constructed ASD's to operate within the following service conditions:
 - (1) Ambient Temperature Rating: 0 to 120 degrees F.
 - (2) Non-condensing relative humidity rating: less than 95 percent.
 - (3) Ambient rating: Not exceed 3,300 feet.

2.1.1.1 ASD for HVAC Application

ASDs must have the following features:

- a. A local operator control providing the following functions:
 - (1) Remote/Local operator selection with password access.
 - (2) Run/Stop and manual speed commands.
 - (3) All programming functions.
 - (4) Scrolling through all display functions.
- b. A local operator control panel with the following data displayed:
 - (1) ASD status.
 - (2) Frequency.
 - (3) Motor RPM.
 - (4) Phase current.

- (5) Scrolling through all display functions.
- (6) Fault diagnostics in descriptive text.
- (7) All programmed parameters.
- c. Standard PI loop controller with input terminal for controlled variable and parameter settings.
- d. User interface terminals for remote control of ASD speed, speed feedback, and an isolated form C SPDT relay, which energizes on a drive fault condition.
- e. An isolated form C SPDT auxiliary relay which energizes on a run command.
- f. An adjustable carrier frequency with 16 KHz minimum upper limit.
- g. A built-in or external line reactor with 3 percent minimum impedance to protect the DC bus capacitors and rectifier section diodes, reduce power line transient voltage, line notching, DC bus over-voltage tripping and improve the inverter over-current and over-voltage conditions.
- h. Historical logging information and displays:
 - (1) Real-time clock with current time and date.
 - (2) Running log of total power versus time.
 - (3) Total run time.
 - (4) Fault log, maintaining last four faults with time and data stamp for each.
- i. The ASD must be capable of automatic control by a remote 0 to 10 VDC signal, by BACnet network command, or manually by the ASD control panel.
- j. ASDs must include the following operator programmable parameters:
 - (1) Upper and lower limit frequency.
 - (2) Acceleration and deceleration rate.
 - (3) Variable torque volts per Hertz curve.
 - (4) Starting voltage level.
 - (5) Starting frequency level.
 - (6) Display speed scaling.
 - (7) Enable/disable soft stall feature.
 - (8) Motor overload level.

- (9) Motor stall level.
 - (10) Jump frequency and hysteresis band.
 - (11) PWM carrier frequency.
- k. ASD must have the following protective features:
- (1) An electronic adjustable inverse time current limit with consideration for additional heating of the motor at frequencies below 45Hz, for the protection of the motor.
 - (2) An electronic adjustable soft stall feature, allowing the ASD to lower the frequency to a point where the motor will not exceed the full-load amperage when an overload ASD will automatically return to the requested frequency when load conditions permit.
 - (3) A separate electronic stall at 110 percent ASD rated current, and a separate hardware trip at 190 percent current.
 - (4) The ability to shut down if inadvertently started into a rotating load without damaging the ASD or the motor.
 - (5) The ability to keep a log of a minimum of four previous fault conditions, indicating the fault type and time of occurrence in descriptive text.
 - (6) The ability to sustain 110 percent rated current for 60 seconds.
 - (7) The ability to shutdown safely or protect against and record the following fault conditions:
 - (a) Over current (and an indication if the over current was during acceleration, deceleration, or running).
 - (b) Over current internal to the drive.
 - (c) Motor overload at start-up.
 - (d) Over voltage from utility power.
 - (e) Motor running overload.
 - (f) Over voltage during deceleration.
 - (g) ASD over heat.
 - (h) Load and ground fault.
 - (h) Abnormal parameters or data in ASD EEPROM.

2.2 ENCLOSURES

Provide equipment enclosures conforming to NEMA 250, NEMA ICS 7, and NEMA ICS 6, with a heater if located outdoors.

2.3 WIRES AND CABLES

All wires and cables must conform to NEMA 250, NEMA ICS 7, NFPA 70.

2.4 NAMEPLATES

Nameplates external to NEMA enclosures must conform with the requirements of Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM. Provide manufacturer's standard, permanent nameplates for internal areas of enclosures.

2.5 SOURCE QUALITY CONTROL

2.5.1 ASD Test Plan

To ensure quality, each ASD must be subject to a series of in-plant quality control inspections before approval for shipment from the manufacturer's facilities. Provide test plans.

2.5.2 ASD Test Report

To ensure quality, each ASD must be subject to a series of in-plant quality control inspections before approval for shipment from the manufacturer's facilities. Provide test reports.

PART 3 EXECUTION

3.1 INSTALLATION

Per NEMA ICS 3.1, install equipment in accordance with the approved manufacturer's printed installation drawings, instructions, wiring diagrams, and as indicated on project drawings and the approved shop drawings. A field representative of the drive manufacturer must supervise the installation of all equipment, and wiring.

3.2 GROUNDING

Per NEMA ICS 7.2, ASD must be solidly grounded to the main distribution.

3.3 FIELD QUALITY CONTROL

Specified products must be tested as a system for conformance to specification requirements prior to scheduling the acceptance tests. Conduct performance verification tests in the presence of Government representative, observing and documenting complete compliance of the system to the specifications. Submit a signed copy of the test results, certifying proper system operation before scheduling tests.

3.3.1 ASD Test

A proposed test plan must be submitted to the contracting officer at least 28 calendar days prior to proposed testing for approval. The tests must conform to NEMA ICS 1, NEMA ICS 7, and all manufacturer's safety regulations. The Government reserves the right to witness all tests and review any documentation. Inform the Government at least 14 working days prior to the dates of testing. Perform the ASD test with the assistance of a factory-authorized service representative.

3.3.2 Performance Verification Tests

"Performance Verification Test" plan must provide the step by step procedure required to establish formal verification of the performance of the ASD. Compliance with the specification requirements must be verified

by inspections, review of critical data, demonstrations, and tests. The Government reserves the right to witness all tests, review data, and request other such additional inspections and repeat tests as necessary to ensure that the system and provided services conform to the stated requirements. Inform the Government 14 calendar days prior to the date the test is to be conducted.

3.3.3 Endurance Test

Immediately upon completion of the performance verification test, the endurance test must commence. The system must be operated at varying rates for not less than 192 consecutive hours, at an average effectiveness level of 0.9998, to demonstrate proper functioning of the complete PCS. Continue the test on a day-to-day basis until performance standard is met. The contractor is not allowed in the building during the endurance test. The system must respond as designed.

3.4 DEMONSTRATION

3.4.1 Training

Coordinate training requirements with the Contracting Officer. Provide video tapes, if available, of all training provided to the Government for subsequent use in training new personnel. Provide all training aids, texts, and expendable support material for a self-sufficient presentation shall be provided, the amount of which to be determined by the contracting officer.

3.4.1.1 Instructions to Government Personnel

Provide the services of competent instructors with minimum two-year field experience with the operation and maintenance of similar ASDs who will give full instruction to designated personnel in operation, maintenance, calibration, configuration, and programming of the complete control system. Orient the training specifically to the system installed. Instructors must be thoroughly familiar with the subject matter they are to teach. The number of training days of instruction furnished must be as specified. A training day is defined as eight hours of instruction, including two 15-minute breaks and excluding lunch time; Monday through Friday. Provide a training manual for each student at each training phase which describes in detail the material included in each training program. Provide one additional copy for archiving. Provide equipment and materials required for classroom training. Provide a list of additional related courses, and offers, noting any courses recommended. List each training course individually by name, including duration, approximate cost per person, and location of course. Unused copies of training manuals must be turned over to the Government at the end of last training session.

3.4.1.2 Operating Personnel Training Program

Provide one 2-hour training session at the site at a time and place mutually agreeable between the Contractor and the Government. Provide session to train 4 operation personnel in the functional operations of the system and the procedures that personnel will follow in system operation. This training shall include:

- a. System overview
- b. General theory of operation

- c. System operation
- d. Alarm formats
- e. Failure recovery procedures
- f. Troubleshooting

3.4.1.3 Engineering/Maintenance Personnel Training

Accomplish the training program as specified. Training must be conducted on site at a location designated by the Government. Provide a one-day training session to train four engineering personnel in the functional operations of the system. This training must include:

- a. System overview
- b. General theory of operation
- c. System operation
- d. System configuration
- e. Alarm formats
- f. Failure recovery procedures
- g. Troubleshooting and repair
- h. Maintenance and calibration
- i. System programming and configuration

-- End of Section --

SECTION 26 32 15.00

ENGINE-GENERATOR SET STATIONARY 15-2500 KW, WITH AUXILIARIES
05/20

PART 1 GENERAL

1.1 REFERENCES

The publications listed below form a part of this specification to the extent referenced. The publications are referred to within the text by the basic designation only.

ASME INTERNATIONAL (ASME)

- ASME B16.3 (2016) Malleable Iron Threaded Fittings, Classes 150 and 300
- ASME B16.5 (2017) Pipe Flanges and Flanged Fittings NPS 1/2 Through NPS 24 Metric/Inch Standard
- ASME B16.11 (2016) Forged Fittings, Socket-Welding and Threaded
- ASME B16.21 (2016) Nonmetallic Flat Gaskets for Pipe Flanges
- ASME B31.1 (2020) Power Piping
- ASME B31.3 (2016) Process Piping
- ASME BPVC SEC IX (2017; Errata 2018) BPVC Section IX-Welding, Brazing and Fusing Qualifications

ASTM INTERNATIONAL (ASTM)

- ASTM A53/A53M (2020) Standard Specification for Pipe, Steel, Black and Hot-Dipped, Zinc-Coated, Welded and Seamless
- ASTM A106/A106M (2019a) Standard Specification for Seamless Carbon Steel Pipe for High-Temperature Service
- ASTM A181/A181M (2014) Standard Specification for Carbon Steel Forgings, for General-Purpose Piping
- ASTM A193/A193M (2020) Standard Specification for Alloy-Steel and Stainless Steel Bolting Materials for High-Temperature Service and Other Special Purpose Applications
- ASTM A194/A194M (2020a) Standard Specification for Carbon Steel, Alloy Steel, and Stainless Steel Nuts for Bolts for High-Pressure or High-Temperature Service, or Both

ASTM A234/A234M (2019) Standard Specification for Piping Fittings of Wrought Carbon Steel and Alloy Steel for Moderate and High Temperature Service

ASTM D975 (2020) Standard Specification for Diesel Fuel Oils

ELECTRICAL GENERATING SYSTEMS ASSOCIATION (EGSA)

EGSA 101P (1995) Performance Standard for Engine Driven Generator Sets

INSTITUTE OF ELECTRICAL AND ELECTRONICS ENGINEERS (IEEE)

IEEE 1 (2000; R 2011) General Principles for Temperature Limits in the Rating of Electric Equipment and for the Evaluation of Electrical Insulation

IEEE 43 (2013) Recommended Practice for Testing Insulation Resistance of Rotating Machinery

IEEE 81 (2012) Guide for Measuring Earth Resistivity, Ground Impedance, and Earth Surface Potentials of a Ground System

IEEE 100 (2000; Archived) The Authoritative Dictionary of IEEE Standards Terms

IEEE 115 (2019) Guide for Test Procedures for Synchronous Machines: Part I Acceptance and Performance Testing; Part II Test Procedures and Parameter Determination for Dynamic Analysis

IEEE 120 (1989; R 2007) Master Test Guide for Electrical Measurements in Power Circuits

IEEE 519 (2014) Recommended Practices and Requirements for Harmonic Control in Electrical Power Systems

IEEE C2 (2017; Errata 1-2 2017; INT 1 2017) National Electrical Safety Code

IEEE C50.12 (2005; R 2010) Standard for Salient Pole 50 HZ and 60 Hz Synchronous Generators and Generation/Motors for Hydraulic Turbine Applications Rated 5 MVA and above

IEEE C57.13 (2016) Requirements for Instrument Transformers

INTERNATIONAL CODE COUNCIL (ICC)

ICC IBC (2018) International Building Code

INTERNATIONAL ELECTRICAL TESTING ASSOCIATION (NETA)

NETA ATS (2017; Errata 2017) Standard for Acceptance Testing Specifications for Electrical Power Equipment and Systems

INTERNATIONAL ORGANIZATION FOR STANDARDIZATION (ISO)

ISO 3046 (2002, 2006, 2009, 2001) Reciprocating Internal Combustion Engines - Performance--Part 1, 3, 4, 5, 6

ISO 8528 (1993; R 2018) Reciprocating Internal Combustion Engine Driven Alternating Current Generator Sets--Part 1, 2, 3, 4, 5, 6, 7, 8, 9, 10, 12, 13

MANUFACTURERS STANDARDIZATION SOCIETY OF THE VALVE AND FITTINGS INDUSTRY (MSS)

MSS SP-58 (2018) Pipe Hangers and Supports - Materials, Design and Manufacture, Selection, Application, and Installation

MSS SP-80 (2019) Bronze Gate, Globe, Angle and Check Valves

NATIONAL ELECTRICAL MANUFACTURERS ASSOCIATION (NEMA)

NEMA ICS 2 (2000; R 2005; Errata 2008) Industrial Control and Systems Controllers, Contactors, and Overload Relays Rated 600 V

NEMA ICS 6 (1993; R 2016) Industrial Control and Systems: Enclosures

NEMA MG 1 (2018) Motors and Generators

NEMA PB 1 (2011) Panelboards

NEMA PB 2 (2011) Deadfront Distribution Switchboards

NEMA/ANSI C12.11 (2006; R 2019) Instrument Transformers for Revenue Metering, 10 kV BIL through 350 kV BIL (0.6 kV NSV through 69 kV NSV)

NATIONAL FIRE PROTECTION ASSOCIATION (NFPA)

NFPA 30 (2018) Flammable and Combustible Liquids Code

NFPA 37 (2018) Standard for the Installation and Use of Stationary Combustion Engines and Gas Turbines

NFPA 54 (2021) National Fuel Gas Code

NFPA 58 (2020) Liquefied Petroleum Gas Code

- NFPA 70 (2020; ERTA 20-1 2020; ERTA 20-2 2020; TIA 20-1; TIA 20-2; TIA 20-3; TIA 20-4)
National Electrical Code
- NFPA 99 (2021) Health Care Facilities Code
- NFPA 110 (2016) Standard for Emergency and Standby Power Systems

SOCIETY OF AUTOMOTIVE ENGINEERS INTERNATIONAL (SAE)

- SAE ARP892 (1965; R 1994) DC Starter-Generator, Engine
- SAE J537 (2016) Storage Batteries

U.S. DEPARTMENT OF DEFENSE (DOD)

- MIL-DTL-16884 (2017; Rev P) Fuel, Naval Distillate
- MIL-STD-461 (2015; Rev G) Requirements for the Control of Electromagnetic Interference Characteristics of Subsystems and Equipment

U.S. NATIONAL ARCHIVES AND RECORDS ADMINISTRATION (NARA)

- 40 CFR 60 Standards of Performance for New Stationary Sources

UNDERWRITERS LABORATORIES (UL)

- UL 142 (2006; Reprint Jul 2013) Steel Aboveground Tanks for Flammable and Combustible Liquids
- UL 467 (2013; Reprint Jun 2017) UL Standard for Safety Grounding and Bonding Equipment
- UL 489 (2016) UL Standard for Safety Molded-Case Circuit Breakers, Molded-Case Switches and Circuit-Breaker Enclosures
- UL 1236 (2015; Reprint Mar 2016) UL Standard for Safety Battery Chargers for Charging Engine-Starter Batteries
- UL 1437 (2006) Electrical Analog Instruments - Panel Board Types

1.2 RELATED MATERIALS

Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM, and Section 26 08 00 APPARATUS INSPECTION AND TESTING apply to this section, except as modified herein.

1.3 SUBMITTALS

Government approval is required for submittals with a "G" designation; submittals not having a "G" designation are for Contractor Quality Control approval. Submittals with an "S" are for inclusion in the Sustainability eNotebook, in conformance to Section 01 33 29 SUSTAINABILITY REPORTING.

Submit the following in accordance with Section 01 33 00 SUBMITTAL PROCEDURES:

SD-02 Shop Drawings

Engine-Generator Set and Auxiliary Equipment; G

Auxiliary Systems; G

Detailed Drawings; G

Acceptance; G

SD-03 Product Data

Harmonic Requirements; G

Engine-Generator Set Efficiencies; G

Emissions; G

filters; G

special tools; G

Engine-Generator Parameter Schedule

Heat Exchanger

Generator

Manufacturer's Catalog

Site Welding

Spare Parts

Onsite Training

Vibration-Isolation

Posted Data and Instructions; G

Instructions; G

Experience

Field Engineer

General Installation

Exciter

SD-05 Design Data

Performance Criteria

Sound Limitations; G

Integral Main Fuel Storage Tank

Day Tank

Power Factor

Heat Exchanger

Time-Delay on Alarms

Cooling System

Vibration Isolation

Battery Charger

Capacity Calculations for Engine-Generator Set; G

Brake Mean Effective Pressure (BMEP) Calculations; G

Torsional Vibration Stress Analysis Computations; G

Capacity Calculations for Batteries; G

Turbocharger Load Calculations; G

SD-06 Test Reports

Performance Tests

Factory Inspection and Tests

Factory Tests

Onsite Inspection and Tests; G

Acceptance Checks and Tests; G

Functional Acceptance Tests; G

Maintenance Procedures; G

Operation and Maintenance Manuals; G

Inspections; G

Functional Acceptance Test Procedure; G

SD-07 Certificates

Cooling System

Vibration Isolation

Prototype Test

Reliability and Durability

Fuel System Certification; G
Start-Up Engineer; G
Instructor's Qualification Resume; G
Engine Emission Limits; G
Sound Limitations
Site Visit
Current Balance
Materials and Equipment
Factory Inspection and Tests

SD-09 Manufacturer's Field Reports

Engine Tests; G
Generator Tests; G
Assembled Engine-Generator Set Tests; G

SD-10 Operation and Maintenance Data

Preliminary Assembled Operation and Maintenance Manuals; G
Submit in accordance with Section 01 78 23 OPERATION AND MAINTENANCE DATA and the paragraph ASSEMBLED OPERATION AND MAINTENANCE MANUALS.

SD-11 Closeout Submittals

Posted Data and Instructions; G
Training Plan; G

1.4 QUALITY ASSURANCE

1.4.1 Conformance to Codes and Standards

Where equipment is specified to conform to requirements of any code or standard such as UL, NEMA, etc., the design, fabrication and installation must also conform to the code.

1.4.2 Site Welding

Weld structural members in accordance with Section 05 05 23.16 STRUCTURAL WELDING. For all other welding, qualify procedures and welders in accordance with ASME BPVC SEC IX.

- a. Welding procedures qualified by others, and welders and welding operators qualified by a previously qualified employer may be accepted as permitted by ASME B31.1.

- b. Submit a copy of qualifying procedures and a list of names and identification symbols of qualified welders and welding operators.
- c. Submit a letter listing the welder qualifying procedures for each welder, complete with supporting data such as test procedures used, what was tested to, and a list of the names of all welders and their identification symbols.
- d. Perform welder qualification tests for each welder whose qualifications are not in compliance with the referenced standards. Notify the Contracting Officer 24 hours in advance of qualification tests which must be performed at the work site, if practical.
- e. The welder or welding operator must apply the personally assigned symbol near each weld made as a permanent record.

1.4.3 Vibration Limitation

Limit the maximum engine-generator set vibration in the horizontal, vertical, and axial directions to **6 mils** (peak-peak RMS), with an overall velocity limit of **0.95 inches/second** RMS, at rated speed for all loads through 110 percent of rated speed. The engine-generator set must be provided with vibration isolation in accordance with the manufacturer's standard recommendation. Where the vibration isolation system does not secure the base to the structure floor or unit foundation, provide seismic restraints in accordance with the seismic parameters specified.

1.4.4 Torsional Analysis

Submit torsional analysis including prototype testing or calculations which certify and demonstrate that no damaging or dangerous torsional vibrations will occur when the prime mover is connected to the generator, at synchronous speeds, plus/minus 10 percent.

1.4.5 Performance Data

Submit vibration isolation system performance data for the range of frequencies generated by the engine-generator set during operation from no load to full load and the maximum vibration transmitted to the floor. Also submit a description of seismic qualification of the engine-generator mounting, base, and vibration isolation.

1.4.6 Experience

Each component manufacturer must have a minimum of 3 years' experience in the manufacture, assembly and sale of components used with stationary engine-generator sets for commercial and industrial use. The engine-generator set manufacturer/assembler must have a minimum of 3 years' experience in the manufacture, assembly and sale of stationary engine-generator sets for commercial and industrial use. Submit a statement showing and verifying these requirements.

1.4.7 Field Engineer

The engine-generator set manufacturer or assembler must furnish a qualified field engineer to supervise the complete installation of the engine-generator set, assist in the performance of the onsite tests, and instruct personnel as to the operational and maintenance features of the equipment. The field engineer must have attended the engine generator

manufacturer's training courses on installation and operation and maintenance of engine generator sets. Submit a letter listing the qualifications, schools, formal training, and experience of the field engineer.

1.4.8 Detailed Drawings

Submit detailed drawings showing the following:

- a. Base-mounted equipment, complete with base and attachments, including anchor bolt template and recommended clearances for maintenance and operation.
- b. Starting system.
- c. Fuel system.
- d. Cooling system.
- e. Exhaust system.
- f. Electric wiring of relays, breakers, programmable controllers, and switches including single line and wiring diagrams.
- g. Lubrication system, including piping, pumps, strainers, filters, electric heater, controls and wiring.
- h. Location, type, and description of vibration isolation devices for all applications.
- i. The safety system, including wiring schematics.
- j. One-line schematic and wiring diagrams of the generator, exciter, regulator, governor, and instrumentation.
- k. Panel layouts.
- l. Mounting and support for each panel and major piece of electrical equipment.
- m. Engine-generator set rigging points and lifting instructions.

1.4.9 Auxiliary Systems Engine-Generator Set and Auxiliary Equipment Drawing Requirements

Submit drawings pertaining to the engine-generator set and auxiliary equipment, including but not limited to the following:

- a. Certified outline, general arrangement (setting plan), and anchor bolt details. Show total weight and center of gravity of assembled equipment on the steel sub-base.
- b. Detailed elementary, schematic wiring, and interconnection diagrams of the engine starting system, jacket coolant heating system, engine protective devices, engine alarm devices, engine speed governor system, generator and excitation system, and other integral devices.
- c. Detailed elementary, schematic wiring; and interconnection diagrams of the fuel system, starting battery system, engine-generator control

panel, generator circuit breaker.

- d. Dimensional drawings or catalog cuts of exhaust silencers, radiator, fuel day tanks, fuel oil cooler, valves and pumps, intake filters, vibration isolators, and other auxiliary equipment not integral with the engine-generator set.

1.4.10 Vibration Isolation System Certification

Submit certification from the manufacturer that the vibration isolation system will reduce the vibration to the limits specified in the paragraph VIBRATION ISOLATION.

1.4.11 Fuel System Certification

When the fuel system requires a fuel oil cooler as described in the paragraph FUEL OIL COOLER, submit certification from the engine manufacturer that the fuel system design is satisfactory.

1.5 DELIVERY, STORAGE, AND HANDLING

Properly protect materials and equipment, in accordance with the manufacturers recommended storage procedures, before, during, and after installation. Protect stored items from the weather and contamination. During installation, cap piping and similar openings to keep out dirt and other foreign matter.

Deliver equipment on pallets or blocking wrapped in heavy-duty plastic, sealed to protect parts and assemblies from moisture and dirt. Protect and prepare batteries for shipment as recommended by the battery manufacturer. Store auxiliary equipment at the site in covered enclosures, protected from atmospheric moisture, dirt, and ground water.

1.6 EXTRA MATERIALS

Provide two sets of special tools and two sets of filters required for maintenance. Special tools are those that only the manufacturer provides, for special purposes, or to reach otherwise inaccessible parts. One handset must be provided for each electronic governor when required to indicate and/or change governor response settings. Furnish 4 liters one gallon of identical paint used on engine-generator set in manufacturer's sealed container with each engine-generator set.

Wrenches and tools specifically designed and required to work on the new equipment, which are not commercially available as standard mechanic's tools, must be furnished to the Contracting Officer.

Provide proposed operating instructions for the engine-generator set and auxiliary equipment laminated between matte-surface thermoplastic sheets and suitable for placement adjacent to corresponding equipment. After approval, install operating instructions where directed.

1.7 MAINTENANCE SERVICES

Submit the operation and maintenance manuals and have them approved prior to commencing onsite tests.

1.7.1 Operation Manual

Provide three copies of the manufacturers standard operation manual . Sections must be separated by heavy plastic dividers with tabs which identify the material in the section. Fold drawings with the title block visible, and placed in 8-1/2 by 11 inch plastic pockets with reinforced holes. The manual must include:

- a. Step-by-step procedures for system startup, operation, and shutdown;
- b. Drawings, diagrams, and single-line schematics to illustrate and define the electrical, mechanical, and hydraulic systems with their controls, alarms, and safety systems;
- c. Procedures for interface and interaction with related systems to include automatic transfer switches fire alarm/suppression systems .

1.7.2 Maintenance Manual

Provide three copies of the manufacturers standard maintenance manual . Separate each section by a heavy plastic divider with tabs. Fold drawings with the title block visible, and placed in plastic pockets with reinforced holes. The manual must include:

- a. Procedures for each routine maintenance item. Procedures for troubleshooting. Factory-service, take-down overhaul, and repair service manuals, with parts lists.
- b. The manufacturer's recommended maintenance schedule.
- c. A component list which includes the manufacturer's name, address, type or style, model or serial number, rating, and catalog number for the major components.
- d. A list of spare parts for each piece of equipment and a complete list of materials and supplies needed for operation.

1.7.3 Assembled Operation and Maintenance Manuals

The contents of the assembled operation and maintenance manuals must include the manufacturer's O&M information required by the paragraph SD-10, OPERATION AND MAINTENANCE DATA and the manufacturer's O&M information specified in Section 26 36 23 AUTOMATIC TRANSFER SWITCHES AND BY-PASS/ISOLATION SWITCH.

- a. Manuals must be in separate books or volumes, assembled and bound securely in durable, hard covered, water resistant binder, and indexed by major assembly and components in sequential order.
- b. A table of contents (index) must be made part of the assembled O&M. The manual must be assembled in the order noted in table of contents.
- c. The cover sheet or binder on each volume of the manuals must be identified and marked with the words, "Operation and Maintenance Manual."

1.8 SITE CONDITIONS

Protect the components of the engine-generator set, including cooling

system components, pumps, fans, and similar auxiliaries when not operating and provide components capable of the specified outputs in the following environment:

- a. Site Location: MCB Camp Lejeune, North Carolina
- b. Site Elevation: 33 feet above mean sea level.
- c. Ambient Temperatures:
 - (1) Maximum 93.2 degrees F dry bulb, 78.1 degrees F wet bulb.
 - (2) Minimum 22.9 degrees F dry bulb.
- d. Design Wind Velocity: 150 mph.
- e. Prevailing Wind Direction: East
- f. Seismic Zone: Zone 0 as defined by ICC IBC.

PART 2 PRODUCTS

2.1 SYSTEM REQUIREMENTS

- a. Provide and install each engine-generator set complete and totally functional, with all necessary ancillary equipment to include: air filtration; starting system; generator controls, protection, and isolation; instrumentation; lubrication; fuel system; cooling system; and engine exhaust system. Each engine-generator set must satisfy the requirements specified in the Engine-Generator Parameter Schedule. Submit certification that the engine-generator set and cooling system function properly in the ambient temperatures specified.
- b. Provide each engine-generator set consisting of one engine, one generator, and one exciter mounted, assembled, and aligned on one base; and all other necessary ancillary equipment which may be mounted separately. Assemble sets having a capacity of 750 kW or smaller and attach to the base prior to shipping. Sets over 750 kW capacity may be shipped in sections. Provide set components that are environmentally suitable for the locations shown and that are the manufacturer's standard product offered in catalogs for commercial or industrial use. Provide a generator strip heater for moisture control when the generator is not operating. Identify any nonstandard products or components and the reason for their use.

2.1.1 Engine-Generator Parameter Schedule

Engine-Generator Set and Auxiliary Equipment Capacity Calculations for Engine-Generator Set

ENGINE-GENERATOR PARAMETER SCHEDULE	
Identification	Make/Model
Electrical Characteristics	

ENGINE-GENERATOR PARAMETER SCHEDULE	
Power Rating	Emergency Standby Gross bhp rating / Net brake power rating As shown on plans kW at 0.8 power factor
Governor Type	Type Make / Model Isochronous
Overload Capacity (Prime applications only)	110 percent of Service Load for 1 hour in 12 consecutive hours
Service Load	Fire Pump Generator: 969.5 - Pumping Station Generator: 914.2 kVA (maximum) Fire Pump Generator: 969.5 - Pumping Station Generator: 914.2 kVA (continuous)
Motor Starting kVA (Max.)	Fire Pump Generator: 931.4 - Pumping Station Generator: 946.4 kVA
Power Factor	0.8 lagging
Engine-Generator Applications	stand-alone
Voltage Regulation (No Load to Full Load) (Stand-alone applications)	plus or minus 2 percent (maximum)
Voltage Bandwidth (steady state)	plus or minus 1 percent
Frequency	60 Hz
Voltage	480Y/277 volts
Phases	3 Phase, Wye
Minimum Generator Sub-transient Reactance	10 percent Sub-transient
Nonlinear Loads	Fire Pump Generator: 0.0 - Pumping Station Generator: 902 kVA
Max Step Load Increase	50 percent of Service Load at 0.8 PF
Transient Recovery Time with Step Load Increase (Voltage)	5 seconds
Transient Recovery	5 seconds
Time with Step Load Increase (Frequency)	
Maximum Voltage Deviation with Step Load Increase	30 percent of rated voltage

ENGINE-GENERATOR PARAMETER SCHEDULE	
Mechanical Characteristics	
Engine Description	Strokes/cycle Number of cylinders Bore and Stroke, inches
Engine Speed	1800 rpm
Piston Speed	2250 fpm
Heat Exchanger Type	fin-tube (radiator)
Engine Cooling Type	water/ethylene glycol
Intercooler Type	Air-to-Air / Jacket Water
Induction Method	Naturally Aspirated / Turbocharged
Turbocharger	Make / Model
Max Time to Start and be Ready to Assume Load	10 seconds
Max Summer Indoor Temp (Prior to Engine-generator Operation)	N/A degrees F
Min Winter Indoor Temp (Prior to Engine-generator Operation)	N/A degrees F
Max Allowable Heat Transferred To Engine Generator Space at Rated Output Capacity	N/A MBTU/hr
Max Summer Outdoor Temp (Ambient)	93 degrees F
Min Winter Outdoor Temp (Ambient)	23 degrees F
Installation Elevation	26 above sea level
Engine-Generator Set Efficiencies	
Fuel Consumption	At 0.8 power factor, Gallons / hour for: 1 / 2 load 3 / 4 load Full Load
Generator Efficiency	At 0.8 power factor, (per cent) for: 1 / 2 load 3 / 4 load Full Load

ENGINE-GENERATOR PARAMETER SCHEDULE	
Radiator Capacity	Coolant Type gpm coolant cfm air through radiator Btu per hr of heat exchange based on optimum coolant temperature to and from engine
Engine-Generator Set Emissions Data	
Exhaust Temperature	Degrees F at full load
Weight of Exhaust Gas	lb per hr at full load
Weight of Intake Air	lb per hr at full load
Total Heat Rejected	Btu per hr, at full load to: Jacket Coolant System Fuel Oil Cooling System
Emissions	lb per hr, at full load Total Suspended Particulate Particulate Matter with an average aerodynamic diameter of 10 microns Sulfur Dioxides Nitrogen Oxides (as NO2) Carbon Monoxide Volatile Organic Compounds
Visible Emissions	Percent opacity at full load
Brake Mean Effective Pressure (BMEP) Calculations	
<p>Calculation must verify that the engine meets the specified maximum BMEP, as follows:</p> $\text{BMEP psi} = \frac{(120,000 \times \text{bkW}) \times (792,000 \times \text{bhp})}{(\text{rpm} \times \text{cu. in.})}$ <p>Where:</p> <p>$\text{bkW bhp} = \text{bkW}' + \text{bkW}'' \text{ bhp}' + \text{bhp}''$ $\text{bkW}'' \text{ bhp}''$ is the Brake kW horsepower required by engine driven fan for cooling radiator or motor driven fan for cooling radiator. $\text{bkW}' \text{ bhp}' = \text{kW}/\text{GEN.EFF. kW}/(\text{GEN.EFF. times } 0.746)$ GEN.EFF. = Generator efficiency cu. in. = Total engine piston displacement in cubic inches rpm = Engine revolutions per minute kW = Minimum power rating</p>	
Torsional Vibration Stress Analysis Computations	

ENGINE-GENERATOR PARAMETER SCHEDULE
<p>Torsional vibrational stresses in the crankshaft and generator shaft of assembled engine and driven generator must not exceed 5000 psi when engine is driving generator at rated speed while assembled unit is loaded to rated engine-generator set power. Computations must be based on a mathematical model of the assembled generator set provided or based on calculations using measured values from tests on a unit identical to the one provided. Calculations based on models of, or measured data from, the unassembled engine and generator will not be acceptable. Calculations must include:</p> <ul style="list-style-type: none"> a. A description of the system relating information pertinent to analysis such as operating speed range and identification plate data. b. A mass elastic assembly drawing, showing the arrangement of the units in the generator set and dimensions of shafting, including minimum diameters (or section moduli) of shafting in the system. c. A labeled line diagram of the mass elastic system indicating values of masses, stiffness, equivalent lengths, and equivalent diameters including basic assumptions and definition of terms. d. Sample computations showing procedures used to obtain resulting stress values. e. Computations indicating assembled engine-generator speed of 1800 rpm with assembly loaded to rated generator power and the resulting computed critical torsional stress values in the assembled engine crankshaft and generator shaft.
Turbocharger Load Calculations
<p>NOTE: When the engine-generator set installation includes field installed exhaust system (i.e., the engine-generator set is installed internal to a building in lieu of in a self-contained outdoor enclosure), include the following paragraph.</p> <p>When the proposed exhaust system layout is different from that shown on the contract drawings, submit calculations showing that the external loads from the exhaust system such as weight and thermal expansion do not exceed the engine manufacturer's maximum allowed forces and moments on the turbocharger.</p>

2.1.2 Rated Output Capacity

Provide each engine-generator-set with power equal to the sum of service load plus the machine's efficiency loss and associated ancillary equipment

loads. Rated output capacity must also consider engine and/or generator oversizing required to meet requirements in paragraph Engine-Generator Parameter Schedule.

The engine must meet the specified maximum BMEP requirements at rated speed as calculated in accordance with the calculations in the engine-generator parameter schedule. The engine capacity must be based on the following:

- a. Engine burning diesel fuel conforming to MIL-DTL-16884 or ASTM D975, Grade 2-Dat an ambient temperature of 85 degrees F. For stationary engines operated in the United States, diesel fuel requirements are found in 40 CFR 60 Subpart IIII.
- b. Engine cooled by a radiator fan mechanically driven by the engine or remote with a motor driven fan.
- c. Engine cooled by coolant mixture of water and ethylene glycol, 50 percent by volume of each.

Maximum BMEP, psi			
	Naturally Aspirated	Turbocharged	Turbocharged and Intercooled
Four-cycle engines		340	
Engine speed, rpm:		1800	

2.1.2.1 Engine Emission Limits

Engine must be certified by the manufacturer to meet applicable EPA emission standards found in 40 CFR 60 Subpart IIII. In addition, engine must meet any applicable state or local emission requirements (ex: California SCAQMD).

2.1.2.2 Performance Class

The voltage and frequency behavior of the generator set must be in accordance with ISO 8528 operating limit values for performance Class G2.

2.1.3 Power Ratings

Power ratings must be in accordance with EGSA 101P.

2.1.4 Transient Response

The engine-generator set governor and voltage regulator must cause the engine-generator set to respond to the maximum step load changes such that output voltage and frequency recover to and stabilize within the operational bandwidth within the transient recovery time. The engine-generator set must respond to maximum step load changes such that the maximum voltage and frequency deviations from bandwidth are not exceeded.

2.1.5 Reliability and Durability

Each standby engine-generator set must have both an engine and a generator capable of delivering the specified power on a standby basis with an anticipated mean time between overhauls of no less than 5,000

hours operating with a load factor of 70 percent. Cite two like engines and two like generators that have performed satisfactorily in a stationary power plant, independent and separate from the physical location of the manufacturer's and assembler's facilities, for standby without any failure to start, including all periodic exercise. Provide like engines and generators that have had no failures resulting in downtime for repairs in excess of 72 hours during two consecutive years of service. Provide engines that are the same model, speed, bore, stroke, number and configuration of cylinders, and rated output capacity. Provide generators that are the same model, speed, pitch, cooling, exciter, voltage regulator and rated output capacity.

Submit a reliability and durability certification letter from the manufacturer and assembler to prove that existing facilities are and have been successfully utilizing the same components proposed to meet this specification, in similar service. Certification may be based on components, i.e. engines used with different models of generators and generators used with different engines, and does not exclude annual technological improvements made by a manufacturer in the basic standard-model component on which experience was obtained, provided parts interchangeability has not been substantially affected and the current standard model meets the performance requirements specified. Provide a list with the name of the installations, completion dates, and name and telephone number of a point of contact.

2.1.6 Engine-Generator Set Enclosure

Provide engine-generator set enclosures that are corrosion resistant and fully weather resistant. The enclosure must contain all set components and provide ventilation to permit operation at Service Load under secured conditions. Provide access doors to controls and equipment requiring periodic maintenance or adjustment. Provide removable panels for access to components requiring periodic replacement. The enclosure must be capable of being removed without disassembly of the engine-generator set or removal of components other than the exhaust system. The enclosure must reduce the noise of the generator set to within the limits specified in the paragraph SOUND LIMITATIONS.

2.1.7 Vibration Isolation

Provide an engine-generator set with a vibration isolation system in accordance with the manufacturer's standard recommendation. Submit vibration isolation system performance data for the range of frequencies generated by the engine-generator set during operation from no load to full load and the maximum vibration transmitted to the floor plus description of seismic qualification of the engine-generator mounting, base, and vibration isolation. Submit torsional analysis including prototype testing or and calculations which certify and demonstrate that no damaging or dangerous torsional vibrations will occur when the prime mover is connected to the generator, at synchronous speeds, plus 10 percent. Design and qualify vibration isolation systems as an integral part of the base and mounting system in accordance with the seismic parameters specified. Where the vibration isolation system does not secure the base to the structure floor or unit foundation, provide seismic restraints in accordance with the seismic parameters specified.

2.1.8 Harmonic Requirements

Non-linear loads to be served by each engine-generator set are as

indicated. The maximum linear load demand (kVA at PF) when non-linear loads will also be in use is as indicated.

2.1.9 Starting Time Requirements

Upon receipt of a signal to start, each engine generator set will start, reach rated frequency and voltage and be ready to assume load within the time specified. For standby sets used in emergency power applications, each engine generator set will start, reach rated frequency and voltage, and power will be supplied to the load terminals of the automatic transfer switch within the starting time specified.

2.2 NAMEPLATES

Provide the manufacturer's name, type or style, model or serial number and rating on a plate secured to the equipment for each major component of this specification. Provide plates and tags sized so that inscription is readily legible to operating or maintenance personnel and securely mounted to or attached in proximity of their identified controls or equipment. Lettering must be normal block lettering, a minimum of 0.25 inch high. As a minimum, provide nameplates for:

Engines	Relays
Generators	Transformers (CT & PT)
Regulators	Day tanks
Pumps and pump motors	Governors
Generator Breaker	Air Starting System
Economizers	Heat exchangers (other than base mounted)

Where the following equipment is not provided as a standard component by the engine generator set manufacturer, the nameplate information may be provided in the maintenance manual in lieu of nameplates.

Battery charger	Heaters
Switchboards	Exhaust mufflers
Switchgear	Silencers
Battery	Exciters

2.2.1 Materials

Construct ID plates and tags of 16 gage minimum thickness bronze or stainless steel sheet metal engraved or stamped with inscription. Construct plates and tags not exposed to the weather or high operational temperature of the engine of laminated plastic, 0.125 inch thick, matte white finish with black center core, with lettering accurately aligned and engraved into the core.

2.2.2 Control Devices and Operation Indicators

Provide ID plates or tags for control devices and operation indicators, including valves, off-on switches, visual alarm annunciators, gages and thermometers, that are required for operation and maintenance of provided mechanical systems. Plates or tags must be minimum of 0.5 inch high and 2 inches long and must indicate component system and component function.

2.2.3 Equipment

Provide ID plates of a minimum size of high and 5 inches long on provided equipment indicating the following information:

- a. Manufacturer's name, address, type and model number, serial number, and certificate of compliance with applicable EPA mission standards;
- b. Contract number and accepted date;
- c. Capacity or size;
- d. System in which installed; and
- e. System which it controls.

2.3 SAFETY DEVICES

Exposed moving parts, parts that produce high operating temperatures, parts which may be electrically energized, and parts that may be a hazard to operating personnel must be insulated, fully enclosed, guarded, or fitted with other types of safety devices. Install safety devices such that proper operation of the equipment is not impaired.

2.4 MATERIALS AND EQUIPMENT

Submit certification stating that where materials or equipment are specified to comply with requirements of UL, written proof of such compliance has been obtained. The label or listing of the specified agency, or a written certificate from an approved, nationally recognized testing organization equipped to perform such services, stating that the items have been tested and conform to the requirements and testing methods of the specified agency are acceptable as proof.

2.4.1 Circuit Breakers, Low Voltage

UL 489.

2.4.2 Filter Elements

Provide the manufacturer's standard fuel-oil, lubricating-oil, and combustion-air filter elements.

2.4.3 Instrument Transformers

NEMA/ANSI C12.11.

2.4.4 Revenue Metering

IEEE C57.13.

2.4.5 Pipe (Fuel/Lube-Oil, Compressed Air, Coolant, and Exhaust)

ASTM A53/A53M, or ASTM A106/A106M steel pipe. Pipe smaller than 2 inches must be Schedule 80. Pipe 2 inches and larger must be Schedule 40.

2.4.5.1 Flanges and Flanged Fittings

ASTM A181/A181M, Class 60, or ASME B16.5, Grade 1, Class 150.

2.4.5.2 Pipe Welding Fittings

ASTM A234/A234M, Grade WPB or WPC, Class 150 or ASME B16.11, 3000 lb.

2.4.5.3 Threaded Fittings

ASME B16.3, Class 150.

2.4.5.4 Valves

MSS SP-80, Class 150.

2.4.5.5 Gaskets

Manufacturer's standard.

2.4.6 Pipe Hangers

MSS SP-58.

2.4.7 Electrical Enclosures

NEMA ICS 6.

2.4.7.1 Switchboards

NEMA PB 2.

2.4.7.2 Panelboards

NEMA PB 1.

2.4.8 Electric Motors

Provide electric motors that conform to the requirements of NEMA MG 1. Motors must have sealed ball bearings and a maximum speed of 1800 rpm. Motors used indoors must have drip-proof frames; enclose those that are used outside. Alternating current motors larger than 1/2 Hp must be of the squirrel-cage induction type for operation on 208 volts or higher, 60 Hz, and three-phase power. Alternating current motors 1/2 Hp or smaller, must be suitable for operation on 120 volts, 60 Hz, and single-phase power. Direct current motors must be suitable for operation on 125 volts.

2.4.9 Motor Controllers

Provide motor controllers and starters that conform to the requirements of NFPA 70 and NEMA ICS 2.

2.5 ENGINE

Each engine must operate on No. 2-D diesel fuel conforming to [ASTM D975](#), must be designed for stationary applications and must be complete with ancillaries. The engine must be a standard production model shown in the [manufacturer's catalog](#) describing and depicting each engine-generator set and all ancillary equipment in sufficient detail to demonstrate complete specification compliance. The engine must be naturally aspirated, supercharged, or turbocharged. The engine must be 2- or 4-stroke-cycle and compression-ignition type. The engine must be vertical in-line, V- or opposed-piston type, with a solid cast block or individually cast cylinders. The engine must have a minimum of two cylinders. Opposed-piston type engines must have more than four cylinders. Each block must have a coolant drain port. Equip each engine with an over-speed sensor.

[ISO 3046](#). Diesel engines must be four-cycle naturally aspirated, or turbocharged, or turbocharged and intercooled; vertical in-line or vertical Vee type; designed for stationary service. Engines must be capable of immediate acceleration from rest to normal speed without intermediate idle/warm up period or pre-lubrication to provide essential electrical power. Two-cycle engines are not acceptable.

2.5.1 Sub-base Mounting

Mount each engine-generator set on a structural steel sub-base sized to support the engine, generator, and necessary accessories, auxiliaries and control equipment to produce a complete self-contained unit as standard with the manufacturer. Design the structural sub-base to properly support the equipment and maintain proper alignment of the engine-generator set in the specified seismic zone. In addition, provide sub-base with both lifting rings and jacking pads properly located to facilitate shipping and installation of the unit. Factory align engine and generator on the sub-base and securely bolt into place in accordance with the manufacturer's standard practice. Crankshaft must have rigid coupling for connection to the generator.

2.5.2 Assembly

Completely shop assemble each engine-generator set on its structural steel sub-base. Paint entire unit with manufacturer's standard paints and colors. After factory tests and before shipping, thoroughly clean and retouch painting as necessary to provide complete protection.

2.5.3 Turbocharger

If required by the manufacturer to meet the engine-generator set rating, provide turbine type driven by exhaust gas from engine cylinders, and direct connected to the blower supplying air to the engine intake manifold.

2.5.4 Intercooler

Provide manufacturer's standard intercooler for engine size specified.

2.5.5 Crankcase Protection

2.5.6 Miscellaneous Engine Accessories

Provide the following engine accessories where the manufacturer's standard

design permits:

- a. Piping on engine to inlet and outlet connections, including nonstandard companion flanges.
- b. Structural steel sub-base and vibration isolators, foundation bolts, nuts, and pipe sleeves.
- c. Level jack screws or shims, as required.
- d. Rails, chocks, and shims for installation of sub-base on the foundation.
- e. Removable guard, around fan. Support guard, on engine sub-base, to suit manufacturer's standard.

2.5.7 Intercooler

Provide manufacturer's standard intercooler for engine size specified.

2.6 FUEL SYSTEM

Provide fuel system conforming to the requirements of [NFPA 30](#) and [NFPA 37](#) and containing the following elements.

2.6.1 Pumps

Fuel transfer pumps may be mounted on the day tank. Pumps must be horizontal, positive displacement. Direct-connect pump to motor through a flexible coupling. Equip each pump with a bypass relief valve, if not provided with an internal relief valve. Provide motor and controller in accordance with the paragraphs ELECTRIC MOTORS and MOTOR CONTROLLERS, respectively.

2.6.1.1 Main Pump

Provide engines with an engine driven pump. The pump must supply fuel at a minimum rate sufficient to provide the amount of fuel required to meet the performance indicated within the parameter schedule. Base the fuel flow rate on meeting the load requirements and all necessary recirculation.

2.6.1.2 Auxiliary Fuel Pump

Provide auxiliary fuel pumps to maintain the required engine fuel pressure, if either required by the installation or indicated on the drawings. The auxiliary pump must be driven by a dc electric motor powered by the starting/station batteries. Automatically actuate the auxiliary pump by a pressure-detecting device.

2.6.2 Fuel Filter

Provide a minimum of one full-flow fuel filter for each engine. The filter must be readily accessible and capable of being changed without disconnecting the piping or disturbing other components. Mark the inlet and outlet connections of the filter.

Provide intake filter assemblies for each engine of the oil bath or dry type, as standard with the manufacturer. Filters must be capable of removing a minimum of 92 percent of dirt and abrasive 3 microns and larger

from intake air. Size filters to suit engine requirements at 100 percent of rated full load. Design unit for field access for maintenance purposes.

2.6.3 Relief/Bypass Valve

Provide a relief/bypass valve to regulate pressure in the fuel supply line, return excess fuel to a return line and prevent the build-up of excessive pressure in the fuel system.

2.6.4 Integral Main Fuel Storage Tank

Provide each engine with an integral main fuel tank. Each tank must be factory installed and provided as an integral part of the generator manufacturer's product. Provide each tank with connections for fuel supply line, fuel return line, local fuel fill port, gauge, vent line, and float switch assembly. Provide a fuel return line cooler as recommended by the manufacturer and assembler. The temperature of the fuel returning to the tank must be below the flash point of the fuel. Mount the tank within the enclosure for each engine-generator set provided with weatherproof enclosures. The fuel fill line must be accessible without opening the enclosure.

- a. All Tanks: **UL 142**. Provide integral in skid double wall (110 percent containment) fuel tanks with a capacity as indicated. Epoxy coat day tanks inside and prime and paint outside. Construct tanks of not less than **3/16 inch** steel plate with welded joints and necessary stiffeners on exterior of tank. Provide a braced structural steel framework support. Weld tank top tight. Provide **4 1/2 inch** square inspection port with a 2 inch NPT fill connection and spill box. Provide proper normal and emergency venting for the primary tank and emergency venting only for the secondary tank / containment basin in accordance with **UL 142** requirements.
- b. Float Switches for Day Tanks: Provide tank-top mounted or external float cage, single-pole, single-throw type designed for use on fuel oil tanks. Arrange high level float switches to close on rise of liquid level, and low level float switches to close on fall of liquid level. Mount float cage units with isolating and drain valves. Contacts must be suitable for the station battery voltage.
 - (1) Critical low level float switch which must activate at 5 percent of normal liquid level must shut engine off.
 - (2) Low-low level float switch which must activate alarm at 30 percent of normal liquid level.
 - (3) Low level float switch which must open the fuel oil solenoid valve and start the fuel transfer pump at 75 percent of normal liquid level.
 - (4) High level float switch which must close the fuel oil solenoid valve and stop the fuel transfer pump at 90 percent of normal liquid level.
 - (5) Critical high level float switch which must activate alarm at 95 percent of normal liquid level.
- c. Leak Detector Switch for All Tanks: Actuates when fuel is detected in containment basin, stops fuel transfer pump, and closes the fuel oil

solenoid valve.

- d. Control Panel for All Tanks: Provide NEMA ICS 6, Type 4X stainless steel, enclosed control panel for each day tank. Control panel must include the following accessories.
 - (1) Power available LED (green).
 - (2) Critical low fuel alarm contacts for shut down of engine.
 - (3) Low-low level fuel alarm LED.
 - (4) Low-low level fuel alarm contracts for remote annunciator.
 - (5) Critical high level fuel alarm LED.
 - (6) Leak detecting alarm LED.
 - (7) Alarm horn.
- e. Tank Gages for All Tanks: Provide buoyant force type gages for fuel tanks with dial indicator not less than 4 inches in size and arranged for top mounting. Calibrate each reading dial or scale for its specific tank to read from empty to full, with intermediate points of 1/4, 1/2, and 3/4.
- f. Integral Base Tanks Used as Primary Tank: Provide a 2 inch opening at the tank fill port, fitted an overflow prevention valve (OPV). Additionally, the fill opening must be perpendicular to the tank in order to allow operation of the OPV. Integral base tank must be sized and configured such that the filling and venting nozzles are outside the generator cabinet for ease of accessibility, inspection, and maintenance. Level gage must be in the line of sight from the fill port.
- g. Integral Base Tanks Located Inside Buildings. The tank vents must discharge outside the building in accordance with NFPA 30 and NFPA 37. The fill pipe must terminate outside the building. The fill pipe connection point must be housed in a sealed spill box. High level alarms or level gauges used as overflow protection mechanisms must announce at the fill connection point. Provide an overflow prevention valve (OPV) at the tank with a check valve mounted on the fill line in the spill box. The fill connection point must be labeled with tank contents and capacity.
- h. External tanks (all non-integral base tanks) are specified in Section 33 56 10 FACTORY-FABRICATED FUEL STORAGE TANKS.

2.6.4.1 Fuel Transfer Pumps

Fuel transfer pumps may be mounted on the day tank. Pumps must be horizontal, positive displacement. Direct-connect pump to motor through a flexible coupling. Equip each pump with a bypass relief valve, if not provided with an internal relief valve. Provide motor and controller in accordance with the paragraphs ELECTRIC MOTORS and MOTOR CONTROLLERS, respectively.

2.6.4.2 Capacity

Each tank must have capacity as shown at 100 percent rated load without being refilled.

2.6.4.3 Local Fuel Fill

Each local fuel fill port on the day tank must have a screw-on cap.

2.6.4.4 Fuel Level Controls

Provide tanks with a float-switch assembly to perform the following functions:

- a. Activate the "Low Fuel Level" alarm at 70 percent of the rated tank capacity.
- b. Activate the "Overfill Fuel Level" alarm at 95 percent of the rated tank capacity.

2.6.4.5 Arrangement

Integral tanks may allow gravity flow into the engine. Gravity flow tanks and any tank that allows a fuel level above the fuel injectors must have an internal or external factory installed valve located as near as possible to the shell of the tank. The valve must close when the engine is not operating. Provide integral day tanks with any necessary pumps to supply fuel to the engine as recommended by the generator set manufacturer. The fuel supply line from the tank to the manufacturer's standard engine connection must be welded pipe.

2.6.5 Fuel Supply System

Provide the fuel supply from the main storage of fuel to the day tank as specified in Section 33 56 10 FACTORY-FABRICATED FUEL STORAGE TANKS.

2.6.6 Strainer

Simplex strainers must comply with Section 33 52 10 SERVICE PIPING, FUEL SYSTEMS.

2.6.7 Fuel Oil Meters

Fuel oil meter must comply with Section 33 52 10 SERVICE PIPING, FUEL SYSTEMS.

2.6.8 Fuel Oil Cooler

Provide an air cooled fuel oil cooler if the temperature of the fuel returned to the tank from the engine will cause overheating of the tank fuel above the maximum fuel temperature allowed by the engine manufacturer when operating at maximum rated generator power output and low fuel level in the tank. The fuel oil cooler must be furnished by the engine manufacturer for the application and the installation must be complete including piping and power requirements.

2.7 LUBRICATION

Provide engine with a separate lube-oil system conforming to NFPA 30 and

NFPA 37. Pressurize each system by engine-driven pumps. Regulate system pressure as recommended by the engine manufacturer. Provide a pressure relief valve on the crankcase for closed systems. Vent the crankcase in accordance with the manufacturer's recommendation. Do not vent the crankcase to the engine exhaust system. Crankcase breathers, if provided on engines installed in buildings or enclosures, must be piped to vent to the outside. The system must be readily accessible for service such as draining, refilling, etc. Each system must permit addition of oil and have oil-level indication with the set operating. The system must utilize an oil cooler as recommended by the engine manufacturer.

2.7.1 Lube-Oil Filter

Provide one full-flow filter for each pump. The filter must be readily accessible and capable of being changed without disconnecting the piping or disturbing other components. Mark inlet and outlet connections.

2.7.2 Lube-Oil Sensors

Equip each engine with lube-oil pressure sensors located downstream of the filters and provide signals for required indication and alarms. Submit two complete sets of filters, required for maintenance, supplied in a suitable storage box. Provide these filters in addition to filters replaced after testing.

2.7.3 Precirculation Pump

Provide a motor-driven precirculation pump powered by the station battery, complete with motor starter, if recommended by the engine manufacturer.

2.8 COOLING SYSTEM

Provide each engine with its own cooling system to operate automatically while its engine is running. The cooling system coolant must use a combination of water and ethylene-glycol sufficient for freeze protection at the minimum winter outdoor temperature specified. The maximum temperature rise of the coolant across each engine must not exceed that recommended below. Submit a letter which certifies that the engine-generator set and cooling system function properly in the ambient temperature specified, stating the following values:

- a. The maximum allowable inlet temperature of the coolant fluid.
- b. The minimum allowable inlet temperature of the coolant fluid through the engine.
- c. The maximum allowable temperature rise in the coolant fluid through the engine.
- d. The minimum allowable inlet fuel temperature.

2.8.1 Coolant Pumps

Provide centrifugal coolant pumps. Each engine must have an engine-driven primary pump. Provide secondary pumps that are electric motor driven and have automatic controllers. Control raw-water circulating pump by manual-off-automatic controllers and must be engine driven.

2.8.2 Heat Exchanger

Provide heat exchanger with the size and capacity to limit the maximum allowable temperature rise in the coolant across the engine to that recommended and submitted for the maximum summer outdoor design temperature and site elevation. Submit manufacturer's data to quantify heat rejected to the space with the engine generator set at rated capacity. Provide heat exchangers that are corrosion resistant, suitable for service in ambient conditions of application.

2.8.2.1 Fin-Tube-Type Heat Exchanger (Radiator)

Heat exchanger may be factory coated with corrosion resistant film, provided that corrective measures are taken to restore the heat rejection capability of the radiator to the initial design requirement via oversizing, or other compensating methods. Provide internal surfaces that are compatible with liquid fluid coolant used. Materials and coolant are subject to approval by the Contracting Officer. Provide heat exchangers that are pressure type incorporating a pressure valve, vacuum valve and a cap. Design caps for pressure relief prior to removal. Provide heat exchanger and cooling system that is capable of withstanding a minimum pressure of 7 psi and protect with a strong grille or screen guard. Provide heat exchanger with at least two tapped holes; equip one tapped hole with a drain cock, and plug the rest.

Provide for each engine-generator set, as standard with the manufacturer.

- a. Design Conditions: Each radiator unit must have ample capacity to remove not less than the total Btu per hour of heat rejected by its respective engine at 100 percent full-rated load to the jacket water, fuel oil, and lubricating oil system, and intercooler. Radiator capacity must be rated at optimum temperature of coolant leaving the engine and intercooler as recommended by the engine manufacturer with an ambient dry bulb air temperature outside the enclosure of 93 degrees F maximum, and 23 degrees F minimum at the site elevation specified in the paragraph SITE CONDITIONS, and with the coolant mixture specified in the paragraph ENGINE CAPACITY. Pressure drop through the radiator must not exceed 6 psi when circulating the maximum required coolant flow. Radiator air velocity must be a maximum of 1500 feet per minute.
- b. Engine Mounted Radiator Construction: Radiator fan must direct airflow from the engine outward through the radiator. Fan must be V-belt driven directly from the engine crankshaft. Radiator fan must have sufficient capacity to meet design conditions against a static restriction of 1 inch of water. Fan static capacity must be adjusted to suit the ductwork furnished. Cooling section must have a tube and fin-type core consisting of copper or copper base alloy tubes with nonferrous fins. Select engine-driven fans for quiet vibration-free operation. Make provision for coolant expansion either by self-contained expansion tanks or separately mounted expansion tanks, as standard with the manufacturer. Provide suitable guards for each fan and drive.
- c. Coolant solution must be a mixture of clean water and ethylene glycol, 50 percent by volume each. Provide an anti-freeze solution tester suitable for the mixture.

2.8.3 Thermostatic Control Valve

Provide a modulating type, thermostatic control valve in the coolant system to maintain the coolant temperature range submitted in paragraph SUBMITTALS.

2.8.4 Temperature Sensors

Equip each engine with coolant temperature sensors. Provide temperature sensors with signals for pre-high and high indication and alarms.

2.9 SOUND LIMITATIONS

Submit sound power level data for the packaged unit operating at 100 percent load in a free field environment. The data should demonstrate compliance with the sound limitation requirements of this specification. Submit certification from the manufacturer stating that the sound emissions meet the specification. Do not exceed the following sound pressure levels in any of the indicated frequencies when measured in a free field at a radial distance of 22.9 feet 7 meters at 45 degrees apart in all directions when operating at 100 percent load.

Frequency Band (Hz)	Maximum Acceptable Sound Level (Decibels)
31	72
63	72
125	72
250	72
500	72
1,000	72
2,000	72
4,000	72
8,000	72

2.10 AIR INTAKE EQUIPMENT

Locate filters and silencers in locations that are convenient for servicing. Provide high-frequency filter type silencers and locate in the air intake system as recommended by the engine manufacturer. Provide silencer to reduce the noise level at the air intake so that the indicated pressure levels specified in paragraph SOUND LIMITATIONS will not be exceeded. A combined filter-silencer unit meeting requirements for the separate filter and silencer items may be provided. Provide copper expansion elements in air-intake lines.

Provide intake filter assemblies for each engine of the oil bath or dry type, as standard with the manufacturer. Filters must be capable of removing a minimum of 92 percent of dirt and abrasive 3 microns and larger

from intake air. Size filters to suit engine requirements at 100 percent of rated full load. Design unit for field access for maintenance purposes.

2.11 EXHAUST SYSTEM

Provide a separate and complete system for each engine. Support piping to minimize vibration. Where a V-type engine is provided, use a V-type connector, with necessary flexible sections and hardware, to connect the engine exhaust outlets.

2.11.1 Flexible Sections and Expansion Joints

Provide a flexible section at each engine and an expansion joint at each muffler. Provide flexible sections and expansion joints that have flanged connections. Provide flexible sections made of convoluted seamless tube without joints or packing. Provide bellows type expansion joints. Provide stainless steel expansion and flexible elements suitable for engine exhaust gas at the maximum exhaust temperature that is specified by the engine manufacturer. Provide expansion and flexible elements that are capable of absorbing vibration from the engine and compensation for thermal expansion and contraction.

2.11.2 Exhaust Muffler

Provide a chamber type exhaust muffler. Provide welded steel muffler designed for outside horizontal mounting. Provide eyebolts, lugs, flanges, or other items as necessary for support in the location and position indicated. Do not exceed the engine manufacturer's recommended pressure drop. Outside mufflers must be zinc coated or painted with high temperature 400 degrees F resisting paint. The muffler and exhaust piping together must reduce the noise level to less than the maximum acceptable level listed for sound limitations in paragraph SOUND LIMITATIONS. Provide muffler with a drain valve, nipple, and cap at the low-point of the muffler.

A residential class silencer must be provided for each engine which will reduce the exhaust sound spectrum by the following listed values at a 75 foot radius from the outlet, with generator set loaded to rated capacity and clear weather. Inlet and outlet connections must be flanged.

Octave Band Center Frequency (Hertz)								
Minimum Silencer Attenuation Decibels	63	125	250	500	1000	2000	4000	8000
Residential Class	10	25	32	30	25	25	24	23

2.11.3 Exhaust Piping

Slope horizontal sections of exhaust piping downward away from the engine to a drip leg for collection of condensate with drain valve and cap. Changes in direction must be long radius. Insulate exhaust piping, mufflers and silencers installed inside any building in accordance with paragraph THERMAL INSULATION and covered to protect personnel. Provide vertical exhaust piping with a hinged, gravity-operated, self-closing, rain cover.

Field installed exhaust piping must conform to the following:

- a. Exhaust Piping: Provide flanges for connections to engines, exhaust mufflers, and flexible connections. Provide steel pipe conforming to [ASTM A53/A53M](#) for each engine complete with necessary fittings, flanges, gaskets, bolts, and nuts. Exhaust piping must be Schedule 40 pipe for [12 inches](#) and smaller, standard weight for sizes [14 inches](#) through [24 inches](#), and [0.25 inch](#) wall thickness for sizes larger than [24 inches](#). Flanges must be Class 150 slip-on forged steel welding flanges in accordance with [ASME B16.5](#), with material in accordance with [ASTM A181/A181M](#), Grade I. Fittings must be butt welding conforming to [ASTM A234/A234M](#), with wall thickness same as adjoining piping. Fittings must be of same material and wall thickness as pipe. Built-up miter welded fittings may be used. Miter angles of each individual section must not exceed 22.5 degrees total and not more than 11.25 degrees relative to the axis of the pipe at any one cut. Gaskets for exhaust piping must be of high temperature asbestos-free material suitable for the service and must be [ASME B16.21](#), composition ring, [0.0625 inch](#) thick. Bolting material for exhaust flanges must be alloy-steel bolt-studs conforming to [ASTM A193/A193M](#), Grade B7 bolts and alloy-steel nuts conforming to [ASTM A194/A194M](#), Grade 7. Bolts must be of sufficient length to obtain full bearing on the nuts and must project not more than two full threads beyond the nut. Provide stainless steel counterbalance type rain caps at termination of each exhaust pipe.
- b. Expansion (Flexible) Joints: Provide sections of multiple corrugated stainless steel expansion joints in the engine exhaust piping for each engine to absorb expansion strains and vibration transmitted to the piping. Flexible joints must be suitable for operation at [200 degrees F](#) above normal exhaust gas temperature at 100 percent load, 10,000 cycles, minimum. Joints must be flanged and located between engine exhaust manifold and exhaust piping, must be the same size as exhaust piping size, and must be designed and constructed for engine exhaust service.
- c. Hangers and Supports: [MSS SP-58](#).
- d. Piping Sleeves: Provide where piping passes through masonry or concrete walls, floors, roofs, and partitions. Sleeves must be placed during construction. Unless indicated otherwise, pipe sleeves must comply with following requirements: sleeves in outside walls below and above grade, in floor, or in roof slabs, must be standard weight zinc coated steel pipe. Sleeves in partitions must be zinc coated sheet steel having a nominal weight of not less than [0.90 pound per square foot](#). Space between piping insulation and the sleeve must not be less than [0.25 inch](#). Sleeves must be held securely in proper position and location during construction. Sleeves must be sufficient length to pass through entire thickness of walls, partitions, or slabs. Sleeves in floor slabs must extend [2 inches](#) above the finished floor. Space between the pipe and the sleeve must be firmly packed with insulation and caulked at both ends of the sleeve with plastic waterproof cement.
- e. Piping Insulation: Provide exhaust piping insulation in accordance with Section [23 07 00 THERMAL INSULATION FOR MECHANICAL SYSTEMS](#).

2.12 PYROMETER

Provide a pyrometer, multi-point selector switch, and individual thermocouples with calibrated leads to show the temperature of the combined exhaust. For a supercharged engine, provide additional points, thermocouples and leads to show the temperature in the turbocharger exhaust gas outlet and combustion air discharge passages. Graduated scale length less than 6 inches is not acceptable. Provide double pole selector switch with an "off" position, one set of points for each thermocouple, and suitable indicating dial. Calibrate the pyrometer, thermocouples, leads and compensating devices to show true exhaust temperature within plus or minus 1 percent above the highest temperature encountered at 110 percent load conditions.

2.13 EMISSIONS

The finished installation must comply with Federal, state, and local regulations and restrictions regarding the limits of emissions, as listed here: [as required by MCB Camp Lejeune Environmental standards](#). Submit certification from the engine manufacturer stating that the engine exhaust emissions meet the federal, state, and local regulations and restrictions specified. At a minimum this certification must include emission factors for criteria pollutants including nitrogen oxides, carbon monoxide, particulate matter, sulfur dioxide, non-methane hydrocarbon, and for hazardous air pollutants (HAPs).

2.14 STARTING SYSTEM

Provide starting system for standby engine generator sets used in emergency applications in accordance with [NFPA 99](#) and [NFPA 110](#) and as follows.

2.14.1 Controls

Provide an engine control switch with functions including: run/start (manual), off/reset, and, automatic mode. Provide start-stop logic for adjustable cycle cranking and cool-down operation. Arrange the logic for fully automatic starting in accordance with paragraph AUTOMATIC ENGINE-GENERATOR-SET SYSTEM OPERATION. Provide electrical starting systems with an adjustable cranking limit device to limit cranking periods from 1 second up to the maximum duration.

2.14.2 Capacity

Provide starting system with sufficient capacity, at the maximum outdoor summer temperature specified to crank the engine without damage or overheating. The system must provide a minimum of three cranking periods with 15 second intervals between cranks. Each cranking period must have a maximum duration of 15 seconds. Starting must be accomplished using an adequately sized dc starter system with a positive shift solenoid to engage the starter motor and to crank the engine continuously for 60 seconds without overheating.

2.14.3 Electrical Starting

Manufacturers recommended dc system, utilizing a negative circuit ground. Starting motors must be in accordance with [SAE ARP892](#).

2.14.3.1 Battery

Provide a starting battery system including the battery, battery rack, intercell connectors, spacers, automatic battery charger with overcurrent protection, metering and relaying. Provide battery in accordance with [SAE J537](#). Size critical system components (rack, protection, etc.) to withstand the seismic acceleration forces specified. Provide lead-acid battery with sufficient capacity, at the minimum outdoor and maximum outdoor temperature specified, to provide the specified cranking periods. Valve-regulated lead-acid batteries are not acceptable.

Provide maintenance free, sealed, lead-acid, SAE Type D engine starting batteries. Batteries must have sufficient capacity to provide 60 seconds of continuous cranking of the engine in an ambient temperature of [23 degrees F](#).

2.14.3.2 Battery Charger

Provide a current-limiting battery charger, conforming to [UL 1236](#), that automatically recharges the batteries. Submit battery charger sizing calculations. The charger must be capable of an equalize charging rate for recharging fully depleted batteries within 24 hours and a floating charge rate for maintaining the batteries at fully charged condition. Provide an ammeter to indicate charging rate. Provide a voltmeter to indicate charging voltage. Provide a timer for the equalize charging-rate setting. A battery is considered to be fully depleted when the output voltage falls to a value which will not operate the engine generator set and its components.

Provide 120 volt ac, enclosed, automatic equalizing, dual-rate, solid-state, constant voltage type battery charger with automatic ac line compensation. DC output must be voltage regulated and current limited. Charger must have two ranges, float and equalize, and must provide continuous taper charging. The charger must have a continuous output rating of not less than 10 amperes and must be sized to recharge the engine starting batteries in a minimum of 8 hours while providing the control power needs of the engine-generator set. Enclosure must be [NEMA ICS 6](#), Type [4X stainless steel](#). The following accessories must be included:

- a. DC ammeter
- b. DC voltmeter
- c. Equalize light
- d. AC on light
- e. Low voltage light
- f. High voltage light
- g. Equalize test button/switch
- h. AC circuit breaker
- i. Low dc voltage alarm relay
- j. High dc voltage alarm relay

k. Current failure relay

l. AC power failure relay

2.14.4 Storage Batteries

Provide storage batteries of suitable rating and capacity to supply and maintain power for the remote alarm annunciator for a period of 90 minutes minimum without the voltage applied falling below 87.5 percent of normal. Provide a 120 volt ac automatic battery charger.

2.14.5 Starting Aids

Provide one or more of other following methods to assist engine starting.

2.14.5.1 Glow Plugs

Design glow plugs to provide sufficient heat for combustion of fuel within the cylinders to guarantee starting at an ambient temperature of -25 degrees F.

2.14.5.2 Jacket-Coolant Heaters

Mount a thermostatically controlled electric heater in the engine coolant jacketing to automatically maintain the coolant within plus or minus 3 degrees F of the control temperature. The heater must operate independently of engine operation so that starting times are minimized. Power for the heaters must be 208 volts ac. Include necessary equipment, piping, controls, wiring, and accessories.

2.14.5.2.1 Standby Rated Sets

The control temperature must be the temperature recommended by the engine manufacturer to meet the starting time specified at the minimum winter outdoor temperature.

2.14.5.3 Lubricating-Oil Heaters

Mount a thermostatically controlled electric heater in the engine lubricating-oil system to automatically maintain the oil temperature within plus or minus 3 degrees F of the control temperature. The heater must operate independently of engine operation so that starting times are minimized. Power for the heaters must be 208 volts ac.

2.14.6 Exerciser

Provide exerciser in accordance with Section 26 36 23 AUTOMATIC TRANSFER SWITCH AND BY-PASS/ISOLATION SWITCH.

2.15 GOVERNOR

Provide a forward acting type engine speed governor system. Steady-state frequency band and frequency regulation (droop) must be in accordance with the operating limit values of the performance class specified in the paragraph PERFORMANCE CLASS.

Provide engine with a governor which maintains the frequency within a bandwidth of the rated frequency, over a steady-state load range of zero

to 100 percent of rated output capacity. Configure the governor for safe manual adjustment of the speed/frequency during operation of the engine-generator set, without **special tools**, from 90 to 110 percent of the rated speed/frequency, over a steady state load range of 0 to 100 percent or rated capacity. Submit two complete sets of special tools required for maintenance (except for electronic governor handset). Special tools are those that only the manufacturer provides, for special purposes, or to reach otherwise inaccessible parts. Provide a suitable tool box for tools. Provide one handset for each electronic governor when required to indicate and/or change governor response settings. Maintain the midpoint of the frequency bandwidth at the same value for steady-state loads over the range of zero to 100 percent of rated output capacity for isochronous governors.

2.16 GENERATOR

Provide synchronous type, one or two bearing, generator conforming to the **performance criteria** in **NEMA MG 1**, equipped with winding terminal housings in accordance with **NEMA MG 1**, equipped with an amortisseur winding, and directly connected to the engine. Submit calculations of the engine and generator output power capability, including efficiency and parasitic load data. Provide Class F insulation.

- a. Select **NEMA MG 1**, Part 16, standby duty, and temperature rise of 130 degrees C for engine-generator sets which are expected to operate for less than 300 hours per year. Select **NEMA MG 1**, Part 22, continuous duty, and temperature rise of 105 degrees C for engine-generator sets expected to operate 300 hours or greater per year or rated 300 kW and above.
- b. Select 2/3 pitch design option for engine-generator sets rated 300 kW and above.
- c. Select 10-12 lead re-connectable for engine-generator sets rated 300 kW to 800 kW.
- d. For applications requiring high SCR loading or in harsh environments laden with salts and chemicals, select vacuum pressure impregnation (VPI) insulated coils. When engine-generator sets are rated 800 kW and larger, also select form wound coils.
- e. Provide salient-pole type, ac, brushless-excited, revolving field, air-cooled, self-ventilated, coupled type, synchronous generator conforming to **NEMA MG 1**, Part 16, and **IEEE C50.12**. Generator must be rated for standby duty at 100 percent of the power rating of the engine-generator set as specified in paragraph ENGINE-GENERATOR SET RATINGS AND PERFORMANCE. Temperature rise of each of the various parts of the generator must not exceed 105 degrees C as measured by resistance, based on a maximum ambient temperature of 40 degrees C. Winding insulation must be Class H.
- f. Stator: Stator windings must be 2/3 pitch design 10-12 lead re-connectable .
- g. Rotor: The rotor must have connected amortisseur windings.
- h. Generator Space Heater: Provide 208 volt ac heaters. Heater capacity must be as recommended by the generator manufacturer to aid in keeping the generator insulation dry.

- i. Grounding: Provide non-corrosive steel grounding pads located at two opposite mounting legs.
- j. Filters: Provide manufacturer's standard generator cooling air filter assembly.
- k. Design generator to protect against mechanical, electrical and thermal damage due to vibration, 25 percent overspeeds, or voltages and temperatures at a rated output capacity of 110 percent for prime applications and 100 percent for standby applications.
- l. Provide generator ancillary equipment meeting the short circuit requirements of **NEMA MG 1**. Select drip-proof guarded option for generators without weatherproof enclosures.
- m. Submit manufacturer's standard data for each generator (prototype data at the specified rating or above is acceptable), listing the following information:
 - (1) Direct-Axis sub-transient reactance (per unit).
 - (2) The generator kW rating and short circuit current capacity (both symmetric and asymmetric).

2.16.1 Current Balance

At 100 percent rated output capacity, and load impedance equal for each of the 3 phases, the permissible current difference between any 2 phases must not exceed 2 percent of the largest current on either of the 2 phases. Submit certification stating that the flywheel has been statically and dynamically balanced and is capable of being rotated at 125 percent of rated speed without vibration or damage.

2.16.2 Voltage Balance

At any balanced load between 75 and 100 percent of rated output capacity, the difference in line-to-neutral voltage among the 3 phases must not exceed 1 percent of the average line-to-neutral voltage. For a single phase load condition, consisting of 25 percent load at unity power factor placed between any phase and neutral with no load on the other 2 phases, the maximum simultaneous difference in line-to-neutral voltage between the phases must not exceed 3 percent of rated line to neutral voltage. The single-phase load requirement must be valid utilizing normal exciter and regulator control. The interpretation of the 25 percent load for single phase load conditions means 25 percent of rated current at rated phase voltage and unity power factor.

2.16.3 Waveform

The deviation factor of the line-to-line voltage at zero load and at balanced rated output capacity must not exceed 10 percent. The RMS of all harmonics must be less than 5.0 percent and that of any one harmonic less than 3.0 percent of the fundamental at rated output capacity. Design and configure engine-generator to meet the total harmonic distortion limits of **IEEE 519**.

2.17 EXCITER

Provide brushless generator exciter. Provide semiconductor rectifiers that have a minimum safety factor of 300 percent for peak inverse voltage and forward current ratings for all operating conditions, including 110 percent generator output at 104 degrees F ambient. The exciter and regulator in combination must maintain generator-output voltage within the limits specified.

Provide a brushless excitation system consisting of an exciter and rotating rectifier assembly, and permanent magnet generator integral with the generator and a voltage regulator. Insulation class for parts integral with the generator must be as specified in paragraph GENERATOR. System must provide a minimum short circuit of 300 percent rated engine-generator set current for at least 10 seconds. Steady state voltage regulation must be in accordance with the operating limit values of the performance class specified in the paragraph PERFORMANCE CLASS.

- a. Exciter and Rotating Rectifier Assembly: Rectifiers must be provided with surge voltage protection.
- b. Permanent Magnet Generator: Provide a voltage spike suppression device for permanent magnet generator (PMG) excitation systems.
- c. Voltage Regulator: Voltage regulator must be solid state or digital, automatic, three-phase sensing, volts per hertz type regulator. Regulator must receive its input power from a PMG. Voltage variation for any 40 degree C change over the operating temperature range must be less than plus or minus 1.0 percent. Operating temperature must be minus 40 degree C to plus 70 degree C. Voltage adjust range must be plus to minus 5.0 percent of nominal. Inherent regulator features must include over excitation shutdown.

2.17.1 Electromagnetic Interference (EMI) Suppression

Provide as an integral part of the generator and excitation system, EMI suppression complying with MIL-STD-461.

2.18 VOLTAGE REGULATOR

Provide a solid-state voltage regulator, separate from the exciter, for each generator. Maintain the voltage within a bandwidth of the rated voltage, over a steady-state load range of zero to 100 percent of rated output capacity. Configure regulator for safe manual adjustment of the engine-generator voltage output without special tools, during operation, from 90 to 110 percent of the rated voltage over the steady state load range of 0 to 100 percent of rated output capacity. Regulation drift exceeding plus or minus 0.5 percent for an ambient temperature change of 68 degrees F is not acceptable. Reactive droop compensation or reactive differential compensation must load share the reactive load proportionally between sets during parallel operation. Provide voltage regulator with a maximum droop of 2 percent of rated voltage over a load range from 0 to 100 percent of rated output capacity and automatically maintain the generator output voltage within the specified operational bandwidth.

2.19 GENERATOR ISOLATION AND PROTECTION

Provide necessary devices for electrical protection and isolation of each engine-generator set and its ancillary equipment. The generator circuit

breaker (IEEE Device 52) ratings must be consistent with the generator rated voltage and frequency, with continuous, short circuit withstand, and interrupting current ratings to match the generator capacity. Provide operated as indicated generator circuit breaker. Mount a set of surge capacitors at the generator terminals. Provide monitoring and control devices as specified in paragraph GENERATOR PANEL.

The generator circuit breaker must comply with **UL 489** requirements for molded case, adjustable thermal magnetic trip type circuit breaker. The circuit breaker continuous current rating must be adequate for the power rating of the engine-generator set and the circuit breaker must be rated to withstand the short circuit current provided by the generator set. Provide circuit breaker in a **NEMA ICS 6**, Type **4X stainless steel** enclosure mounted on the engine-generator set.

2.19.1 Devices

Provide switches, circuit breakers, switchgear, fuses, relays, and other protective devices as specified in Section **26 28 01.00 10 COORDINATED POWER SYSTEM PROTECTION**.

Furnish with respective pieces of equipment. Motors, controllers, contactors, and disconnects must conform to Section **26 20 00 INTERIOR DISTRIBUTION SYSTEM**. Provide electrical connections under Section **26 20 00 INTERIOR DISTRIBUTION SYSTEM**. Provide controllers and contactors with maximum of 120-volt control circuits, and auxiliary contacts for use with controls furnished. When motors and equipment furnished are larger than size indicated, the cost of providing additional electrical service and related work must be included under this section.

2.20 SAFETY SYSTEM

Provide and install devices, wiring, remote panels, and local panels, etc., as a complete system to automatically activate the appropriate signals and initiate the appropriate actions. Provide a safety system with a self-test method to verify its operability. Provide alarm signals that have manual acknowledgment and reset devices. The alarm signal systems must reactivate for new signals after acknowledgment is given to any signal. Configure the systems so that loss of any monitoring device will be dealt with as an alarm on that system element.

2.20.1 Audible Signal

Provide audible alarm signal sound at a frequency of 70 Hz at a volume of 75 dB at **10 feet**. The sound must be continuously activated upon alarm and silenced upon acknowledgment. Locate signal devices as shown.

2.20.2 Visual Signal

The visual alarm signal must be a panel light. The light must be normally off, activated to be blinking upon alarm. The light must change to continuously lit upon acknowledgement. If automatic shutdown occurs, the display must maintain activated status to indicate the cause of failure and must not be reset until cause of alarm has been cleared and/or restored to normal condition. Shutdown alarms must be red; all other alarms must be amber.

2.20.3 Alarms and Action Logic

2.20.3.1 Shutdown

Accomplish simultaneous activation of the audible signal, activation of the visual signal, stopping the engine, and opening the generator main circuit breakers.

2.20.3.2 Problem

Accomplish activation of the visual signal.

2.20.4 Safety Indications and Shutdowns

Provide a local alarm panel with the following shutdown and alarm functions in accordance with NFPA 110 level 2 mounted either on or adjacent to the engine generator set.

A remote alarm panel is is not required for audible alarms, e.g., in the control room.

Indicator Function (at battery voltage)	NFPA 99 Level 1 CV S RA	NFPA 110 Level 1 CV S RA	NFPA 110 Level 2 CV S RA
Overcrank	X X X	X X X	X X O
Low water temperature	X NA X	X NA X	X NA O
High engine temperature pre-alarm	X NA X	X NA X	O NA NA
High engine temperature	X X X	X X X	X X O
Low lube oil pressure pre-alarm	X NA X	NA NA NA	NA NA NA
Low lube oil pressure	X X X	X X X	X X O
Overspeed	X X X	X X X	X X O
Low fuel main tank	X NA X	X NA X	O NA O
Low coolant level	X O X	X O X	X O X
EPS supplying load	X NA NA	X NA NA	O NA NA
Control switch not in automatic position	X NA X	X NA X	X NA X
High battery voltage	X NA NA	X NA NA	O NA NA
Low cranking voltage	X NA X	X NA X	O NA NA
Low voltage in battery	X NA NA	X NA NA	O NA NA

Indicator Function (at battery voltage)	NFPA 99 Level 1 CV S RA	NFPA 110 Level 1 CV S RA	NFPA 110 Level 2 CV S RA
Battery charger ac failure	X NA NA	X NA NA	O NA NA
Lamp test	X NA NA	X NA NA	X NA NA
Contacts for local and remote common alarm	X NA X	X NA X	X NA X
Audible alarm silencing switch	NA NA X	NA NA X	NA NA O
Low starting air pressure	X NA NA	X NA NA	O NA NA
Low starting hydraulic pressure	X NA NA	X NA NA	O NA NA
Air shutdown damper when used	X X X	X X X	X X O
Remote emergency stop	NA X NA	NA X NA	NA X NA
Symbology: CV: Control panel-mounted visual. S: Shutdown of EPS indication. RA: Remote audible. Symbology: CV: Control panel-mounted visual. S: Shutdown of EPS indication. RA: Remote audible. X: Required. O: Optional. NA: Not applicable.			

2.20.5 Time-Delay on Alarms

For startup of the engine-generator set, install time-delay devices bypassing the low lubricating oil pressure alarm during cranking, and the coolant-fluid outlet temperature alarm. Submit the magnitude of monitored values which define alarm or action set points, and the tolerance (plus and/or minus) at which the devices activate the alarm or action for items contained within the alarm panels. The lube-oil time-delay device must return its alarm to normal status after the engine starts. The coolant time-delay device must return its alarm to normal status 5 minutes after the engine starts.

2.21 SYNCHRONIZING PANEL

Provide panel as specified in paragraph PANELS and provide controls,

gauges, meters, and displays to include:

- a. Frequency meters, dial type, with a range of 90 to 110 percent of rated frequency. Do not use vibrating-reed type meters. One must monitor generator output frequency ("Generator Frequency Meter") and the other must monitor the frequency of the parallel source ("Bus Frequency Meter").
- b. Voltmeters, ac, dial type, 3-phase, with 4-position selector switch for the generator output ("Generator Volt Meter") and for the parallel power source ("Bus volt meter").
- c. Automatic synchronizer.
- d. Manual synchronizing controls.
- e. Indicating lights for supplementary indication of synchronization.
- f. Synchroscope.
- g. Wattmeter, indicating.

2.22 PANELS

Each panel must be of the type and kind necessary to provide specified functions. Mount panels as shown. Mount instruments flush or semiflush. Provide convenient access to the back of panels to facilitate maintenance. Calibrate instruments using recognized industry calibration standards. Provide a panel identification plate identifying the panel function. Provide a plate identifying the device and its function for each instrument and device on the panel. Provide switch plates identifying the switch-position function.

2.22.1 Enclosures

Design enclosures for the application and environment, conforming to [NEMA ICS 6](#). Locking mechanisms must be keyed alike.

Provide for each engine-generator set and fabricate from [stainless steel](#) in accordance with the manufacturer's standard design. Provide a complete, weatherproof enclosure for the engine, generator, and auxiliary systems and equipment. Support exhaust piping and silencer so that the turbocharger is not subjected to exhaust system weight or lateral forces generated in connecting piping that exceed the engine manufacturer's maximum allowed forces and moments. The housing must have sufficient louvered openings to allow entrance of outside air for engine and generator cooling at full load. Design louvered openings to exclude driving rain and snow. Provide properly arranged and sized, hinged panels in the enclosure to allow convenient access to the engine, generator, and control equipment for maintenance and operational procedures. Provide hinged panels with spring type latches which must hold the panels closed securely and will not allow them to vibrate. Brace the housing internally to prevent excessive vibration when the set is in operation

2.22.2 Analog

Provide analog electrical indicating instruments in accordance with [UL 1437](#) with semi-flush mounting. Switchboard, switchgear, and control-room panel-mounted instruments must have 250 degree scales with an accuracy of

not less than 99 percent. Unit-mounted instruments must be the manufacturer's standard with an accuracy of not less than 98 percent. The instrument's operating temperature range must be **minus 4 to plus 158 degrees F**. Distorted generator output voltage waveform of a crest factor less than 5 must not affect metering accuracy for phase voltages, hertz and amps.

2.22.3 Electronic

Electronic indicating instruments must be true RMS indicating instruments, 100 percent solid state, state-of-the-art, microprocessor controlled to provide specified functions. Provide control, logic, and function devices that are compatible as a system, sealed, dust and water tight, and that utilize modular components with metal housings and digital instrumentation. Provide an interface module to decode serial link data from the electronic panel and translate alarm, fault and status conditions to set of relay contacts. Instrument accuracy less than 98 percent for unit mounted devices and 99 percent for control room, panel mounted devices, throughout a temperature range of **minus 4 to 158 degrees F** is not acceptable. Provide LED or back lit LCD data display. Additionally, the display must provide indication of cycle programming and diagnostic codes for troubleshooting. Numeral height must be **0.5 inch**.

2.22.4 Parameter Display

Provide indication or readouts of the tachometer, lubricating-oil pressure, ac voltmeter, ac ammeter, frequency meter, and safety system parameters. Specify a momentary switch for other panels.

2.23 SURGE PROTECTION

Electrical and electronic components must be protected from, or designed to withstand the effects of surges from switching and lightning.

2.24 AUTOMATIC ENGINE-GENERATOR-SET SYSTEM OPERATION

Provide fully automatic operation for the following operations: engine-generator set starting and load transfer upon loss of normal source; retransfer upon restoration of the normal source; sequential starting; paralleling, and load-sharing for multiple engine-generator sets; and stopping of each engine-generator set after cool-down. Devices must automatically reset after termination of their function.

2.24.1 Automatic Transfer Switch

Provide automatic transfer switches in accordance with Section **26 36 23** AUTOMATIC TRANSFER SWITCH AND BY-PASS/ISOLATION SWITCH.

2.24.2 Monitoring and Transfer

Provide devices to monitor voltage and frequency for the normal power source and each engine-generator set, and control transfer from the normal source and retransfer upon restoration of the normal source. Describe functions, actuation, and time delays as described in Section **26 36 23** AUTOMATIC TRANSFER SWITCH AND BY-PASS/ISOLATION SWITCH.

2.25 MANUAL ENGINE-GENERATOR-SET SYSTEM OPERATION

Provide complete facilities for manual starting and testing of each set

without load, loading and unloading of each set.

2.26 BASE

Provide a stainless steel base. Design the base to rigidly support the engine-generator set, ensure permanent alignment of rotating parts, be arranged to provide easy access to allow changing of lube-oil, and ensure that alignment is maintained during shipping and normal operation. The base must permit skidding in any direction during installation and must withstand and mitigate the affects of synchronous vibration of the engine and generator. Provide base with suitable holes for anchor bolts and jacking screws for leveling.

2.27 THERMAL INSULATION

Provide thermal insulation as specified in Section 23 07 00 THERMAL INSULATION FOR MECHANICAL SYSTEMS.

2.28 PAINTING AND FINISHING

Clean, prime and paintthe engine-generator set in accordance with the manufacturer's standard color and practice.

2.29 FACTORY INSPECTION AND TESTS

Submit six complete reproducible copies of the factory inspection result on the checklist format specified below. Perform the factory tests on each engine-generator set. The component manufacturer's production line test is acceptable as noted. Run each engine-generator set for at least 1 hour at rated output capacity prior to inspections. Complete inspections and make all necessary repairs prior to testing. Use engine generator controls and protective devices that are provided by the generator set manufacturer as part of the standard package for factory tests. When controls and switchgear are not provided as part of the generator set manufacturer's standard package, the actual controls and protective devices provided for the project are not required to be used during the factory test. The Contracting Officer may provide one or more representatives to witness inspections and tests.

2.29.1 Factory Inspection

Perform inspections prior to beginning and after completion of testing of the assembled engine-generator set. Look for leaks, looseness, defects in components, proper assembly, etc. and note any item found to be in need of correction as a necessary repair. Use the following checklist for the inspection:

INSPECTION ITEM	GOOD	BAD	NOTES
Drive belts			
Governor and adjustments			
Engine timing mark			
Starting motor			

INSPECTION ITEM	GOOD	BAD	NOTES
Starting aids			
Coolant type and concentration			
Radiator drains			
Block coolant drains			
Coolant fill level			
All coolant line connections			
All coolant hoses			
Combustion air filter			
Combustion air silencer			
Lube oil type			
Lube oil sump drain			
Lube-oil filter			
Lube-oil-level indicator			
Lube-oil-fill level			
All lube-oil line connections			
All lube-oil lines			
Fuel type and amount			
All fuel-line connections			
All fuel lines			
Fuel filter			
Coupling and shaft alignment			
Voltage regulators			
Battery-charger connections			
All wiring connections			
Instrumentation			
Hazards to personnel			

INSPECTION ITEM	GOOD	BAD	NOTES
Base			
Nameplates			
Paint			
Exhaust-heat recovery unit			
Switchboard			
Switchgear			

2.29.2 **Factory Tests**

Submit a letter giving notice of the proposed dates of factory inspections and tests at least 14 days prior to beginning tests, including:

- a. A detailed description of the manufacturer's procedures for factory tests at least 14 days prior to beginning tests.
- b. Six copies of the Factory Test data described below in 8-1/2 by 11 inch binders having a minimum of 3 rings from which material may readily be removed and replaced, including a separate section for each test. Separate sections by heavy plastic dividers with tabs. Provide full size (8-1/2 by 11 inch minimum) data plots showing grid lines, with full resolution.
 - (1) A detailed description of the procedures for factory tests.
 - (2) A list of equipment used, with calibration certifications.
 - (3) A copy of measurements taken, with required plots and graphs.
 - (4) The date of testing.
 - (5) A list of the parameters verified.
 - (6) The condition specified for the parameter.
 - (7) The test results, signed and dated.
 - (8) A description of adjustments made.

On engine-generator set tests where the engine and generator are required to be connected and operated together, the load power factor must be the power factor specified in the engine generator set parameter schedule . For engine-generator set with dual-fuel operating capability, perform the following tests using the primary fuel type . Perform electrical measurements in accordance with IEEE 120. Temperature limits in the rating of electrical equipment and for the evaluation of electrical insulation must be in accordance with IEEE 1. In the following tests where measurements are to be recorded after stabilization of an engine-generator set parameter (voltage, frequency, current, temperature,

etc.), stabilization is considered to have occurred when measurements are maintained within the specified bandwidths or tolerances, for a minimum of four consecutive readings. Tests specifically for the generator may be performed utilizing any prime mover.

- a. Insulation Resistance for Stator and Exciter Test, [IEEE 115](#) and [IEEE 43](#), to the performance criteria in [NEMA MG 1](#), Part 22. Generator manufacturer's production line test is acceptable.
- b. High Potential Test, in accordance with [IEEE 115](#) and [NEMA MG 1](#), test voltage in accordance with [NEMA MG 1](#). Generator manufacturer's production line test is acceptable.
- c. Winding Resistance Test, Stator and Exciter, in accordance with [IEEE 115](#). Generator manufacturer's production line test is acceptable.
- d. Phase Balance Voltage Test, to the performance criteria specified in paragraph GENERATOR. This test can be performed with any prime mover. Generator manufacturer's production line test results are acceptable.
 - (1) Start and operate the generator at no load.
 - (2) Adjust a regulated phase voltage (line-to-neutral) to rated voltage.
 - (3) Read and record the generator frequency, line-to-neutral voltages, and the line-to-line voltages.
 - (4) Apply 75 percent rated load and record the generator frequency, line-to-neutral voltages, and the line-to-line voltages.
 - (5) Apply rated load and record the generator frequency, line-to-neutral voltages, and the line-to-line voltages.
 - (6) Calculate average line-neutral voltage and percent deviation of individual line-neutral voltages from average for each load condition.
- e. Current Balance on Stator Winding Test, by measuring the current on each phase of the winding with the generator operating at 100 percent of Rated Output Capacity, with the load impedance equal for each of the three phases: to the performance criteria specified in paragraph GENERATOR.
- f. Voltage Waveform Deviation and Distortion Test in accordance with [IEEE 115](#) to the performance criteria specified in paragraph GENERATOR. Use high-speed recording instruments capable of recording voltage waveform deviation and all distortion, including harmonic distortion. Include appropriate scales to provide a means to measure and interpret results.
- g. Voltage and Frequency Droop Test. Verify that the output voltage and frequency are within the specified parameters as follows:
 - (1) With the generator operating at no load, adjust voltage and frequency to rated voltage and frequency. Record the generator output frequency and line-line and line-neutral voltages.

- (2) Increase load to Rated Output Capacity. Record the generator output frequency and line-line and line-neutral voltages.
- (3) Calculate the percent droop for voltage and frequency with the following equations:

$$\text{Voltage droop percent} = \frac{(\text{No-Load Volts}) - (\text{Rated Capacity Volts})}{(\text{Service-Load Volts})} \times 100$$

$$\text{Frequency droop percent} = \frac{(\text{No-Load Hertz}) - (\text{Rated Capacity Hertz})}{(\text{Service-Load Hertz})} \times 100$$

- (4) Repeat steps 1 through 3 two additional times without making any adjustments.
- h. Frequency and Voltage Stability and Transient Response. Verify that the engine-generator set responds to addition and dropping of blocks of load in accordance with the transient response requirements. Document maximum voltage and frequency variation from bandwidth and verify that voltage and frequency return to and stabilize within the specified bandwidth, within the specified response time period. Document results in tabular form and with high resolution, high speed strip chart recorders or comparable digital recorders, as approved by the Contracting Officer. Include the following tabular data:

- (1) Ambient temperature (at 15 minute intervals).
- (2) Generator output current (before and after load changes).
- (3) Generator output voltage (before and after load changes).
- (4) Frequency (before and after load changes).
- (5) Generator output power (before and after load changes).
- (6) Graphic representations must include the actual instrument trace of voltage and frequency showing: charts marked at start of test; observed steady-state band; mean of observed band; momentary overshoot and undershoot (generator terminal voltage and frequency) and recovery time for each load change together with the voltage and frequency maximum and minimum trace excursions for each steady state load condition prior to and immediately following each load change. Generator terminal voltage and frequency transient recovery time for each step load increase and decrease.
 - (a) Perform and record engine manufacturer's recommended pre-starting checks and inspections.
 - (b) Start the engine, make and record engine manufacturer's after-starting checks and inspections during a reasonable warm-up period and no load. Verify stabilization of voltage and frequency within specified bandwidths.
 - (c) With the unit at no load, apply the Maximum Step Load Increase.

- (d) Apply load in steps equal to the Maximum Step Load Increase until the addition of one more step increase will exceed the Service Load.
 - (e) Decrease load to the unit such that addition of the Maximum Step Load Increase will load the unit to 100 percent of Service Load.
 - (f) Apply the Maximum Step Load Increase.
 - (g) Decrease load to zero percent in steps equal to the Maximum Step Load Decrease.
 - (h) Repeat steps (c) through (g).
- j. Test Voltage Unbalance with Unbalanced Load (Line-to-Neutral) to the performance criteria specified in paragraph GENERATOR. [Prototype test](#) data is acceptable in lieu of the actual test. Submit manufacturer's standard certification that prototype tests were performed for the generator model proposed. This test may be performed using any prime mover.
- (1) Start and operate the generator set at rate voltage, no load, rated frequency, and under control of the voltage regulator. Read and record the generator frequency, line-to-neutral voltages, and the line-to-line voltages.
 - (2) Apply the specified load between terminals L_1-L_2 , L_2-L_0 , and L_3-L_0 in turn. Record all instrument readings at each line-neutral condition.
 - (3) Express the greatest difference between any two of the line-to-line voltages and any two of the line-to-neutral voltages as a percent of rated voltage.
 - (4) Compare the largest differences expressed in percent with the maximum allowable difference specified.

PART 3 EXECUTION

3.1 EXAMINATION

After becoming familiar with all details of the job, perform a [Site Visit](#) to verify the information shown on the drawings, before performing any work. Submit a letter stating the date the site was visited and listing discrepancies found. Notify the Contracting Officer in writing of any discrepancies.

3.2 [GENERAL INSTALLATION](#)

Provide clear space for operation and maintenance in accordance with [NFPA 70](#) and [IEEE C2](#). Submit a copy of the manufacturer's installation procedures and a detailed description of the manufacturer's recommended break-in procedure. Install pipe, duct, conduit, and ancillary equipment to facilitate easy removal and replacement of major components and parts of the engine-generator set.

3.3 PIPING INSTALLATION

Weld piping. Provide flanged valve connections. Provide flanged connections at equipment. Provide threaded connections to the engine if the manufacturers standard connection is threaded. Except where otherwise specified, use welded flanged fittings to allow for complete dismantling and removal of each piping system from the facility without disconnecting or removing any portion of any other system's equipment or piping. Make connections to equipment with vibration isolation-type flexible connectors. Support and align piping and tubing to prevent stressing of flexible hoses and connectors. Flash pipes extending through the roof. Install piping clear of windows, doors and openings, to permit thermal expansion and contraction without damage to joints or hangers, and install a 1/2 inch drain valve with cap at each low point.

The installation of gas engines must conform to the requirements of NFPA 37 and its references therein, including NFPA 54, NFPA 58, and ASME B31.3.

3.3.1 Support

Provide hangers, inserts, and supports to accommodate any insulation and conforming to MSS SP-58. Space supports no more than 7 feet on center for pipes 2 inches in diameter or less, no more than 12 feet on center for pipes larger than 2 inches but smaller than 4 inches in diameter, and not more than 17 feet on center for pipes larger than 4 inches in diameter. Provide supports at pipe bends or change of direction.

3.3.1.1 Ceiling and Roof

Support exhaust piping with appropriately sized Type 41 single pipe roll and threaded rods; support all other piping with appropriately sized Type 1 clevis and threaded rods.

3.3.1.2 Wall

Make wall supports for pipe by suspending the pipe from appropriately sized Type 33 brackets with the appropriate ceiling and roof pipe supports.

3.3.2 Flanged Joints

Provide flanges that are Class 125 type, drilled, and of the proper size and configuration to match the equipment and engine connections. Provide gasketed flanged joints that are square and tight.

3.3.3 Cleaning

After fabrication and before assembly, piping interiors must be manually wiped clean of debris.

3.3.4 Pipe Sleeves

Fit pipes passing through construction such as ceilings, floors, or walls with sleeves. Extend each sleeve through and fasten in its respective structure and cut flush with each surface. Build the structure tightly to the sleeve. The inside diameter of each sleeve must be minimum 1/2 inch, and where pipes pass through combustible materials 1 inch larger than the outside diameter of the passing pipe or pipe insulation/covering.

3.4 ELECTRICAL INSTALLATION

Perform electrical installation in compliance with NFPA 70, IEEE C2, and Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM. For vibration isolation, provide flexible fittings for conduit, cable trays, and raceways attached to engine-generator sets; provide flexible stranded conductor for metallic conductor cables installed on the engine generator set and from the engine generator set to equipment not mounted on the engine generator set; and provide crimp-type terminals or lugs for terminations of conductors on the engine generator set.

3.5 FIELD PAINTING

Perform field painting as specified in Section 09 90 00 PAINTS AND COATINGS.

3.6 ONSITE INSPECTION AND TESTS

Perform and report on factory tests and inspections prior to shipment. Provide certified copies of manufacturer's test data and results. Test procedures must conform to ASME, IEEE, and ANSI standards, and to ISO requirements on testing, as appropriate and applicable. The manufacturer performing the tests must provide equipment, labor, and consumables necessary for tests and measuring and indicating devices must be certified to be within calibration. Tests must indicate satisfactory operation and attainment of specified performance. If satisfactory, equipment tested will be given a tentative approval. Equipment must not be shipped before approval of the factory test reports for the following tests.

Submit a letter giving notice of the proposed dates of onsite inspections and tests at least 14 days prior to beginning tests.

- a. Submit a detailed description of the Contractor's procedures for onsite tests including the test plan and a listing of equipment necessary to perform the tests at least 30 days prior to beginning tests.
- b. Submit six copies of the onsite test data described below in 8-1/2 by 11 inch binders having a minimum of 3 rings from which material may readily be removed and replaced, including a separate section for each test. Separate sections by heavy plastic dividers with tabs. Provide full size (8-1/2 by 11 inch minimum) data plots showing grid lines, with full resolution.
 - (1) A detailed description of the procedures for onsite tests.
 - (2) A list of equipment used, with calibration certifications.
 - (3) A copy of measurements taken, with required plots and graphs.
 - (4) The date of testing.
 - (5) A list of the parameters verified.
 - (6) The condition specified for the parameter.
 - (7) The test results, signed and dated.
 - (8) A description of adjustments made.

3.6.1 Test Conditions

3.6.1.1 Data

Make and record measurements of all parameters necessary to verify that each set meets specified parameters. If the results of any test step are not satisfactory, make adjustments, replacements, or repairs and repeat the step until satisfactory results are obtained. Unless otherwise indicated, record data in 15 minute intervals during engine-generator set operation and include: readings of all engine-generator set meters and gauges for electrical and power parameters; oil pressure; ambient temperature; and engine temperatures available from meters and gauges supplied as permanent equipment on the engine-generator set. Perform electrical measurements in accordance with [IEEE 120](#). Definitions of terms are in accordance with [IEEE 100](#). Provide temperature limits in the rating of electrical equipment and for the evaluation of electrical insulations in accordance with [IEEE 1](#).

3.6.1.2 Power Factor

Submit the generator capability curve showing generator kVA output capability (kW vs. kvar) for both leading and lagging power factors ranging from 0 to 1.0. For all engine-generator set operating tests the load power factor must be the power factor specified in the engine-generator set parameter schedule .

3.6.1.3 Contractor Supplied Items

Provide equipment and supplies required for inspections and tests including fuel, test instruments, and loadbanks at the specified power factors.

3.6.1.4 Instruments

Verify readings of panel gauges, meters, displays, and instruments provided as permanent equipment during test runs, using test instruments of greater precision and accuracy. Test instrument accuracy must be within the following: current plus or minus 1.5 percent, voltage plus or minus 1.5 percent, real power plus or minus 1.5 percent, reactive power plus or minus 1.5 percent, power factor plus or minus 3 percent, frequency plus or minus 0.5 percent. Calibrate test instruments by a recognized standards laboratory within 30 days prior to testing.

3.6.1.5 Sequence

Provide the sequence of testing as specified in the approved testing plan unless variance is authorized by the Contracting Officer. Perform field testing in the presence of the Contracting Officer. Schedule and sequence tests in order to optimize run-time periods; however, follow the general order of testing: Construction Tests; Inspections; Pre-operational Tests; Safety Run Tests; Performance Tests; and Final Inspection.

3.6.2 Construction Tests

Perform individual component and equipment functional tests for fuel piping, coolant piping, and lubricating-oil piping, electrical circuit continuity, insulation resistance, circuit protective devices, and equipment not provided by the engine-generator set manufacturer prior to

connection to the engine-generator set.

3.6.2.1 Piping Test

- a. Flush lube-oil and fuel-oil piping with the same type of fluid intended to flow through the piping, until the outflowing fluid has no obvious sediment or emulsion.
- b. Test fuel piping which is external to the engine-generator set in accordance with **NFPA 30**. Pressure all remaining piping which is external to the engine-generator set with air pressure at 150 percent of the maximum anticipated working pressure, but not less than 150 psi, for a period of 2 hours to prove the piping has no leaks. If piping is to be insulated, perform the test before the insulation is applied.

3.6.2.2 Electrical Equipment Tests

- a. Perform low-voltage cable insulation integrity tests for cables connecting the generator breaker to the automatic transfer switch . Test low-voltage cable, complete with splices, for insulation resistance after the cables are installed, in their final configuration, ready for connection to the equipment, and prior to energization. Apply a test voltage of 500 volts dc for one minute between each conductor and ground and between all possible combinations conductors in the same trench, duct, or cable, with all other conductors in the same trench, duct, or conduit. Provide the minimum value of insulation as follows:
 - (1) $R \text{ in meg-ohms} = (\text{rated voltage in kV plus } 1) \times 304.8 / (\text{length of cable in meters})$
 - (2) $R \text{ in meg-ohms} = (\text{rated voltage in kV plus } 1) \times 1000 / (\text{length of cable in feet})$
 - (3) Each cable failing this test must be repaired or replaced. The repair cable must be retested until failures have been eliminated.
- c. Ground-Resistance Tests. Measure the resistance of the ground ring using the fall-of-potential method defined in **IEEE 81**. On systems consisting of interconnected ground rods, perform tests after interconnections are complete. Take measurements in normally dry weather, not less than 48 hours after rainfall. Provide site diagram indicating location of test probes with associated distances, and provide a plot of resistance vs. distance. The combined resistance of separate systems may be used to meet the requirements resistance, but the specified number of electrodes must still be provided as follows:
 - (2) Multiple rod electrodes - 5 ohms.
- d. Examine and test circuit breakers and switchgear in accordance with the manufacturer's published instructions for functional testing.

3.6.3 Inspections

Perform the following inspections jointly by the Contracting Officer and the Contractor, after complete installation of each engine-generator set and its associated equipment, and prior to startup of the engine-generator set. Submit a letter certifying that all facilities are complete and functional; that each system is fully functional; and that each item of equipment is complete, free from damage, adjusted, and ready for beneficial use. Perform checks applicable to the installation. Document and submit the results of those which are physical inspections (I) in accordance with paragraph SUBMITTALS. Present manufacturer's data for the inspections designated (D) at the time of inspection. Verify that equipment type, features, accessibility, installation and condition are in accordance with the contract specification. Provide manufacturer's statements to certify provision of features which cannot be verified visually.

Drive belts	I
Governor type and features	I
Engine timing mark	I
Starting motor	I
Starting aids	I
Coolant type and concentration	D
Radiator drains	I
Block coolant drains	I
Coolant fill level	I
Coolant line connections	I
Coolant hoses	I
Combustion air filter	I
Intake air silencer	I
Lube oil type	D
Lube oil sump drain	I
Lube-oil filter	I
Lube-oil level indicator	I
Lube-oil fill level	I
Lube-oil line connections	I

Lube-oil lines	I
Fuel type	D
Fuel level	I
Fuel-line connections	I
Fuel lines	I
Fuel filter	I
Access for maintenance	I
Voltage regulator	I
Battery-charger connections	I
Wiring and terminations	I
Instrumentation	I
Hazards to personnel	I
Base	I
Nameplates	I
Paint	I
Exhaust-heat system	I
Exhaust muffler	I
Switchboard	I
Switchgear	I
Access provided to controls	I
Enclosure is weather resistant	I
Engine and generator mounting bolts (application)	I

3.6.4 Engine Tests

Perform customary commercial factory tests in accordance with [ISO 3046](#) on each engine and associated engine protective device, including, but not limited to the following:

- a. Perform dynamometer test at rated power. Record horsepower at rated speed and nominal characteristics such as lubricating oil pressure, jacket water temperature, and ambient temperature.

- b. Test and record the values that the low oil pressure alarm and protective shutdown devices actuate prior to assembly on the engine.
- c. Test and record values that the high jacket water temperature alarm and protective shutdown devices actuate prior to assembly on the engine.

3.6.5 Generator Tests

Tests must be performed on the complete factory assembled generator prior to shipment. Conduct tests in accordance with IEEE 115, and NEMA MG 1.

3.6.5.1 Routine Tests

Perform the following routine tests on the generators and their exciters:

- a. Resistance of armature and field windings.
- b. Mechanical balance.
- c. Phases sequence.
- d. Open circuit saturation curve and phase (voltage) balance test.
- e. Insulation resistance of armature and field windings.
- f. High potential test

3.6.5.2 Design Tests

Submit the following design tests made on prototype machines that are physically and electrically identical to the generators specified.

- a. Temperature rise test
- b. Short circuit saturation curve and current balance test

3.6.6 Assembled Engine-Generator Set Tests

Perform the following tests on the assembled engine-generator set.

3.6.6.1 Initial Stabilization Readings

Operate the engine-generator set and allow the set to stabilize at rated kW at rated power factor, rated voltage, and rated frequency. During this period record instrument readings for output power (kW), terminal voltage, line current, power factor, frequency (rpm) generator (exciter) field voltage and current, lubricating oil pressure, jacket water temperature, and ambient temperature at minimum intervals of 15 minutes. Adjust the load, voltage, and frequency to maintain rated load at rated voltage and frequency. Adjustments to load, voltage, or frequency controls must be recorded on the data sheet at the time of adjustment. Stabilization must be considered to have occurred when four consecutive voltage and current recorded readings of the generator (or exciter) field either remain unchanged or have only minor variations about an equilibrium condition with no evident continued increase or decrease in value after the last adjustment to the load, voltage, or frequency has been made.

3.6.6.2 Regulator Range Test

Remove load and record instrument readings (after transients have subsided). Adjust voltage to the maximum attainable value or to a value just prior to actuation of the overvoltage protection device. Apply rated load and adjust voltage to the minimum attainable value or a value just prior to activation of the under-voltage protection device. The data sheets must indicate the voltage regulation as a percent of rated voltage and the maximum and minimum voltages attainable. Voltage regulation must be defined as follows:

$$\text{Percent Regulation} = \frac{((\text{No-Load Voltage}) - (\text{Rated-Load Voltage})) \times 100}{(\text{Rated-Load Voltage})}$$

3.6.6.3 Frequency Range Test

Adjust the engine-generator set frequency for the maximum attainable frequency at rated load. Record instrument readings. Adjust the engine-generator set frequency for the specified minimum attainable frequency at rated load. Record instrument readings. Reduce the load to zero and adjust the engine-generator set frequency for the maximum attainable frequency. Record instrument readings. Adjust the engine-generator set frequency for the minimum attainable frequency. Record instrument readings. The data sheet must show the maximum and minimum frequencies attained at rated load, and at no load.

3.6.6.4 Transient Response Test

Drop the load to no load and re-apply rated load three times to ensure that the no load and rated load voltage and frequency values are repeatable and that the frequency and voltage regulation is within the limits specified. Record generator terminal voltage and frequency using a high speed strip chart recorder. The data sheet must show the following results:

a. Frequency

- (1) Stability bandwidth or deviation in percent of rated frequency.
- (2) Recovery time.
- (3) Overshoot and undershoot.

b. Voltage

- (1) Stability bandwidth or deviation in percent of rated voltage.
- (2) Recovery time.
- (3) Overshoot and undershoot.

3.6.7 Pre-operational Tests

3.6.7.1 Insulation Test

Test generator and exciter circuits insulation resistance in accordance with IEEE 43. Take stator readings including generator leads to switchboard at the circuit breaker. Record results of insulation

resistance tests. Readings must be within limits specified by the manufacturer. Verify mechanical operation, insulation resistance, protective relay calibration and operation, and wiring continuity of switchboard assembly. Do not damage generator components during test.

3.6.7.2 Engine-Generator Connection Coupling Test

When the generator provided is a two-bearing machine, inspect and check the engine-generator connection coupling by dial indicator to prove that no misalignment has occurred. Use the dial indicator to measure variation in radial positioning and axial clearance between the coupling halves. Take readings at four points, spaced 90 degrees apart. Align solid couplings and pin-type flexible couplings within a total indicator reading of 0.0005 to 0.001 inch for both parallel and angular misalignment. For gear-type or grid-type couplings, 0.002 inch will be acceptable.

3.6.8 Safety Run Test

For the following tests, repeat the associated safety tests if any parts are changed, or adjustments made to the generator set, its controls, or auxiliaries.

- a. Perform and record engine manufacturer's recommended prestarting checks and inspections.
- b. Start the engine, record the starting time, make and record engine manufacturer's after-starting checks and inspections during a reasonable warm-up period.
- c. Activate the manual emergency stop switch and verify that the engine stops.
- d. Remove the high and pre-high lubricating oil temperature sensing elements from the engine and temporarily install a temperature gauge in their normal locations on the engine (required for safety, not for recorded data). Where necessary provide temporary wiring harness to connect the sensing elements to their permanent electrical leads.
- e. Start the engine, record the starting time, make and record engine manufacturer's after-starting checks and inspections during a reasonable warm-up period. Operate the engine-generator set at no load until the output voltage and frequency stabilize. Monitor the temporarily installed temperature gauges. If either temperature reading exceeds the value required for an alarm condition, activate the manual emergency stop switch.
- f. Immerse the elements in a vessel containing controlled-temperature hot oil and record the temperature at which the pre-high alarm activates and the temperature at which the engine shuts down. Remove the temporary temperature gauges and reinstall the temperature sensors on the engine.
- g. Remove the high and pre-high coolant temperature sensing elements from the engine and temporarily install a temperature gauge in their normal locations on the engine (required for safety, not for recorded data). Where necessary provide temporary wiring harness to connect the sensing elements to their permanent electrical leads.
- h. Start the engine, record the starting time, make and record engine

manufacturer's after-starting checks and inspections during a reasonable warm-up period. Operate the engine generator-set at no load until the output voltage and frequency stabilize.

- i. Immerse the elements in a vessel containing controlled-temperature hot oil and record the temperature at which the pre-high alarm activates and the temperature at which the engine shuts down. Remove the temporary temperature gauges and reinstall the temperature sensors on the engine.
- j. Start the engine, record the starting time, make and record engine manufacturer's after-starting checks and inspections during a reasonable warm-up period.
- k. Operate the engine generator-set for at least 2 hours at 75 percent of Service Load.
- l. Verify proper operation and set-points of gauges and instruments.
- m. Verify proper operation of ancillary equipment.
- n. Manually adjust the governor to increase engine speed past the over-speed limit. Record the RPM at which the engine shuts down.
- o. Start the engine, record the starting time, make and record engine manufacturer's after-starting checks and inspections and operate the engine generator-set for at least 15 minutes at 75 percent of Service Load.
- p. Manually adjust the governor to increase engine speed to within 2 percent of the over-speed trip speed previously determined and operate at that point for 5 minutes. Manually adjust the governor to the rated frequency.
- q. Manually fill the day tank to a level above the overfill limit. Record the level at which the overfill alarm sounds. Verify shutdown of the fuel transfer pump. Drain the day tank down below the overfill limit.
- r. Shut down the engine. Remove the time-delay low lube oil pressure alarm bypass and try to start the engine.
- s. Attach a manifold to the engine oil system (at the oil pressure sensor port) that contains a shutoff valve in series with a connection for the engine's oil pressure sensor followed by an oil pressure gauge ending with a bleed valve. Move the engine's oil pressure sensor from the engine to the manifold. Open the manifold shutoff valve and close the bleed valve.
- t. Start the engine, record the starting time, make and record engine manufacturer's after-starting checks and inspections and operate the engine generator-set for at least 15 minutes at 75 percent of Service Load.
- u. Close the manifold shutoff valve. Slowly allow the pressure in the manifold to bleed off through the bleed valve while watching the pressure gauge. Record the pressure at which the engine shuts down. Catch oil spillage from the bleed valve in a container. Add the oil from the container back to the engine, remove the manifold, and reinstall the engine's oil pressure sensor on the engine.

- v. Start the engine, record the starting time, make and record engine manufacturer's after-starting checks and inspections and operate the engine generator-set for at least 15 minutes at 100 percent of Service Load. Record the maximum sound level in each frequency band at a distance of 75 feet from the end of the exhaust and air intake piping directly along the path of intake and discharge for horizontal piping; or at a radius of 75 feet from the engine at 45 degrees apart in all directions for vertical piping. If a sound limiting enclosure is provided, modify or replace the enclosure, the muffler, and intake silencer must be modified or replaced as required to meet the sound requirements contained within this specification
- w. Manually drain off fuel slowly from the day tank to empty it to below the low fuel level limit and record the level at which the audible alarm sounds. Add fuel back to the day tank to fill it above low level alarm limits.

3.6.9 Performance Tests

In the following tests, where measurements are to be recorded after stabilization of an engine-generator set parameter (voltage, frequency, current, temperature, etc.), stabilization is considered to have occurred when measurements are maintained within the specified bandwidths or tolerances, for a minimum of four consecutive readings. For the following tests, repeat the associated tests if any parts are changed, or adjustments made to the generator set, its controls, or auxiliaries.

3.6.9.1 Continuous Engine Load Run Test

Test the engine-generator set and ancillary systems at service load to demonstrate durability; verify that heat of extended operation does not adversely affect or cause failure in any part of the system; and check all parts of the system. If the engine load run test is interrupted for any reason, repeat the entire test. Accomplish the engine load run test during daylight hours, with an average ambient temperature of 90 degrees F, during the month of July. After each change in load in the following test, measure the vibration at the end bearings (front and back of engine, outboard end of generator) in the horizontal, vertical, and axial directions. Verify that the vibration is within the allowable range. Take data taken at 15 minute intervals and include the following:

Electrical: Output amperes, voltage, real and reactive power, power factor, frequency.

Pressure: Lube-oil.

Temperature: Coolant, Lube-oil, Exhaust, Ambient.

- a. Perform and record engine manufacturer's recommended prestarting checks and inspections. Include as a minimum checking of coolant fluid, fuel, and lube-oil levels.
- b. Start the engine, make and record engine manufacturer's after-starting checks and inspections during a reasonable warmup period.
- c. Operate the engine generator-set for 2 hours at 75 percent of Service Load.

- d. Increase load to 100 percent of Service Load and operate the engine generator-set for 4 hours.
- e. For prime rated units, increase load to 110 percent of Service Load and operate the engine generator-set for 2 hours.
- f. Decrease load to 100 percent of Service Load and operate the engine generator-set for 2 hours or until all temperatures have stabilized.
- g. Remove load from the engine-generator set.

3.6.9.2 Voltage and Frequency Droop Test

For the following steps, verify that the output voltage and frequency return to and stabilize within the specified bandwidth values following each load change. Record the generator output frequency and line-line and line-neutral voltages following each load change.

- a. With the generator operating at no load, adjust voltage and frequency to rated voltage and frequency.
- b. Increase load to 100 percent of Rated Output Capacity. Record the generator output frequency and line-line and line-neutral voltages.
- c. Calculate the percent droop for voltage and frequency with the following equations.

$$\text{Voltage droop percent} = \frac{\text{No-load volts} - \text{rated output capacity volts}}{\text{Rated output capacity volts}} \times 100$$

$$\text{Frequency droop percent} = \frac{\text{No load hertz} - \text{rated output capacity hertz}}{\text{Rated output capacity hertz}} \times 100$$

- d. Repeat steps a. through c. two additional times without making any adjustments.

3.6.9.3 Voltage Regulator Range Test

- a. While operating at no load, verify that the voltage regulator adjusts from 90 to 110 percent of rated voltage.
- b. Increase load to 100 percent of Rated Output Capacity. Verify that the voltage regulator adjusts from 90 to 110 percent of rated voltage.

3.6.9.4 Governor Adjustment Range Test

- a. While operating at no load, verify that the governor adjusts from 90 to 110 percent of rated frequency.
- b. Increase load to 100 percent of Rated Output Capacity. Verify that the governor adjusts from 90 to 110 percent of rated frequency.

3.6.9.5 Frequency and Voltage Stability and Transient Response

Verify that the engine-generator set responds to addition and dropping of blocks of load in accordance with the transient response requirements.

Document maximum voltage and frequency variation from bandwidth and verify that voltage and frequency return to and stabilize within the specified bandwidth, within the specified response time period. Document results in tabular form and with high resolution, high speed strip chart recorders or comparable digital recorders, as approved by the Contracting Officer. Include the following tabular data:

- (1) Ambient temperature (at 15 minute intervals).
- (2) Generator output current (before and after load changes).
- (3) Generator output voltage (before and after load changes).
- (4) Frequency (before and after load changes).
- (5) Generator output power (before and after load changes).
- (6) Include the actual instrument trace of voltage and frequency in graphic representations showing:

Charts marked at start of test; observed steady-state band; mean of observed band; momentary overshoot and undershoot (generator terminal voltage and frequency) and recovery time for each load change together with the voltage and frequency maximum and minimum trace excursions for each steady state load condition prior to and immediately following each load change. Generator terminal voltage and frequency transient recovery time for each step load increase and decrease.

- a. Perform and record engine manufacturer's recommended prestarting checks and inspections.
- b. Start the engine, make and record engine manufacturer's after-starting checks and inspections during a reasonable warm-up period and no load. Verify stabilization of voltage and frequency within specified bandwidths.
- c. With the unit at no load, apply the Maximum Step Load Increase.
- d. Apply load in steps equal to the Maximum Step Load Increase until the addition of one more step increase will exceed the Service Load.
- e. Decrease load to the unit such that addition of the Maximum Step Load Increase will load the unit to 100 percent of Service Load.
- f. Apply the Maximum Step Load Increase.
- g. Decrease load to zero percent in steps equal to the Maximum Step Load Decrease.
- h. Repeat steps c. through g.

3.6.10 Parallel Operation Test

Test the capability of each engine-generator set to parallel and share load with other generator sets, individually and in all combinations. This test must be performed with the voltage regulator and governor adjustment settings used for the Frequency and Voltage Stability and Transient Response test. If settings are changed during the performance of this test, a voltage and frequency stability and transient response

test must be performed for each engine generator set using the setting utilized in this test. During operations record load-sharing characteristics of each set in parallel operation. Include the following data:

- (1) Ambient temperature (at 15 minute intervals).
- (2) Generator output current (before and after load changes).
- (3) Generator output voltage (before and after load changes).
- (4) Power division and exchange between generator sets.
- (5) Real power (watts) and reactive power (vars) on each set.

3.6.10.1 Combinations

Connect each set, while operating at no load, parallel with one other set in the system, operating at service load, until all possible combinations have been achieved. Verify stabilization of voltage and frequency within specified bandwidths and proportional sharing of real and reactive loads. Document stabilization of voltage and frequency within specified bandwidth, the active power division, active power exchange, reactive power division, and voltage and frequency stability and transient response in the following steps for each combination.

- a. Divide the load proportionally between the sets and operate in parallel for 15 minutes.
- b. Increase the load, in steps equal to the Maximum Step Increase, until each set is loaded to its service load.
- c. Decrease the load, in steps equal to the Maximum Step Decrease, until each set is loaded to approximately 25 percent of its service load.
- d. Increase the load, in steps equal to the Maximum Step Increase, until each set is loaded to approximately 50 percent of its service load. Verify stabilization of voltage and frequency within specified bandwidths and proportional sharing of real and reactive load.
- e. Reduce the sum of the loads on both sets to the output rating of the smaller set.
- f. Transfer a load equal to the output rating of the smaller of the 2 sets to and from each set. Verify stabilization of voltage and frequency within specified bandwidths and proportional sharing of real and reactive load.
- g. Document the active power division, active power exchange, reactive power division, and voltage and frequency stability and transient response.

3.6.10.2 Multiple Combinations

Connect each set, while operating at no load, parallel with all multiple combinations of all other set in the system, while operating at service load, until all multiple combinations of parallel operations have been achieved.

3.6.11 Parallel Operation Test (Commercial Source)

Connect each set parallel with the commercial power source. Operate in parallel for 15 minutes. Verify stabilization of voltage and frequency within specified bandwidths. Record the output voltage, frequency, and loading to demonstrate ability to synchronize with the commercial power source.

3.6.12 Automatic Operation Tests for Stand-Alone Operation

Test the automatic loading system to demonstrate automatic starting, and loading and unloading of each engine-generator set. Utilize the actual loads to be served for this test, and the loading sequence is the indicated sequence. Perform this test for a minimum of two successive, successful tests. Include the following data:

- (1) Ambient temperature (at 15 minute intervals).
 - (2) Generator output current (before and after load changes).
 - (3) Generator output voltage (before and after load changes).
 - (4) Generator output frequency (before and after load changes).
- a. Initiate loss of the primary power source and verify automatic sequence of operation.
 - b. Restore the primary power source and verify sequence of operation.
 - c. Verify resetting of controls to normal.

3.7 GROUNDING

NFPA 70 and IEEE C2, except that grounding systems must have a resistance to solid earth ground not exceeding 5 ohms.

3.7.1 Grounding Electrodes

Provide driven ground rods as specified in Section 33 71 02 UNDERGROUND ELECTRICAL DISTRIBUTION and Section 33 71 01 OVERHEAD TRANSMISSION AND DISTRIBUTION. Connect ground conductors to the upper end of ground rods by exothermic weld or compression connector. Provide compression connectors at equipment end of ground conductors.

3.7.2 Engine-Generator Set Grounding

Provide separate copper grounding conductors and connect them to the ground system as indicated. When work in addition to that indicated or specified is required to obtain the specified ground resistance, the provision of the contract covering "Changes" must apply.

3.7.3 Connections

Make joints in grounding conductors by exothermic weld or compression connector. Exothermic welds and compression connectors must be installed as specified in Section 33 71 02 UNDERGROUND ELECTRICAL DISTRIBUTION paragraph regarding GROUNDING.

3.7.4 Grounding and Bonding Equipment

UL 467, except as indicated or specified otherwise.

3.8 START-UP ENGINEER

Provide the services of a qualified factory trained start-up engineer, regularly employed by the engine-generator set manufacturer. The start-up services must include conducting preliminary operations and functional acceptance tests. The start-up engineer must be present at the engine generator set installation-site, full-time, while preliminary operations and functional acceptance tests are being conducted.

3.9 PREREQUISITES FOR FUNCTIONAL ACCEPTANCE TESTING

Completion of the following requirements is mandatory prior to scheduling functional acceptance tests for the engine-generator set and auxiliary equipment.

3.9.1 Piping Tests

Complete as specified in Section 33 52 10 SERVICE PIPING, FUEL SYSTEMS.

3.9.2 Performance of Acceptance Checks and Tests

The acceptance checks and tests must be accomplished by the testing organization as described in Section 26 08 00 APPARATUS INSPECTION AND TESTING.

3.9.3 Generator Sets

Complete as specified in the paragraph ACCEPTANCE CHECKS AND TESTS.

3.9.3.1 Automatic Transfer Switches

Complete acceptance checks and tests as specified in Section 26 36 23 AUTOMATIC TRANSFER SWITCHES AND BY-PASS/ISOLATION SWITCH.

3.9.4 Preliminary Operations

The start-up engineer must conduct manufacturer recommended start-up procedures and tests to verify that the engine-generator set and auxiliary equipment are ready for functional acceptance tests. Give the Contracting Officer 15 days' advance notice that preliminary operations will be conducted. After preliminary operation has been successfully conducted, the start-up engineer will notify the Contracting Officer in writing stating the engine-generator set and auxiliary equipment are ready for functional acceptance tests.

3.9.5 Preliminary Assembled Operation and Maintenance Manuals

Preliminary assembled operation and maintenance manuals must have been submitted to and approved by the Contracting Officer. Manuals must be prepared as specified in the paragraph ASSEMBLED OPERATION AND MAINTENANCE MANUALS.

3.9.6 Functional Acceptance Test Procedure

Test procedure must be prepared by the start-up engineer specifically for

the engine-generator set and auxiliary equipment. The test agenda must cover the requirements specified in the paragraph FUNCTIONAL ACCEPTANCE TESTS. The test procedure must indicate in detail how tests are to be conducted. A statement of the tests that are to be performed without indicating how the tests are to be performed is not acceptable. Indicate what work is planned on each workday and identify the calendar dates of the planned workdays. Specify what additional technical support personnel is needed such as factory representatives for major equipment. Specify on which testing workday each technical support personnel is needed. Data recording forms to be used to document test results are to be submitted with the proposed test procedure. A list of test equipment and instruments must also be included in the test procedure.

3.9.7 Test Equipment

Test equipment and instruments must be on hand prior to scheduling field tests or, subject to Contracting Officer approval, evidence must be provided to show that arrangements have been made to have the necessary equipment and instruments on-site prior to field testing.

3.10 FIELD QUALITY CONTROL

Give Contracting Officer 30 days' notice of dates and times scheduled for tests which require the presence of the Contracting Officer. The Contracting Officer will coordinate with the using activity and schedule a time that will eliminate or minimize interruptions and interference with the activity operations. The Contractor must be responsible for costs associated with conducting tests outside of normal working hours and with incorporating special arrangements and procedures, including temporary power conditions. The Contractor must provide labor, equipment, fuel, test load, and consumables required for the specified tests. The test load must be a cataloged product. Calibration of measuring devices and indicating devices must be certified. Refer to Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM, for requirements for a cataloged product. Perform the following field tests.

3.10.1 Acceptance Checks and Tests

Perform in accordance with the manufacturer's recommendations, and include the following visual and mechanical inspections and electrical tests, performed in accordance with [NETA ATS](#).

3.10.1.1 Circuit Breakers -Low Voltage Insulated Case/Molded Case

a. Visual and Mechanical Inspection

- (1) Compare nameplate data with specifications and approved shop drawings.
- (2) Inspect circuit breaker for correct mounting.
- (3) Operate circuit breaker to ensure smooth operation.
- (4) Inspect case for cracks or other defects.
- (5) Verify tightness of accessible bolted connections and cable connections by calibrated torque-wrench method. Thermo-graphic survey is not required.

(6) Inspect mechanism contacts and arc chutes in unsealed units.

b. Electrical Tests

(1) Perform contact-resistance tests.

(2) Perform insulation-resistance tests.

(3) Adjust breaker(s) for final settings in accordance with engine-generator set manufacturer's requirements.

3.10.1.2 Current Transformers

a. Visual and Mechanical Inspection

(1) Compare equipment nameplate data with specifications and approved shop drawings.

(2) Inspect physical and mechanical condition.

(3) Verify correct connection.

(4) Verify that adequate clearances exist between primary and secondary circuit.

(5) Verify tightness of accessible bolted electrical connections by calibrated torque-wrench method. Thermo-graphic survey is not required.

(6) Verify that all required grounding and shorting connections provide good contact.

b. Electrical Tests

(1) Perform insulation-resistance tests.

(2) Perform polarity tests.

(3) Perform ratio-verification tests.

3.10.1.3 Metering and Instrumentation

a. Visual and Mechanical Inspection

(1) Compare equipment nameplate data with specifications and approved shop drawings.

(2) Inspect physical and mechanical condition.

(3) Verify tightness of electrical connections.

b. Electrical Tests

(1) Determine accuracy of meters at 25, 50, 75, and 100 percent of full scale.

(2) Calibrate watt-hour meters according to manufacturer's published data.

- (3) Verify all instrument multipliers.
- (4) Electrically confirm that current transformer secondary circuits are intact.

3.10.1.4 Battery Systems

a. Visual and Mechanical Inspection

- (1) Compare equipment nameplate data with specifications and approved shop drawings.
- (2) Inspect physical and mechanical condition.
- (3) Verify tightness of accessible bolted electrical connections by calibrated torque-wrench method. Thermo-graphic survey is not required.
- (4) Measure electrolyte specific gravity and temperature and visually check fill level.
- (5) Verify adequacy of battery support racks, mounting, anchorage, and clearances.

b. Electrical Tests

- (1) Set charger float and equalizing voltage levels.
- (2) Verify all charger functions and alarms.
- (3) Measure each cell voltage and total battery voltage with charger energized and in float mode of operation.
- (4) Perform a capacity load test.

3.10.1.5 Engine-Generator Set

a. Visual and Mechanical Inspection

- (1) Compare equipment nameplate data with specifications and approved shop drawings.
- (2) Inspect physical and mechanical condition.
- (3) Inspect for correct anchorage and grounding.

b. Electrical and Mechanical Tests

- (1) Perform an insulation-resistance test on generator winding with respect to ground. Calculate polarization index.
- (2) Perform phase rotation test to determine compatibility with load requirements.

3.10.1.6 Grounding System

a. Visual and Mechanical Inspection

- (1) Inspect ground system for compliance with contract plans and

specifications.

b. Electrical Tests

- (1) Perform ground-impedance measurements utilizing the fall-of-potential method defined in IEEE 81. On systems consisting of interconnected ground rods, perform tests after interconnections are complete. Take measurements in normally dry weather, not less than 48 hours after rainfall. Provide site diagram indicating location of test probes with associated distances, and provide a plot of resistance vs. distance.

3.10.2 Functional Acceptance Tests

The tests must be performed by the start-up engineer. Upon successful test completion, the start-up engineer must provide the Contracting Officer with a written test report within 15 calendar days showing the tests performed and the results of each test. The report must include the completed approved test data forms and certification from the start-up engineer that the test results fall within the manufacturer's recommended limits and meet the specified requirements performance. The report must be dated and signed by the start-up engineer, and submitted for approval by the Contracting Officer. The Contracting Officer will witness final acceptance tests. Testing must include, but not be limited to, the following:

- a. Verify proper functioning of each engine protective shutdown device and pre-shutdown alarm device. Testing of the devices must be accomplished by simulating device actuation and observing proper alarm and engine shutdown operation.
- b. Verify proper functioning of the engine over-speed trip device. Testing of the over-speed trip device must be accomplished by raising the speed of the engine-generator set until an over-speed trip is experienced.
- c. Verify proper functioning of the crank cycle/terminate relay. Testing of the relay must be accomplished by engaging the starter motor with the engine being prevented from running. Observe the complete crank/rest cycle as described in the paragraph STARTING SYSTEM.
- d. Verify proper functioning of the following automatic and manual operations. Testing must include, but not be limited to, the following:
 - (1) Loss of Utility: Initiate a normal power failure with connected test load of rated kW at 1.0 power factor. Record time delay on start, cranking time until engine starts and runs, time to come up to operating speed, voltage and frequency overshoot, and time to achieve steady state conditions with all switches transferred to emergency position.
 - (2) Return of Utility: Return normal power and record time delay on retransfer for each automatic transfer switch, and time delay on engine cool-down and shutdown.
 - (3) Manual starting.
 - (4) Emergency stop.

- e. Operate the engine-generator set at rated current (amperes) until the jacket water temperature stabilizes. Stabilization will be considered to have occurred when three consecutive temperature readings remain unchanged. Continue to operate the generator set for an additional 2 hours. Record instrument readings for terminal voltage, line current, frequency (Hz), engine speed rpm, lubricating oil pressure, jacket water temperature, and ambient temperature at 5 minute intervals for first 15 minutes and at 15 minute intervals thereafter.

3.11 DEMONSTRATION

Upon completion of the work and at a time approved by the Contracting Officer, the Contractor must provide instructions by a qualified instructor to the Government personnel in the proper operation and maintenance of the equipment. **four** Government personnel must receive training comparable to the equipment manufacturer's factory training. The duration of instruction must be for not less than one 8 hour working day for instruction of operating personnel and not less than one 8 hour working day for instruction of maintenance personnel.

3.11.1 Instructor's Qualification Resume

Instructors must be regular employees of the engine-generator set manufacturer. The instruction personnel provided to satisfy the requirements above must be factory certified by the related equipment manufacturer to provide instruction services. Submit the name and qualification resume of instructor to the Contracting Officer for approval.

3.11.2 Training Plan

Submit training plan 30 calendar days prior to training sessions. Training plan must include scheduling, content, outline, and training material (handouts). Content must include, but not be limited to, the following:

3.11.2.1 Operating Personnel Training

This instruction includes operating the engine-generator set, auxiliary equipment including automatic transfer switches in all modes, and the use of all functions and features specified.

3.11.2.2 Maintenance Personnel Training

Training must include mechanical, hydraulic, electrical, and electronic instructions for the engine-generator set and auxiliary equipment including automatic transfer switches.

- a. Mechanical Training: Must include at least the following:

- (1) A review of mechanical diagrams and drawings.
- (2) Component location and functions.
- (3) Troubleshooting procedures and techniques.
- (4) Repair procedures.

- (5) Assembly/disassembly procedures.
 - (6) Adjustments (how, when, and where).
 - (7) Preventive maintenance procedures.
 - (8) Review of flow diagram.
 - (9) Valve locations and function.
 - (10) Valve and hydraulic equipment adjustment and maintenance procedures.
 - (11) Hydraulic system maintenance and servicing.
 - (12) Lubrication points, type, and recommended procedures and frequency.
- b. Electrical and Electronic Maintenance Training: Must include at least the following:
- (1) A review of electrical and electronic systems including wiring diagrams and drawings.
 - (2) Troubleshooting procedures for the machine and control systems.
 - (3) Electrical and electronic equipment servicing and care.
 - (4) Use of diagnostics to locate the causes of malfunction.
 - (5) Procedures for adjustments (locating components, adjustments to be made, values to be measured, and equipment required for making adjustments).
 - (6) Maintenance and troubleshooting procedures for microprocessor or minicomputer where applicable.
 - (7) Circuit board repair procedures where applicable (with schematics provided).
 - (8) Use of diagnostic tapes.
 - (9) Recommended maintenance servicing and repair for motors, switches, relays, solenoids, and other auxiliary equipment and devices.

3.12 **ONSITE TRAINING**

Conduct a training course for the operating staff as designated by the Contracting Officer. The training period must consist of a total 4 hours of normal working time and must start after the system is functionally completed but prior to final acceptance.

- a. Submit a letter giving the date proposed for conducting the onsite training course, the agenda of instruction, a description of the digital video recording to be provided. The course instructions must cover pertinent points involved in operating, starting, stopping, servicing the equipment, as well as major elements of the operation and maintenance manuals. Additionally, the course instructions must demonstrate routine **maintenance procedures** as described in the

operation and maintenance manuals.

- b. Submit a digital video recording of the entire training session .
- c. One full size reproducible Mylar ach drawing must accompany the booklets. Mylars must be rolled and placed in a heavy cardboard tube with threaded caps on each end. The manual must include step-by-step procedures for system startup, operation, and shutdown; drawings, diagrams, and single-line schematics to illustrate and define the electrical, mechanical, and hydraulic systems together with their controls, alarms, and safety systems; the manufacturer's name, model number, and a description of equipment in the system. The instructions must include procedures for interface and interaction with related systems to include automatic transfer switches fire alarm/suppression systems . Each booklet must include a CD containing an ASCII file of the procedures.
- d. Provide approved operation and maintenance manuals for the training course. Post approved instructions prior to the beginning date of the training course. Coordinate the training course schedule with the using service's work schedule, and submit for approval 14 days prior to beginning date of proposed beginning date of training.

3.13 INSTALLATION

Installation must conform to the applicable requirements of IEEE C2, NFPA 30, NFPA 37, and NFPA 70.

3.14 FINAL TESTING AND INSPECTION

- a. Start the engine, record the starting time, make and record all engine manufacturer's after-starting checks and inspections during a reasonable warm-up period.
- b. Increase the load in steps no greater than the Maximum Step Load Increase to 100 percent of Service Load, and operate the engine-generator set for at least 30 minutes. Measure the vibration at the end bearings (front and back of engine, outboard end of generator) in the horizontal, vertical, and axial directions. Verify that the vibration is within the same range as previous measurements and is within the required range.
- c. Remove load and shut down the engine-generator set after the recommended cool down period.
- d. Remove the lube oil filter and have the oil and filter examined by the engine manufacturer for excessive metal, abrasive foreign particles, etc. Verify any corrective action for effectiveness by running the engine for 8 hours at Service Load, then re-examine the oil and filter.
- e. Remove the fuel filter and examine the filter for trash, abrasive foreign particles, etc.
- f. Visually inspect and check engine and generator mounting bolts for tightness and visible damage.
- g. Replace air, oil, and fuel filters with new filters.

3.15 MANUFACTURER'S FIELD SERVICE

The engine generator-set manufacturer must furnish a qualified representative to supervise the installation of the engine generator-set, assist in the performance of the onsite tests, and instruct personnel as to the operational and maintenance features of the equipment.

3.16 POSTED DATA AND INSTRUCTIONS

Post Data and Instructions prior to field acceptance testing of the engine generator set. Provide two sets of typed instructions/data in 8-1/2 x 11 inch format, laminated in weatherproof plastic, and placed in three-ring vinyl binders. Place the binders as directed by the Contracting Officer. Provide the instructions prior to acceptance of the engine generator set installation.

- b. Include a one-line diagram, wiring and control diagrams and a complete layout of the system in the first set. Include the condensed operating instructions describing manufacturer's pre-start checklist and precautions; startup procedures for test-mode, manual-start mode, and automatic-start mode (as applicable); running checks, procedures, and precautions; and shutdown procedures, checks, and precautions in the second set. Include procedures for interrelated equipment (such as heat recovery systems, co-generation, load-shedding, and automatic transfer switches).
- c. Submit instructions including: the manufacturers pre-start checklist and precautions; startup procedures for test-mode, manual-start mode, and automatic-start mode (as applicable); running checks, procedures, and precautions; and shutdown procedures, checks, and precautions. Include procedures for interrelated equipment (such as heat recovery systems, co-generation, load-shedding, and automatic transfer switches). Provide weatherproof instructions, laminated in plastic, and post where directed.

3.17 ACCEPTANCE

Submit drawings which accurately depict the as-built configuration of the installation, upon acceptance of the engine-generator set installation. Revise layout drawings to reflect the as-built conditions and submit them with the as-built drawings. Final acceptance of the engine-generator set will not be given until the Contractor has successfully completed all tests and all defects in installation material or operation have been corrected.

-- End of Section --

SECTION 26 36 23

AUTOMATIC TRANSFER SWITCHES AND BY-PASS/ISOLATION SWITCH
05/20

PART 1 GENERAL

1.1 REFERENCES

The publications listed below form a part of this specification to the extent referenced. The publications are referred to within the text by the basic designation only.

ASTM INTERNATIONAL (ASTM)

ASTM B117 (2019) Standard Practice for Operating Salt Spray (Fog) Apparatus

ASTM D709 (2017) Standard Specification for Laminated Thermosetting Materials

INTERNATIONAL ELECTRICAL TESTING ASSOCIATION (NETA)

NETA ATS (2017; Errata 2017) Standard for Acceptance Testing Specifications for Electrical Power Equipment and Systems

NATIONAL ELECTRICAL MANUFACTURERS ASSOCIATION (NEMA)

NEMA 250 (2018) Enclosures for Electrical Equipment (1000 Volts Maximum)

NEMA ICS 2 (2000; R 2005; Errata 2008) Industrial Control and Systems Controllers, Contactors, and Overload Relays Rated 600 V

NEMA ICS 4 (2015) Application Guideline for Terminal Blocks

NEMA ICS 6 (1993; R 2016) Industrial Control and Systems: Enclosures

NATIONAL FIRE PROTECTION ASSOCIATION (NFPA)

NFPA 70 (2020; ERTA 20-1 2020; ERTA 20-2 2020; TIA 20-1; TIA 20-2; TIA 20-3; TIA 20-4) National Electrical Code

NFPA 110 (2016) Standard for Emergency and Standby Power Systems

UNDERWRITERS LABORATORIES (UL)

UL 508 (2018) UL Standard for Safety Industrial Control Equipment

UL 1008 (2014) Transfer Switch Equipment

UL 1066

(2012; Reprint Mar 2017) UL Standard for Safety Low-Voltage AC and DC Power Circuit Breakers Used in Enclosures

1.2 RELATED REQUIREMENTS

Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM, and Section 26 08 00 APPARATUS INSPECTION AND TESTING, applies to this section, with the additions and modifications specified herein.

1.3 SUBMITTALS

Government approval is required for submittals with a "G" designation; submittals not having a "G" designation are for Contractor Quality Control approval. Submit in accordance with Section 01 33 00 SUBMITTAL PROCEDURES:

SD-02 Shop Drawings

Automatic Transfer Switch Drawings; G

SD-03 Product Data

Automatic Transfer Switches; G

BY-PASS/ISOLATION SWITCH (BP/IS); G

SD-06 Test Reports

Acceptance Checks and Tests; G

Functional Acceptance Tests; G

Factory Testing; G

Factory Test Reports; G

SD-07 Certificates

Proof of Listing; G

SD-10 Operation and Maintenance Data

Operation and Maintenance Manual, Submit in accordance with Section 01 78 23 OPERATION AND MAINTENANCE DATA, Data Package 5; G

1.4 OPERATION AND MAINTENANCE MANUAL

Assemble and bind manuals in durable, hard-covered, water resistant binders. Assemble and index the manuals per the following table of contents:

- a. Manufacturer's O&M per "SD-10 Operation and Maintenance Data".
- b. Catalog data required by "SD-03 Product Data"

- c. Drawings required by "SD-02 Shop Drawings".

1.4.1 Additions to Operation and Maintenance Manuals

In addition to requirements of SD-10 Data Package 5, include the followings on the actual equipment provided:

- a. An outline drawing, front, top, and side views.
- b. Prices for spare parts and supply list.
- c. Date of Purchase.
- d. Corrective maintenance procedures.
- e. Operating manual outlining step-by-step procedures for system startup, operation, and shutdown.
- f. Include simplified wiring and control diagrams in the manual for system as installed.
- g. Provide typical contact voltage drop readings under specified conditions for use during periodic maintenance. Provide instructions for determination of contact integrity.

1.5 QUALITY ASSURANCE

1.5.1 Proof of Listing

Submit proof of listing by [UL 1008](#).

1.5.2 Automatic Transfer Switch Drawings

Include the following as a minimum:

- a. An outline drawing, including front, top, and side views.
- b. Provide a nameplate of corrosion-resistant material with not less than $1/8$ inch tall characters showing manufacturer's name and equipment ratings. Mount nameplate to front of enclosure and meet the nameplate requirements of [NEMA ICS 2](#).
- c. Provide detail drawings that include manufacturer's name and catalog number, electrical ratings, total system transfer statement, reduced normal supply voltage at which transfer to the alternate supply is initiated, transfer delay times, short-circuit current rating, wiring diagram, description of interconnections, testing instructions, acceptable conductor type for terminals, tightening torque for each wire connector, and other required [UL 1008](#) markings.
- d. Submit interface equipment connection diagram showing conduit and wiring between ATS and related equipment. Provide diagrams showing interlocking provisions and cautionary notes, if any.
- e. Drawings are to indicate adequate clearance for operation, maintenance, and replacement of operating equipment devices.

1.5.3 Regulatory Requirements

In each of the publications referred to herein, consider the advisory provisions to be mandatory, as though the word "shall" or "must" had been substituted for "should" wherever it appears. Interpret references in these publications to the "authority having jurisdiction," or words of similar meaning, to mean the Contracting Officer. Equipment, materials, installation, and workmanship must be in accordance with the mandatory and advisory provisions of NFPA 70 unless more stringent requirements are specified or indicated

1.5.4 Standard Product

Provide materials and equipment that are products of manufacturers regularly engaged in the production of such products which are of equal material, design and workmanship, and:

- a. Have been in satisfactory commercial or industrial use for 2 years prior to bid opening including applications of equipment and materials under similar circumstances and of similar size.
- b. Have been on sale on the commercial market through advertisements, manufacturers' catalogs, or brochures during the 2-year period.
- c. Where two or more items of the same class of equipment are required, provide products of a single manufacturer; however, the component parts of the item need not be the products of the same manufacturer unless stated in this section.

1.5.4.1 Alternative Qualifications

Products having less than a 2-year field service record are acceptable if the manufacturer has been regularly engaged in the design and production of automatic transfer switches and if a certified record of satisfactory field operation for not less than 6000 hours, exclusive of the manufacturers' factory or laboratory tests, is furnished.

1.5.4.2 Material and Equipment Manufacturing Date

Products manufactured more than 1 years prior to date of delivery to site are not acceptable.

1.6 DELIVERY AND STORAGE

Protect equipment placed in storage from humidity and temperature variations, moisture, water intrusion, dirt, dust, or other contaminants. In harsh environments where temperatures exceed non-operational parameters established within this specification, provide an environmentally controlled equipment storage facility to ensure temperature parameters are within equipment specification. Provide documentation of same to the Government when storage is implemented.

1.7 ENVIRONMENTAL CONDITIONS

Provide an ATS that is suitable for prolonged performance under following service conditions:

- a. Operating altitude: Sea level to 3,300 ft. (Systems applied at higher altitudes are to be derated in accordance with the manufacturer's instructions).

- b. Operating ambient temperature range: 40 to 104 degrees F.
- c. Operating relative humidity: 0 to 90 percent, without condensation.

PART 2 PRODUCTS

2.1 AUTOMATIC TRANSFER SWITCHES

Each automatic transfer switch must be rated and marked for total system transfer and have the current and voltage ratings as indicated. Provide a switch operating mechanism that is electrically operated, have quick-make, quick-break, load break contacts, and be mechanically held in both positions. Switches utilizing circuit breakers are not acceptable. Provide an ATS that is UL listed. ATS must be manufactured and tested in accordance with applicable requirements of NEMA ICS 2, UL 1008 and UL 1066. ATS must conform to NFPA 110. Provide the ATS with the following characteristics:

- a. Voltage: 480Y/277 volts ac.
- b. Amperage: As indicated on plans amps ac. Provide an ATS with a continuous load current rating of the switch rating.
- c. Number of Phases: Three.
- d. Number of Wires: Four.
- e. Frequency: 60 Hz.
- f. Poles: Four switched. One of the poles is the neutral.
- g. ATS Withstand Current Rating: Rated to withstand closing current short-circuit current of As indicated on plans amperes, RMS symmetrical.
- h. Nonwelding Contacts: Provide contacts that are nonwelding at the available fault current rating.
- i. Phase and Neutral Contacts: Provide contacts with silver alloy composition. Provide neutral contacts with the same continuous current rating as main or phase contacts.
- j. Configuration. Provide an ATS for use in emergency systems described in NFPA 70. Provide an ATS that is listed for emergency use.
- k. ATS Configuration. Provide an open transition ATS. Neutral is to break and make with the phase contacts.
- l. Service Entrance Rated. Provide an integrated circuit breaker and automatic transfer switch. Provide a separate deadfront compartment for the circuit breaker on switches 600 amp and larger. Provide label indicating that the ATS is the service disconnect. Provide a circuit breaker that is rated for 100% of the switch contact current rating. All components, except as noted herein, are to have a continuous load rating.

2.1.1 Undervoltage Sensing - Normal/Preferred Source

Undervoltage Sensing - Normal Source. Provide undervoltage sensing for each phase in the normal/preferred source. Sense low phase-to-ground voltage on each phase. Provide sensing circuit with adjustable dropout, 75-98 percent of nominal value and adjustable pickup, 85-100 percent of nominal value. Factory set dropout value to 85percent. Factory set pickup value to 90percent.

2.1.2 Adjustable Time Delay - Override Transfer

Adjustable Time Delay - Override Transfer. For override of normal-source voltage sensing to delay transfer and engine starting signals. Engine starting control contacts with adjustable commit-to-start delay circuit, 0.0-6.0 seconds. Factory set at 1second.

2.1.3 Voltage/Frequency Lockout Relay - Alternate/Emergency Source

Voltage/Frequency Lockout Relay. Prevent premature transfer to alternate/emergency source. Provide pickup voltage that is adjustable from 85-100 percent of nominal. Factory set for pickup at 90 percent. Provide pickup frequency that is adjustable from 90-97 percent of nominal. Factor set frequency pickup for 95 percent.

2.1.4 Adjustable Time Delay - Transfer to Alternate/Emergency Power Source

Adjustable Time Delay - Transfer to Alternate Power Source. Transfer to alternate power source time delay for transfer switches as indicated, adjustable 0-5 minutes. Factory set to 0 seconds. ATS is to monitor the frequency and voltage of alternate power source and transfer when frequency and voltage are stabilized.

2.1.5 Adjustable Time Delay- Re-transfer to Normal/Preferred Source

Adjustable Time Delay- Transfer to Source. Re-transfer to normal source time delay, adjustable 0-30 minutes. Factory set at 10 minutes. Time delay is automatically defeated upon loss or sustained undervoltage of alternate power source, provided that normal source has been restored.

2.1.6 Engine-Generator Exerciser

Exerciser. Solid-state, programmable-time switch exerciser to allow automatic starting of the generator set, subsequent load transfer, retransfer of load and shuts down engine after a preset cool-down period. Initiates exercise cycle at preset intervals adjustable from on a daily, weekly, bi-weekly or monthly basis.. Running periods are adjustable from 10-30 minutes. Factory settings are for 7-day exercise cycle, 20 minute running period and 5-minute cool-down period. Exerciser features include the following:

- a. Exerciser Transfer Selector Switch: Permits selection of exercise with and without load transfer or dual independent exercisers that allow for unloaded and loaded schedule testing.
- b. Push-button programming control with digital display of settings.
- c. Integral battery operation of time switch when normal control power is not available.

2.1.7 Engine Shutdown Time Delay

Engine Shutdown. Provide time delay that is adjustable from 0 to 5 minutes and is factory set at 5 minutes.

2.1.8 Engine Starting Contacts

Provide 2 isolated normally closed and 2 isolated normally open contact that is rated 5 A at 250 VAC/30 VDC minimum.

2.1.9 Controls for Fire Pump Service Automatic Transfer Switch

Provide the following additional controls features:

Phase reversal of the normal source is to initiate transfer to the emergency/alternate source.

2.1.10 Auxiliary Contact for Uninterruptible Power Supply

Provide a contact that closes when transferred to the alternate power source.

2.1.11 Unassigned Auxiliary Contacts

Provide two normally open and two normally closed, single-pole, double-throw auxiliary contacts for each switch position rated at 10 amperes at 240 volts.

2.1.12 Front Panel Devices

Provide devices mounted on cabinet front consisting of:

- a. Mode selector switch with the following positions and associated functions. Selector switch can be part of the microprocessor controller consisting of an LCD screen with a graphical interface or as a stand-alone test switch.
 - (1) TEST - Simulates loss of normal/preferred source system operation.
 - (2) NORMAL - Transfers system to normal/preferred source bypassing re-transfer time delay.
- b. Switch position indicating lights or graphical LCD display. Indicate source to which load is connected.
- c. Source-Available Monitor. Provide source-available indicating lights or graphical LCD display monitor that is labeled to show when one or both sources of power are available. If indicating lights are used, then the preference is to have Green be normal/preferred power and Red be for alternate/emergency power; however, other color schemes are allowed if clearly marked..
- d. Lamp test button.

2.2 BY-PASS/ISOLATION SWITCH (BP/IS)

Include load-break by-pass/isolation switches for the indicated automatic transfer switches that are arranged to select and connect either source of power directly to load, isolating transfer switch from load and from both power sources. Include the following features for each combined by-pass/isolation switch and automatic transfer switch:

- a. Bypass/isolation switch (BP/IS) and associated ATS are to be made by

the same manufacturer and must be completely interconnected and tested at factory and at project site as specified.

- b. ATS is to be manufactured, listed and tested in accordance with paragraph AUTOMATIC TRANSFER SWITCH. BP/IS switch current, voltage, closing, and short-circuit withstand closing ratings are to be equal or exceed comparable ratings specified for ATS and have the same phase arrangement and number of poles.
- c. Provide externally operated and arranged selector switch or handle so designed and constructed not to stop in an intermediate or neutral position during operation and that one person can safely bypass the ATS. Accomplish isolation of the ATS externally by one person without opening a door. Provide interlocks that ensure ATS is disconnected from source and load during isolation. Interlocks prevent ATS operation, except for testing and maintenance, while isolated. BP/IS operation is to be accomplished without disconnecting switch load terminal conductors.
- d. Provide drawout transfer switch that provides physical separation from bypass switch and live parts and accessibility for testing and maintenance operation.
- e. Provide contacts that have the same contact temperature that do not exceed those of the ATS contacts when carrying rated load. Provide contacts as specified for associated ATS, including provisions for inspection of contacts without disassembly of BP/IS or removal of entire contact enclosure. Provide manufacturer instructions for determining contact integrity in order To facilitate maintenance.
- f. The ATS controls remain functional with the ATS isolated or in bypass mode to permit monitoring of the normal power source and automatic starting of the generator in the event of a loss of the normal power source. In the isolated mode, the bypass section is capable of functioning as a manual transfer or automatic switch to transfer the load to either power source. The ATS can be completely removed from the enclosure, if required for maintenance or repair, while the bypass section continues to power the load.
- h. Construct Bypass/isolation switch for convenient removal of parts from front of switch enclosure without removal of other parts or disconnection of external power conductors.
- i. Achieve load by-pass to the source with no load interruption or a load interruption of not more than 0.16 seconds unless the time delay (neutral time delay) option is used.
- j. Provide drawout bypass switch that provides physical separation from ATS and live parts and accessibility for testing and maintenance operation. Provide automatic shutters that closed to isolate the bus.

2.2.1 Markings

Mark isolation handle positions with engraved plates or other approved means to indicate position or operating condition of associated ATS, as follows:

- a. Provide an indication that shows that BP/IS section is providing power to the load.

- b. Provide indication of ATS isolation/test position.
- c. Provide suitable control labels and instruction signs describing operating instructions.
- d. Indicating lamps or LCD screen for indicating that shows the source availability, bypass switch position, transfer switch position, and isolation handle position. If indicating lights are used, provide a lamp test button that turns the indicating lights on, but does not cause any function to take place.

2.2.2 Interconnection

Interconnect BP/IS and associated ATS with suitably sized copper bus bars silver-plated at each connection point, and braced to withstand magnetic and thermal forces created at withstand current rating specified for associated ATS.

2.3 ENCLOSURE

Provide an enclosure that meets the following:

- a. Provide ATS and accessories in a free-standing, floor-mounted, ventilated NEMA 250, Type 1 or 4X as indicated on the plans, smooth sheet metal enclosure constructed in accordance with applicable requirements of NEMA ICS 6, UL 508, UL 1066, and UL 1008. Provide door with suitable hinges, locking handle latch, and gasketed jamb. Provide at least No. 14 metal gauge.
- b. Factory wiring within enclosure and field wiring terminating within enclosure must comply with NFPA 70. Provide wire that is permanently tagged or marked near terminal at each end with wire number shown on approved detail drawing, when wiring is not color coded. Conform terminal block to NEMA ICS 4. Arrange terminals for entrance of external conductors from top and bottom of enclosure as shown. Main switch terminals, including neutral terminal if used, must be pressure type suitable for termination of external copper conductors shown.
- c. Provide thermostatically controlled heater within enclosure to prevent condensation over temperature range stipulated in paragraph SERVICE CONDITIONS.

2.3.1 Construction

Construct enclosure for ease of removal and replacement of ATS components and control devices from front without disconnection of external power conductors or removal or disassembly of major components.

2.3.2 Cleaning and Painting

Protect both the inside and outside surfaces of an enclosure, including means for fastening against corrosion by enameling, galvanizing, plating, powder coating, or other equivalent means. Protection is not required for metal parts that are inherently resistant to corrosion, bearings, sliding surfaces of hinges, or other parts where such protection is impractical. Provide manufacturer's standard finish material, process, and color that is free from runs, sags, peeling, or other defects. An enclosure marked Type 1, 3R, 4 or 12 is acceptable if there is no visible rust at the conclusion of a salt spray (fog) test using the test method in ASTM B117,

employing a 5 percent by weight, salt solution for 24 hours. Type 4X enclosures are acceptable following performance of the above test with an exposure time of 200 hours.

2.3.3 Field Fabricated Nameplates

Nameplate is to comply with [ASTM D709](#). Provide laminated plastic nameplates for each equipment enclosure as specified or as indicated on the drawings. Provide an inscription on each nameplate that identifies the name of the equipment, sources of power, calculated short circuit with date and the location e.g. 'SWB-1 Electrical Room 103'. Provide nameplates that are made of melamine plastic, [0.125 inch](#) thick, white with black center core. Provide the nameplate with a surface that is matte finished and that has square corners.. Accurately align lettering and engrave into the core. Provide nameplates that are at least [1.0 by 2.5 inches](#) with a minimum lettering size of [0.25 inch](#) high normal block style.

2.4 FACTORY TESTING

Submit a description of proposed field test procedures, including proposed date and steps describing each test, its duration and expected results, not less than [4 weeks](#) prior to test date. Submit certified factory and field test reports, within 14 days following completion of tests. Provide reports that are certified and dated and that demonstrate that tests were successfully completed prior to shipment of equipment.

2.4.1 Prototype Factory Testing

A prototype of specified ATS is to be factory tested in accordance with [UL 1008](#). In addition, perform factory tests on each ATS as follows:

- a. Insulation resistance test to ensure integrity and continuity of entire system
- b. Main switch contact resistance test.
- c. Visual inspection to verify that each ATS is as specified.
- d. Mechanical test to verify that ATS sections are free of mechanical hindrances.
- e. Electrical tests to verify complete system electrical operation and to set up time delays and voltage sensing settings.

2.4.2 Factory Test Reports

Provide three certified copies of factory test reports from the manufacturer.

PART 3 EXECUTION

3.1 INSTALLATION

Installation must conform to the requirements of [NFPA 70](#) and manufacturer's recommendation.

3.2 PREREQUISITES FOR FUNCTIONAL ACCEPTANCE TESTING

Completion of the following requirements is mandatory prior to scheduling

functional acceptance tests for the automatic transfer switch.

3.2.1 Performance of Acceptance Checks and tests

Complete as specified in paragraph entitled "Acceptance Checks and Tests". The Acceptance Checks and Tests are to be accomplished by the Testing organization as described in Section 26 08 00 APPARATUS INSPECTION AND TESTING.

3.2.2 Manufacturers O&M Information

The manufacturers O&M information required by the paragraph entitled "SD-10 Operation and Maintenance Data", is to be submitted to and approved by the Contracting Officer.

3.2.3 Test Equipment

Ensure all test equipment and instruments is on hand prior to scheduling field tests, or subject to Contracting Officer's approval, evidence must be provided to show that arrangements have been made to have the necessary equipment and instruments on site prior to field testing.

3.3 FIELD QUALITY CONTROL

Give Contracting Officer 15 days notice of dates and times scheduled for tests which require the presence of the Contracting Officer. The Contracting Officer will coordinate with the using activity and schedule a time that will eliminate or minimize interruptions and interference with the activity operations. The contractor is responsible for costs associated with conducting tests outside of normal working hours and with incorporating special arrangements and procedures, including temporary power conditions. The contractor provides labor, equipment, apparatus, including test load, and consumables required for the specified tests. Calibration of all measuring devices and indicating devices must be certified. Provide the services of a qualified factory-trained manufacturer's representative to assist the contractor in installation and start-up of the equipment specified under this section. The manufacturer's representative is to provide technical direction and assistance to the contractor in general assembly of the equipment, connections and adjustments, and testing of the assembly components contained herein. Provide a test load that is a cataloged product in accordance with Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM. Perform the following field tests in accordance with the manufacturer's recommendations and include the following visual and mechanical inspections and electrical tests, performed in accordance with NETA ATS.

3.3.1 Automatic Transfer Switch [Acceptance Checks and Tests](#)

a. Visual and Mechanical Inspection

- (1) Compare equipment nameplate data with specifications and approved shop drawings.
- (2) Inspect physical and mechanical condition.
- (3) Confirm correct application of manufacturer's recommended lubricants.
- (4) Verify that manual transfer warnings are attached and visible.

- (5) Verify tightness of all control connections.
- (6) Verify tightness of accessible bolted connections by calibrated torque-wrench method. Thermographic survey is not required.
- (7) Perform manual transfer operation.
- (8) Verify positive mechanical interlocking between normal and alternate sources.

b. Electrical Tests

- (1) Measure contact-resistance. Correct values that exceed 500 microhms and values for 1 pole deviating by more than 50 percent from other poles.
- (2) Perform insulation-resistance on each pole, phase-to-phase and phase-to-ground with switch closed, and across each open pole for one minute. Perform tests in both source positions.
- (3) Verify settings and operations of control devices.
- (4) Calibrate and set all relays and timers.
- (5) Test ground-fault protective device.

3.3.2 Functional Acceptance Tests

Functional Acceptance Tests must be coordinated with Section 26 32 15.00 ENGINE-GENERATOR SET STATIONARY 15-2500 KW, WITH AUXILIARIES. Functional Acceptance Test must be coordinated with Section 21 30 00 FIRE PUMPS. Include simulating power failure and demonstrating the following operations for each automatic transfer switch. Demonstrate in service that the automatic transfer switches are in good operating condition, and function not less than five times.

a. Perform automatic transfer tests:

- (1) Simulate loss of normal/preferred power.
- (2) Return to normal/preferred power.
- (3) Simulate loss of emergency/alternate power.
- (4) Simulate all forms of single-phase conditions.

b. Verify correct operation and timing of the following functions:

- (1) Normal source voltage-sensing relays.
- (2) Engine start sequence.
- (3) Time delay upon transfer.

- (4) Alternate source voltage-sensing relays.
- (5) Automatic transfer operation.
- (6) Interlocks and limit switch function.
- (7) Time delay and retransfer upon normal power restoration.
- (8) By-pass/isolation functional modes and related automatic transfer switch operations.

3.3.3 Infrared Scanning

After Substantial Completion, but not more than 60 days after Final Acceptance, perform an infrared scan of each switch. Remove all access panels so joints and connections are accessible to portable scanner.

- a. Follow-up Infrared Scanning: Perform an additional follow-up infrared scan of each switch 11 months after acceptance.
- b. Instrument: Use an infrared scanning device designed to measure temperature or to detect significant deviations from normal values. Provide calibration record for device.
- c. Record of Infrared Scanning: Prepare a certified report that identifies switches checked and that describes scanning results. Include notation of deficiencies detected, remedial action taken, and observations after remedial action.

3.4 TRAINING

Provide 4 hours of training to maintenance personnel on the proper operation, maintenance and adjustment of the automatic transfer switch. Coordinate this training with that of the generator equipment.

-- End of Section --

SECTION 26 41 00

LIGHTNING PROTECTION SYSTEM

11/13

PART 1 GENERAL

1.1 REFERENCES

The publications listed below form a part of this specification to the extent referenced. The publications are referred to within the text by the basic designation only.

INSTITUTE OF ELECTRICAL AND ELECTRONICS ENGINEERS (IEEE)

IEEE 81 (2012) Guide for Measuring Earth Resistivity, Ground Impedance, and Earth Surface Potentials of a Ground System

NATIONAL FIRE PROTECTION ASSOCIATION (NFPA)

NFPA 70 (2020; ERTA 20-1 2020; ERTA 20-2 2020; TIA 20-1; TIA 20-2; TIA 20-3; TIA 20-4) National Electrical Code

NFPA 780 (2017) Standard for the Installation of Lightning Protection Systems

UNDERWRITERS LABORATORIES (UL)

UL 96 (2016) UL Standard for Safety Lightning Protection Components

UL 467 (2013; Reprint Jun 2017) UL Standard for Safety Grounding and Bonding Equipment

UL Electrical Construction (2012) Electrical Construction Equipment Directory

1.2 RELATED REQUIREMENTS

1.2.1 Verification of Dimensions

Confirm all details of work, verify all dimensions in field, and advise Contracting Officer of any discrepancy before performing work. Obtain prior approval of Contracting Officer before making any departures from the design.

1.2.2 System Requirements

Provide a system furnished under this specification consisting of the latest UL Listed products of a manufacturer regularly engaged in production of lightning protection system components. Comply with **NFPA 70**, **NFPA 780**, and **UL 96**.

1.2.3 Lightning Protection System Installers Documentation

Provide documentation showing that the installer is certified with a

commercial third-party inspection company whose sole work is lightning protection, or is a UL Listed Lightning Protection Installer. In either case, the documentation must show that they have completed and passed the requirements for certification or listing, and have a minimum of 2 years documented experience installing lightning protection systems for DoD projects of similar scope and complexity.

1.3 SUBMITTALS

Government approval is required for submittals with a "G" designation; submittals not having a "G" designation are for Contractor Quality Control approval.. When used, a designation following the "G" designation identifies the office that will review the submittal for the Government. Submittals with an "S" are for inclusion in the Sustainability eNotebook, in conformance to Section 01 33 29 SUSTAINABILITY REPORTING. Submit the following in accordance with Section 01 33 00 SUBMITTAL PROCEDURES:

SD-02 Shop Drawings

Overall lightning protection system; G

Each major component; G

SD-06 Test Reports

Lightning Protection and Grounding System Test Plan; G

Lightning Protection and Grounding System Test; G

SD-07 Certificates

Lightning Protection System Installers Documentation; G

Component UL Listed and Labeled; G

Lightning protection system inspection certificate; G

Roof manufacturer's warranty; G

1.4 QUALITY ASSURANCE

In each standard referred to herein, consider the advisory provisions to be mandatory, as though the word "shall" or "must" has been substituted for "should" wherever it appears. Interpret references in these standards to "authority having jurisdiction," or words of similar meaning, to mean Contracting Officer.

1.4.1 Installation Drawings

1.4.1.1 Overall System Drawing

Submit installation shop drawing for the overall lightning protection system. Include on the drawings the physical layout of the equipment (plan view and elevations), mounting details, relationship to other parts of the work, and wiring diagrams.

1.4.1.2 Major Components

Submit detail drawings for each major component including manufacturer's

descriptive and technical literature, catalog cuts, and installation instructions.

1.4.2 Component UL Listed and Labeled

Submit proof of compliance that components are UL Listed and Labeled. Listing alone in **UL Electrical Construction**, which is the UL Electrical Construction Directory, is not acceptable evidence. In lieu of Listed and Labeled, submit written certificate from an approved, nationally recognized testing organization equipped to perform such services, stating that items have been tested and conform to requirements and testing methods of Underwriters Laboratories.

1.4.3 Lightning Protection and Grounding System Test Plan

Provide a lightning protection and grounding system test plan. Detail both the visual inspection and electrical testing of the system and components in the test plan. Identify (number) the system test points/locations along with a listing or description of the item to be tested and the type of test to be conducted. As a minimum, include a sketch of the facility and surrounding lightning protection system as part of the specific test plan for each structure. Include the requirements specified in paragraph, "Testing of Integral Lightning Protection System" in the test plan.

1.4.4 Lightning Protection System Inspection Certificate

Provide certification from a commercial third-party inspection company whose sole work is lightning protection, stating that the lightning protection system complies with **NFPA 780**. Third party inspection company cannot be the system installer or the system designer. Alternatively, provide a UL Lightning Protection Inspection Master Label Certificate for each facility indicating compliance to **NFPA 780**.

Inspection must cover every connection, air terminal, conductor, fastener, accessible grounding point and other components of the lightning protection system to ensure 100% system compliance. This includes witnessing the tests for the resistance measurements for ground rods with test wells, and for continuity measurements for bonds. It also includes verification of proper surge protective devices for power, data and telecommunication systems. Random sampling or partial inspection of a facility is not acceptable.

1.5 SITE CONDITIONS

Confirm all details of work, verify all dimensions in field, and advise Contracting Officer of any discrepancy before performing work. Obtain prior approval of Contracting Officer before changing the design.

PART 2 PRODUCTS

2.1 MATERIALS

Do not use a combination of materials that forms an electrolytic couple of such nature that corrosion is accelerated in the presence of moisture unless moisture is permanently excluded from the junction of such metals. Where unusual conditions exist which would cause corrosion of conductors, provide conductors with protective coatings, such as tin or lead, or oversize conductors. Where a mechanical hazard is involved, increase

conductor size to compensate for the hazard or protect conductors. When metallic conduit or tubing is provided, electrically bond conductor to conduit or tubing at the upper and lower ends by clamp type connectors or welds (including exothermic). All lightning protection components, such as bonding plates, air terminals, air terminal supports and braces, chimney bands, clips, connector fittings, and fasteners are to comply with the requirements of [UL 96](#) classes as applicable.

2.1.1 Main and Bonding Conductors

[NFPA 780](#) and [UL 96](#) Class I, Class II, or Class II modified materials as applicable.

2.2 COMPONENTS

2.2.1 Air Terminals

Provide solid air terminals with a blunt tip. Tubular air terminals are not permitted. Support air terminals more than [24 inches](#) in length by suitable brace, supported at not less than one-half the height of the terminal.

2.2.2 Ground Rods

Provide ground rods made of copper-clad steel conforming to conform to [UL 467](#). Provide ground rods that are not less than [3/4 inch](#) in diameter and [10 feet](#) in length. Do not mix ground rods of copper-clad steel or solid copper on the job.

2.2.3 Connections and Terminations

Provide connectors for splicing conductors that conform to [UL 96](#), class as applicable. Conductor connections can be made by clamps or welds (including exothermic). Provide style and size connectors required for the installation.

2.2.4 Connector Fittings

Provide connector fittings for "end-to-end", "Tee", or "Y" splices that conform to [NFPA 780](#) and [UL 96](#).

PART 3 EXECUTION

3.1 INTEGRAL SYSTEM

Provide a lightning protection system that meets the requirements of [NFPA 780](#). Lightning protection system consists of air terminals, roof conductors, down conductors, ground connections, grounding electrodes and ground ring electrode conductor. Expose conductors on the structures except where conductors are required to be in protective sleeves. Bond secondary conductors with grounded metallic parts within the building. Make interconnections within side-flash distances at or below the level of the grounded metallic parts.

3.1.1 Roof-Mounted Components

Coordinate with the roofing manufacturer and provide certification that the [roof manufacturer's warranty](#) is not violated by the installation methods for air terminals and roof conductors.

3.1.1.1 Air Terminals

Use a standing seam base for installation of air terminals on a standing seam metal roof that does not produce any roof penetrations.

3.1.1.2 Roof Conductors

Use a standing seam base for installation of roof conductors on a standing seam metal roof that does not produce any roof penetrations.

3.1.2 Down Conductors

Protect exposed down conductors from physical damage as required by [NFPA 780](#). Use Schedule 80 PVC to protect down conductors. Paint the Schedule 80 PVC to match the surrounding surface with paint that is approved for use on PVC. Down conductors are to be concealed within the wall cavities.

3.1.3 Ground Connections

Attach each down conductor and ground ring electrode to ground rods by welding (including exothermic), brazing, or compression. All connections to ground rods below ground level must be by exothermic weld connection or with a high compression connection using a hydraulic or electric compression tool to provide the correct circumferential pressure. Accessible connections above ground level and in test wells can be accomplished by mechanical clamping.

3.1.4 Grounding Electrodes

Extend driven ground rods vertically into the existing undisturbed earth for a distance of not less [10 feet](#). Set ground rods not less than [3 feet](#) nor more than [8 feet](#), from the structure foundation, and at least beyond the drip line for the facility. After the completed installation, measure the total resistance to ground using the fall-of-potential method described in [IEEE 81](#). Maximum allowed resistance of a driven ground rod is [5 ohms](#), under normally dry conditions when a ground ring electrode is not used. Contact the Contracting Officer for direction on how to proceed when two of any three ground rods, driven not less than [10 feet](#) into the ground, a minimum of [10 feet](#) apart, and equally spaced around the perimeter, give a combined value exceeding [50 ohms](#) immediately after having driven. For ground ring electrode, provide continuous No. [4/0](#) bare stranded copper cable. Lay ground ring electrode around the perimeter of the structure in a trench not less than [3 feet](#) nor more than [8 feet](#) from the nearest point of the structure foundation, and at least beyond the drip line for the facility. Install ground ring electrode to a minimum depth of [30 inches](#). Install a ground ring electrode in earth undisturbed by excavation, not earth fill, and do not locate beneath roof overhang, or wholly under paved areas or roadways where rainfall cannot penetrate to keep soil moist in the vicinity of the cable.

3.2 APPLICATIONS

3.2.1 Nonmetallic Exterior Walls with Metallic Roof

Bond metal roof sections together which are insulated from each other so that they are electrically continuous, having a surface contact of at least [3 square inches](#).

3.3 INTERFACE WITH OTHER STRUCTURES

3.3.1 Fences

Bond metal fence and gate systems to the lightning protection system whenever the fence or gate is within 6 feet of any part of the lightning protection system in accordance with ANSI C2.

3.4 RESTORATION

Where sod has been removed, place sod as soon as possible after completing the backfilling. Restore, to original condition, the areas disturbed by trenching, storing of dirt, cable laying, and other work. Overfill to accommodate for settling. Include necessary topsoil, fertilizing, liming, seeding, sodding, sprigging or mulching in any restoration. Maintain disturbed surfaces and replacements until final acceptance.

3.5 FIELD QUALITY CONTROL

3.5.1 Lightning Protection and Grounding System Test

Test the lightning protection and grounding system to ensure continuity is not in excess of 1 ohm and that resistance to ground is not in excess of 5 ohms. Provide documentation for the measured values at each test point. Test the ground rod for resistance to ground before making connections to the rod. Tie the grounding system together and test for resistance to ground. Make resistance measurements in dry weather, not earlier than 48 hours after rainfall. Include in the written report: locations of test points, measured values for continuity and ground resistances, and soil conditions at the time that measurements were made. Submit results of each test to the Contracting Officer.

-- End of Section --

SECTION 26 51 00

INTERIOR LIGHTING

05/20

PART 1 GENERAL

1.1 REFERENCES

The publications listed below form a part of this specification to the extent referenced. The publications are referred to within the text by the basic designation only.

ASTM INTERNATIONAL (ASTM)

- | | |
|-------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| ASTM A580/A580M | (2018) Standard Specification for Stainless Steel Wire |
| ASTM A641/A641M | (2019) Standard Specification for Zinc-Coated (Galvanized) Carbon Steel Wire |
| ASTM A653/A653M | (2020) Standard Specification for Steel Sheet, Zinc-Coated (Galvanized) or Zinc-Iron Alloy-Coated (Galvannealed) by the Hot-Dip Process |
| ASTM A1008/A1008M | (2020) Standard Specification for Steel, Sheet, Cold-Rolled, Carbon, Structural, High-Strength Low-Alloy, High-Strength Low-Alloy with Improved Formability, Solution Hardened, and Bake Hardenable |
| ASTM B164 | (2003; R 2014) Standard Specification for Nickel-Copper Alloy Rod, Bar, and Wire |
| ASTM B633 | (2019) Standard Specification for Electrodeposited Coatings of Zinc on Iron and Steel |
| ASTM D4674 REV A | (2002; R 2010) Standard Practice for Accelerated Testing for Color Stability of Plastics Exposed to Indoor Office Environments |

EUROPEAN UNION (EU)

- | | |
|----------------------|------------------------------------------------------------------------------------------------------|
| Directive 2011/65/EU | (2011) Restriction of the Use of Certain Hazardous Substances in Electrical and Electronic Equipment |
|----------------------|------------------------------------------------------------------------------------------------------|

ILLUMINATING ENGINEERING SOCIETY (IES)

- | | |
|-----------|---------------------------------------------------------------------------------|
| IES HB-10 | (2011; Errata 2015) IES Lighting Handbook |
| IES LM-79 | (2008) Electrical and Photometric Measurements of Solid-State Lighting Products |

- IES LM-80 (2019) Measuring Lumen Maintenance of LED Light Sources
- IES RP-16 (2017) Nomenclature and Definitions for Illuminating Engineering
- IES TM-15 (2011) Luminaire Classification System for Outdoor Luminaires
- IES TM-21 (2019) Projecting Long Term Lumen Maintenance of LED Light Sources
- IES TM-30 (2018) IES Method for Evaluating Light Source Color Rendition

INSTITUTE OF ELECTRICAL AND ELECTRONICS ENGINEERS (IEEE)

- IEEE 100 (2000; Archived) The Authoritative Dictionary of IEEE Standards Terms
- IEEE C2 (2017; Errata 1-2 2017; INT 1 2017) National Electrical Safety Code
- IEEE C62.41 (1991; R 1995) Recommended Practice on Surge Voltages in Low-Voltage AC Power Circuits

NATIONAL ELECTRICAL MANUFACTURERS ASSOCIATION (NEMA)

- NEMA 77 (2017) Temporal Light Artifacts: Test Methods and Guidance for Acceptance Criteria
- NEMA 250 (2018) Enclosures for Electrical Equipment (1000 Volts Maximum)
- NEMA ANSLG C78.377 (2017) Electric Lamps- Specifications for the Chromaticity of Solid State Lighting Products
- NEMA C82.77-10 (2020) Harmonic Emission Limits - Related Power Quality Requirements
- NEMA ICS 2 (2000; R 2005; Errata 2008) Industrial Control and Systems Controllers, Contactors, and Overload Relays Rated 600 V
- NEMA ICS 6 (1993; R 2016) Industrial Control and Systems: Enclosures
- NEMA SSL 1 (2016) Electronic Drivers for LED Devices, Arrays, or Systems
- NEMA SSL 3 (2011) High-Power White LED Binning for General Illumination
- NEMA SSL 7A (2015) Phase-Cut Dimming for Solid State Lighting: Basic Compatibility

NEMA WD 1 (1999; R 2015) Standard for General Color Requirements for Wiring Devices

NEMA WD 7 (2011; R 2016) Occupancy Motion Sensors Standard

NATIONAL FIRE PROTECTION ASSOCIATION (NFPA)

NFPA 70 (2020; ERTA 20-1 2020; ERTA 20-2 2020; TIA 20-1; TIA 20-2; TIA 20-3; TIA 20-4) National Electrical Code

NFPA 101 (2021) Life Safety Code

U.S. NATIONAL ARCHIVES AND RECORDS ADMINISTRATION (NARA)

47 CFR 15 Radio Frequency Devices

UNDERWRITERS LABORATORIES (UL)

UL 20 (2010; Reprint Feb 2012) General-Use Snap Switches

UL 94 (2013; Reprint Jun 2020) UL Standard for Safety Tests for Flammability of Plastic Materials for Parts in Devices and Appliances

UL 508 (2018) UL Standard for Safety Industrial Control Equipment

UL 844 (2012; Reprint Jul 2020) UL Standard for Safety Luminaires for Use in Hazardous (Classified) Locations

UL 916 (2015) Standard for Energy Management Equipment

UL 924 (2016; Reprint May 2020) UL Standard for Safety Emergency Lighting and Power Equipment

UL 1472 (2015) UL Standard for Safety Solid-State Dimming Controls

UL 1598 (2008; Reprint Oct 2012) Luminaires

UL 1598C (2014) Standard for Light-Emitting Diode (LED) Retrofit Luminaire Conversion Kits

UL 2043 (2013) Fire Test for Heat and Visible Smoke Release for Discrete Products and Their Accessories Installed in Air-Handling Spaces

UL 8750 (2015; Reprint Sep 2020) UL Standard for Safety Light Emitting Diode (LED) Equipment for Use in Lighting Products

1.2 RELATED REQUIREMENTS

Materials not considered to be luminaires, luminaire accessories, or lighting equipment are specified in Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM. Luminaires and accessories that are mounted in exterior environments and not attached to the exterior of the building are specified in Section 26 56 00 EXTERIOR LIGHTING. Cybersecurity requirements are specified in Section 25 05 11. CYBERSECURITY FOR FACILITY-RELATED CONTROL SYSTEMS. Commissioning requirements for Army and Air Force projects are specified in Section 01 91 00.15 10 TOTAL BUILDING COMMISSIONING. Commissioning requirements for Navy projects are specified in Section 01 91 00.15 TOTAL BUILDING COMMISSIONING. Emergency lighting requirements are specified in Section 26 52 00.00 40 EMERGENCY LIGHTING.

1.3 DEFINITIONS

- a. Unless otherwise specified or indicated, electrical and electronics terms used in these specifications and on the drawings, must be as defined in IEEE 100 and IES RP-16.
- b. For LED luminaire light sources, "Useful Life" is the operating hours before reaching 70 percent of the initial rated lumen output (L70) with no catastrophic failures under normal operating conditions. This is also known as 70 percent "Rated Lumen Maintenance Life" as defined in IES LM-80.
- c. For LED luminaires, "Luminaire Efficacy" (LE) is the appropriate measure of energy efficiency, measured in lumens/watt. This is gathered from LM-79 data for the luminaire, in which absolute photometry is used to measure the lumen output of the luminaire as one entity, not the source separately and then the source and housing together.
- d. Total harmonic distortion (THD) is the root mean square (RMS) of all the harmonic components divided by the total fundamental current.

1.4 SUBMITTALS

Government approval is required for submittals with a "G" designation; submittals not having a "G" designation are for Contractor Quality Control approval. Submittals with an "S" are for inclusion in the Sustainability eNotebook, in conformance with Section 01 33 29 SUSTAINABILITY REPORTING. Submit the following in accordance with Section 01 33 00 SUBMITTAL PROCEDURES:

SD-02 Shop Drawings

Luminaire Drawings; G

Occupancy/Vacancy Sensor Coverage Layout; G; S

Lighting Control System One-Line Diagram; G

Sequence of Operation for Lighting Control System; G

SD-03 Product Data

Luminaires; G

Light Sources; G

LED Drivers; G

Luminaire Warranty; G

Lighting Controls Warranty; G

Local Area Controller; G

Lighting Relay Panel; G

Lighting Contactor; G

Switches; G

Wall Box Dimmers; G

Occupancy/Vacancy Sensors; G

Photosensors; G

Power Packs; G

Exit Signs; G

Emergency Drivers; G

SD-05 Design Data

Luminaire Design Data; G

SD-06 Test Reports

IES LM-79 Test Report; G

IES LM-80 Test Report; G

IES TM-21 Test Report; G

IES TM-30 Test Report; G

Occupancy/Vacancy Sensor Verification Test; G

Photosensor Verification Test; G

SD-07 Certificates

LED Driver and Dimming Switch Compatibility Certificate; G

SD-10 Operation and Maintenance Data

Lighting System, Data Package 5; G

Lighting Control System, Data Package 5; G

Maintenance Staff Training Plan; G

End-User Training Plan; G

1.5 QUALITY ASSURANCE

Data, drawings, and reports must employ the terminology, classifications and methods prescribed by the IES HB-10 as applicable, for the lighting system specified.

1.5.1 Luminaire Drawings

Include dimensions, accessories installation details, and construction details. Photometric data, including CRI, CCT, LED driver type, zonal lumen data, and candlepower distribution data must accompany shop drawings.

1.5.2 Luminaire Design Data

- a. Provide safety certification and file number for the luminaire family that must be listed, labeled, or identified in accordance with the NFPA 70. Applicable testing bodies are determined by the US Occupational Safety Health Administration (OSHA) as Nationally Recognized Testing Laboratories (NRTL) and include: CSA (Canadian Standards Association), ETL (Edison Testing Laboratory), and UL (Underwriters Laboratories).
- b. Provide long term lumen maintenance projections for each LED luminaire in accordance with IES TM-21. Data used for projections must be obtained from testing in accordance with IES LM-80.

1.5.3 IES LM-79 Test Report

Submit test report on manufacturer's standard production model of specified luminaire. Testing must be performed at the same operating drive current as specified luminaire. Include all applicable and required data in IES format as outlined under "14.0 Test Report" in IES LM-79.

1.5.4 IES LM-80 Test Report

Submit report on manufacturer's standard production LED light source (package, array, or module) of specified luminaire. Testing must be performed at the same operating drive current as specified luminaire. Include all applicable and required data as outlined under "8.0 Test Report" in IES LM-80.

1.5.5 IES TM-21 Test Report

Submit test report on manufacturer's standard production LED light source

(package, array, or module) of specified luminaire. Testing must be performed at the same operating drive current as specified luminaire. Include all applicable and required data, as well as required interpolation information as outlined under "7.0 Report" in IES TM-21.

1.5.6 IES TM-30 Test Report

Submit color vector graphic in accordance with IES TM-30 on manufacturer's standard production LED light source (package, array, or module) of specified luminaire. Include spectral distribution of test LED light source.

1.5.7 LED Driver and Dimming Switch Compatibility Certificate

Submit certification from the luminaire, driver, or dimmer switch manufacturer that ensures compatibility and operability between devices without flickering and to specified dimming levels.

1.5.8 Occupancy/Vacancy Sensor Coverage Layout

Provide floor plans showing coverage layouts of all devices using manufacturer's product information.

1.5.9 Test Laboratories

Test laboratories for the IES LM-79 and IES LM-80 test reports must be one of the following:

- a. National Voluntary Laboratory Accreditation Program (NVLAP) accredited for solid-state lighting testing as part of the Energy-Efficient Lighting Products laboratory accreditation program for both LM-79 and LM-80 testing.
- b. One of the qualified labs listed on the Department of Energy - LED Lighting Facts Approved Testing Laboratories List for LM-79 testing.
- c. One of the EPA-Recognized Laboratories listed for LM-80 testing.

1.5.10 Regulatory Requirements

Equipment, materials, installation, and workmanship must be in accordance with the mandatory and advisory provisions of NFPA 70, unless more stringent requirements are specified or indicated. Provide luminaires and assembled components that are approved by and bear the label of UL for the applicable location and conditions unless otherwise specified.

1.5.11 Standard Products

Provide materials and equipment that are products of manufacturers regularly engaged in the production of such products which are of equal material, design, and workmanship. Products must have been in satisfactory commercial or industrial use for six months prior to bid opening. The six-month period must include applications of equipment and materials under similar circumstances and of similar size. The product must have been on sale on the commercial market through advertisements, manufacturers' catalogs, or brochures during the six-month period. Where two or more items of the same class of equipment are required, these items must be products of a single manufacturer; however, the component parts of the item need not be the products of the same manufacturer unless stated

in this section.

1.5.11.1 Alternative Qualifications

Products having less than a six-month field service record will be acceptable if a certified record of satisfactory field operation for not less than 6000 hours, exclusive of the manufacturers' factory or laboratory tests, is furnished.

1.5.11.2 Material and Equipment Manufacturing Date

Do not use products manufactured more than six months prior to date of delivery to site, unless specified otherwise.

1.6 WARRANTY

Support all equipment items by service organizations which are reasonably convenient to the equipment installation in order to render satisfactory service to the equipment on a regular and emergency basis during the warranty period of the contract.

1.6.1 Luminaire Warranty

Provide and transfer to the government the original LED luminaire manufacturers standard commercial warranty for each different luminaire manufacturer used in the project.

- a. Provide a written five year minimum replacement warranty for material, luminaire finish, and workmanship. Provide written warranty document that contains all warranty processing information needed, including customer service point of contact, whether or not a return authorization number is required, return shipping information, and closest return location to the luminaire location.
 - (1) Finish warranty must include failure and substantial deterioration such as blistering, cracking, peeling, chalking, or fading.
 - (2) Material warranty must include:
 - (a) All LED drivers and integral control equipment.
 - (b) Replacement when more than 10 percent of LED sources in any lightbar or subassembly(s) are defective, non-starting, or operating below 70 percent of specified lumen output.
- b. Warranty period must begin in accordance with the manufacturer's standard warranty starting date.
- c. Provide replacements that are promptly shipped, without charge, to the using Government facility point of contact and that are identical to or an improvement upon the original equipment. All replacements must include testing of new components and assembly.

1.6.2 Lighting Controls Warranty

Provide and transfer to the government the original lighting controls manufacturers standard commercial warranty for each different lighting controls manufacturer used in the project. Warranty coverage must begin from date of final system commissioning or three months from date of

delivery, whichever is the earliest. Warranty service must be performed by a factory-trained engineer or technician.

- a. Unless otherwise noted, provide a written five year minimum warranty on the complete system for all systems with factory commissioning. Provide warranty that covers 100 percent of the cost of any replacement parts and services required over the five years which are directly attributable to the product failure. Failures include, but are not limited to, the following:
 - (1) Software: Failure of input/output to execute switching or dimming commands.
 - (2) Damage of electronic components due to transient voltage surges.
 - (3) Failure of control devices, including but not limited to occupancy sensors, photosensors, and manual wall station control devices.
- b. Provide a written five year minimum warranty on all input devices against defect in workmanship or materials provided by device manufacturer.
- c. Provide a written five year minimum warranty on all control components attached to luminaires against defect in workmanship or materials.

1.7 OPERATION AND MAINTENANCE MANUALS

1.7.1 Lighting System

Provide operation and maintenance manuals for the lighting system in accordance with Section 01 78 23 OPERATION AND MAINTENANCE DATA that provide basic data relating to the design, operation, and maintenance of the lighting system for the building. Additional O&M Manual requirements for the Army are provided in Section 01 78 24.00 10 FACILITY DATA REQUIREMENTS. Additional requirements for the Navy are provided in Section 01 78 24.00 20 FACILITY ELECTRONIC OPERATION AND MAINTENANCE SUPPORT INFORMATION (eOMSI). Include the following:

- a. Manufacturers' operating and maintenance manuals.
- b. Luminaire shop drawings for modified and custom luminaires.
- c. Luminaire Manufacturers' standard commercial warranty information as specified in paragraph LUMINAIRE WARRANTY.

1.7.2 Lighting Control System

Provide operation and maintenance manuals for the lighting control system in accordance with Section 01 78 23 OPERATION AND MAINTENANCE DATA that provide basic data relating to the design, operation, and maintenance of the lighting control system for the building. Include the following:

- a. Lighting control system layout and wiring plan.
- b. Lighting control system one-line diagram.
- c. Product data for all devices, including installation and programming instructions.

- d. Occupancy/vacancy sensor coverage layout.
- e. Training materials, such as videos or in-depth manuals, that cover basic operation of the lighting control system and instructions on modifying the lighting control system. Training materials must include calibration, adjustment, troubleshooting, maintenance, repair, and replacement.
- f. Sequence of operation descriptions for each typical room type, including final programming, schedules, and calibration settings.

PART 2 PRODUCTS

2.1 PRODUCT COORDINATION

2.2 LUMINAIRES

UL 1598, NEMA C82.77-10. Provide luminaires as indicated in the luminaire schedule and NL plates or details on project plans, complete with light source, wattage, and lumen output indicated. All luminaires of the same type must be provided by the same manufacturer. Luminaires must be specifically designed for use with the driver and light source provided.

2.2.1 Luminaires

UL 8750, IES LM-79, IES LM-80. For all luminaires, provide:

- a. Complete system with LED drivers and light sources.
- b. Housings constructed of non-corrosive materials. All new aluminum housings must be anodized or powder-coated. All new steel housings must be treated to be corrosion resistant.
- c. IES TM-21, IES LM-80. Minimum L70 lumen maintenance value of 50,000 hours unless otherwise indicated in the luminaire schedule. Luminaire drive current value must be identical to that provided by test data for luminaire in question.
- d. Minimum efficacy as specified in the luminaire schedule. Theoretical models of initial lamp lumens per watt are not acceptable. If efficacy values are not listed in the luminaire schedule, provide luminaires that meet the following minimum values:

Luminaire Style	Minimum Luminaire Efficacy
Recessed 1 by 4, 2 by 4, and 2 by 2	100 LPW
Recessed Downlight (fixed, adjustable, wallwash)	80 LPW
Linear, Accent (undercabinet, cove)	45 LPW
Linear, Ambient (indirect wall mount, linear pendent)	100 LPW
High Bay, Low Bay, and Industrial Locations	100 LPW

Luminaire Style	Minimum Luminaire Efficacy
Food Service and Hazardous Locations	60 LPW
Other (track, residential diffusers)	50 LPW
Exterior Wall Sconce	50 LPW
Steplight	30 LPW
Parking Garage Luminaire	100 LPW

- e. UL listed for dry or damp location typical of interior installations. Any luminaire mounted on the exterior of the building must be UL listed for wet location typical of exterior installations.
- f. LED driver and light source package, array, or module are accessible for service or replacement without removal or destruction of luminaire.
- g. Lenses constructed of heat tempered borosilicate glass, UV-resistant acrylic, or silicone. Provide polycarbonate vandal-resistant lenses as indicated. Sandblasting, etching and polishing must be performed as indicated in the luminaire description.
- h. **IES TM-15**. Provide exterior building-mounted luminaires that do not exceed the BUG ratings as listed in the luminaire schedule. If BUG ratings are not listed in the luminaire schedule, provide luminaires that meet the following minimum values for each application and mounting conditions:

Lighting Application	Mounting Conditions	BUG Rating
Exterior Wall Sconce	Above 4 feet AFF	B1-U0-G2
Exterior Wall Sconce	Below or at 4 feet AFF	B4-U0-G4
Steplight	Above 4 feet AFF	B1-U1-G2
Steplight	Below or at 4 feet AFF	B4-U1-G4
Parking Garage Luminaire	Ceiling mounted	B4-U4-G3

2.2.1.1 Luminaire Conversion Kits

Provide luminaire conversion kits that meet **UL 1598C** Standard for Light-Emitting Diode (LED) Retrofit Luminaire Conversion Kits.

2.2.2 Luminaires for Hazardous Locations

In addition to requirements stated herein, provide LED luminaires for hazardous locations which conform to **UL 844** or which have Factory Mutual certification for the class and division indicated.

2.3 LIGHT SOURCES

NEMA ANSLG C78.377, NEMA SSL 3. Provide type, delivered lumen output, and wattage as indicated in the luminaire schedule on project plans.

2.3.1 LED Light Sources

Provide LED light sources that meet the following requirements:

- a. **NEMA ANSLG C78.377.** Emit white light and have a nominal CCT of 4000 Kelvin.
- b. Minimum Color Rendering Index (CRI) of 90.
- c. **Directive 2011/65/EU.** Restriction of Hazardous Substances (RoHS) compliant.
- d. Light source color consistency by utilizing a binning tolerance within a 3-step McAdam ellipse.

2.4 LED DRIVERS

NEMA SSL 1, UL 8750. Provide LED drivers that are electronic, UL Class 1 or Class 2, constant-current type and that comply with the following requirements:

- a. The combined driver and LED light source system does not exceed the minimum luminaire efficacy values as listed in the luminaire schedule provided.
- b. Operates at a voltage of 120-277 volts at 50/60 hertz, with input voltage fluctuations of plus/minus 10 percent.
- c. Power Factor (PF) greater than or equal to 0.90 at full input power and across specified dimming range.
- d. Maximum Total Harmonic Distortion (THD) less than 20 percent at full input power and across specified dimming range.
- e. Operates for at least 50,000 hours at maximum case temperature and 90 percent non-condensing relative humidity.
- f. Withstands Category A surges of 4 kV without impairment of performance. Provide surge protection that is integral to the driver.
- g. Integral thermal protection that reduces the output power to protect the driver and light source from damage if the case temperature approaches or exceeds the driver's maximum operating temperature.
- h. **47 CFR 15.** Complies with the requirements of the Federal Communications Commission (FCC) rules and regulations, Non-Consumer (Class A) for EMI/RFI (conducted and radiated).
- i. Class A sound rating.
- j. **Directive 2011/65/EU.** Restriction of Hazardous Substances (RoHS) compliant.
- k. Provide dimming capability as indicated in the luminaire schedule on

project plans. Dimmable drivers must dim down to 1 percent. Dimmable drivers must be controlled by a Class 2 low voltage 0-10VDC controller dimming signal protocol unless otherwise specified. LED drivers of the same family/series must track evenly across multiple luminaires at all light levels.

2.5 LIGHTING CONTROLS

Provide network certification for all networked lighting control systems and devices in accordance with the requirements of Section 25 05 11. CYBERSECURITY FOR FACILITY-RELATED CONTROL SYSTEMS. Provide lighting control systems that do not switch off battery-operated or emergency backup luminaires or exit signs in path of egress. Provide system with override of lighting control devices controlling luminaires in path of egress with activation of fire alarm system.

2.5.1 System

Provide lighting control system that operates the lighting system as described in the lighting control strategies in the project plans. Submit [Sequence of Operation for Lighting Control System](#) describing the operation of the proposed lighting control system and devices. Sequence of Operation must provide the strategies identified in the lighting control strategies.

2.5.1.1 Localized Control Systems

Provide room or area-wide lighting control system capable of manual control, time-based control, and receiving input from photosensors and occupancy/vacancy sensors.

2.5.1.1.1 Local Area Controller

Provide controller designed for single area or room with the following requirements:

- a. Operates at a voltage of 120-277 volts at 50/60 hertz.
- b. 2 zone, with 1 relay rated 20 amps with one manual switchdimmer per zone.
- c. Provide inputs for occupancy/vacancy sensors, photosensors, and low-voltage wall switches.
- d. Capable of 0-10V dimming.
- e. Provide override 'ON' function with input from Fire Alarm Control Panel for all emergency lighting. Controller must not turn off power to emergency batteries or exit signs.

2.5.1.2 Centralized Control Systems

Provide a centralized lighting control system capable of manual control, time-based control, receiving input from photosensors and occupancy/vacancy sensors, with the capabilities of controlling, monitoring, and programming changes from one centralized on-site location, and integration with other building systems.

2.5.1.2.1 Lighting Relay Panel

UL 924. Enclose panel hardware in a surface-mounted, NEMA 1, painted, steel enclosure with lockable access door and ventilation openings. Internal low-voltage compartment must be separated from line-voltage compartment of enclosure with only low-voltage compartment accessible upon opening of door. Provide additional remote cabinets that communicate back to main control panel as required. Provide Lighting Control Panels that meet the following criteria:

- a. Input voltage of 120-277 at 50/60 Hz, with internal low voltage power supply as required.
- b. 16 single-pole latching relays rated at 20 amps, 120-277 volts. Provide provision for relays to close upon power failure. Provide relays designed for 10 years of use at full rated load.
- c. Relay control module operates at 24 VDC and is rated to control a minimum of 16 relays.

2.5.1.2.2 Lighting Contactor

NEMA ICS 2, NEMA ICS 6. Provide an electrically-held lighting contactor housed in a NEMA 1 or 4X enclosure, as indicated on plans. Provide contactor with one normally-open(NO), single double pole contacts, rated 600 volts, 30 amps. Provide coil operating voltage of 277 volts.

2.5.2 Devices

2.5.2.1 Switches

Provide line-voltage toggle switches as specified in Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM. When used for non-digital loads, devices must be rated at 20 Amps inductive load, and be compatible with the lighting control systems.

2.5.2.2 Wall Box Dimmers

UL 1472, UL 20, IEEE C62.41, NEMA 77, NEMA SSL 7A. Dimmers must provide flicker-free, continuously variable light output throughout the dimming range of 1 percent to 100 percent. Devices must be capable of operating at their full rated capacity regardless of being single or ganged-mounted, and be compatible with three-way and four-way switching scenarios.

Provide wall-box dimmers that meet the following requirements:

- a. Device operates as an independent control device.
- b. Device operates with the use of a vertical slider, paddle, rotary, button, or toggle with adjacent vertical slider.
- c. Finish of device matches switches and outlets in the same area.
- d. Back box in wall has sufficient depth to accommodate body of switch and wiring.
- e. Dimmer is capable of controlling 0-10 volt LED drivers. Dimmers and the drivers they control must be provided from the same manufacturer or tested and certified as compatible for use together.

f. Radio frequency interference suppression is integral to device.

2.5.2.3 Occupancy/Vacancy Sensors

IEEE C62.41, NEMA WD 1, UL 94, UL 916, UL 508, ASTM D4674 REV A, NEMA WD 7. Provide occupancy/vacancy sensors with coverage patterns as indicated on project plans. Provide no less quantity of sensors as shown on plans, but add additional sensors when required to fulfill coverage requirement for the specific model of sensor provided. Provide occupancy sensor operation that requires movement to activate luminaires controlled and turns luminaires off after a set time of inactivity. Provide ceiling or wall-mounted occupancy/vacancy sensors that meet the following requirements:

- a. Operating voltage of 12-24 volts.
- b. Time delay of 30 seconds to 30 minutes with at least four intermediate time delay settings.
- c. Sensors are ceiling mounted.
- d. Does not exceed a maximum load requirement of 20mA at 24VDC.
- e. Shielded or controlled by internal logic to adjust sensitivity to avoid false triggering due to ambient temperature, air temperature variations or HVAC air movement.
- f. Sensor is equipped to automatically energize the connected load upon loss of normal power when located in a means of egress.
- g. Occupancy and vacancy operation is field-adjustable and programmable with push-button or dip switch on the sensor device.
- h. No leakage current to load when in the off mode.
- i. Utilize zero-crossing circuitry to prevent damage from high inrush current and to promote long life operation.
- j. Allow the adding or deleting of specific luminaires or zones to the assigned sensor without the use of ladders.
- k. Provide an isolated relay for integrating control of HVAC or other automated systems.

2.5.2.3.1 Passive Infrared Sensors

Provide Passive Infrared Sensors (PIR) sensors that detect occupancy by sensing heat and movement in the area of coverage. Provide sensors are constructed of a housing of high-impact, injection-molded thermoplastic. Provide PIR sensors that are temperature compensated, with a dual element sensor and a multi-element fresnel lens of POLY IR4 material.

2.5.2.3.2 Ultrasonic Sensors

Provide ultrasonic sensors that detect occupancy by sensing a change in pattern of reflected ultrasonic waves in the area of coverage. Provide sensors that are constructed of a housing of high-impact, injection-molded thermoplastic. Provide ultrasonic sensors that operate at 40 kHz.

2.5.2.3.3 Dual Technology Sensors

Provide dual technology sensors that meet the requirements for PIR sensors and ultrasonic sensors indicated above. If either the PIR or ultrasonic sensing registers occupancy, the luminaires must remain on.

2.5.2.3.4 High Bay Sensors

Provide occupancy/vacancy sensors specifically designed for high-bay mounting applications for all ceiling-mounted sensors mounted above 35 feet using PIR technology. Provide high-bay sensors with interchangeable lenses for 360 degree open area coverage or narrow rectangular warehouse aisle coverage.

2.5.2.3.5 Power Packs

UL 2043. Provide power packs to provide power to lighting control sensors as required in accordance with the manufacturer's specifications. Provide power packs that meet the following requirements:

- a. Operate at an input voltage of 120-277 VAC, with an output voltage 12-24 VDC at 225 mA.
- b. Constructed of plenum-rated, high-impact thermoplastic enclosure.
- c. Utilizes zero-crossing circuitry to prevent damage from inrush current.
- d. Maximum load rating of 16 amps for electronic lighting loads.
- e. Directive 2011/65/EU. Restriction of Hazardous Substances (RoHS) compliant.

2.5.2.4 Photosensors

Provide photosensors that meet the following requirements:

- a. Detect changes in ambient lighting level and enable dimming as required by sequence of operation by operating in an open-loop system.
- b. Contain a detection cone, where the base of the cone may be circular or an elongated shape, and where the smallest angle between the edge and the axis of the cone is between 20 and 50 degrees. The cone axis may be tilted to the vertical when installed to give the sensor preferred directionality.
- c. Sensors are ceiling-mounted with sensitivity, filtering, range and viewing angle to meet requirements of sequence of operation, scope of work and construction documents.
- d. Time delay that is adjustable from 1 to 30 seconds ON delay, and 1 to 30 minutes OFF delay to prevent cycling, with deadband adjustment of 25 percent to 100 percent above lower setpoint.
- e. Output dimming signal is linear to light level with less than 1 percent variation. Cadmium sulfide photo-resistors are not acceptable.
- f. Sensor is not combined in the same housing or location with occupancy or vacancy sensors if the proper location for one function compromises

the successful operation of the other function, or in any way reduces the system's ability to meet the design intent.

2.6 EXIT AND EMERGENCY LIGHTING EQUIPMENT

2.6.1 Exit Signs

UL 924, NFPA 101. Provide wattage as indicated in the luminaire schedule on project plans. Provide LED Exit Signs that meet the following criteria:

- a. Housing constructed of clear polycarbonate housing.
- b. UL listed for damp location.
- c. Configured for universal mounting.
- d. 6 inch high, 3/4 inch stroke red lettering on face of sign with chevrons on either side of lettering to indicate direction.
- e. Single or double face as indicated in project plans and luminaire schedule.

2.6.1.1 Exit Signs with Battery Backup

Equip with automatic power failure device, test switch, and pilot light, and fully automatic high/low trickle charger in a self-contained power pack. Battery must be sealed, maintenance free nickel-cadmium type, and must operate unattended for a period of not less than five years. Emergency run time must be a minimum of 1-1/2 hours. LEDs must have a minimum rated life of 10 years. Provide self-diagnostic circuitry integral to emergency LED driver.

2.6.2 Emergency Lighting Unit (ELU)

UL 924, NFPA 101. Provide emergency lighting units (ELUs) completely assembled with wiring and mounting devices, ready for installation at the locations indicated. Provide in UV-stable, thermo-plastic housing with UL damp label as indicated. Emergency lighting units must be rated for 12 volts, except units having no remote-mounted light sources and having no more than two unit-mounted light sources may be rated six volts. Equip units with brown-out sensitive circuit to activate battery when input voltage falls to 75 percent of normal. Equip with two LED light sources, automatic power failure device, test switch, and pilot light, and fully automatic high/low trickle charger in a self-contained power pack. Battery must be sealed, maintenance free lead-calcium type, and must operate unattended for a period of not less than five years. Emergency run time must be a minimum of 90 minutes. LEDs must have a minimum rated life of 10 years. Provide self-diagnostic circuitry integral to emergency LED driver.

2.6.3 LED Emergency Drivers

UL 924, NFPA 101. Provide LED emergency driver with automatic power failure detection, test switch and LED indicator (or combination switch/indicator) located on luminaire exterior, and fully-automatic solid-state charger, battery and inverter integral to a self-contained housing. Provide self-diagnostic function integral to emergency driver. Integral nickel-cadmium/lead-calcium battery is required to supply a minimum of 90 minutes of emergency power at 10 watts, 10-50 VDC compatible

with LED forward voltage requirements, constant output. Driver must be RoHS compliant, rated for installation in plenum-rated spaces and damp locations, and be warranted for a minimum of five years.

2.6.4 Self-Diagnostic Circuitry for LED Drivers

UL 924, NFPA 101. Provide emergency lighting unit with fully-automatic, integral self-testing/diagnostic electronic circuitry. Circuitry must provide for a one minute diagnostic test every 28 days, and a 30 minute diagnostic test every six months, minimum. Any malfunction of the unit must be indicated by LED(s) visible from the exterior of the luminaire. A manual test switch must also be provided to perform a diagnostic test at any given time.

2.7 LUMINAIRE MOUNTING ACCESSORIES

2.7.1 Suspended Luminaires

- a. Provide hangers capable of supporting twice the combined weight of luminaires supported by hangers.
- b. Hangers must allow luminaires to swing within an angle of 45 degrees. Brace pendants 4 feet or longer to limit swinging. Provide with swivel hangers to ensure a plumb installation for rigid stem pendants. Provide cadmium-plated steel with a swivel-ball tapped for the conduit size indicated.
- c. Single-unit suspended luminaires must have cable hangers. Multiple-unit or continuous row luminaires with a separate power supply cord must have a tubing or stem for wiring at one point and a tubing or rod suspension provided for each unit length of chassis, including one at each end.
- d. Provide all linear pendent and surface mounted luminaires with two supports per four-foot section or three per eight-foot section unless otherwise recommended by manufacturer.
- e. Provide rods in minimum 0.18 inch diameter.

2.7.2 Recess and Surface Mounted Luminaires

Provide access to light source and LED driver from bottom of luminaire. Provide trim and lenses for the exposed surface of flush-mounted luminaires as indicated on project drawings and specifications. Luminaires recessed in ceilings which have a fire resistive rating of one hour or more must be enclosed in a box which has a fire resistive rating equal to that of the ceiling. For surface mounted luminaires with brackets, provide flanged metal stem attached to outlet box, with threaded end suitable for supporting the luminaire rigidly in design position. Flanged part of luminaire stud must be of broad base type, secured to outlet box at not fewer than three points.

2.7.3 Luminaire Support Hardware

2.7.3.1 Wire

ASTM A641/A641M. Galvanized, soft tempered steel, minimum 0.11 inches in diameter, or galvanized, braided steel, minimum 0.08 inches in diameter.

2.7.3.2 Wire for Humid Spaces

ASTM A580/A580M. Composition 302 or 304, annealed stainless steel, minimum 0.11 inches in diameter.

ASTM B164. UNS NO4400, annealed nickel-copper alloy, minimum 0.11 inches in diameter.

2.7.3.3 Threaded Rods

Threaded steel rods, 3/16 inch diameter, zinc or cadmium coated.

2.7.3.4 Straps

Galvanized steel, one by 3/16 inch, conforming to **ASTM A653/A653M**, with a light commercial zinc coating or **ASTM A1008/A1008M** with an electrodeposited zinc coating conforming to **ASTM B633**, Type RS.

2.7.4 Power Hook Luminaire Hangers

UL 1598. Provide an assembly consisting of through-wired power hook housing, interlocking plug and receptacle, power cord, and luminaire support loop. Power hook housing must be cast aluminum having two 3/4 inch threaded hubs. Support hook must have safety screw. Luminaire support loop must be cast aluminum with provisions for accepting 3/4 inch threaded stems. Power cord must include 16 inches of 3 conductor No. 16 Type SO cord. Assembly must be rated 120 volts or 277 volts, 15 amperes.

2.8 EQUIPMENT IDENTIFICATION

2.8.1 Manufacturer's Nameplate

Each item of equipment must have a nameplate bearing the manufacturer's name, address, model number, and serial number securely affixed in a conspicuous place; the nameplate of the distributing agent will not be acceptable.

2.8.2 Labels

UL 1598. All luminaires must be clearly marked for operation of specific light sources and LED drivers. The labels must be easy to read when standing next to the equipment, and durable to match the life of the equipment to which they are attached. Note the following light source characteristics in the format "Use Only _____":

- a. Correlated Color Temperature (CCT) and Color Rendering Index (CRI) for all luminaires.
- b. Driver and dimming protocol.

All markings related to light source type must be clear and located to be readily visible to service personnel, but unseen from normal viewing angles when light sources are in place. LED drivers must have clear markings indicating dimming type and indicate proper terminals for the various outputs.

2.9 FACTORY APPLIED FINISH

NEMA 250. Provide all luminaires and lighting equipment with

factory-applied painting system that as a minimum, meets requirements of corrosion-resistance testing.

PART 3 EXECUTION

3.1 INSTALLATION

IEEE C2, NFPA 70.

3.1.1 Light Sources

When light sources are not provided as an integral part of the luminaire, deliver light sources of the type, wattage, lumen output, color temperature (CCT), color rendering index (CRI), and voltage rating indicated to the project site and install just prior to project completion, if not already installed in the luminaires from the factory.

3.1.2 Luminaires

Set luminaires plumb, square, and level with ceiling and walls, in alignment with adjacent luminaires and secure in accordance with manufacturers' directions and approved drawings. Provide accessories as required for ceiling construction type indicated on Finish Schedule. Luminaire catalog numbers do not necessarily denote specific mounting accessories for type of ceiling in which a luminaire may be installed. Provide wires, straps, or rods for luminaire support in this section. Install luminaires with vent holes free of air blocking obstacles.

3.1.2.1 Suspended Luminaires

Measure mounting heights from the bottom of the luminaire for ceiling-mounted luminaires and to center of luminaire for wall-mounted luminaires. Obtain architect approval of the exact mounting height on the job before commencing installation and, where applicable, after coordinating with the type, style, and pattern of the ceiling being installed. Support suspended luminaires from structural framework of ceiling or from inserts cast into slab.

- a. Provide suspended luminaires with 45 degree swivel hangers so that they hang plumb and level.
- b. Locate so that there are no obstructions within the 45 degree range in all directions.
- c. The stem, canopy and luminaire must be capable of 45 degree swing.
- d. Rigid pendent stem, aircraft cable, rods, or chains 4 feet or longer excluding luminaire must be braced to prevent swaying using three cables at 120 degree separation.
- e. Suspended luminaires in continuous rows must have internal wireway systems for end to end wiring and must be properly aligned to provide a straight and continuous row without bends, gaps, light leaks or filler pieces.
- f. Utilize aligning splines on extruded aluminum luminaires to assure minimal hairline joints.
- g. Support steel luminaires to prevent "oil-canning" effects.

- h. Match supporting pendants with supported luminaire. Aircraft cable must be stainless steel.
- i. Match finish of canopies to match the ceiling, and provide low profile canopies unless otherwise shown.
- j. Maximum distance between suspension points must be 10 feet or as recommended by the manufacturer, whichever is less.

3.1.2.2 Recessed and Semi-Recessed Luminaires

- a. Support recessed and semi-recessed luminaires independently from the building structure by a minimum of two wires, straps or rods per luminaire and located near opposite corners of the luminaire. Secure horizontal movement with clips provided by manufacturer. Ceiling grid clips are not allowed as an alternative to independently supported luminaires.
- b. Support round luminaires or luminaires smaller in size than the ceiling grid independently from the building structure by a minimum of four wires, straps or rods per luminaire, spaced approximately equidistant around.
- c. Do not support luminaires by acoustical tile ceiling panels.
- d. Where luminaires of sizes less than the ceiling grid are indicated to be centered in the acoustical panel, support each independently and provide at least two 3/4 inch metal channels spanning, and secured to, the ceiling tees for centering and aligning the luminaire.
- e. Luminaires installed in suspended ceilings must also comply with the requirements of Section 09 51 00 ACOUSTICAL CEILINGS.
- f. Adjust aperture rings on all applicable ceiling recessed luminaires to accommodate various ceiling material thickness. Coordinate cut-out size in ceiling to ensure aperture covers cut-out entirely. Install aperture rings such that the bottom of the ring is flush with finished ceiling or not more than 1/16 inch above. Do not install luminaires such that the aperture ring extends below the finished ceiling surface.

3.1.3 LED Drivers

Provide LED drivers integral to luminaire as constructed by the manufacturer.

3.1.4 Exit Signs

NFPA 101. Wire exit signs and emergency lighting units ahead of the local switch, to the normal lighting circuit located in the same room or area.

3.1.5 Lighting Controls

Refer to Section 25 05 11. CYBERSECURITY FOR FACILITY-RELATED CONTROL SYSTEMS for additional lighting control installation requirements.

3.1.5.1 Occupancy/Vacancy Sensors

- a. Provide quantity of sensor units indicated as a minimum. Provide

additional units to give full coverage over controlled area. Full coverage must provide hand and arm motion detection for office and administration type areas and walking motion for industrial areas, warehouses, storage rooms and hallways.

- b. Locate ceiling-mounted sensors no closer than 6 feet from the nearest HVAC supply or return diffuser.
- c. Locate the sensor(s) as indicated and in accordance with the manufacturer's recommendations.

3.1.5.2 Photosensors

Locate and aim sensor as indicated and in accordance with the manufacturer's recommendations. Adjust sensor set-point in accordance with the manufacturer's recommendations and for the indicated light level of the area of coverage, measured at the work plane.

3.2 FIELD QUALITY CONTROL

3.2.1 Tests

3.2.1.1 Lighting Control Verification Tests

Verify lighting control system and devices operate according to approved sequence of operations. Verification tests are to be completed after commissioning.

- a. Verify occupancy/vacancy sensors operate as described in sequence of operations. Provide testing of sensor coverage, sensitivity, and time-out settings in all spaces where sensors are placed. This is to be completed only after all furnishings have been installed. Submit [occupancy/vacancy sensor verification test](#).
- b. Verify photosensors operate as described in sequence of operations. Provide testing of sensor coverage, aiming, and calibration in all spaces where sensors are placed. This is to be completed only after all furnishings have been installed. Submit [photosensor verification test](#).
- c. Verify wall box dimmers and scene wallstations operate as described in sequence of operations.

3.2.1.2 Emergency Lighting Test

Interrupt power supply to demonstrate proper operation of emergency lighting. If adjustments are made to the lighting system, re-test system to show compliance with standards.

3.3 CLOSEOUT ACTIVITIES

3.3.1 Commissioning

[NFPA 101](#). Commission all components of the lighting system and lighting control system in accordance with Section 01 91 00.15 10 TOTAL BUILDING COMMISSIONING. Commission all components of the lighting system and lighting control system in accordance with Section 01 91 00.15 TOTAL BUILDING COMMISSIONING. Factory Trained Field Service Technician is responsible for calibration and programming sequences for input devices

and systems in accordance with the requirements described in the sequence of operation.

3.3.2 Training

3.3.2.1 Maintenance Staff Training

Submit a [Maintenance Staff Training Plan](#) at least 30 calendar days prior to training session that describes training procedures for Owner's personnel in the operation and maintenance of lighting and lighting control system. Provide on-site training which demonstrates full system functionality, assigning schedules, calibration adjustments for light levels and sensor sensitivity, integration procedures for connecting to third-party devices, and manual override including information on appropriate use. Provide protocols for troubleshooting, maintenance, repair, and replacement, and literature on available system updates and process for implementing updates.

3.3.2.2 End-User Training

Submit an [End-User Training Plan](#) at least 30 calendar days prior to training session that describes training procedures for end-users on the lighting control system. Provide users with a list of control devices located within user-occupied spaces, such as photosensors and occupancy and vacancy sensors, including information on the proper operation and schedule for each device. Provide demonstration for each type of interface. Provide users with the building schedule as currently commissioned, including conditional programming based on astronomic time clock functionality. Provide users with the correct contact information for maintenance personnel who will be available to address any lighting control issues.

Provide laminated instructions to the user at each scene wallstation. Provide only instructions relevant to the functionality of the specific scene wallstation. Provide a description of each labeled scene control button. If the room utilizes occupancy/vacancy sensors or photosensors, include a description of this functionality on the instruction sheet.

-- End of Section --

SECTION 26 56 00

EXTERIOR LIGHTING

05/20

PART 1 GENERAL

1.1 REFERENCES

The publications listed below form a part of this specification to the extent referenced. The publications are referred to within the text by the basic designation only.

AMERICAN ASSOCIATION OF STATE HIGHWAY AND TRANSPORTATION OFFICIALS (AASHTO)

AASHTO LTS (2013; Errata 2013) Standard Specifications for Structural Supports for Highway Signs, Luminaires and Traffic Signals

AMERICAN SOCIETY OF CIVIL ENGINEERS (ASCE)

ASCE 7-16 (2017; Errata 2018; Supp 1 2018) Minimum Design Loads and Associated Criteria for Buildings and Other Structures

ASTM INTERNATIONAL (ASTM)

ASTM A153/A153M (2016a) Standard Specification for Zinc Coating (Hot-Dip) on Iron and Steel Hardware

ASTM B108/B108M (2019) Standard Specification for Aluminum-Alloy Permanent Mold Castings

ASTM B117 (2019) Standard Practice for Operating Salt Spray (Fog) Apparatus

EUROPEAN UNION (EU)

Directive 2011/65/EU (2011) Restriction of the Use of Certain Hazardous Substances in Electrical and Electronic Equipment

ILLUMINATING ENGINEERING SOCIETY (IES)

IES HB-10 (2011; Errata 2015) IES Lighting Handbook

IES LM-79 (2008) Electrical and Photometric Measurements of Solid-State Lighting Products

IES LM-80 (2019) Measuring Lumen Maintenance of LED Light Sources

IES RP-8 (2018; Addenda 1 2020) Recommended Practice for Lighting Roadway and Parking Facilities

IES RP-16 (2017) Nomenclature and Definitions for Illuminating Engineering

IES TM-15 (2011) Luminaire Classification System for Outdoor Luminaires

IES TM-21 (2019) Projecting Long Term Lumen Maintenance of LED Light Sources

INSTITUTE OF ELECTRICAL AND ELECTRONICS ENGINEERS (IEEE)

IEEE 100 (2000; Archived) The Authoritative Dictionary of IEEE Standards Terms

IEEE C2 (2017; Errata 1-2 2017; INT 1 2017) National Electrical Safety Code

IEEE C62.41.2 (2002) Recommended Practice on Characterization of Surges in Low-Voltage (1000 V and Less) AC Power Circuits

NATIONAL ELECTRICAL MANUFACTURERS ASSOCIATION (NEMA)

ANSI C136.3 (2020) Roadway and Area Lighting Equipment - Luminaire Attachments

ANSI C136.13 (2014) Roadway and Area Lighting Equipment - Metal Brackets for Wood Poles

ANSI C136.21 (2014) American National Standard for Roadway and Area Lighting Equipment - Vertical Tenons Used with Post-Top-Mounted Luminaires

NEMA 250 (2018) Enclosures for Electrical Equipment (1000 Volts Maximum)

NEMA ANSLG C78.377 (2017) Electric Lamps- Specifications for the Chromaticity of Solid State Lighting Products

NEMA C82.77-10 (2020) Harmonic Emission Limits - Related Power Quality Requirements

NEMA C136.31 (2018) Roadway and Area Lighting Equipment - Luminaire Vibration

NEMA ICS 2 (2000; R 2005; Errata 2008) Industrial Control and Systems Controllers, Contactors, and Overload Relays Rated 600 V

NEMA SSL 1 (2016) Electronic Drivers for LED Devices, Arrays, or Systems

NEMA SSL 3 (2011) High-Power White LED Binning for General Illumination

NEMA WD 7 (2011; R 2016) Occupancy Motion Sensors

Standard

NATIONAL FIRE PROTECTION ASSOCIATION (NFPA)

NFPA 70 (2020; ERTA 20-1 2020; ERTA 20-2 2020; TIA 20-1; TIA 20-2; TIA 20-3; TIA 20-4)
National Electrical Code

UNDERWRITERS LABORATORIES (UL)

UL 773 (2016; Reprint Jul 2020) UL Standard for Safety Plug-In, Locking Type Photocontrols for Use with Area Lighting

UL 773A (2016; Reprint Jun 2020) UL Standard for Safety Nonindustrial Photoelectric Switches for Lighting Control

UL 924 (2016; Reprint May 2020) UL Standard for Safety Emergency Lighting and Power Equipment

UL 1310 (2018) UL Standard for Safety Class 2 Power Units

UL 1598 (2008; Reprint Oct 2012) Luminaires

UL 8750 (2015; Reprint Sep 2020) UL Standard for Safety Light Emitting Diode (LED) Equipment for Use in Lighting Products

1.2 RELATED REQUIREMENTS

Materials not considered to be luminaires, luminaire accessories, or lighting equipment are specified in Section(s) 33 71 02 UNDERGROUND ELECTRICAL DISTRIBUTION 33 71 01 OVERHEAD TRANSMISSION AND DISTRIBUTION. Luminaires and accessories installed in interior of buildings or attached to the exterior of a building are specified in Section 26 51 00 INTERIOR LIGHTING. Cybersecurity requirements are specified in Section 25 05 11. CYBERSECURITY FOR FACILITY-RELATED CONTROL SYSTEMS. Commissioning requirements for Navy projects are specified in Section 01 91 00.15 TOTAL BUILDING COMMISSIONING.

1.3 DEFINITIONS

- a. Unless otherwise specified or indicated, electrical and electronics terms used in these specifications and on the drawings must be as defined in IEEE 100 and IES RP-16.
- b. For LED luminaire light sources, "Useful Life" is the operating hours before reaching 70 percent of the initial rated lumen output (L70) with no catastrophic failures under normal operating conditions. This is also known as 70 percent "Rated Lumen Maintenance Life" as defined in IES LM-80.
- c. For LED luminaires, "Luminaire Efficacy" (LE) is the appropriate measure of energy efficiency, measured in lumens/watt. This is gathered from LM-79 data for the luminaire, in which absolute photometry is used to measure the lumen output of the luminaire as one

entity, not the source separately and then the source and housing together.

- d. Total Harmonic Distortion (THD) is the Root Mean Square (RMS) of all the harmonic components divided by the total fundamental current.
- e. The "Groundline Section" of wood poles is that portion of the pole between one foot above, and 2 feet below the groundline.

1.4 SUBMITTALS

Government approval is required for submittals with a "G" designation; submittals not having a "G" designation are for Contractor Quality Control approval. Submittals with an "S" are for inclusion in the Sustainability eNotebook, in conformance with Section 01 33 29 SUSTAINABILITY REPORTING. Submit the following in accordance with Section 01 33 00 SUBMITTAL PROCEDURES:

SD-02 Shop Drawings

Luminaire Drawings; G

Pole Drawings; G

Control System One-Line Diagram; G

Sequence of Operation for Exterior Lighting Control System; G

SD-03 Product Data

Luminaires; G

Light Sources; G

LED Drivers; G

Luminaire Warranty; G

Lighting Controls Warranty; G

Pole Warranty; G

Motion Sensors; G

Photosensors; G

Lighting Contactor; G

Poles; G

Brackets

SD-05 Design Data

Luminaire Design Data; G

Photometric Plan; G

SD-06 Test Reports

IES LM-79 Test Report; G

IES LM-80 Test Report; G

IES TM-21 Test Report; G

SD-08 Manufacturer's Instructions

Poles

SD-10 Operation and Maintenance Data

Lighting System, Data Package 5; G

Exterior Lighting Control System, Data Package 5; G

Maintenance Staff Training Plan; G

End-User Training Plan; G

1.5 QUALITY ASSURANCE

Data, drawings, and reports must employ the terminology, classifications and methods prescribed by the IES HB-10 as applicable, for the lighting system specified.

1.5.1 Drawing Requirements

1.5.1.1 Luminaire Drawings

Include dimensions, effective projected area (EPA), weight, accessories, and installation and construction details. Photometric data, including CRI, CCT, TM-15-11 BUG rating, LED driver type, aiming diagram, zonal lumen data, and candlepower distribution data per LM-79 must accompany shop drawings.

1.5.1.2 Pole Drawings

Include dimensions, wind load determined in accordance with ASCE 7-16, pole deflection, pole class, and other applicable information. For concrete poles, include: section and details to indicate quantities and position of prestressing steel, spiral steel, inserts, and through holes; initial prestressing steel tension; and concrete strengths at release and at 28 days.

1.5.2 Luminaire Design Data

- a. Provide distribution data according to IES classification type as defined in IES HB-10 and IES RP-8.

- b. B.U.G. rating for the installed position as defined by IES TM-15 and shielding as defined by IES RP-8.
- c. Provide safety certification and file number for the luminaire family. Include listing, labeling and identification in accordance with NFPA 70 (NEC). Applicable testing bodies are determined by the US Occupational Safety Health Administration (OSHA) as Nationally Recognized Testing Laboratories (NRTL) and include: CSA (Canadian Standards Association), ETL (Edison Testing Laboratory), and UL (Underwriters Laboratories).
- d. Provide long term lumen maintenance projections for each LED luminaire in accordance with IES TM-21. Data used for projections must be obtained from testing in accordance with IES LM-80.
- e. Provide wind loading calculations for luminaires mounted on poles. Weight and effective projected area (EPA) of luminaires and mounting brackets must not exceed maximum rating of pole as installed in particular wind zone area.

1.5.3 IES LM-79 Test Report

Submit test report on manufacturer's standard production model of specified luminaire. Testing must be performed at the same operating drive current as specified luminaire. Include all applicable and required data as outlined under "14.0 Test Report" in IES LM-79.

1.5.4 IES LM-80 Test Report

Submit report on manufacturer's standard production LED light source (package, array, or module) of specified luminaire. Testing must be performed at the same operating drive current as specified luminaire. Include all applicable and required data as outlined under "8.0 Test Report" in IES LM-80.

1.5.5 IES TM-21 Test Report

Submit test report on manufacturer's standard production LED light source (package, array or module) of specified luminaire. Testing must be performed at the same operating drive current as specified luminaire. Include all applicable and required data, as well as required interpolation information as outlined under "7.0 Report" in IES TM-21.

1.5.6 Test Laboratories

Test laboratories for the IES LM-79 and IES LM-80 test reports must be one of the following:

- a. National Voluntary Laboratory Accreditation Program (NVLAP) accredited for solid-state lighting testing as part of the Energy-Efficient Lighting Products laboratory accreditation program.
- b. One of the qualified labs listed on the Department of Energy - Energy Efficiency & Renewable Energy, Solid-State Lighting web site.
- c. One of the EPA-Recognized Laboratories listed at for LM-80 testing.

1.5.7 Regulatory Requirements

Equipment, materials, installation, and workmanship must be in accordance with the mandatory and advisory provisions of NFPA 70 unless more stringent requirements are specified or indicated. Provide luminaires and assembled components that are approved by and bear the label of UL for the applicable location and conditions unless otherwise specified.

1.5.8 Standard Products

Provide materials and equipment that are products of manufacturers regularly engaged in the production of such products which are of equal material, design and workmanship. Products must have been in satisfactory commercial or industrial use for six months prior to bid opening. The six-month period must include applications of equipment and materials under similar circumstances and of similar size. The product must have been on sale on the commercial market through advertisements, manufacturers' catalogs, or brochures during the six-month period. Where two or more items of the same class of equipment are required, these items must be products of a single manufacturer; however, the component parts of the item need not be the products of the same manufacturer unless stated in this section.

1.5.8.1 Alternative Qualifications

Products having less than a six-month field service record will be acceptable if a certified record of satisfactory field operation for not less than 6000 hours, exclusive of the manufacturers' factory or laboratory tests, is furnished.

1.5.8.2 Material and Equipment Manufacturing Date

Do not use products manufactured more than six months prior to date of delivery to site, unless specified otherwise.

1.6 DELIVERY, STORAGE, AND HANDLING OF POLES

1.6.1 Aluminum Poles

Do not store poles on ground. Support poles so they are at least one foot above ground level and growing vegetation. Do not remove factory-applied pole wrappings until just before installing pole.

1.7 WARRANTY

Support all equipment items by service organizations which are reasonably convenient to the equipment installation in order to render satisfactory service to the equipment on a regular and emergency basis during the warranty period of the contract.

1.7.1 Luminaire Warranty

Provide and transfer to the government the original LED luminaire manufacturers standard commercial warranty for each different luminaire manufacturer used in the project.

- a. Provide a written five year minimum replacement warranty for material, luminaire finish, and workmanship. Provide written warranty document that contains all warranty processing information needed, including

customer service point of contact, whether or not a return authorization number is required, return shipping information, and closest return location to the luminaire location.

(1) Finish warranty must include failure and substantial deterioration such as blistering, cracking, peeling, chalking, or fading.

(2) Material warranty must include:

(a) All LED drivers and integral control equipment.

(b) Replacement when more than 10 percent of LED sources in any lightbar or subassembly(s) are defective, non-starting, or operating below 70 percent of specified lumen output.

b. Warranty period must begin in accordance with the manufacturer's standard warranty starting date.

c. Provide replacements that are promptly shipped, without charge, to the using Government facility point of contact and that are identical to or an improvement upon the original equipment. All replacements must include testing of new components and installation.

1.7.2 Lighting Controls Warranty

Provide and transfer to the government the original lighting controls manufacturers standard commercial warranty for each different lighting controls manufacturer used in the project. Warranty coverage must begin from date of final system commissioning or three months from date of delivery, whichever is the earliest. Warranty service must be performed by a factory-trained engineer or technician.

a. Unless otherwise noted, provide a written five year minimum warranty on the complete system for all systems with factory commissioning. Provide warranty that covers 100 percent of the cost of any replacement parts and services required over the five years which are directly attributable to the product failure. Failures include, but are not limited to, the following:

(1) Software: Failure of input/output to execute switching or dimming commands.

(2) Damage of electronic components due to transient voltage surges.

(3) Failure of control devices, including but not limited to photosensors and motion sensors.

b. Provide a written five year minimum warranty on all input devices against defect in workmanship or materials provided by device manufacturer.

c. Provide a written five year minimum warranty on all control components attached to luminaires against defect in workmanship or materials.

1.7.3 Pole Warranty

Provide and transfer to the government the original pole manufacturers standard commercial warranty for each different pole manufacturer used in the project. Warranty coverage must begin from date of final system

commissioning or three months from date of delivery, whichever is the earliest. Provide a written one year minimum replacement warranty for material, luminaire finish, and workmanship. Warranty service must be performed by a factory-trained engineer or technician.

1.8 OPERATION AND MAINTENANCE MANUALS

1.8.1 Lighting System

Provide operation and maintenance manuals for the lighting system in accordance with Section 01 78 23 OPERATION AND MAINTENANCE DATA that provide basic data relating to the design, operation, and maintenance of the lighting system. Additional O&M Manual requirements for the Army are provided in Section 01 78 24.00 10 FACILITY DATA REQUIREMENTS. Additional requirements for the Navy are provided in Section 01 78 24.00 20 FACILITY ELECTRONIC OPERATION AND MAINTENANCE SUPPORT INFORMATION (eOMSI). Include the following:

- a. Manufacturers' operating and maintenance manuals.
- b. Luminaire shop drawings for modified and custom luminaires.
- c. Luminaire Manufacturers' standard commercial warranty information as specified in paragraph LUMINAIRE WARRANTY.

1.8.2 Exterior Lighting Control System

Provide operation and maintenance manuals for the exterior lighting control system in accordance with Section 01 78 23 OPERATION AND MAINTENANCE DATA that provide basic data relating to the design, operation, and maintenance of the exterior lighting control system. Include the following:

- a. Control System One-Line Diagram
- b. Product data for all devices, including installation and programming instructions.
- c. Training materials, such as videos or in-depth manuals, that cover basic operation of the lighting control system and instructions on modifying the control system. Training materials must include calibration, adjustment, troubleshooting, maintenance, repair, and replacement.
- d. Motion sensor coverage layout.

PART 2 PRODUCTS

2.1 PRODUCT COORDINATION

2.2 LUMINAIRES

UL 1598, NEMA C82.77-10. Provide luminaires as indicated in the luminaire schedule and XL plates or details on project plans, complete with light source, wattage, and lumen output indicated. All luminaires of the same type must be provided by the same manufacturer. Luminaires must be specifically designed for use with the LED driver and light source provided.

2.2.1 Luminaires

UL 8750, IES LM-79, IES LM-80. For all luminaires, provide:

- a. Complete system with LED drivers and light sources.
- b. Housing constructed of non-corrosive materials. All new aluminum housings must be anodized or powder-coated. All new steel housings must be treated to be corrosion resistant.
- c. IES TM-21, IES LM-80. Minimum L70 lumen maintenance value of 50,000hours unless otherwise indicated in the luminaire schedule. Luminaire drive current value must be identical to that provided by test data for luminaire in question.
- d. Minimum efficacy as specified in the luminaire schedule. Theoretical models of initial lamp lumens per watt are not acceptable. If efficacy values are not listed in the luminaire schedule, provide luminaires that meet the following minimum values:

Luminaire Style	Minimum Luminaire Efficacy
Area and Roadway (pole mounted, arm mounted)	95 LPW
Pedestrian Post-Top (pole mounted, arm mounted)	90 LPW
Bollard	35 LPW
Accent (adjustable landscape, sign lighting)	35 LPW
Linear Accent (facade, wallwash)	80 LPW
Exterior Wall Sconce	50 LPW
Steplight	30 LPW
Parking Garage Luminaire	100 LPW

- e. Product rated for operation within an ambient temperature range of minus 22 degrees F to 104 degrees F.
- f. UL listed for wet locations.
- g. IES HB-10. Light distribution and NEMA field angle classifications as indicated in luminaire schedule on project plans.
- h. Housing finish that is baked-on enamel, anodized, or baked-on powder coat paint. Finish must be capable of surviving ASTM B117 salt fog environment testing for 2500 hours minimum without blistering or peeling.
- i. LED driver and light source package, array, or module are accessible for service or replacement without removal or destruction of luminaire.
- j. IES TM-15. Does not exceed the BUG ratings as listed in the luminaire schedule.. If BUG ratings are not listed in the luminaire schedule, provide luminaires that meet the following minimum values for each

application and mounting conditions:

Lighting Application	Mounting Conditions	BUG Rating
Area and Roadway	All	B3-U0-G3
Pedestrian Post-Top	All	B2-U1-G1
Exterior Wall Sconce	Above 4 feet AFF	B1-U0-G2
Exterior Wall Sconce	Below or at 4 feet AFF	B4-U0-G4
Steplight	Above 4 feet AFF	B1-U1-G2
Steplight	Below or at 4 feet AFF	B4-U1-G4
Parking Garage Luminaire	Ceiling mounted	B4-U4-G3

- k. Fully assembled and electrically tested prior to shipment from factory.
- l. Finish color is as indicated in the luminaire schedule or detail on the project plans.
- m. Lenses constructed of clear tempered glass or UV-resistant acrylic. Provide polycarbonate vandal-resistant lenses.
- n. All factory electrical connections are made using crimp, locking, or latching style connectors. Twist-style wire nuts are not acceptable.
- o. **NEMA C136.31**. Comply with 3G vibration testing.
- p. Luminaire arm bolts constructed from 304 stainless steel or zinc-plated steel.
- r. Incorporate modular electrical connections, and construct luminaires to allow replacement of all or any part of the optics, heat sinks, LED drivers, surge suppressors and other electrical components using only a simple tool, such as a manual or cordless electric screwdriver.
- s. **ANSI C136.3**. For all roadway and area luminaires, provide products with an integral tilt adjustment of plus or minus 5 degrees to allow the unit to be leveled.

2.3 LIGHT SOURCES

NEMA ANSLG C78.377, NEMA SSL 3. Provide type, lumen rating, and wattage as indicated in luminaire schedule on project plans.

2.3.1 LED Light Sources

Provide LED light sources that meet the following requirements:

- a. **NEMA ANSLG C78.377**. Emit white light and have a nominal Correlated Color Temperature (CCT) of 4000 Kelvin.
- b. Minimum Color Rendering Index (CRI) of 80.

- c. [Directive 2011/65/EU](#). Restriction of Hazardous Substances (RoHS) compliant.
- d. Light source color consistency by utilizing a binning tolerance within a 4-step McAdam ellipse.

2.4 LED DRIVERS

[NEMA SSL 1](#), [UL 1310](#). Provide LED Drivers that are electronic, UL Class 1 or Class 2, constant-current type and meet the following requirements:

- a. The combined LED driver and LED light source system is greater than or equal to the minimum luminaire efficacy values as listed in the luminaire schedule provided.
- b. Operate at a voltage of 120-277 volts at 50/60 hertz, with input voltage fluctuations of plus or minus 10 percent.
- c. Power Factor (PF) greater than or equal to 0.90 at full input power and across specified dimming range.
- d. Maximum Total Harmonic Distortion (THD) less than or equal to 20 percent at full input power and across specified dimming range.
- e. Operates for at least 50,000 hours at maximum case temperature and 90 percent non-condensing relative humidity.
- f. Meets the "Elevated" (10kV/10kA) requirements per [IEEE C62.41.2-2002](#). Manufacturer must indicate whether failure of the electrical immunity system can possibly result in disconnect of power to luminaire. Provide surge protection that is integral to the LED driver.
- g. Contains integral thermal protection that reduces the output power to protect the driver and light source from damage if the case temperature approaches or exceeds the driver's maximum operating temperature.
- h. Complies with the requirements of the Federal Communications Commission (FCC) rules and regulations, Title 47 CFR part 15, Non-Consumer (Class A) for EMI/RFI (conducted and radiated).
- i. Class A sound rating for all drivers mounted under a covered structure, such as a canopy, or where otherwise appropriate.
- j. [Directive 2011/65/EU](#). Restriction of Hazardous Substances (RoHS) compliant.
- k. UL listed for wet locations typical of exterior installations.
- l. Dimmable, and compatible with a standard dimming control circuit of 0 - 10V.
- m. Rated to operate between ambient temperatures of [minus 22 degrees F](#) and [104 degrees F](#).

2.5 LIGHTING CONTROLS

Provide a control system interface within each luminaire that is

compatible with the energy management or control system used by the utility department in charge of the project area for control of site lighting. Provide network certification for all networked lighting control systems and devices in accordance with the requirements of Section 25 05 11. CYBERSECURITY FOR FACILITY-RELATED CONTROL SYSTEMS.

2.5.1 System

Provide exterior lighting control system that operates the exterior lighting system as described in the exterior lighting control strategies in the project plans. Submit [Sequence of Operation for Exterior Lighting Control System](#) describing the operation of the proposed exterior lighting control system and devices. Sequence of Operation must provide the strategies identified in the exterior lighting control strategies.

2.5.1.1 Relay Panel

Enclose panel hardware in a surface-mounted, NEMA 1, painted, steel enclosure with lockable access door and ventilation openings. Internal low-voltage compartment must be separated from line-voltage compartment of enclosure with only low-voltage compartment accessible upon opening of door. Provide additional remote cabinets that communicate back to main control panel as required. Provide relay panel that meets the following criteria:

- a. Input voltage of 120-277 at 50/60 Hz, with internal low voltage power supply as required.
- b. [UL 924](#). 16 single-pole latching relays rated at 20 amps, 120-277 volts. Provide provision for relays to close upon power failure. Provide relays designed for 10 years of use at full rated load.
- c. Relay control module operates at 24 VDC and is rated to control a minimum of 16 relays.

2.5.2 Devices

2.5.2.1 Photosensors

[UL 773](#), [UL 773A](#). Provide Photosensors that meet the following requirements:

- a. Hermetically sealed, silicon diode light sensor type, rated at 1800 watts, 277 volts, 50/60 Hz with single-pole, double-throw contacts.
- b. Turns ON at 1 to 3 footcandles and turns OFF at 3 to 15 footcandles.
- c. Designed to fail to the ON position.
- d. Housing is constructed of UV stabilized polypropylene, rated to operate within a temperature range of minus 40 to 158 degrees F.
- e. Time delay that prevents accidental switching from transient light sources.
- f. Directional lens in front of the cell to prevent fixed light sources from creating a turnoff condition.
- g. Designed for 20-year service to match life expectancy of long-life LED

fixtures and exceed 15,000 operations at full load. Provide photosensors with zero-cross technology to withstand severe in-rush current and extend relay life.

- h. Swivel base type housing with 1/2 in threaded base for mounting to a junction box or conduit.
- j. Provide photosensors with metal oxide varistor (MOV) type surge protection.

2.5.2.2 Motion Sensors

NEMA WD 7, UL 773A. Provide sensors that meet the following requirements:

- a. Operating voltage of 120-277 volts.
- b. Passive infrared type sensors with 270 degree coverage.
- c. Time delay that can be adjusted from 15 seconds to 15 minutes.
- d. Default state is "Fail to ON position."
- e. Sensors installed integral to the luminaire must be provided by the luminaire manufacturer.
- f. Sensor contains an integral light level sensor that does not allow luminaires to operate during daylight hours
- g. Mounted directly to luminaire.
- h. Operates in conjunction with bi-level controllers that reduce the connected lighting power by 50 percent.

2.5.2.3 Lighting Contactor

NEMA ICS 2. Provide a electrically-held lighting contactor housed in a NEMA 1 or 4X enclosure conforming to NEMA ICS 6, as indicated on the plans. Contactor must have 6 poles, configured as normally open (NO). Contacts must be rated 600 volts, 30 amperes for a resistive load. Coil operating voltage must be 277 volts. Contactor must have silver cadmium oxide double-break contacts and must require no arcing contacts. Provide contactor with hand-off-automatic on-off selector switch.

2.6 POLES

ASCE 7-16. Provide round tapered poles designed for wind loading of 150 miles per hour while supporting luminaires and all other appurtenances indicated. The effective projected areas (EPA) of luminaires and appurtenances used in calculations must be specific for the actual products provided on each pole. Provide poles that are anchor-base type designed for use with underground supply conductors. Poles must have oval-shaped hand hole having a minimum clear opening of 3 by 5 inches. Secure hand hole covers by stainless steel captive screws. Provide metal poles with an internal grounding connection accessible from the hand hole near the bottom of each pole. Install a means of wire disconnection accessible from the hand hole. Do not install square poles. Provide poles from a Manufacturer with a standard provision for protecting the finish during shipment and installation. Do not install scratched,

stained, chipped, or dented poles.

2.6.1 Aluminum Poles

Provide aluminum poles with uniform satin finish unless otherwise noted in luminaire schedule on project plans. Do not paint aluminum poles. Provide poles that meet the following requirements:

- a. **AASHTO LTS**. Manufactured of corrosion resistant aluminum alloys for Alloy 6063-T6 or Alloy 6005-T5 for wrought alloys and Alloy 356-T4 (3,5) for cast alloys.
- b. Seamless extruded or spun seamless-type with minimum 0.188 inch wall thickness.
- c. Top of shaft is fitted with a round or tapered cover.
- d. **ASTM B108/B108M**. Pole base is mounted by anchor bolts, made of cast 356-T6 aluminum alloy. Base must be machined to receive the lower end of shaft.
- e. Joint between shaft and base is welded.
- f. **ASTM B108/B108M**. Base cover is cast 356-T6 aluminum alloy.
- g. All hardware other than anchor bolts are either 2024-T4 anodized aluminum alloy or stainless steel.
- h. Grounding connection is designed to prevent electrolysis when used with copper ground wire.

2.6.2 Brackets and Supports

ANSI C136.3, **ANSI C136.13**, and **ANSI C136.21**. Provide pole brackets that are not less than 1 1/4 inch aluminum secured to pole. Slip-fitter or pipe-threaded brackets may be used, but brackets must be coordinated to luminaires provided, and brackets for use with one type of luminaire must be identical. Brackets for pole-mounted street lights must correctly position luminaire no lower than mounting height indicated. Mount brackets not less than 24 feet above street. Provide special mountings or brackets as indicated and of metal which will not promote galvanic reaction with luminaire head.

2.6.3 Pole Foundations

Provide anchor bolts consisting of a steel rod with a minimum yield strength of 50,000 psi; the top 12 inches of the rod must be galvanized in accordance with **ASTM A153/A153M**. Concrete must be as specified in Section 03 30 00 CAST-IN-PLACE CONCRETE and Section 33 71 02 UNDERGROUND ELECTRICAL DISTRIBUTION.

2.7 EQUIPMENT IDENTIFICATION

2.7.1 Manufacturer's Nameplate

Each item of equipment must have a nameplate bearing the manufacturer's name, address, model number, and serial number securely affixed in a conspicuous place; the nameplate of the distributing agent will not be acceptable.

2.7.2 Labels

UL 1598. Luminaires must be clearly marked for operation of specific light sources and drivers according to proper light source type. Note the following luminaire characteristics in the format "Use Only _____":

- a. Correlated color temperature (CCT) and color rendering index (CRI) for all luminaires.
- b. Driver and dimming protocol.

Markings related to light source type must be clear and located to be readily visible to service personnel, but unseen from normal viewing angles when light sources are in place. LED drivers must have clear markings indicating dimming type and indicate proper terminals for the various outputs.

2.8 FACTORY APPLIED FINISH

NEMA 250. Provide all luminaires and lighting equipment with factory-applied painting system that as a minimum meets requirements of corrosion-resistance testing.

PART 3 EXECUTION

3.1 INSTALLATION

IEEE C2, NFPA 70.

3.1.1 Luminaires

Install all luminaires in accordance with the luminaire manufacturer's written instructions. Install all luminaires at locations and heights as indicated on the project plans. Level all luminaires in accordance to manufacturer's written instructions. Aim all luminaires in accordance with aiming diagram.

3.1.2 LED Drivers

Provide LED drivers integral to luminaire as constructed by the manufacturer.

3.1.3 Aluminum and Steel Poles

Provide pole foundations with galvanized steel anchor bolts, threaded at the top end and bent 90 degrees at the bottom end. Provide ornamental covers to match pole and galvanized nuts and washers for anchor bolts. Concrete for anchor bases, polyvinyl chloride (PVC) conduit bells, and ground rods must be as specified in Section 03 30 00 CAST-IN-PLACE CONCRETE and Section 33 71 02 UNDERGROUND ELECTRICAL DISTRIBUTION. Thoroughly compact backfill with compacting arranged to prevent pressure between conductor, jacket, or sheath and the end of conduit ell. Adjust poles as necessary to provide a permanent vertical position with the bracket arm in proper position for luminaire location.

3.1.4 Lighting Controls

Refer to Section 25 05 11. CYBERSECURITY FOR FACILITY-RELATED CONTROL

SYSTEMS for additional lighting control installation requirements.

3.1.4.1 Photosensors

Aim photosensor according to manufacturer's recommendations.

3.1.4.2 Motion Sensors

Locate sensors in accordance with the manufacturer's recommendation. Locate sensors to achieve coverage of areas as indicated on project plans. Coverage patterns must be derated as recommended by manufacturer based on mounting height of sensor and any obstructions such as trees. Do not use gross rated coverage in manufacturer's product literature.

3.1.5 Grounding

Ground noncurrent-carrying parts of equipment including metal poles, luminaires, mounting arms, brackets, and metallic enclosures as specified in Section 33 71 02 UNDERGROUND ELECTRICAL DISTRIBUTION. Where copper grounding conductor is connected to a metal other than copper, provide specially treated or lined connectors suitable for this purpose.

3.2 FIELD QUALITY CONTROL

3.2.1 Tests

Upon completion of installation, verify that equipment is properly installed, connected, and adjusted. Perform initial operational test, consisting of the entire system energized for 72 consecutive hours without any failures of any kind occurring in the system. All circuits must test clear of faults, grounds, and open circuits.

3.2.1.1 Lighting Control Verification Test

Verify lighting control system and devices operate according to approved sequence of operations. Verification tests are to be completed after commissioning.

3.3 CLOSEOUT ACTIVITIES

3.3.1 Training

Provide on-site training to the Owner's personnel in the operation and maintenance of lighting and lighting control system. Provide training that includes calibration, adjustment, troubleshooting, maintenance, repair, and replacement.

3.3.1.1 Maintenance Staff Training

Submit a [Maintenance Staff Training Plan](#) at least 30 calendar days prior to training session that describes training procedures for Owner's personnel in the operation and maintenance of lighting and lighting control system. Provide on-site training which demonstrate full system functionality, assigning schedules, calibration adjustments for light levels and sensor sensitivity, integration procedures for connecting to third-party devices, and manual override including information on appropriate use. Provide protocols for troubleshooting, maintenance, repair, and replacement, and literature on available system updates and process for implementing updates.

3.3.1.2 End-User Training

Submit a [End-User Training Plan](#) at least 30 calendar days prior to training session that describes training procedures for end-users on the lighting control system. Provide demonstration for each type of user interface. Provide users with the curfew schedule as currently commissioned, including conditional programming based on astronomic time clock functionality. Provide users with the correct contact information for maintenance personnel who will be available to address any lighting control issues.

-- End of Section --

SECTION 27 10 00

BUILDING TELECOMMUNICATIONS CABLING SYSTEM

06/17

PART 1 GENERAL

1.1 REFERENCES

The publications listed below form a part of this specification to the extent referenced. The publications are referred to within the text by the basic designation only.

ASTM INTERNATIONAL (ASTM)

ASTM D709 (2017) Standard Specification for Laminated Thermosetting Materials

ELECTRONIC COMPONENTS INDUSTRY ASSOCIATION (ECIA)

ECIA EIA/ECA 310-E (2005) Cabinets, Racks, Panels, and Associated Equipment

INSTITUTE OF ELECTRICAL AND ELECTRONICS ENGINEERS (IEEE)

IEEE 100 (2000; Archived) The Authoritative Dictionary of IEEE Standards Terms

INSULATED CABLE ENGINEERS ASSOCIATION (ICEA)

ICEA S-83-596 (2016) Indoor Optical Fiber Cables

ICEA S-90-661 (2012) Category 3, 5, & 5e Individually Unshielded Twisted Pair Indoor Cables for Use in General Purpose and LAN Communications Wiring Systems Technical Requirements

NATIONAL ELECTRICAL CONTRACTORS ASSOCIATION (NECA)

NECA/BICSI 568 (2006) Standard for Installing Building Telecommunications Cabling

NATIONAL ELECTRICAL MANUFACTURERS ASSOCIATION (NEMA)

ANSI/NEMA WC 66 (2013) Performance Standard for Category 6 and Category 7 100 Ohm Shielded and Unshielded Twisted Pairs

NATIONAL FIRE PROTECTION ASSOCIATION (NFPA)

NFPA 70 (2020; ERTA 20-1 2020; ERTA 20-2 2020; TIA 20-1; TIA 20-2; TIA 20-3; TIA 20-4) National Electrical Code

TELECOMMUNICATIONS INDUSTRY ASSOCIATION (TIA)

TIA-1152 (2009) Requirements for Field Test

- Instruments and Measurements for Balanced Twisted-Pair Cabling
- TIA-455-21 (1988a; R 2012) FOTP-21 - Mating Durability of Fiber Optic Interconnecting Devices
 - TIA-492AAAA (2009b) 62.5-um Core Diameter/125-um Cladding Diameter Class 1a Graded-Index Multimode Optical Fibers
 - TIA-526-14 (2015c) OFSTP-14A Optical Power Loss Measurements of Installed Multimode Fiber Cable Plant
 - TIA-526-7 (2015a) OFSTP-7 Measurement of Optical Power Loss of Installed Single-Mode Fiber Cable Plant
 - TIA-568-C.0 (2009; Add 1 2010; Add 2 2012) Generic Telecommunications Cabling for Customer Premises
 - TIA-568-C.1 (2009; Add 2 2011; Add 1 2012) Commercial Building Telecommunications Cabling Standard
 - TIA-568-C.2 (2009; Errata 2010; Add 2 2014; Add 1 2016) Balanced Twisted-Pair Telecommunications Cabling and Components Standards
 - TIA-568-C.3 (2008; Add 1 2011) Optical Fiber Cabling Components Standard
 - TIA-569 (2015d) Commercial Building Standard for Telecommunications Pathways and Spaces
 - TIA-570 (2012c) Residential Telecommunications Infrastructure Standard
 - TIA-606 (2012b; Add 1 2015) Administration Standard for the Telecommunications Infrastructure
 - TIA-607 (2015c; Addendum 1 2017) Generic Telecommunications Bonding and Grounding (Earthing) for Customer Premises
 - TIA/EIA-598 (2014d) Optical Fiber Cable Color Coding
 - TIA/EIA-604-3 (2004b; R 2014) Fiber Optic Connector Intermateability Standard (FOCIS), Type SC and SC-APC, FOCIS-3

U.S. FEDERAL COMMUNICATIONS COMMISSION (FCC)

- FCC Part 68 Connection of Terminal Equipment to the Telephone Network (47 CFR 68)

UNDERWRITERS LABORATORIES (UL)

UL 1286	(2008; Reprint Feb 2015) Office Furnishings
UL 1666	(2007; Reprint Jun 2012) Test for Flame Propagation Height of Electrical and Optical-Fiber Cables Installed Vertically in Shafts
UL 444	(2008; Reprint Apr 2015) Communications Cables
UL 467	(2013; Reprint Jun 2017) UL Standard for Safety Grounding and Bonding Equipment
UL 50	(2015) UL Standard for Safety Enclosures for Electrical Equipment, Non-Environmental Considerations
UL 514C	(2014; Reprint Feb 2020) UL Standard for Safety Nonmetallic Outlet Boxes, Flush-Device Boxes, and Covers
UL 969	(1995; Reprint Sep 2014) Standard for Marking and Labeling Systems
UL 2043	(2013) Fire Test for Heat and Visible Smoke Release for Discrete Products and Their Accessories Installed in Air-Handling Spaces

1.2 RELATED REQUIREMENTS

Section 01 33 00 SUBMITTAL PROCEDURES, Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM and Section 33 82 00.00 22 TELECOMMUNICATIONS, OUTSIDE PLANT (OSP) apply to this section with additions and modifications specified herein.

Contact Camp Lejeune Base Telephone (aka Telecommunications Support Division or TSD) for special requirements on classified service cabling and color, unofficial service, under slab cabling, using water block, and any item not covered in this document.

Buildings with Special Network Requirements such as Classified networks, other government agencies (Navy NMCfI, Navy Medical, DLA, VA. Etc.), Marine Corps Community Services, Commercial ISP's, and CATV may require additional guidance outside this specification. Controlled or Restricted Access Areas may contain Classified networks may require Protected Distribution System which shall be installed in accordance with the current CNSSI No. 7003, UFGS27 05 29.00 10, and other restricted release publications. Classified networks may require shielded twisted pair, specific separation, distinct colored components, and shall be in accordance with current CNSSAM TEMPEST 1-13, RED/BLACK Separation documentation. In these cases contact Telecommunications Support Division G-6 MCIEAST-MCB CAMLEJ for additional guidance at (910) 451-9439 or (910) 451-3100.

Contact AHJ for special requirements on classified service, unofficial

service, under slab cabling, using water block, and any item not covered in this document.

1.3 DEFINITIONS

Unless otherwise specified or indicated, electrical and electronics terms used in this specification shall be as defined in TIA-568-C.1, TIA-568-C.2, TIA-568-C.3, TIA-569, TIA-606 and IEEE 100 and herein.

1.3.1 Main Distribution Frame (MDF)

A physical structure at a central location for terminating permanent backbone cables to interconnect with service provider (SP) equipment at the activity minimum point of presence. The MDF generally includes vendor specific components to support voice and data circuits, building surge protector assemblies, main cross connect blocks, equipment support frames, and fire rated plywood backboard. Depending upon local site conditions, the MDF, BDF and EF may be the same space.

1.3.2 Building Distribution Frame (BDF)

A structure with terminations for connecting backbone, campus, and horizontal cabling. The BDF generally includes a cross connect, equipment support frame or lockable terminal cabinet, cable supports, and fire rated plywood backboard. The BDF shall include building protector assemblies when used for campus backbone or SP cabling. Also known as a (BD).

1.3.3 Intermediate Distribution Frame (IDF)

An intermediate termination point for horizontal wiring and cross connections within telecommunications rooms. Shall be connected to MDF with both fiber and copper. Secure Internet Protocol (SIPR) vault or cabinet is considered an IDF. Also known as a (FD).

1.3.4 Communications Room (CR)

An enclosed space for telecommunications equipment, terminations, and cross connect wiring for horizontal cabling. Also known as (TR), (CR), and IT Room. Terms are used interchangeably in this section and are considered to have the same meaning.

1.3.5 Campus Distributor (CD)

A distributor from which the campus backbone cabling emanates. (International expression for main cross-connect (MC). Also known as Central Office (CO) or Area Distribution Node (ADN)).

1.3.6 Building Distributor (BD)

A distributor in which the building backbone (customer owned outside plant) cables terminate and at which connections to the campus backbone cables may be made. (International expression for intermediate cross-connect (IC).)

1.3.7 Floor Distributor (FD)

A distributor used to connect horizontal cable and cabling subsystems or equipment. (International expression for horizontal cross-connect (HC)).

1.3.8 Telecommunications Room (TR)

An enclosed space for housing telecommunications equipment, cable, terminations, and cross-connects. The room is the recognized cross-connect between the backbone cable and the horizontal cabling. Also known as a (CR), and IT Room.

1.3.9 Entrance Facility (EF) (Telecommunications) (can be same as the MDF)

An entrance to the building for both private and public network service cables (including wireless) including the entrance point at the building wall and continuing to the equipment room.

1.3.10 Equipment Room (ER) (Telecommunications) (can be same as communications room)

An environmentally controlled centralized space for telecommunications equipment that serves the occupants of a building. Equipment housed therein is considered distinct from a telecommunications room because of the nature of its complexity.

1.3.11 Open Cable

Cabling that is not run enclosed in a raceway as defined by NFPA 70. This refers to cabling that is "open" to the space in which the cable has been installed and is therefore exposed to the environmental conditions associated with that space, such as wire basket tray, cable tray, J-hooks, D-rings, or bridal rings. D rings should only be used in the communications room for cable management and J-hooks/bridal rings shall not be used.

1.3.12 Open Office

A floor space division provided by furniture, moveable partitions, or other means instead of by building walls, normally over 100 square feet.

1.3.13 Pathway

A physical infrastructure utilized for the placement and routing of telecommunications cable. Also known as raceway.

1.4 SYSTEM DESCRIPTION

The building telecommunications cabling and pathway system shall include permanently installed backbone and horizontal cabling, horizontal and backbone pathways, service entrance facilities, work area pathways, telecommunications outlet assemblies, conduit, raceway, and hardware for splicing, terminating, and interconnecting cabling necessary to transport telephone data, and other communications systems (including LAN A/V, intercom, PA, CATV, CCTV, and WiFi) between equipment items in a building. The horizontal system shall be wired in a star topology from the telecommunications work area to the floor distributor/IDF or building distributor/MDF or campus distributor or communications room at the center or hub of the star. The backbone cabling and pathway system includes intrabuilding and interbuilding interconnecting cabling, pathway, and terminal hardware. The intrabuilding backbone provides connectivity from the floor distributors to the building distributors or to the campus distributor and from the building distributors to the campus distributor as required. The backbone system shall be wired in a star topology with

the campus distributor (Area Distribution Node) at the center or hub of the star. The interbuilding backbone system provides connectivity between the campus distributors and is specified in Section 33 82 00.00 22 TELECOMMUNICATIONS OUTSIDE PLANT (OSP). Provide telecommunications pathway systems referenced herein as specified in Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM. The telecommunications contractor must coordinate with MCB CL Base Telephone (TSD) concerning access to and configuration of telecommunications spaces. The telecommunications contractor may be required to coordinate work effort within the telecommunications spaces with the electrical sub and general contractor, ROICC and MCI East G-6 Telecommunications Support Division (TSD).

1.5 SUBMITTALS

Government approval is required for submittals with a "G" designation; submittals not having a "G" designation are for Contractor Quality Control approval. Submit the following in accordance with Section 01 33 00 SUBMITTAL PROCEDURES:

SD-02 Shop Drawings

Telecommunications drawings; G

Telecommunications Space Drawings; G

In addition to Section 01 33 00 SUBMITTAL PROCEDURES, provide shop drawings in accordance with paragraph SHOP DRAWINGS.

SD-03 Product Data

Telecommunications cabling (backbone and horizontal); G

Patch panels; G

Telecommunications outlet/connector assemblies; G

Equipment support frame; G

Connector blocks; G

Submittals shall include the manufacturer's name, trade name, place of manufacture, and catalog model or number. Include performance and characteristic curves. Submittals shall also include applicable federal, military, industry, and technical society publication references. Should manufacturer's data require supplemental information for clarification, the supplemental information shall be submitted as specified in paragraph REGULATORY REQUIREMENTS and as required in Section 01 33 00 SUBMITTAL PROCEDURES.

SD-06 Test Reports

Telecommunications cabling testing; G

SD-07 Certificates

Telecommunications Contractor Qualifications; G

Key Personnel Qualifications; G

Manufacturer Qualifications; G

Test plan; G

SD-09 Manufacturer's Field Reports

Factory reel tests; G

SD-10 Operation and Maintenance Data

Telecommunications cabling and pathway system Data Package 5; G

SD-11 Closeout Submittals

Record Documentation; G

1.5.1 Additional Submittal Requirements

All submittals of material, equipment and design must be approved by the Telecommunications Support Division (TSD) prior to installing any telecommunications wiring, equipment, or power to support communications.

1.6 QUALITY ASSURANCE

1.6.1 Shop Drawings

In exception to Section 01 33 00 SUBMITTAL PROCEDURES, submitted plan drawings shall be a minimum of 11 by 17 inches in size using a minimum scale of 1/8 inch per foot. Include wiring diagrams and installation details of equipment indicating proposed location, layout and arrangement, control panels, accessories, piping, ductwork, and other items that must be shown to ensure a coordinated installation. Wiring diagrams shall identify circuit terminals and indicate the internal wiring for each item of equipment and the interconnection between each item of equipment. Drawings shall indicate adequate clearance for operation, maintenance, and replacement of operating equipment devices. Submittals shall include the nameplate data, size, and capacity. Submittals shall also include applicable federal, military, industry, and technical society publication references.

1.6.1.1 Telecommunications Drawings

Provide Registered Communications Distribution Designer (RCDD) approved, drawings in accordance with TIA-606. The identifier for each termination and cable shall appear on the drawings. Drawings shall depict final telecommunications installed wiring system infrastructure in accordance with TIA-606. The drawings should provide details required to prove that the distribution system shall properly support connectivity from the EF telecommunications and ER telecommunications, CD's, BD's, and FD's to the telecommunications work area outlets. Provide a plastic laminated schematic of the as-installed telecommunications cable system showing cabling, CD's, BD's, FD's, and the EF and ER for telecommunications keyed to floor plans by room number. Mount the laminated schematic in the EF telecommunications space as directed by the Contracting Officer. The following drawings shall be provided as a minimum:

- a. T1 - Layout of complete building per floor - Building Area/Serving Zone Boundaries, Backbone Systems, and Horizontal Pathways. Layout of

complete building per floor. The drawing indicates location of building areas, serving zones, vertical backbone diagrams, telecommunications rooms, access points, pathways, grounding system, and other systems that need to be viewed from the complete building perspective.

- b. T2 - Serving Zones/Building Area Drawings - Drop Locations and Cable Identification (ID'S). Shows a building area or serving zone. These drawings show drop locations, telecommunications rooms, **dedicated electrical**, access points and detail call outs for common equipment rooms and other congested areas.
- c. T4 - Typical Detail Drawings - Faceplate Labeling, Firestopping, Americans with Disabilities Act (ADA), Safety, Department of Transportation (DOT). Detailed drawings of symbols and typicals such as faceplate labeling, faceplate types, faceplate population installation procedures, detail racking, and raceways.

1.6.1.2 Telecommunications Space Drawings

Provide T3 drawings in accordance with **TIA-606** that include telecommunications rooms plan views, pathway layout (cable tray, racks, ladder-racks, etc.), mechanical/electrical layout, and cabinet, rack, backboard and wall elevations. Drawings shall show layout of applicable equipment including incoming cable stub or connector blocks, building protector assembly, outgoing cable connector blocks, **mechanical/electrical**, patch panels and equipment spaces and cabinet/racks. Drawings shall include a complete list of equipment and material, equipment rack details, proposed layout and anchorage of equipment and appurtenances, and equipment relationship to other parts of the work including clearance for maintenance and operation. Drawings may also be an enlargement of a congested area of T1 or T2 drawings.

1.6.2 Telecommunications Contractor Qualifications

Work under this section shall be performed by and the equipment shall be provided by the approved telecommunications contractor and key personnel. Qualifications shall be provided for: the telecommunications system contractor, the telecommunications system installer, and the supervisor (if different from the installer). A minimum of 30 days prior to installation, submit documentation of the experience of the telecommunications contractor and of the key personnel.

1.6.2.1 Telecommunications Contractor

The telecommunications contractor shall be a firm which is regularly and professionally engaged in the business of the applications, installation, and testing of the specified telecommunications systems and equipment. The telecommunications contractor shall demonstrate experience in providing successful telecommunications systems within the past 3 years of similar scope and size. Submit documentation for a minimum of three and a maximum of five successful telecommunication system installations for the telecommunications contractor. **Also IAW Section on QC Specialists; a Telecommunications Systems QC Specialist may be required on site, full time with 10 years minimum experience in telecom installation and experience. Specialist shall be very familiar with UFGS Divisions 27, 28, 33 concerning communications systems work and installation.**

1.6.2.2 Key Personnel

Provide key personnel who are regularly and professionally engaged in the business of the application, installation and testing of the specified telecommunications systems and equipment. There may be one key person or more key persons proposed for this solicitation depending upon how many of the key roles each has successfully provided. Each of the key personnel shall demonstrate experience in providing successful telecommunications systems within the past 3 years.

Supervisors and installers assigned to the installation of this system or any of its components shall be Building Industry Consulting Services International (BICSI) Registered Cabling Installers, Technician Level. Submit documentation of current BICSI certification for each of the key personnel.

In lieu of BICSI certification, supervisors and installers assigned to the installation of this system or any of its components shall have a minimum of 3 years experience in the installation of the specified copper and fiber optic cable and components. They shall have factory or factory approved certification from each equipment manufacturer indicating that they are qualified to install and test the provided products. Submit documentation for a minimum of three and a maximum of five successful telecommunication system installations for each of the key personnel. Documentation for each key person shall include at least two successful system installations provided that are equivalent in system size and in construction complexity to the telecommunications system proposed for this solicitation. Include specific experience in installing and testing telecommunications systems and provide the names and locations of at least two project installations successfully completed using optical fiber and copper telecommunications cabling systems. All of the existing telecommunications system installations offered by the key persons as successful experience shall have been in successful full-time service for at least 18 months prior to the issuance date for this solicitation. Provide the name and role of the key person, the title, location, and completed installation date of the referenced project, the referenced project owner point of contact information including name, organization, title, and telephone number, and generally, the referenced project description including system size and construction complexity.

Indicate that all key persons are currently employed by the telecommunications contractor, or have a commitment to the telecommunications contractor to work on this project. All key persons shall be employed by the telecommunications contractor at the date of issuance of this solicitation, or if not, have a commitment to the telecommunications contractor to work on this project by the date that the bid was due to the Contracting Officer.

Note that only the key personnel approved by the Contracting Officer in the successful proposal shall do work on this solicitation's telecommunications system. Key personnel shall function in the same roles in this contract, as they functioned in the offered successful experience. Any substitutions for the telecommunications contractor's key personnel requires approval from The Contracting Officer.

1.6.2.3 Minimum Manufacturer Qualifications

Cabling, equipment and hardware manufacturers shall have a minimum of 3 years experience in the manufacturing, assembly, and factory testing of

components which comply with TIA-568-C.1, TIA-568-C.2 and TIA-568-C.3.

1.6.3 Test Plan

Provide a complete and detailed test plan for the telecommunications cabling system including a complete list of test equipment for the components and accessories for each cable type specified, 60 days prior to the proposed test date. Include procedures for certification, validation, sample report, and testing.

1.6.4 Regulatory Requirements

In each of the publications referred to herein, consider the advisory provisions to be mandatory, as though the word, "shall" had been substituted for "should" wherever it appears. Interpret references in these publications to the "authority having jurisdiction," or words of similar meaning, to mean the Contracting Officer. Equipment, materials, installation, and workmanship shall be in accordance with the mandatory and advisory provisions of NFPA 70, manufacturer recommendations/installation manual, best known industry practices, and industry standards, unless more stringent requirements are specified or indicated.

1.6.5 Standard Products

Provide materials and equipment that are products of manufacturers regularly engaged in the production of such products which are of equal material, design and workmanship. Products shall have been in satisfactory commercial or industrial use for 2 years prior to bid opening. The 2-year period shall include applications of equipment and materials under similar circumstances and of similar size. The product shall have been on sale on the commercial market through advertisements, manufacturers' catalogs, or brochures during the 2-year period. Where two or more items of the same class of equipment are required, these items shall be products of a single manufacturer; however, the component parts of the item need not be the products of the same manufacturer unless stated in this section. Modification of manufacturer's standard products such as painting faceplates is not authorized.

1.6.5.1 Alternative Qualifications

Products having less than a 2-year field service record will be acceptable if a certified record of satisfactory field operation for not less than 6000 hours, exclusive of the manufacturers' factory or laboratory tests, is furnished.

1.6.5.2 Material and Equipment Manufacturing Date

Products manufactured more than 1 year prior to date of delivery to site shall not be used, unless specified otherwise.

1.7 DELIVERY AND STORAGE

Provide protection from weather, moisture, extreme heat and cold, dirt, dust, and other contaminants for telecommunications cabling and equipment placed in storage.

1.8 ENVIRONMENTAL REQUIREMENTS

Connecting hardware shall be rated for operation under ambient conditions of 0 to 60 degrees C 32 to 140 degrees F and in the range of 0 to 95 percent relative humidity, noncondensing. All telecommunications spaces shall follow TIA-569 design.

1.9 WARRANTY

The equipment items shall be supported by service organizations which are reasonably convenient to the equipment installation in order to render satisfactory service to the equipment on a regular and emergency basis during the warranty period of the contract.

1.10 MAINTENANCE

1.10.1 Operation and Maintenance Manuals

Commercial off the shelf manuals shall be furnished for operation, installation, configuration, and maintenance of products provided as a part of the telecommunications cabling and pathway system, Data Package 5. Submit operations and maintenance data in accordance with Section 01 78 23 OPERATION AND MAINTENANCE DATA and as specified herein not later than 2 months prior to the date of beneficial occupancy. In addition to requirements of Data Package 5, include the requirements of paragraphs TELECOMMUNICATIONS DRAWINGS, TELECOMMUNICATIONS SPACE DRAWINGS, and RECORD DOCUMENTATION. Ensure that these drawings and documents depict the as-built configuration. Also provide copies of all telecommunications manuals to TSD.

1.10.2 Record Documentation

Provide T5 drawings including documentation on cables and termination hardware in accordance with TIA-606. T5 drawings shall include schedules to show information for cut-overs and cable plant management, patch panel layouts and cover plate assignments, cross-connect information and connecting terminal layout as a minimum. T5 drawings shall be provided in hard copy format and on electronic media (PDF and AutoCAD 2016 format). Provide the following T5 drawing documentation as a minimum:

- a. Cables - A record of installed cable shall be provided in accordance with TIA-606. The cable records shall include only the required data fields in accordance with TIA-606. Include manufacture date of cable with submittal.
- b. Termination Hardware - A record of installed patch panels, cross-connect points, distribution frames, terminating block arrangements and type, and outlets shall be provided in accordance with TIA-606. Documentation shall include the required data fields as a minimum in accordance with TIA-606.

PART 2 PRODUCTS

2.1 COMPONENTS

Components shall be UL or third party certified. Where equipment or materials are specified to conform to industry and technical society reference standards of the organizations, submit proof of such compliance. The label or listing by the specified organization will be

acceptable evidence of compliance. In lieu of the label or listing, submit a certificate from an independent testing organization, competent to perform testing, and approved by the Contracting Officer. The certificate shall state that the item has been tested in accordance with the specified organization's test methods and that the item complies with the specified organization's reference standard. Provide a complete system of telecommunications cabling and pathway components using star topology. Provide support structures and pathways, complete with outlets, cables, connecting hardware and telecommunications cabinets/racks. Cabling and interconnecting hardware and components for telecommunications systems shall be UL listed or third party independent testing laboratory certified, and shall comply with NFPA 70 and conform to the requirements specified herein.

2.2 TELECOMMUNICATIONS PATHWAY

Provide telecommunications pathways in accordance with TIA-569 and as specified in Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM. Provide system furniture pathways in accordance with UL 1286.

2.2.1 Pathways Aboard Camp Lejeune Greater Area, Including MCAS New River

Pathway shall be conduit, cable tray, or modular access flooring that provides protection for cabling. Under floor duct, free laying and wireway shall not be used. Cantilever-type center hung tray or Poke-Thru devices shall not be used. J-hooks/D-rings/bridal rings and other open face type cable pathways are not authorized except in minor renovations or to continue like existing system. Provide grounding and bonding as required by TIA-607. Cable tray wiring shall comply with NFPA 70. All conduits entering the communications room shall be grouped and consolidated. Conduits can be "Home Run" or stubbed to cable tray using approved pull boxes after every 180 degrees of bends or every 100 feet. All homerun conduits shall have insulated bonding bushings in the TR, and shall extend down from the ceiling to within 3 to 4 inches of the ladder rack, or 3 to 6 inches onto the backboard, and shall be bonded to the TMGB or TGB by a minimum 6 AWG green sheathed, copper stranded bonding conductor. All penetrations will be sealed in accordance with code (fire-stopping). A minimum of two 3 inch conduits overhead will be installed between the main communications room and other communication rooms (IDFs); if installed below slab they are considered OSP and will have a minimum of three 4-inch pathways; refer to Section 33 82 00.00 22 TELECOMMUNICATIONS, OUTSIDE PLANT (OSP). Distribution Enclosures shall not be used as a pull box and will only be approved for their intended use.

2.2.2 Work area Pathways

Comply with TIA-569, except minimum 1 1/4 inch diameter conduit shall be used. System furniture pathways shall comply with UL 1286. In system furniture that blocks access to or is distant from the communications wall outlets, each system furniture desk/cubical shall be equipped with listed manufacturer telecommunication raceway and outlets. All system furniture outlets shall be extended from a consolidation point (CP) to the system furniture outlet locations, and shall comply with TIA-568-C.1 through TIA-568-C.3. When office reconfiguration will be frequent, a multi-user terminal outlet assembly (MUTOA) may be used in lieu of a CP.

2.2.3 Pull Boxes

Pull boxes shall be constructed of galvanized sheet steel with

screw-fastened covers. Size pull boxes per TIA-569, except a 5 inches wide by 5 inches in length by 2 7/8 inches deep telecommunications box may be used for individual 1 1/4 inch diameter conduit runs. Provide pull boxes where length of conduit exceeds 100 feet or where more than 180 degree of cumulative bends occur. Align conduit ends on opposite sides of pull boxes as a straight pull through. Provide pull boxes in straight lengths of conduit only; direction changes in pull boxes are authorized. Electrical pull points, LC, LB, condulets, distribution enclosures, and splice boxes, are not pull boxes and are not authorized.

2.2.4 Consolidation Points

Consolidation Points (CP) shall be used when system furniture will be installed. CP's shall not support more than 12 work areas. CP's shall be centrally located permanent area, near the work area served, fully accessible, and should be located at least 50 feet from the FD when used for balanced twisted pair cabling. CP's shall be installed per TIA-569, except a S210 interface is required.

2.3 TELECOMMUNICATIONS OUTLET BOXES

Communications outlet boxes shall be placed in all work areas and any areas that can be converted to work areas. Work areas shall have an outlet connection within 6 feet'. Recommended practice is 6" to the left or right of (the outside edge of) each electrical outlet box in workable office areas or any area that could be converted into workable office area such as a large storage closet. Conference rooms should have one floor box and one box just above the ceiling. All administrative areas shall have a minimum of one ceiling mounted outlet box every 5,000 square feet of open administrative space for wireless LAN deployment. Additional boxes may be required where building composition prohibits wireless LAN coverage. Boxes shall be standard type 5 inches square by 2-7/8 inches deep with 1-1/4 inch diameter knock-outs, with a double gang to single gang reducer ring. Mount flush on finished walls/ceilings or just above ceiling tile for grid ceilings, height indicated by drawings. Outlet boxes for wall-mounted telephones shall be mounted at ADA required height. Outlet boxes for work counter area shall be mounted at a height 48 inches above finished floor, or other appropriate height as required. Install outlet boxes for security cameras, televisions, wall monitors, etc. at height indicated in drawings. Outlet boxes installed in floor shall be communications floor boxes large enough to support a surge of users with proper cable protection and ports that are in multiples of 4 and not parallel to the floor. For raised access flooring, boxes shall be below the floor with an access cover flush with the floor. Tombstones or boxes below floor that require removal of the floor panels to access are not allowed. Floor boxes and under slab cabling should not be used on the first floor or in wet areas; tele electric poles or furniture managed pathways fed from above the wet area should be used. Multi-user Telecommunications Outlet Assembly i.e. Multi-User Terminal Outlet Assemblies (MUTOA) should be placed where best suited for open office spaces may be frequently reconfigured.

2.4 TELECOMMUNICATIONS CABLING

Cabling shall be UL listed for the application and shall comply with TIA-568-C.0, TIA-568-C.1, TIA-568-C.2, TIA-568-C.3 and NFPA 70. Provide a labeling system in accordance with the manufacturer and local AHJ guidance for cabling as required by TIA-606 and UL 969. Confirm labeling is compatible with Camp Lejeune requirements. Ship cable on reels or in

boxes bearing manufacture date for unshielded/shielded twisted pair (UTP/STP) in accordance with ICEA S-90-661 and optical fiber cables in accordance with ICEA S-83-596 for all cable used on this project. Cabling manufactured more than 12 months prior to date of installation shall not be used.

2.4.1 Backbone Cabling

2.4.1.1 Backbone Copper

Copper backbone and riser cable shall be solid conductor, 24 AWG, 100 ohm, 25 to 100 -pair, Category 3, UTP, in accordance with ICEA S-90-661, TIA-568-C.1, TIA-568-C.2 and UL 444, formed into 25 pair binder groups covered with a gray thermoplastic jacket and overall metallic shield if required for additional protection. Cable shall be imprinted with manufacturers name or identifier, flammability rating, gauge of conductor, transmission performance rating (category designation) at regular length marking intervals in accordance with ICEA S-90-661. Sufficient pair count of CAT 3 or 5, as required shall be installed between the MDF and each of the IDF's. Provide plenum (CMP), riser (CMR), or non-jell filled indoor/outdoor communications rated cabling in accordance with NFPA 70. Substitution of a higher rated cable shall be permitted in accordance with NFPA 70. If under slab it is considered Outside Plant shall be installed per Section 33 82 00.00 22 TELECOMMUNICATIONS, OUTSIDE PLANT (OSP) with proper surge protection at both ends.

2.4.1.2 Backbone Optical Fiber

Provide in accordance with ICEA S-83-596, TIA-568-C.3, UL 1666 and NFPA 70. Cable shall be imprinted with fiber count, fiber type and aggregate length at regular intervals not to exceed 40 inches.

Provide the number of strands indicated, (but not less than 12 strands between the main telecommunication room and each of the other telecommunication rooms or secure racks), of single-mode(OS1), tight buffered fiber optic cable.

Provide tight buffered fiber optic multimode, 62.5/125-um diameter(OM1) cable, conforming to TIA-492AAAA as indicated (but not less than 12 strands of multimode between the main communication room and each of the other communications rooms and secure racks).

Provide plenum (OFNP), riser (OFNR), or general purpose (OFN or OFNG) rated non-conductive, fiber optic cable in accordance with NFPA 70. Substitution of a higher rated cable shall be permitted in accordance with NFPA 70. The cable cordage jacket, fiber, unit, and group color shall be in accordance with TIA/EIA-598.

Provide plenum (OFNP), riser (OFNR), or general purpose (OFN or OFNG) rated non-conductive, fiber optic cable in accordance with NFPA 70. Substitution of a higher rated cable shall be permitted in accordance with NFPA 70. The cable cordage jacket, fiber, unit, and group color shall be in accordance with TIA/EIA-598.

2.4.2 Horizontal Cabling

Provide horizontal cable in compliance with NFPA 70 and performance characteristics in accordance with TIA-568-C.1.

2.4.2.1 Horizontal Copper

Provide a minimum of four horizontal copper cables to each work area outlet (faceplate), minimum size 24 AWG conductors, 100 ohm, Category 6 or 6A, with green thermoplastic jacket for all unclassified outlets (color and cable type for classified services shall be in accordance with current CNSSAM TEMPEST RED/BLACK Installation documentation including Table 1 below) in accordance with TIA-568-C.2, UL 444, ANSI/NEMA WC 66, ICEA S-90-661. Cable shall be imprinted with manufacturers name or identifier, flammability rating, gauge of conductor, transmission performance rating (category designation) and length marking at regular intervals in accordance with ICEA S-90-661. Provide plenum (CMP), riser (CMR), or general purpose (CM or CMG) communications rated cabling in accordance with NFPA 70. Substitution of a higher rated cable shall be permitted in accordance with NFPA 70. Cables installed in conduit within and under slabs are not recommended but can be used if approved by local AHJ and shall be UL listed and labeled for wet locations in accordance with NFPA 70. Contact AHJ for special requirements on classified service, unofficial service, under slab cabling, using water block, and any item not covered in this document.

Communications CAT 6 twisted pair shall have a minimum of 12 inches of available slack at the communications outlet boxes. Minimum manufacturer's bend radius for each type of cable shall be maintained. All communications work area outlet boxes should have 4 cables to a double gang box (no rough in or empty conduit for future use allowed).

Table 1 - (U/FOUO) Cable Color Scheme

Classification Level	Cable Color
Unclassified	Green
Collateral Confidential	Blue
Collateral Secret	Red
Collateral Top Secret	Orange
Special Category	Yellow

2.4.2.2 Horizontal Optical Fiber

Provide optical fiber horizontal cable in accordance with ICEA S-83-596 and TIA-568-C.3. Cable shall be tight buffered, multimode, 62.5.125-um diameter, OM1 or single-mode, 8/125-um diameter, OS1. Cable shall be imprinted with manufacturer, flammability rating and fiber count at regular intervals not to exceed 40 inches.

Provide plenum (OFNP), riser (OFNR), or general purpose (OFN or OFNG) rated non-conductive, fiber optic cable in accordance with NFPA 70. Substitution of a higher rated cable shall be permitted in accordance with NFPA 70. Cables installed in conduit within and under slabs shall be UL listed and labeled for wet locations in accordance with NFPA 70. The cable jacket shall be of single jacket construction with color coding of cordage jacket, fiber, unit, and group in accordance with TIA/EIA-598.

2.4.3 Work Area Cabling (Equipment Cables)

2.4.3.1 Work Area Copper

Provide work area copper cable in accordance with TIA-568-C.2, with a green thermoplastic jacket for unclassified services (classified color code shall be in accordance with current CNSSAM TEMPEST RED/BLACK Installation documentation and Section 2.4.2.1 of this specification).

2.4.3.2 Work Area Optical Fiber

Provide optical work area cable in accordance with TIA-568-C.3.

2.5 TELECOMMUNICATIONS SPACES

Provide connecting hardware and termination equipment in the telecommunications entrance facility and telecommunication equipment rooms to facilitate installation as shown on design drawings for terminating and cross-connecting permanent cabling. Provide telecommunications interconnecting hardware color coding in accordance with TIA-606.

Space shall be a minimum 8' x 10' unless a local waiver is provided by the AHJ (authority having jurisdiction) which is the Telecommunications Support Division (TSD) aboard Camp Lejeune. Communications room could be much larger depending on building size, usable square footage served, and customer requirements. Communications rooms shall be centrally located unless there are multiple Communication rooms, and then each room should be centrally located within the area served. Communications Rooms shall not share or be on a wet wall. Generally, the space should be sized to approximately 1.1 percent of the area it serves. For example, a 10,000 sq feet (929 sq m) area should be served by a minimum of one 10 ft x 11 feet (3 m x 3.4 m) Communications room. Access to Rooms shall be from a common area such as a hallway and door shall swing out. Additional/Multiple communications rooms are required if the usable floor space to be served exceeds 10,000 square feet, or the cable length between the horizontal cross-connect and the communications outlet, including slack and vertical distance, exceeds 295 feet. Multiple communications rooms and IDF's shall be stacked and connected by a minimum of two way 3-inch conduits overhead. If under slab it is considered Outside Plant and 3 way 4" shall be used per Section 33 82 00.00 22 TELECOMMUNICATIONS, OUTSIDE PLANT (OSP) with proper surge protection at both ends. The minimum clear height in the room shall be 2.4 m (8 ft) without obstructions. The height between the finished floor and the lowest point of the ceiling should be a minimum of 3 m (10 ft) to accommodate overhead pathways. The flooring shall be sealed concrete to reduce dust and static electricity; no carpet or VCT tile. Two separate dedicated 20 amp electrical outlet will be installed above or behind but not attached to each communications equipment rack. Dedicated outlets and conduits shall be installed on the longest farthest wall from the door, same wall as the communications backboard. OSP conduits shall be to the far left of the communications backboard while facing it. There should not be an electrical panel within the communications room unless it serves only the room, and it should be located as close to the door as possible. The room requires a lockable door keyed or key padded to restrict access to MCIEAST-MCB G-6 personnel only. Room shall not have any windows or skylights. At least one wall, where the point of presence is located, and two adjacent walls should be covered with fire rated plywood backboard for mounting equipment;

additional boards may be needed for mounting additional equipment. Light, as measured within the communications room, should be a minimum of 500 lx (50 foot-candles). Lighting design should seek to minimize shadows within the telecommunications room (minimum two light fixtures). Equipment not related to the support of the communications room (e.g., piping, ductwork, pneumatic tubing) shall not be installed in, pass through, or enter the telecommunications room. Equipment related to the support of the communications room (e.g., piping, ductwork, HVAC drains, dedicated power) shall be installed in support of the communications equipment and not pose a drip/moisture/trip hazard and be usable as intended.

2.5.1 Backboards

Provide void-free, interior grade A-C plywood 3/4 inch thick 4 by 8 feet as indicated. Backboards shall be fire rated by manufacturing process. Fire stamp shall be clearly visible. Backboards shall be provided on a minimum of one telecom wall, two adjacent walls, and anywhere mounting is needed in the telecommunication spaces.

2.5.2 Equipment Support Frame

Provide in accordance with ECIA EIA/ECA 310-E and UL 50. Steel construction shall be treated to resist corrosion.

- a. Bracket, wall mounted (for buildings with very low jack/pair count and no secured electronic equipment requirement), 8 gauge aluminum minimum. Provide hinged bracket compatible with 19 inches panel mounting and must be in a secured communications room.
- b. Racks, wall or floor mounted modular type, 16 gauge steel construction minimum, treated to resist corrosion. Provide rack with vertical and horizontal cable management channels, top and bottom cable troughs, grounding lug and a surge protected power strip with 6 duplex 20 amp receptacles. Racks shall be large enough to support all telephone/data equipment required plus 25 percent spare and shall have a maximum of 7' height. Rack shall be compatible with 19 inches panel mounting and must be in a secured communications room.
- c. Cabinets, freestanding modular type, 16 gauge steel or 11 gauge aluminum construction minimum, treated to resist corrosion. Cabinet shall have removable and lockable side panels, front and rear doors, and have adjustable feet for leveling. All cabinets shall be keyed to current TSD key and large enough to support all telephone/data equipment required in the building plus 25% for future expansion. Dedicated electrical outlets should be installed within the cabinet. A backboard for mounting equipment is still needed when a cabinet is installed. Cabinet shall be mounted to the far right of the board to allow space for OSP cable, lightning protection, and bus bar to be installed on the board's far left. Dedicated power shall be within the cabinet on the backboard. Cabinet shall be vented in the roof and rear door. Cabinet shall have cable access in the roof and base and be compatible with 19 inches panel mounting. Provide cabinet with grounding bar, 550 CFM fan with filter and a surge protected power strip with 6 duplex 20 amp receptacles. All cabinets shall be keyed alike.
- d. Cabinets, wall-mounted modular type, 16 gauge steel or 11 gauge aluminum construction minimum, treated to resist corrosion. Cabinet shall have lockable front and rear doors, louvered side panels, 250 CFM

fan, ground lug, and top and bottom cable access. Cabinets shall be no smaller than 24"W X 48"H X 30"D, shall be keyed to current TSD key, and large enough to support all telephone/data equipment required in the building plus 25% for future expansion. Dedicated electrical outlets should be installed within the cabinet. A backboard for mounting equipment is still needed when a cabinet is installed. Cabinet shall be mounted to the far right of the board to allow space for OSP cable, lightning protection, and bus bar to be installed on the board's far left. Cabinet shall be compatible with 19 inches panel mounting. All cabinets shall be keyed alike. A surge protected power strip with 6 duplex 20 amp receptacles shall be provided within the cabinet.

2.5.3 Connector Blocks

Voice riser shall be terminated on angled insulation displacement connector (IDC), Type 110, 50 pair, 89D style mounted blocks, compatible with industry standard 110 blade punch down tool, designed for Category 3 and higher systems. Provide 50 pair blocks for the number of riser and backbone cables terminated plus 25 percent spare. Also provide sufficient blocks for cross connects for all IDFs. Blocks shall be mounted on an 89D style bracket on a frame, in rack or in cabinet.

2.5.4 Building Protector Assemblies

Building protector assembly is required on all OSP cables and shall have 710 type connector blocks for connection to the exterior cable at full capacity. M150-66 type IDC for connection to the voice cross connect blocks. 110 type IDC is not approved on building protector assembly. For Central office Area Distribution Nodes a R399 type central office protector shall be used.

2.5.5 Cable Guides

Provide cable guides specifically manufactured for the purpose of routing cables, wires and patch cords horizontally and vertically on 19 inches equipment racks, cabinets, and telecommunications backboards. Cable guides of ring or bracket type devices mounted on rack, cabinet, panels, and backboard for horizontal cable management and individually mounted for vertical cable management. Mount cable guides with screws, or nuts and lockwashers. Cable guides are not to be used outside of the communications room.

2.5.6 Patch Panels

Provide capacity for the number of horizontal and backbone cables terminated on the panel plus 25 percent spare. Provide factory terminated SC type SM optical fiber patch cables and factory terminated CAT 6 stranded copper patch cables for patch panels. Provide patch cords as complete assemblies of various appropriate lengths and with matching connectors and sheath color matched to network in Section 2.4.2.1. Provide fiber optic patch cables with crossover orientation in accordance with TIA-568-C.3. Patch cords shall meet minimum performance requirements specified in TIA-568-C.1, TIA-568-C.2 and TIA-568-C.3 for cables, cable length and hardware specified. Classified service may require shielded jack sets and panels as approved by AHJ.

2.5.6.1 Modular to 110 Block Patch Panel

Provide in accordance with TIA-568-C.1 and TIA-568-C.2. Panels shall be third party verified and shall comply with ANSI/TIA Category 6/6A requirements. Panel shall be constructed of 0.09 inches minimum aluminum and shall be cabinet/rack mounted and compatible with an ECIA EIA/ECA 310-E 19 inches equipment rack. Panel shall support connectors that comply with ANSI/TIA-568-C.2, Category 6 UTP requirements Connectors/Outlets shall be UL2043 listed, non-keyed, compatible with RJ-45 and RJ-11 plugs, glass-reinforced nylon housing, pass through mounting from the front or rear of the patch panel, with enclosed IDC termination and color-coded for both T568A and T568B wiring. Connectors shall be color matched to network type in Section 2.4.2.1 unless specified otherwise and approved by AHJ Each outlet/connector shall be terminated T568A. The rear of each panel shall have incoming cable strain-relief and routing guides. DO NOT USE ZIP TIES ON STRAIN-RELIEF GUIDES. Panels shall have each port factory numbered and be equipped with laminated plastic nameplates above each port. Labeling shall comply with Section 3.2 of this specification.

2.5.6.2 Fiber Optic Patch Panel

Provide panel for maintenance and cross-connecting of optical fiber cables. Panel shall be constructed of 16 or 18 gauge steel or 11 gauge aluminum minimum and shall be cabinet/rack mounted and compatible with a ECIA EIA/ECA 310-E 19 inches equipment rack. Each panel shall provide multimode/single-mode adapters as required in duplex SC in accordance with TIA/EIA-604-3 with zirconia ceramic alignment sleeves. Provide dust cover for unused adapters. The rear of each panel shall have a cable management tray a minimum of 8 inches deep with removable cover, incoming cable strain-relief and routing guides. Panels shall have each adapter factory numbered and be equipped with laminated plastic nameplates above each adapter. When populating the panel working left to right start with OSP feed, SM ISO to IDF, MM ISO to IDF, lastly row to row within same comm room.

2.5.7 Optical Fiber Distribution Panel

Cabinet/rack mounted optical fiber distribution panel (OFDP) shall be constructed in accordance with ECIA EIA/ECA 310-E utilizing 16 or 18 gauge steel or 11 gauge aluminum minimum. Panel shall be divided into two sections, distribution and user. Distribution section shall have strain relief, routing guides, splice tray and shall be lockable. User section shall have a cover for patch cord protection. Each panel shall provide multimode and single-mode pigtailed and adapters as required. Provide adapters as duplex SC with zirconia ceramic alignment sleeves. Provide dust covers for adapters. Provide patch cords as specified in the paragraph PATCH PANELS. When populating the panel working left to right start with OSP feed, SM ISO to IDF, MM ISO to IDF, lastly row to row within same communications room.

2.6 TELECOMMUNICATIONS OUTLET/CONNECTOR ASSEMBLIES

2.6.1 Outlet/Connector Copper

Outlet/connectors shall comply with FCC Part 68, TIA-568-C.1, and ANSI/TIA-568-C.2, Category 6 UTP requirements. Outlet/connectors shall be UL 2043 listed, non-keyed, compatible with RJ-45 and RJ-11 plugs, rated for 2500 plug mating cycles, glass-reinforced nylon housing, pass through mounting from the front or rear of the faceplate, with enclosed IDC

termination and color-coded for both T568A and T568B wiring. Connectors shall be color matched to network type in Section 2.4.2.1 unless specified otherwise and approved by AHJ. Each outlet/connector shall be terminated 568A. UTP outlet/connectors installed in outdoor or marine environments shall be rated for the environmental conditions.

2.6.2 Optical Fiber Adapters (Couplers)

Provide optical fiber adapters suitable for duplex SC in Accordance with TIA/EIA-604-3 with zirconia ceramic alignment sleeves, as indicated. Provide dust cover for adapters. Optical fiber adapters shall comply with TIA-455-21 for 500 mating cycles.

2.6.3 Optical Fiber Connectors

Provide in accordance with TIA-455-21. Optical fiber connectors shall be duplex SC in accordance with TIA/EIA-604-3 with zirconia ceramic ferrule, epoxyless crimp style compatible with 62.5/125 multimode and 8/125 single-mode fiber. The connectors shall provide a maximum attenuation of 0.3 dB at 850/1300 and 1310/1550 nm with less than a 0.2 dB change after 500 mating cycles.

2.6.4 Cover Plates

Telecommunications cover plates shall comply with UL 514C, and TIA-568-C.1, TIA-568-C.2, ; flush or oversized design constructed of high impact thermoplastic material, color to match the network color designation in Section 2.4.2.1, or as otherwise specified in Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM and authorized by the AHJ.. Provide labeling in accordance with the paragraph LABELING in this section. Additionally, outlet cover plate coloring shall be specified in design, and may be required to match the network color designation in Section 2.4.2.1 of this specification.

2.7 MULTI-USER TELECOMMUNICATIONS OUTLET ASSEMBLY (MUTOA)

Provide MUTOA(s) in accordance with TIA-568-C.1. Ensure proper separation from other networks and power.

For Modular Furniture, provide horizontal cabling from the MUTOA to an adaptor plate in the Modular Furniture. The MUTOA should be limited to serving a maximum of six work areas with 2 cables each for a total of 12 cables.

2.8 TERMINAL CABINETS

Construct of zinc-coated sheet steel, 36 by 24 by 6 inches deep, as indicated. Trim shall be fitted with hinged door and locking latch. Doors shall be maximum size openings to box interiors. Boxes shall be provided with 5/8 inch backboard with two-coat varnish finish. Match trim, hardware, doors, and finishes with panelboards. Provide label and identification systems for telecommunications wiring and components consistent with TIA-606.

2.9 GROUNDING AND BONDING PRODUCTS

Provide in accordance with UL 467, TIA-607, and NFPA 70. Components shall be identified as required by TIA-606. Provide ground rods, bonding conductors, and grounding busbars as specified in Section 26 20 00

INTERIOR DISTRIBUTION SYSTEM. The preferred ground for the Telephone Main Grounding Bus (TMGB) bar will be to the Main electrical Distribution Panel (MDP) bus bar and building steel. In most cases, but not all; a #6 AWG bonding conductor is recommended for telecommunications. All grounding and bonding conductors within the Telecommunications room will be green sheathed copper conductor, stranded, and labeled as suitable for use as such and tagged "DO NOT REMOVE". All grounding and bonding conductors running out of the Telecommunications room should be protected in conduit or attached to the outside of the cable tray and sized according to references. The minimum size of the TMGB shall be no smaller than 4" by 10" by 1/4 inch thick; bus bar should be factory made and factory drilled, not fabricated or drilled onsite. All bonding and grounding terminations shall be irreversible and secured with a double hole crimp termination. Do not exceed minimum bend radius on bonding and grounding conductors. Mount Bus Bar to far left of telecomm backboard at approximately 70" AFF.

2.10 FIRESTOPPING MATERIAL

Provide as specified in Section 07 84 00 FIRESTOPPING.

2.11 MANUFACTURER'S NAMEPLATE

Each item of equipment shall have a nameplate bearing the manufacturer's name, address, model number, and serial number securely affixed in a conspicuous place; the nameplate of the distributing agent will not be acceptable.

2.12 FIELD FABRICATED NAMEPLATES

ASTM D709. Provide laminated plastic nameplates for each equipment enclosure, relay, switch, and device; as specified or as indicated on the drawings. Each nameplate inscription shall identify the function and, when applicable, the position. Nameplates shall be melamine plastic, 0.125 inches thick, white with black center core. Surface shall be matte finish. Corners shall be square. Accurately align lettering and engrave into the core. Minimum size of nameplates shall be one by 2.5 inches. Lettering shall be a minimum of 0.25 inches high normal block style.

2.13 TESTS, INSPECTIONS, AND VERIFICATIONS

2.13.1 Factory Reel Tests

Provide documentation of the testing and verification actions taken by manufacturer to confirm compliance with TIA-568-C.1, TIA-568-C.2, TIA-568-C.3, TIA-526-7 for single mode optical fiber, and TIA-526-14 for multimode optical fiber cables.

PART 3 EXECUTION

3.1 INSTALLATION

Install telecommunications cabling and pathway systems, including the horizontal and backbone cable, pathway systems, telecommunications outlet/connector assemblies, and associated hardware in accordance with NECA/BICSI 568, TIA-568-C.1, TIA-568-C.2, TIA-568-C.3, TIA-569, NFPA 70, manufacturer instructions, current industry best practices, and UL standards as applicable. Provide cabling in a star topology network. Provide residential cabling in a star wiring architecture from the distribution device as required by TIA-570. Pathways and outlet boxes

shall be installed as specified in Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM. Standard type 5" x 5" x 2 7/8" square boxes with a single gang plaster ring shall be used except in concrete or concrete masonry units where a standard 4 11/16" square or a floor box will be used. Mount flush in finished walls at height indicated by drawings and with proper clearances from other networks and power systems. Depth of boxes shall be large enough to allow manufacturer's recommended conductor bend radii, normally 2 7/8" depth. Install telecommunications cabling with copper media in accordance with the following criteria to avoid potential electromagnetic interference between power and telecommunications equipment. The interference ceiling shall not exceed 3.0 volts per meter measured over the usable bandwidth of the telecommunications cabling (normal minimum clearance distances of 4 feet from motors, generators, frequency converters, transformers, x-ray equipment or uninterrupted power system, 300 mm (12 in) from power conduits and cable systems, 125 mm (5 inches) from fluorescent or high frequency lighting system fixtures). Cabling shall be run with horizontal and vertical cable guides in telecommunications spaces with terminating hardware and interconnection equipment.

3.1.1 Cabling

Install UTP/STP, and optical fiber telecommunications cabling system as detailed in TIA-568-C.1, TIA-568-C.2, TIA-568-C.3 and TIA-570 for residential cabling. Screw terminals shall not be used except where specifically indicated on plans. Use an approved insulation displacement connection (IDC) tool kit for copper cable terminations. Do not untwist Category 6 UTP cables more than 1/2" (12 mm) from the point of termination to maintain cable geometry. Provide service loop on each end of the cable, minimum 10' (3 meters) in the telecommunications room, 6" (150mm) in or close to the work area outlet for UTP. Do not exceed manufacturers' cable pull tensions for copper and optical fiber cables. Provide a device to monitor cable pull tensions. Do not exceed 25 pounds pull tension for four pair copper cables. Do not chafe or damage outer jacket materials. Use only lubricants approved by cable manufacturer. Do not over cinch cables, or crush cables with staples. Only hook and loop fasteners are allowed on Category 6/6A cable and optical fiber cable. DO NOT USE ZIP TIES. For UTP cable, bend radii shall not be less than four times the cable diameter. Cables shall be terminated; no cable shall contain unterminated elements (See NFPA 70 abandoned cabling). Cables shall not be spliced. Label cabling in accordance with paragraph LABELING in this section.

3.1.1.1 Open Cable

Use only where specifically indicated on plans or use in cable trays, or below raised floors in approved pathway (cable free laid on floor is not authorized). Install in accordance with TIA-568-C.1, TIA-568-C.2 and TIA-568-C.3. Do not exceed cable pull tensions recommended by the manufacturer. Copper cable not in a wireway or pathway shall be suspended a minimum of 8 inches above ceilings by cable supports no greater than 60 inches apart. Cable shall not be run through structural members or in contact with pipes, ducts, or other potentially damaging items. Placement of cable parallel to power conductors shall be avoided, if possible; a minimum separation of 12 inches shall be maintained when such placement cannot be avoided.

Plenum cable shall be used where open cables are routed through plenum areas. Cable routed exposed under raised floors shall be plenum rated.

Plenum cables shall comply with flammability plenum requirements of NFPA 70. Install cabling after the flooring system has been installed in raised floor areas. Cable 6 feet long shall be neatly coiled not less than 12 inches in diameter below each feed point in raised floor areas.

3.1.1.2 Backbone Cable

- a. Copper Backbone Cable. Install intrabuilding backbone copper cable, in minimum 2-way 3 inch overhead conduit or larger in indicated pathways, between the campus distributor, located in the telecommunications entrance facility or room, the building distributors and the floor distributors located in telecommunications rooms and telecommunications equipment rooms as indicated on drawings.
- b. Optical fiber Backbone Cable. Install intrabuilding backbone optical fiber in indicated pathways (normally in one of multiple inner ducts installed in conduit so as to maximize pathways). Do not exceed manufacturer's recommended bending radii and pull tension. Prepare cable for pulling by cutting outer jacket 10 inches leaving strength members exposed for approximately 10 inches. Twist strength members together and attach to pulling eye. Vertical cable support intervals shall be in accordance with manufacturer's recommendations.

3.1.1.3 Horizontal Cabling

Install horizontal cabling as indicated in the specification and on drawings. Do not untwist Category 6 UTP cables more than one half inch from the point of termination to maintain cable geometry. Provide slack cable in the form of a figure eight or large service loop on each end of the cable (prevent inductance caused by small coils), 10 feet in the telecommunications room, and 12 inches in the work area outlet.

3.1.2 Pathway Installations

Provide in accordance with TIA-569 and NFPA 70, except that 1 1/4 inch diameter conduit from cable tray or telecommunication room backboard to each work area outlet is required. Provide building pathway as specified in Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM.

Conceal conduit within finished walls, ceilings, and floors (not in wet areas). Keep conduit minimum 12 inches away from parallel runs of electrical power equipment, flues, steam, light ballast, and hot water pipes. Install conduit parallel with or at right angles to ceilings, walls, and structural members where located above accessible ceilings and where conduit is visible after completion of project. Run conduits in crawl spaces as if exposed. Install no more than two 90 degree bends for a single horizontal cable run. All bends/turns in conduits will be in straight runs of conduit; a pull box shall be installed after every 180 degrees of bends or 100'; in no case will a turn be made within a pull box. The minimum size for a pull box for a single 1 1/4" conduit will be 5" long by 5" wide by 2 7/8" deep, and for a 3" conduit 30"W x 54"L x 9"D. All conduits shall contain an insulated bushing at each end to protect the cable from damage and required bonding. Pull points, LC, LB, and condulets are not authorized.

Under floor cabling, under floor duct, and conduit under floor slabs should be avoided in the Camp Lejeune Greater area due to wet area close to coastal waters.

3.1.3 Service Entrance Conduit, Overhead

Provide service entrance overhead as specified in this section and Section 26 20 00 INTERIOR DISTRIBUTION SYSTEMS.

Ensure entrance fitting or weather head is sized to ensure min bend radius for largest cable is maintained.

3.1.4 Service Entrance Conduit, Underground

Provide service entrance underground as specified in this section and Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM.

Underground portion shall be encased in minimum of 3 inches of concrete extending from the building entrance to OSP demarcation point and shall be a minimum of 18 inches below slab or grade. Location of entrance conduit in communications room shall be to the left of the longest furthest wall from the door.

3.1.5 Cable Tray Installation

Install cable tray as specified in Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM. Only CMP and OFNP type cable shall be installed in a plenum.

A continuous stranded bonding conductor shall be run on the outside along the tray tapped to each section of tray with a listed connector to ensure bonding. Remove all sharps from cable tray and pathways. Ensure bonding is on the pathway so as not to obstruct horizontal cabling. Maintain proper clearance and work space per TIA-569 and TEMPEST.

3.1.6 Work Area Outlets

3.1.6.1 Terminations

Terminate UTP cable in accordance with TIA-568-C.1, TIA-568-C.2 and wiring configuration as specified. Terminate fiber optic cables in accordance with TIA-568-C.3.

All work areas will contain a minimum of two work area outlets . Any work area larger than 80 sq feet will require additional work area outlets to service any work location in the room within 6 feet of an electrical outlet. This also applies to any area that could be converted to work space in the future. Recommend one work area outlet box be placed 6" to the left or right of every electrical outlet in a usable space. All work area face plates shall contain four category 6 jacks as specified herein, terminated T568A configuration unless otherwise approved by AHJ. MUTOAs contain 12 cables and may require additional clearance and power. All other outlets shall contain a minimum of 2 Category six jacks, with the exception of single jack wall phone studded faceplates.

3.1.6.2 Cover Plates

As a minimum, each outlet/connector shall be labeled as to its function and a unique number to identify cable link in accordance with the paragraph LABELING in this section. (For secured networks contact AHJ as shielded twisted pair and color coded face plates may be necessary.)

3.1.6.3 Cables

Unshielded/shielded twisted pair and fiber optic cables shall have a minimum of 12 inches of available service slack loosely coiled into the telecommunications outlet boxes or in cable tray as close as possible to outlet box. Minimum manufacturer's bend radius for each type of cable shall not be exceeded.

3.1.6.4 Pull Cords

Pull cords shall be installed in conduit serving telecommunications outlets that do not have cable installed (this is not normal as all outlets should be cabled).

3.1.6.5 Multi-User Telecommunications Outlet Assembly (MUTOA)

Run horizontal cable per specifications and terminate cables in a MUTOA in each system furniture zone. MUTOAs shall not be located in ceiling spaces, or any obstructed area. MUTOAs shall not be installed in furniture unless that unit of furniture is permanently secured to the building structure. MUTOAs shall be located in an open work area so that each furniture cluster is served by at least one MUTOA. The MUTOA shall be limited to serving a maximum of six work areas with 2 cables each for a total of 12 cables/12 ports. Maximum work area cable length requirements shall also be taken into account. MUTOAs must be labeled to include the maximum length of work area cables. MUTOA labeling is in addition to the labeling described in TIA-606, or other applicable cabling administration standards. Work area cables extending from the MUTOA to the work area device must also be uniquely identified and labeled.

3.1.7 Telecommunications Space Termination

Install termination hardware required for Category 6 and optical fiber system. A single punch manufacture approved insulation displacement tool shall be used for terminating copper cable to insulation displacement connectors.

3.1.7.1 Connector Blocks

Connector blocks shall be cabinet/rack mounted, as approved by the AHJ, in orderly rows and columns. Adequate vertical and horizontal wire routing areas shall be provided between groups of blocks. Install in accordance with industry standard wire routing guides in accordance with TIA-569.

3.1.7.2 Patch Panels

Patch panels shall be mounted in equipment cabinets/racks with sufficient ports to accommodate the installed cable plant plus 25 percent spares.

- a. Copper Patch Panel. Copper cable entering a patch panel shall be secured to a rear cable manager with hook and loop ties as recommended by the manufacturer to prevent movement of the cable.
- b. Fiber Optic Patch Panel. Fiber optic cable loop shall be 3 feet in length provided as recommended by the manufacturer. The outer jacket of each cable entering a patch panel shall be secured to the panel to prevent movement of the fibers within the panel, using clamps or brackets specifically manufactured for that purpose.

3.1.7.3 Equipment Support Frames

Install in accordance with TIA-569:

- a. Bracket, wall mounted. Mount bracket to right on plywood backboard in accordance with manufacturer's recommendations. Mount rack so height of highest panel does not exceed 78 inches above floor. Mount so there is sufficient space remaining on backboard to mount lightning protection, bonding, and cable managers or install additional backboards.
- b. Racks, floor mounted modular type. Permanently anchor rack to the floor in accordance with manufacturer's recommendations. Install sections of ladder rack anchored to telephone rack/cabinet and at least two walls.
- c. Cabinets, freestanding modular type. Permanently anchor to the floor in accordance with manufacturer's recommendations. When cabinets are connected together, remove adjoining side panels for cable routing between cabinets. Mount rack mounted fan and 19" power/surge strip in cabinet. Install sections of ladder rack anchored to telephone rack/cabinet and at least two walls.
- d. Cabinets, wall-mounted modular type. Mount cabinet to right on plywood backboard in accordance with manufacturer's recommendations. Mount cabinet so height of highest panel does not exceed 78 inches above floor. Mount so there is sufficient space remaining on backboard to mount lightning protection, bonding, and cable managers or install additional backboards.

3.1.8 Electrical Penetrations

Seal openings around electrical penetrations through fire resistance-rated wall, partitions, floors, or ceilings as specified in Section 07 84 00 FIRESTOPPING.

3.1.9 Grounding and Bonding

Provide in accordance with TIA-607, NFPA 70 and as specified in this section and Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM except only two hole irreversible compression lugs will be accepted.

3.2 LABELING

3.2.1 Labels

Provide labeling in accordance with TIA-606 except jacks will be numbered in a logical, sequential, clockwise numbering system from 1 to X with a closet designator. Example would be 145 C 146, would be the 145th & 146th jacks from the C telecom room. All labels shall be numbered with manufacturer's labeling system (not fabricated) and be equipped with laminated plastic cover. All terminations that are not to work area outlets should be in the last patch panel locations and labeled accordingly i.e. DDC, FACP, Elevator, Wall phones, or Wireless access points.

3.2.2 Cable

Cables shall be labeled using color labels on both ends with identifiers

in accordance with TIA-606.

3.2.3 Termination Hardware

Workstation outlets and patch panel connections shall be labeled using manufacturing labeling system, color coded labels with identifiers in accordance with this section and TIA-606. Coordinate with Base Telephone.

3.3 FIELD APPLIED PAINTING

Paint electrical equipment as required to match finish of adjacent surfaces or to meet the indicated or specified safety criteria. Painting shall be as specified in Section 09 90 00 PAINTS AND COATINGS.

3.3.1 Painting Backboards

Camp Lejeune no longer paints backboards as fire rated plywood is available. Manufactured fire retardant backboard shall be used, so as not to increase flame spread and smoke density and must be appropriately labeled.

3.4 FIELD FABRICATED NAMEPLATE MOUNTING

Provide number, location, and letter designation of nameplates as indicated. Fasten nameplates to the device with a minimum of two sheet-metal screws or two rivets.

3.5 TESTING

3.5.1 Telecommunications Cabling Testing

Perform telecommunications cabling inspection, verification, and performance tests on both Backbone and Horizontal cabling in accordance with TIA-568-C.1, TIA-568-C.2, TIA-568-C.3 and AHJ local guidance. Test equipment shall conform to TIA-1152. Perform optical fiber field inspection tests via attenuation measurements on factory reels and provide results along with manufacturer certification for factory reel tests. Remove failed cable reels from project site upon attenuation test failure.

3.5.1.1 Inspection

Visually inspect all telecommunications cabling jacket materials for UL or third party certification markings. Inspect cabling terminations in telecommunications rooms and at workstations to confirm color code for T568A pin assignments, and inspect cabling connections to confirm compliance with TIA-568-C.1, TIA-568-C.2, TIA-568-C.3, and TIA-570 for residential cabling. Visually confirm Category 6 marking of outlets, cover plates, outlet/connectors, cable physical damage, and patch panels.

3.5.1.2 Verification Tests

Backbone copper cabling shall be tested for DC loop resistance, shorts, opens, intermittent faults, and polarity between conductors, and between conductors and shield, if cable has overall shield. Test operation of shorting bars in connection blocks. Test cables after all terminations are complete but prior to being cross-connected.

For multimode optical fiber, perform optical fiber end-to-end attenuation tests in accordance with TIA-568-C.3 and TIA-526-14 using Tier 1 Option

with power meter and light source for optical fiber. Validate/troubleshoot failures with Tier 2 Option. For single-mode optical fiber of sufficient distance (normally OSP), perform optical fiber end-to-end attenuation tests in accordance with TIA-568-C.3 and TIA-526-7 using Tier 2 Option, OTDR for single-mode optical fiber. Perform verification acceptance tests.

3.5.1.3 Performance Tests

Provide summary in .pdf (hard and soft copy) detailed tester results in test format .flw (soft copy only), and fiber power meter/OTDR reports (summary hard copy and detailed soft copy). All Test reports should have a building or project number on it. The final QC and certification of installation will be performed by TSD after the contractor has provided passing and acceptable test results matching work area outlet labels, as-built drawings showing all telecommunications outlets and their labeled designator to include any empty conduit or ports coiled in overhead for future use and all building automated system ports such as DDC, Elevator, FACP, or WAPs. Test results that are marginal may not be accepted. Also fiber tests that pass the link budget but exceed tolerance on any connector or splice are considered a failure. All discrepancies must be repaired and retested.

Perform testing for each outlet and MUTOA as follows:

- a. Perform Category 6 link tests in accordance with TIA-568-C.1 and TIA-568-C.2. Tests shall include wire map, length, insertion loss, NEXT, PSNEXT, ELFEXT, PSELFEXT, return loss, propagation delay, and delay skew.
- b. Optical fiber Links. Perform optical fiber end-to-end link tests in accordance with TIA-568-C.3.

3.5.1.4 Final Verification Tests

Perform verification tests for all copper and optical fiber systems after the complete telecommunications cabling and workstation outlet/connectors are installed.

- a. Voice Tests. These tests assume that dial tone service has been installed (normally only done for FACP, Elevator, or emergency phones). Connect to the network interface device at the demarcation point. Go off-hook and listen and receive a dial tone. If a test number is available, make and receive a local, long distance, and DSN telephone call.
- b. Data Tests. These tests assume the Information Technology Staff has a network installed and are available to assist with testing (normally this is only done for VTC, CCTV). Connect to the network interface device at the demarcation point. Log onto the network to ensure proper connection to the network.

-- End of Section --

SECTION 28 31 76

INTERIOR FIRE ALARM AND MASS NOTIFICATION SYSTEM, ADDRESSABLE
08/20

PART 1 GENERAL

1.1 REFERENCES

The publications listed below form a part of this specification to the extent referenced. The publications are referred to within the text by the basic designation only.

ACOUSTICAL SOCIETY OF AMERICA (ASA)

ASA S3.2 (2009; R 2014) Method for Measuring the Intelligibility of Speech Over Communication Systems (ASA 85)

ASME INTERNATIONAL (ASME)

ASME A17.1/CSA B44 (2019) Safety Code for Elevators and Escalators

ASTM INTERNATIONAL (ASTM)

ASTM F402 (2005; R 2012) Safe Handling of Solvent Cements, Primers, and Cleaners Used for Joining Thermoplastic Pipe and Fittings

FM GLOBAL (FM)

FM APP GUIDE (updated on-line) Approval Guide
<http://www.approvalguide.com/>

INSTITUTE OF ELECTRICAL AND ELECTRONICS ENGINEERS (IEEE)

IEEE C62.41.1 (2002; R 2008) Guide on the Surges Environment in Low-Voltage (1000 V and Less) AC Power Circuits

IEEE C62.41.2 (2002) Recommended Practice on Characterization of Surges in Low-Voltage (1000 V and Less) AC Power Circuits

NATIONAL FIRE PROTECTION ASSOCIATION (NFPA)

NFPA 4 (2018) Standard for Integrated Fire Protection and Life Safety System Testing

NFPA 70 (2020; ERTA 20-1 2020; ERTA 20-2 2020; TIA 20-1; TIA 20-2; TIA 20-3; TIA 20-4) National Electrical Code

NFPA 72 (2019; TIA 19-1; ERTA 1 2019) National Fire Alarm and Signaling Code

NFPA 90A (2021) Standard for the Installation of Air Conditioning and Ventilating Systems

NFPA 170 (2018) Standard for Fire Safety and Emergency Symbols

U.S. DEPARTMENT OF DEFENSE (DOD)

UFC 3-601-02 (2010) Operations and Maintenance: Inspection, Testing, and Maintenance of Fire Protection Systems

UFC 4-010-06 (2016; with Change 1, 2017) Cybersecurity of Facility-Related Control Systems

U.S. NATIONAL ARCHIVES AND RECORDS ADMINISTRATION (NARA)

47 CFR 15 Radio Frequency Devices

47 CFR 90 Private Land Mobile Radio Services

UNDERWRITERS LABORATORIES (UL)

UL 228 (2006; Reprint Nov 2008) Door Closers-Holders, With or Without Integral Smoke Detectors

UL 268 (2016; Reprint Oct 2019) UL Standard for Safety Smoke Detectors for Fire Alarm Systems

UL 268A (2008; Reprint Oct 2014) Smoke Detectors for Duct Application

UL 464 (2016; Reprint Sep 2017) UL Standard for Safety Audible Signaling Devices for Fire Alarm and Signaling Systems, Including Accessories

UL 497A (2001; Bul. 2019) UL Standard for Safety Secondary Protectors for Communications Circuits

UL 497B (2004; Reprint Dec 2012) Protectors for Data Communication Circuits

UL 521 (1999; Reprint Dec 2017) UL Standard for Safety Heat Detectors for Fire Protective Signaling Systems

UL 864 (2014; Reprint May 2020) UL Standard for Safety Control Units and Accessories for Fire Alarm Systems

UL 1283 (2017) UL Standard for Safety Electromagnetic Interference Filters

UL 1449 (2014; Reprint Jul 2017) UL Standard for Safety Surge Protective Devices

- UL 1480 (2016; Reprint Sep 2017) UL Standard for Safety Speakers for Fire Alarm and Signaling Systems, Including Accessories
- UL 1638 (2016; Reprint Sep 2017) UL Standard for Safety Visible Signaling Devices for Fire Alarm and Signaling Systems, Including Accessories
- UL 1971 (2002; Reprint Oct 2008) Signaling Devices for the Hearing Impaired
- UL 2034 (2017; Reprint Sep 2018) UL Standard for Safety Single and Multiple Station Carbon Monoxide Alarms
- UL 2075 (2013; Bul. 2019) UL Standard for Safety Gas and Vapor Detectors and Sensors
- UL 2572 (2016; Bul. 2018) UL Standard for Safety Mass Notification Systems
- UL Fire Prot Dir (2012) Fire Protection Equipment Directory

1.2 RELATED SECTIONS

Section 25 05 11 Cybersecurity for Facility-Related Control Systems, applies to this section, with the additions and modifications specified herein. In addition, refer to the following sections for related work and coordination:

- [Section 21 13 13 WET PIPE SPRINKLER SYSTEM, FIRE PROTECTION]
- [Section 21 30 00 FIRE PUMPS]
- [Section 21 23 00.00 20 WET CHEMICAL FIRE EXTINGUISHING for KITCHEN CABINET]
- [Section 21 13 16 DRY PIPE FIRE SPRINKLER SYSTEMS]
- [Section 21 13 18 PREACTION FIRE SPRINKLER SYSTEMS]
- [Section 21 13 19 DELUGE FIRE SPRINKLER SYSTEMS]
- [Section 23 30 00 HVAC AIR DISTRIBUTION]
- [Section 21 13 24.00 10 AQUEOUS FILM-FORMING FOAM (AFFF) FIRE PROTECTION SYSTEM]
- [Section 21 13 25 HIGH-EXPANSION FOAM SYSTEM, FIRE PROTECTION]
- [Section 21 13 20.00 20 FOAM FIRE EXTINGUISHING FOR AIRCRAFT HANGARS]
- [Section 21 13 21.00 20 FOAM FIRE EXTINGUISHING FOR FUEL TANK PROTECTION]
- [Section 21 13 22.00 20 FOAM FIRE EXTINGUISHING FOR HAZ/FLAM MATERIAL FACILITY]
- [Section 21 21 01.00 20 CARBON DIOXIDE FIRE EXTINGUISHING (HIGH PRESSURE)]
- [Section 21 21 02.00 20 CARBON DIOXIDE FIRE EXTINGUISHING (LOW PRESSURE)]
- [Section 21 21 03.00 10 WET CHEMICAL FIRE EXTINGUISHING SYSTEM]
- [Section 08 71 00 DOOR HARDWARE for [door release][door unlocking] and additional work related to finish hardware.]
- [Section[s] [14 21 13 ELECTRIC TRACTION FREIGHT ELEVATORS] [14 21 23 ELECTRIC TRACTION PASSENGER ELEVATORS] [and] [14 24 13 HYDRAULIC FREIGHT ELEVATORS] [14 24 23 HYDRAULIC PASSENGER ELEVATORS] for additional work related to elevators.]

[Section 07 84 00 FIRESTOPPING for additional work related to firestopping.]

1.3 SUMMARY

1.3.1 Scope

- a. This work includes designing and [providing a new, complete,][modifying the existing] fire alarm and mass notification (MNS) system as described herein and on the contract drawings[for the _____]. Include system wiring, raceways, pull boxes, terminal cabinets, outlet and mounting boxes, control equipment, initiating devices, notification appliances, supervising station fire alarm transmitters/mass notification transceiver, and other accessories and miscellaneous items required for a complete operational system even though each item is not specifically mentioned or described. Provide system[s] complete and ready for operation.[Existing interior fire alarm system was manufactured by [____].] Design and installation must comply with UFGS 25 05 11, UFC 4-010-06 and AFGM 2019-320-02.
- b. Provide equipment, materials, installation, workmanship, inspection, and testing in strict accordance with NFPA 72, except as modified herein. [The system layout on the drawings show the intent of coverage and suggested locations. Final quantity, system layout, and coordination are the responsibility of the Contractor.]
- [c. Each remote fire alarm control unit must be powered from a wiring riser specifically for that use or from a local emergency power panel located on the same floor as the remote fire alarm control unit. Where remote fire control units are provided, equipment for notification appliances may be located in the remote fire alarm control units.]
- [d. Where a fire pump is provided, the fire alarm and mass notification system must monitor and transmit the fire pump controller signals in accordance with the provisions of NFPA 72.]
- [e. Where an emergency generator provides standby power supply for life safety system circuits, the generator must be monitored by the FMCU and transmit emergency generator signals in accordance with NFPA 72.]
- f. The fire alarm and mass notification system must be independent of the building security, building management, and energy/utility monitoring systems other than for control functions.

1.3.2 Qualified Fire Protection Engineer (QFPE)

Services of the QFPE must include:

- a. Reviewing SD-02, SD-03, and SD-05 submittal packages for completeness and compliance with the provisions of this specification. Construction (shop) drawings and calculations must be prepared by, or prepared under the immediate supervision of, the QFPE. The QFPE must affix their professional engineering stamp with signature to the shop drawings, calculations, and material data sheets, indicating approval prior to submitting the shop drawings to the DFPE.
- b. Providing a letter documenting that the SD-02, SD-03, and SD-05 submittal package has been reviewed and noting any outstanding

comments.

- c. Performing in-progress construction surveillance prior to installation of ceilings (rough-in inspection).
- d. Witnessing pre-Government [and final Government]functional performance testing and performing a final installation review.
- e. Signing applicable certificates under SD-07.

1.4 DEFINITIONS

Wherever mentioned in this specification or on the drawings, the equipment, devices, and functions must be defined as follows:

1.4.1 Interface Device

An addressable device that interconnects hard wired systems or devices to an analog/addressable system.

1.4.2 Fire Alarm and Mass Notification Control Unit (FMCU)

A master control unit having the features of a fire alarm control unit (FACU) and an autonomous control unit (ACU) where these units are interconnected to function as a combined fire alarm/mass notification system. The FACU and ACU functions may be contained in a single cabinet or in independent, interconnected, and co-located cabinets.

1.4.3 Remote Fire Alarm and Mass Notification Control Unit

A control unit, physically remote from the fire alarm and mass notification control unit, that receives inputs from automatic and manual fire alarm devices; may supply power to detection devices and interface devices; may provide transfer of power to the notification appliances; may provide transfer of condition to relays or devices connected to the control unit; and reports to and receives signals from the fire alarm and mass notification control unit.

1.4.4 Local Operating Console (LOC)

A unit designed to allow emergency responders and/or building occupants to operate the MNS including delivery of recorded messages and/or live voice announcements, initiate visual, textual visual, and audible appliance operation and other relayed functions.

1.4.5 Terminal Cabinet

A steel cabinet with locking, hinge-mounted door where terminal strips are securely mounted inside the cabinet.

1.4.6 Control Module and Relay Module

Terms utilized to describe emergency control function interface devices as defined by NFPA 72.

1.4.7 Designated Fire Protection Engineer (DFPE)

The DoD fire protection engineer that oversees that Area of Responsibility for that project. This is sometimes referred to as the "cognizant" fire

protection engineer. Interpret reference to "authority having jurisdiction" and/or AHJ in referenced standards to mean the Designated Fire Protection Engineer (DFPE). The DFPE may be responsible for review of the contractor submittals having a "G" designation, and for witnessing final inspection and testing.

1.4.8 Qualified Fire Protection Engineer (QFPE)

A QFPE is an individual who is a licensed professional engineer (P.E.), who has passed the fire protection engineering written examination administered by the National Council of Examiners for Engineering and Surveying (NCEES) and has relevant fire protection engineering experience.

1.5 SUBMITTALS

Government approval is required for submittals with a "G" designation; submittals not having a "G" designation are for [Contractor Quality Control approval.][information only.] When used, a designation following the "G" designation identifies the office that will review the submittal for the Government. Submittals with an "S" are for inclusion in the Sustainability eNotebook, in conformance to Section 01 33 29 SUSTAINABILITY REPORTING.

Shop drawings (SD-02), product data (SD-03) and calculations (SD-05) must be prepared by the fire alarm designer and combined and submitted as one complete package. The QFPE must review the SD-02/SD-03/SD-05 submittal package for completeness and compliance with the Contract provisions prior to submission to the Government. The QFPE must provide a Letter of Confirmation that they have reviewed the submittal package for compliance with the contract provisions. This letter must include their registered professional engineer stamp and signature. Partial submittals and submittals not reviewed by the QFPE will be returned by the Government disapproved without review.

Submit the following in accordance with Section 01 33 00 SUBMITTAL PROCEDURES:

SD-01 Preconstruction Submittals

Qualified Fire Protection Engineer (QFPE); G[, [_____]]

Fire alarm system designer; G[, [_____]]

Supervisor; G[, [_____]]

Technician; G[, [_____]]

Installer; G[, [_____]]

Test Technician; G[, [_____]]

Fire Alarm System Site-Specific Software Acknowledgement; G[, [_____]]

SD-02 Shop Drawings

Nameplates; G[, [_____]]

Instructions; G[, [_____]]

Wiring Diagrams; G[, [_____]]

System Layout; G[, [_____]]

Notification Appliances; G[, [_____]]

Initiating devices; G[, [_____]]

Amplifiers; G[, [_____]]

Battery Power; G[, [_____]]

Voltage Drop Calculations; G[, [_____]]

SD-03 Product Data

Fire Alarm and Mass Notification Control Unit (FMCU); G[, [_____]]

Local Operating Console (LOC); G[, [_____]]

Amplifiers; G[, [_____]]

Tone Generators; G[, [_____]]

Digitalized voice generators; G[, [_____]]

[Video Display Unit (VDU); G[, [_____]]]

LCD Annunciator; G[, [_____]]

Manual Stations; G[, [_____]]

Smoke Detectors; G[, [_____]]

Duct Smoke Detectors; G[, [_____]]

[Projected Beam Smoke Detector; G[, [_____]]]

[Air sampling smoke detectors; G[, [_____]]]

Heat Detectors; G[, [_____]]

[Flame Detectors; G[, [_____]]]

[Multi-Criteria Detectors; G[, [_____]]]

Carbon monoxide detector; G[, [_____]]

Addressable Interface Devices; G[, [_____]]

Addressable Control Modules; G[, [_____]]

Isolation Modules; G[, [_____]]

Notification Appliances; G[, [_____]]

Textual Display Sign Control Panel; G[, [_____]]

- Textual Display Signs; G[, [_____]]
- Batteries; G[, [_____]]
- Battery Chargers; G[, [_____]]
- [Supplemental Notification Appliance Circuit Panels; G[, [_____]]]
- [Auxiliary Power Supply Panels; G[, [_____]]]
- Surge Protective Devices; G[, [_____]]
- Alarm Wiring; G[, [_____]]
- [Back Boxes and Conduit; G[, [_____]]]
- [Ceiling Bridges for Ceiling-Mounted Appliances; G[, [_____]]]
- Terminal Cabinets; G[, [_____]]
- Digital Alarm Communicator Transmitter (DACT); G[, [_____]]
- [Automatic Fire Alarm Transmitters (including housing); G[, [_____]]
-]
- [Radio Transmitter and Interface Panels; G[, [_____]]]
- [Mass Notification Transceiver; G[, [_____]]]
- Electromagnetic Door Holders; G[, [_____]]
- Environmental Enclosures or Guards; G[, [_____]]
- [Firefighter Telephone; G[, [_____]]]
- [Printer; G[, [_____]]]
- Document Storage Cabinet; G[, [_____]]

SD-05 Design Data

- [Air Sampling Smoke Detection System Calculations; G[, [_____]]
-]

SD-06 Test Reports

- Test Procedures; G[, [_____]]

SD-07 Certificates

- Verification of Compliant Installation; G[, [_____]]
- Request for Government Final Test; G[, [_____]]

SD-10 Operation and Maintenance Data

- Operation and Maintenance (O&M) Instructions; G[, [_____]]
- Instruction of Government Employees; G[, [_____]]

SD-11 Closeout Submittals

As-Built Drawings

Spare Parts

1.6 SYSTEM OPERATION

Fire alarm system/mass notification system including textual display sign control panel(s), components requiring power, except for the FMCU(s) power supply, must operate on 24 volts DC unless noted otherwise in this section.

The interior fire alarm and mass notification system must be a complete, supervised, noncoded, analog/addressable fire alarm and mass notification system conforming to NFPA 72, UL 864, and UL 2572. Systems meeting UL 2017 only are not acceptable. The system must be activated into the alarm mode by actuation of an alarm initiating device. The system must remain in the alarm mode until the initiating device is reset and the control unit is reset and restored to normal. The system may be placed in the alarm mode by local microphones, LOC, FMCU, or remotely from authorized locations/users.

[Provide the system with an interconnected riser loop or network having Class [A][X] supervision. Ensure that the return portion of the loop is remote from the supply portion of the loop.][Where the building has two stairs for egress from floors above grade or floors below grade, ensure that a single impairment cannot adversely affect more than one floor. Where three or more stairs are provided for egress from floors above grade or below grade, ensure that a single impairment cannot adversely affect more than one-half of any floor.][Ensure that any single impairment of the system does not affect the system on more than [one][one-half] of any floor.]

1.6.1 Alarm Initiating Devices and Notification Appliances (Visual, Voice, Textual)

- a. Connect alarm initiating devices to initiating device circuits (IDC) [Class "A"][Class "B"], or to signaling line circuits (SLC) Class ["A"]["B"]["X"] and installed in accordance with NFPA 72.
- b. Connect notification appliances to notification appliance circuits (NAC) [Class "A"][Class "B"].

1.6.2 Functions and Operating Features

The system must provide the following functions and operating features:

- a. Power, annunciation, supervision, and control for the system. Addressable systems must be microcomputer (microprocessor or microcontroller) based with a minimum word size of eight bits with sufficient memory to perform as specified.
- b. Visual alarm notification appliances must be synchronized as required by NFPA 72.
- c. Electrical supervision of the primary power (AC) supply, presence of the battery, battery voltage, and placement of system modules within the control unit.

- d. An audible and visual trouble signal to activate upon a single break or open condition, or ground fault[(or short circuit for Class "X")]. The trouble signal must also operate upon loss of primary power (AC) supply, absence of a battery supply, low battery voltage, or removal of alarm or supervisory control unit modules. After the system returns to normal operating conditions, the trouble signal must again sound until the trouble is acknowledged. A smoke detector in the process of being verified for the actual presence of smoke must not initiate a trouble condition.
- e. A trouble signal silence feature that must silence the audible trouble signal, without affecting the visual indicator.
- f. Program capability via switches in a locked portion of the FMCU to bypass the automatic notification appliance circuits, [fire reporting system][air handler shutdown][smoke control operation][elevator recall][door release][door unlocking] features. Operation of this programmed action must indicate on the FMCU display[and printer output] as a supervisory or trouble condition.[Notification appliance bypass must be selectable by floor.]
- g. Alarm functions must override trouble or supervisory functions. Supervisory functions must override trouble functions.
- h. The system must be capable of being programmed from the control unit keyboard. Programmed information must be stored in non-volatile memory.
- i. The system must be capable of operating, supervising, and/or monitoring non-addressable alarm and supervisory devices.
- j. There must be no limit, other than maximum system capacity, as to the number of addressable devices that may be in alarm simultaneously.
- k. Where the fire alarm/mass notification system is responsible for initiating an action in another emergency control device or system, such as [HVAC,][atrium exhaust,][smoke control,][elevator recall,][releasing service,]the addressable fire alarm relay must be located in the vicinity of the emergency control device.
- l. An alarm signal must automatically initiate the following functions:
 - (1) Transmission of an alarm signal to [the fire department][a remote supervising station].
 - (2) Visual indication of the device operated on the FMCU, [Video Display unit (VDU),] [and on the [graphic][remote]annunciator].[Indication on the graphic annunciator must be by floor, zone or circuit, and type of device.]
 - [(3) Record the event on the system printer.]
 - (4) Actuation of alarm notification appliances.
 - (5) Recording of the event electronically in the history log of the FMCU.
 - [(6) Release of doors held open by electromagnetic devices.]

- [(7) Operation of the [smoke control system][atrium exhaust system].]
 - [(8) Release of power to electric locks (delayed egress locks) on doors that are part of the means of egress.]
 - [(9) Elevator recall as described in this section.]
 - [(10) Operation of [_____] must release the [_____] fire extinguishing system after a [_____] second time delay.]
 - [(11) Operation of a sprinkler waterflow switch serving an elevator machinery room or elevator shaft must operate shunt trip circuit breaker(s) to shut down power to the elevators in accordance with ASME A17.1/CSA B44.]
 - [(12) Operation of an interface that operates vibrating pagers worn by hearing-impaired occupants.]
- m. A supervisory signal must automatically initiate the following functions:
- (1) Visual indication of the device operated on the FMCU, [Video Display unit (VDU),] [and on the [graphic][remote]annunciator]. [Indication on the graphic annunciator must be by floor, zone or circuit, and type of device.]
 - [(2) Record the event on the system printer.]
 - (3) Transmission of a supervisory signal to [the fire department][a remote supervising station].
 - (4) Operation of a duct smoke detector must shut down the appropriate air handler in accordance with NFPA 90A in addition to other requirements of this paragraph and as allowed by NFPA 72.
 - (5) Recording of the event electronically in the history log of the FMCU.
- n. A trouble condition must automatically initiate the following functions:
- (1) Visual indication of the device operated on the FMCU, [Video Display unit (VDU),] [and on the [graphic][remote]annunciator]. [Indication on the graphic annunciator must be by floor, zone or circuit, and type of device.]
 - [(2) Record the event on the system printer.]
 - (3) Transmission of a trouble signal to [the fire department][a remote supervising station].
 - (4) Recording of the event electronically in the history log of the FMCU.
- [o. Activation of a carbon monoxide alarm initiating device must automatically initiate the following functions:
- (1) Visual indication of the device operated on the FMCU, [LCD, LED Display unit (VDU),][and on the [graphic][remote

]annunciator].[Indication on the graphic annunciator must be by floor and room number, device address, and device type.]

- (2) Transmission of a carbon monoxide alarm signal to [the fire department][a remote supervising station].
 - (3) Activation of all strobes and the audible carbon monoxide message throughout the building.
 - (4) Recording of the event electronically in the history log of the FMCU.]
- p. System control equipment must be programmed to provide a 60-minute to 180-minute delay in transmission of trouble signals resulting from primary power failure.
- [q. Activation of a LOC pushbutton must activate the audible and visual alarms in the facility. The audible message must be the one associated with the pushbutton activated.]

[1.6.3 Elevator Recall

Provide elevator recall in accordance with ASME A17.1/CSA B44, Section [14 21 13 ELECTRIC TRACTION FREIGHT ELEVATORS][14 21 23 ELECTRIC TRACTION PASSENGER ELEVATORS][14 24 13 HYDRAULIC FREIGHT ELEVATORS][14 24 23 HYDRAULIC PASSENGER ELEVATORS], and as specified herein. Activation of any smoke detector in an elevator shaft, machine room, or lobby (except at designated recall level) must cause all elevators associated with that shaft, machine room, or lobby to return nonstop to the designated level. Activation of a smoke detector in the lobby or machine room at the designated level must cause all elevators associated with that lobby to return nonstop to the assigned alternate level. Activation of a detector in an elevator shaft, machine room, or lobby must also cause illumination of elevator cab warning signal (fire hat) and complete operation of fire alarm system as specified in paragraph titled "Functions and Operating Features".

]1.7 TECHNICAL DATA AND SITE-SPECIFIC SOFTWARE

Technical data and site-specific software (meaning technical data that relates to computer software) that are specifically identified in this project, and may be required in other specifications, must be delivered, strictly in accordance with the CONTRACT CLAUSES. The fire alarm system manufacturer must submit written confirmation of this contract provision as "[Fire Alarm System Site-Specific Software Acknowledgement](#)". Identify data delivered by reference to the specification paragraph against which it is furnished. Data to be submitted must include complete system, equipment, and software descriptions. Descriptions must show how the equipment will operate as a system to meet the performance requirements of this contract. The site-specific software data package must also include the following:

- a. Items identified in NFPA 72, titled "Site-Specific Software".
- b. Identification of programmable portions of the system equipment and capabilities.
- c. Description of system revision and expansion capabilities and methods of implementation detailing both equipment and software requirements.

- d. Provision of operational software data on all modes of programmable portions for fire alarm and mass notification.
- e. Description of Fire Alarm and Mass Notification Control Unit equipment operation.
- f. Description of auxiliary and remote equipment operations.
- g. Library of application software.
- h. Operation and maintenance manuals.

[1.8 EXISTING EQUIPMENT

- a. Equipment and devices must be compatible and operable with the existing fire alarm/mass notification system and must not impair reliability or operational functions of existing supervising station fire alarm system. [The proprietary type supervising station (PSS) is located [in Building [____].][____].][The supervising equipment is existing and consists of the following brands and models: [supervising station control unit [____].][____][signal reporting components [____]], [annunciator [____]][____]].
- [b. Equipment and devices must be compatible and operable with the existing building fire alarm/mass notification system. Equipment must not impair reliability or operational functions of the existing system. The existing building system control unit is [____].]
- c. Equipment and devices must be compatible and operable with the existing installation-wide mass notification system and must not impair reliability or operational functions of the existing system. The installation-wide mass notification system utilizes [____] transceivers.

]1.9 QUALITY ASSURANCE

1.9.1 Submittal Documents

1.9.1.1 Preconstruction Submittals

Within 36 days of contract award but not less than [14 days][____] prior to commencing any work on site, the Contractor must submit the following for review and approval. SD-02, SD-03 and SD-05 submittals received prior to the review and approval of the qualifications of the fire alarm subcontractor and QFPE must be returned disapproved without review. All resultant delays must be the sole responsibility of the Contractor.

1.9.1.2 Shop Drawings

Shop drawings must not be smaller than [ISO A1][ANSI D][the Contract Drawings]. Drawings must comply with the requirements of NFPA 72 and **NFPA 170**. Minimum scale for floor plans must be 1/8"=1'.

1.9.1.3 Nameplates

Nameplate illustrations and data to obtain approval by the Contracting Officer before installation.

1.9.1.4 Wiring Diagrams

[_____] copies of point-to-point wiring diagrams showing the points of connection and terminals used for electrical field connections in the system, including interconnections between the equipment or systems that are supervised or controlled by the system. Diagrams must show connections from field devices to the FMCU and remote FMCU, initiating circuits, switches, relays and terminals, including pathway diagrams between the control unit and shared communications equipment within the protected premises. Point-to-point wiring diagrams must be job specific and must not indicate connections or circuits not being utilized. Provide complete riser diagrams indicating the wiring sequence of all devices and their connections to the control equipment. Include a color-code schedule for the wiring.

1.9.1.5 System Layout

[_____] copies of plan view drawing showing device locations, terminal cabinet locations, junction boxes, other related equipment, conduit routing, conduit sizes, wire counts, conduit fill calculations, wire color-coding, circuit identification in each conduit, and circuit layouts for all floors. Indicate candela rating of each visual notification appliance. Indicate the wattage of each speaker. Clearly identify the locations of isolation modules. Indicate the addresses of all devices, modules, relays, and similar. Show/identify all acoustically similar spaces. Indicate if the environment for the FMCU is within its environmental listing (e.g. temperature/humidity).

Provide a complete description of the system operation in matrix format similar to the "Typical Input/Output Matrix" included in the Annex of [NFPA 72](#).

[For air sampling smoke detection systems, provide floor plan layouts indicating location of fire alarm control unit, air sampling piping (lengths of pipe) and sampling ports (sizes and locations). Floor plan must also indicate geographic monitor zone boundaries, location of display control unit, bar level annunciation panels if separate, and all other associated equipment that is required to provide a complete operational system.]

1.9.1.6 Notification Appliances

Calculations and supporting data on each circuit to indicate that there is at least 25 percent spare capacity for notification appliances. Annotate data for each circuit on the drawings.

1.9.1.7 Initiating Devices

Calculations and supporting data on each circuit to indicate that there is at least [25][_____] percent spare capacity for initiating devices. Annotate data for each circuit on the drawings.

1.9.1.8 Amplifiers

Calculations and supporting data to indicate that amplifiers have sufficient capacity to simultaneously drive all notification speakers at tapped settings plus [25][_____] percent spare capacity. Annotate data for each circuit on the drawings.

1.9.1.9 Battery Power

Calculations and supporting data as required in paragraph Battery Power Calculations for alarm, alert, and supervisory power requirements. Calculations including ampere-hour requirements for each system component and each control unit component, and the battery recharging period, must be included on the drawings.

1.9.1.10 Voltage Drop Calculations

Voltage drop calculations for each notification circuit indicating that sufficient voltage is available for proper operation of the system and all components, at a minimum rated voltage of the system operating on batteries. Include the calculations on the system layout drawings.

1.9.1.11 Product Data

[_____] copies of annotated descriptive data to show the specific model, type, and size of each item. Catalog cuts must also indicate the NRTL listing. The data must be highlighted to show model, size, and options that are intended for consideration. Data must be adequate to demonstrate compliance with all contract requirements. Product data for all equipment must be combined into a single submittal.

Provide an equipment list identifying the type, quantity, make, and model number of each piece of equipment to be provided under this submittal. The equipment list must include the type, quantity, make and model of spare equipment. Types and quantities of equipment submitted must coincide with the types and quantities of equipment used in the battery calculations and those shown on the shop drawings.

[1.9.1.12 Air Sampling Smoke Detection System Calculations

Submit air sampling detection system design analysis calculations consisting of battery capacity, loading calculations, and fan speed and air flow/transport calculations. Include schematic diagrams showing pipe segments, pipe diameters, lengths of pipe, node numbers, and sample port diameters to verify the requirements are met.

]1.9.1.13 Operation and Maintenance (O&M) Instructions

[Six][_____] copies of the Operation and Maintenance Instructions. The O&M Instructions must be prepared in a single volume or in multiple volumes, with each volume indexed, and may be submitted as a Technical Data Package. Manuals must be approved prior to training. The Interior Fire Alarm And Mass Notification System Operation and Maintenance Instructions must include the following:

- a. "Manufacturer Data Package [five][_____] as specified in [Section 01 78 23 OPERATION AND MAINTENANCE DATA][_____].
- b. Operating manual outlining step-by-step procedures required for system startup, operation, and shutdown. The manual must include the manufacturer's name, model number, service manual, parts list, and preliminary equipment list complete with description of equipment and their basic operating features.
- c. Maintenance manual listing routine maintenance procedures, possible breakdowns and repairs, and troubleshooting guide. The manuals must

include conduit layout, equipment layout and simplified wiring, and control diagrams of the system as installed.

- d. Complete procedures for system revision and expansion, detailing both equipment and software requirements.
- e. Software submitted for this project on CD/DVD media utilized.
- f. Printouts of configuration settings for all devices.
- g. Routine maintenance checklist. The routine maintenance checklist must be arranged in a columnar format. The first column must list all installed devices, the second column must state the maintenance activity or state no maintenance required, the third column must state the frequency of the maintenance activity, and the fourth column provided for additional comments or reference. All data (devices, testing frequencies, and similar) must comply with **UFC 3-601-02**.
- h. A final Equipment List must be submitted with the Operating and Maintenance (O&M) manual.

1.9.1.14 As-Built Drawings

The drawings must show the system as installed, including deviations from both the project drawings and the approved shop drawings. These drawings must be submitted within two weeks after the final Government test of the system. At least one set of the as-built (marked-up) drawings must be provided at the time of, or prior to the final Government test.

1.9.2 Qualifications

1.9.2.1 Fire Alarm System Designer

The fire alarm system designer must be certified as a Level [III][IV] (minimum) Technician by National Institute for Certification in Engineering Technologies (NICET) in the Fire Alarm Systems subfield of Fire Protection Engineering Technology or meet the qualifications for a QFPE.

1.9.2.2 Supervisor

[A NICET Level [III][or][IV] fire alarm technician must supervise the installation of the fire alarm/mass notification system[, including the air sampling smoke detection system].][A fire alarm technician with a minimum of eight years of experience must supervise the installation of the fire alarm/mass notification system.] The fire alarm technicians supervising the installation of equipment must be factory trained in the installation, adjustment, testing, and operation of the equipment specified herein and on the drawings.

1.9.2.3 Technician

Fire alarm technicians with a minimum of four years of experience must be utilized to install and terminate fire alarm/mass notification devices, cabinets and control units. The fire alarm technicians installing the equipment must be factory trained in the installation, adjustment, testing, and operation of the equipment specified herein and on the drawings[, and must be thoroughly experienced in the installation of air sampling detection systems].

1.9.2.4 Installer

[Fire alarm installer with a minimum of two years of experience utilized to assist in the installation of fire alarm/mass notification devices, cabinets and control units] [NICET Level II technician to assist in the installation of fire alarm/mass notification devices, cabinets and control units]. A licensed electrician must be allowed to install wire, cable, conduit and backboxes for the fire alarm system/mass notification system. The fire alarm installer must be factory trained in the installation, adjustment, testing, and operation of the equipment specified herein and on the drawings.

1.9.2.5 Test Technician

Fire alarm technicians with a minimum of eight years of experience and NICET Level [III][or][IV]utilized in testing and certification of the installation of the fire alarm/mass notification devices, cabinets and control units. The fire alarm technicians testing the equipment must be factory trained in the installation, adjustment, testing, and operation of the equipment installed as part of this project.

1.9.2.6 Manufacturer

Components must be of current design and must be in regular and recurrent production at the time of installation. Provide design, materials, and devices for a protected premises fire alarm system, complete, conforming to NFPA 72, except as specified herein.

1.9.3 Regulatory Requirements

Equipment and material must be listed or approved. Listed or approved, as used in this Section, means listed, labeled or approved by a Nationally Recognized Testing Laboratory (NRTL) such as UL Fire Prot Dir or FM APP GUIDE. The omission of these terms under the description of any item of equipment described must not be construed as waiving this requirement. All listings or approvals by testing laboratories must be from an existing ANSI or UL published standard. The recommended practices stated in the manufacturer's literature or documentation must be considered as mandatory requirements.

1.10 DELIVERY, STORAGE, AND HANDLING

Protect equipment delivered and placed in storage from the weather, humidity, and temperature variation, dirt and dust, and other contaminants.

1.11 MAINTENANCE

1.11.1 Spare Parts

Furnish the following spare parts in the manufacturers original unopened containers:

- a. [Five][_____] complete sets of system keys.
- b. [Two][_____] of each type of fuse required by the system.
- c. [One][_____] manual stations.

- [d. [Two][_____] of each type of detector installed.]
- e. [Two][_____] of each type of detector base and head installed.
- [f. [One][_____] electromagnetic door holders.]
- [g. One smoke detector manufacturer's test screen, card or magnet for each ten beam smoke detectors, or fraction thereof, installed in the system.]
- [h. Two air sampling smoke detection system filter assemblies.]
- i. [Two][_____] of each type of audible and visual alarm device installed.
- j. [One][_____] textual visual notification appliance.
- k. [Two][_____] of each type of addressable monitor module installed.
- l. [Two][_____] of each type of addressable control module installed.
- m. [Two][_____] low voltage, [one][_____] [telephone][internet][ethernet], and [one][_____] 120 VAC surge protective device.
- [n. [Two][_____] spare reams of paper for the system printer, plus sufficient paper for testing.]
- [o. [Two][_____] spare printer ribbons.]

1.11.2 Special Tools

Software, connecting cables and proprietary equipment, necessary for the maintenance, testing, and reprogramming of the equipment must be furnished to the Contracting Officer, prior to the instruction of Government employees.

PART 2 PRODUCTS

2.1 GENERAL PRODUCT REQUIREMENT

All fire alarm and mass notification equipment must be listed for use under the applicable reference standards. Interfacing of [UL 864](#) or similar approved industry listing with Mass Notification equipment listed to [UL 2572](#) must be done in a laboratory listed configuration, if the software programming features cannot provide a listed interface control.

2.2 MATERIALS AND EQUIPMENT

2.2.1 Standard Products

Provide materials, equipment, and devices that have been tested by a nationally recognized testing laboratory and listed for fire protection service when so required by [NFPA 72](#) or this specification. Select material from one manufacturer, where possible, and not a combination of manufacturers, for any particular classification of materials. Material and equipment must be the standard products of a manufacturer regularly engaged in the manufacture of the products for at least [2][_____] years prior to bid opening.

2.2.2 Nameplates

Major components of equipment must have the manufacturer's name, address, type or style, model or serial number, catalog number, date of installation, installing Contractor's name and address, and the contract number provided on a new name plate permanently affixed to the item or equipment. Major components include, but are not limited to, the following:

a. FMCU

Nameplates must be etched metal or plastic, permanently attached by screws to control units or adjacent walls.

2.2.3 Keys

Keys and locks for equipment, control units and devices must be identical. [Master all keys and locks to a single key as required by the [Installation Fire Department][_____]]. [Keys must be CAT [60][_____].]

2.2.4 Instructions

Provide a typeset printed or typewritten instruction card mounted behind a Lexan plastic or glass cover in a stainless steel or aluminum frame. [Install the instructions on the interior of the FMCU.][Install the frame in a conspicuous location observable from the FMCU.] The card must show those steps to be taken by an operator when a signal is received as well as the functional operation of the system under all conditions, normal, alarm, supervisory, and trouble. The instructions must also include procedures for operating live voice microphones. The instructions and their mounting location must be approved by the Contracting Officer before being posted.

2.3 FIRE ALARM AND MASS NOTIFICATION CONTROL UNIT

Provide a complete [fire alarm and mass notification control unit \(FMCU\)](#) fully enclosed in a lockable steel cabinet as specified herein. Operations required for testing or for normal care, maintenance, and use of the system must be performed from the front of the enclosure. If more than a single unit is required at a location to form a complete control unit, the unit cabinets must match exactly.[If more than a single unit is required, and is located in the lobby/entrance, notify the Contracting Officer's Designated Representative (COR), prior to installing the equipment.] The system must be capable of defining any module as an alarm module and report alarm trouble, loss of polling, or as a supervisory module, and reporting supervisory short, supervisory open or loss of polling such as waterflow switches, valve supervisory switches, fire pump monitoring, independent smoke detection systems, relays for output function actuation.

- a. Each control unit must provide power, supervision, control, and logic for the entire system, utilizing solid state, modular components, internally mounted and arranged for easy access. Each control unit must be suitable for operation on a 120 volt, 60 hertz, normal building power supply. Provide each control unit with supervisory functions for power failure, internal component placement, and operation.
- b. Visual indication of alarm, supervisory, or trouble initiation on the

FMCU must be by liquid crystal display or similar means with a minimum of 80 characters. The mass notification control unit must have the capability of temporarily deactivate the fire alarm audible notification appliances while delivering voice messages.

- c. Provide secure operator console for initiating recorded messages, strobes and displays; and for delivering live voice messages. Provide capacity for at least eight prerecorded messages. Provide the ability to automatically repeat prerecorded messages. Provide a secure microphone for delivering live messages. Provide adequate discrete outputs to temporarily deactivate fire alarm audible notification, initiate/synchronize strobes and initiate textual visual notification appliances. Provide a complete set of self-diagnostics for controller and appliance network. Provide local diagnostic information display and local diagnostic information and system event log file.

2.3.1 Cabinet

Install control unit components in cabinets large enough to accommodate all components and also to allow ample gutter space for interconnection of control units as well as field wiring. The cabinet must be a sturdy steel housing, complete with back box, hinged steel door with cylinder lock, and [surface][semi-recessed] mounting provisions. The enclosure must be identified by an engraved phenolic resin nameplate. Lettering on the nameplate must say "Fire Alarm and Mass Notification control unit" and must not be less than 1-inch high. Provide prominent rigid plastic or metal identification plates for lamps, circuits, meters, fuses, and switches.

2.3.2 Silencing Switches

2.3.2.1 Alarm Silencing Switch

Provide an alarm silencing switch at the FMCU that must silence the audible and visual notification appliances. Subsequent activation of initiating devices must cause the notification appliances to re-activate.

2.3.2.2 Supervisory/Trouble Silencing Switch

Provide supervisory and trouble silencing switch(es) that must silence the audible trouble and supervisory signal(s), but not extinguish the visual indicator. This switch must be overridden upon activation of a subsequent supervisory or trouble condition. Audible trouble indication must resound automatically every 24 hours after the silencing feature has been operated if the supervisory or trouble condition still exists.

2.3.3 Non-Interfering

Power and supervise each circuit such that a signal from one device does not prevent the receipt of signals from any other device. Initiating devices must be manually reset by switch from the FMCU after the initiating device or devices have been restored to normal.

2.3.4 Audible Notification System

The Audible Notification System must comply with the requirements of NFPA 72 for Emergency Voice/Alarm Communications System requirements, except as specified herein. The system must be a one-way, multi-channel voice notification system incorporating user selectability of a minimum

eight distinct sounds for tone signaling, and the incorporation of a voice module for delivery of recorded messages. Audible appliances must produce a three-pulse temporal pattern for three cycles followed by a voice message that is repeated until the control unit is reset or silenced. For carbon monoxide detector activation, audible appliances must produce a four-pulse temporal pattern for three cycles followed by a voice message that is repeated until the control unit is reset or silenced. Automatic messages must be broadcast through speakers throughout the building/facility but not in stairs or elevator cabs. A live voice message must override the automatic audible output through use of a microphone input at the control unit or the LOC.

- a. When using the microphone, live messages must be broadcast [throughout a selected floor or floors,][selectable by zone,] or all call. The system must be capable of operating all speakers at the same time. [The Audible Notification System must support Public Address (PA) paging for the facility.][This must be accomplished with the provision of a separate microphone with a head unit that interfaces with the FMCU. The public address paging function must not override any fire alarm or mass notification functions. The microphone must be [desktop][hand-held][_____] style. Hand-held microphones must be housed in a separate protective cabinet. The cabinet must be accessible without the use of a key. The location of the microphone(s) must be approved by the [_____] Designated Fire Protection Engineer (DFPE).] Activation of the public address microphone must not initiate activation of visual notification appliances or LED text displays.
- b. The microprocessor must actively interrogate circuitry, field wiring, and digital coding necessary for the immediate and accurate rebroadcasting of the stored voice data into the appropriate amplifier input. Loss of operating power, supervisory power, or any other malfunction that could render the digitalized voice module inoperative must automatically cause the three-pulse temporal pattern to take over all functions assigned to the failed unit in the event an alarm is activated.

2.3.4.1 Outputs and Operational Modules

All outputs and operational modules must be fully supervised with on-board diagnostics and trouble reporting circuits. Provide form "C" contacts for system alarm and trouble conditions. Provide circuits for operation of auxiliary appliance during trouble conditions. During a Mass Notification event, the control unit must not generate nor cause any trouble alarms to be generated with the Fire Alarm system.

2.3.4.2 Mass Notification

- a. The system must have the capability of utilizing an LOC with redundant controls of the FMCU. Notification Appliance Circuits (NAC) must be provided for the activation of strobe appliances. Audio output must be selectable for line level. A hand-held microphone must be provided and, upon activation, must take priority over any tone signal, recorded message or PA microphone operation in progress, while maintaining the strobe NAC circuit activation.
- b. The Mass Notification functions must override the manual or automatic fire alarm notification, [and public address (PA) functions]. Other fire alarm functions including transmission of a signal(s) to the fire

department must remain operational. When a mass notification announcement is disengaged and a fire alarm condition still exists, the audible and visual notification appliances must resume activation for alarm conditions. The fire alarm message must be of lower priority than all other messages (except any "test" messages) and must not override any other messages.

- [c. Messages must be recorded professionally utilizing standard industry methods, in a professional [male][female] voice. Message and tone volumes must both be at the same decibel level. Messages recorded from the system microphone must not be accepted. A 1000 Hz tone (as required by NFPA 72) must precede messages and be similar to the following unless Installation or Facility specific messages are required:
- (1) "May I have your attention please. May I have your attention please. [Insert installation specific message here.]" (Provide a [2][_____] second pause.) "May I have your attention please, (repeat the tones and message [on a continuous loop][[_____] times])."
 - (2) Carbon Monoxide: "May I have your attention please. May I have your attention please. Carbon monoxide has been detected in the building. Please walk to the nearest exit and leave the building." (Provide a [2][_____] second pause.) "May I have your attention please, (repeat the tones and message [on a continuous loop][[_____] times])."
 - (3) Fire: "May I have your attention please. May I have your attention please. A fire emergency has been reported in the building. Please leave the building by the nearest exit[or exit stairway].[Do not use the elevators.]" (Provide a [2][_____] second pause.) "May I have your attention please, (repeat the tones and message on a continuous loop)."
 - (4) Test: "May I have your attention please. May I have your attention please. This is a test of the building mass notification system. Please continue your normal duties. This is only a test." (Provide a [2][_____] second pause.)
 - (5) All Clear: "May I have your attention please. May I have your attention please. An all clear has been issued, resume normal activities." (Provide a [2][_____] second pause.)
- d. Auxiliary Input Module must be designed to be an outboard expansion module to either expand the number of optional LOC's, or allow a telephone interface.

[2.3.4.3 Installation-Wide Control

If an installation-wide control system for mass notification exists on the Base, the autonomous control unit must communicate with the central control unit of the Installation-wide system. The autonomous control unit must receive commands/messages from the central control unit and provide status information.

]2.3.5 Memory

Provide each control unit with non-volatile memory and logic for all

functions. The use of long life batteries, capacitors, or other age-dependent devices must not be considered as equal to non-volatile processors, PROMS, or EPROMS.

2.3.6 Field Programmability

Provide control units and control units that are fully field programmable for both input and output of control, initiation, notification, supervisory, and trouble functions. The system program configuration must be menu driven. System changes must be password protected. Any proprietary equipment and proprietary software needed by qualified technicians to implement future changes to the fire alarm system must be provided as part of this contract.

2.3.7 Input/Output Modifications

The FMCU must contain features that allow the bypassing of input devices from the system or the modification of system outputs. These control features must consist of a control unit mounted keypad[and a keyboard]. Any bypass or modification to the system must indicate a trouble condition on the FMCU.

2.3.8 Resetting

Provide the necessary controls to prevent the resetting of any alarm, supervisory, or trouble signal while the alarm, supervisory or trouble condition on the system still exists.

2.3.9 Walk Test

The FMCU must have a walk test feature. When using this feature, operation of initiating devices must result in limited system outputs, so that the notification appliances operate for only a few seconds and the event is indicated in the history log[and on the system printer], but no other outputs occur.

2.3.10 History Logging

The control unit must have the ability to store a minimum of 400 events in a log. These events must be stored in a battery-protected memory and must remain in the memory until the memory is downloaded or cleared manually. Resetting of the control unit must not clear the memory.

2.3.11 Manual Access

An operator at the control unit, having a proper access level, must have the capability to manually access the following information for each initiating device.

- a. Primary status.
- b. Device type.
- c. Present average value.
- d. Present sensitivity selected.
- e. Detector range (normal, dirty).

[2.3.12 Heat Detector Self-Test Routines

Automatic self-test routines must be performed on each detector that will functionally check detector sensitivity electronics and ensure the accuracy of the value being transmitted. Any detector that fails this test must indicate a trouble condition with the detector location at the control unit.

]2.4 LOCAL OPERATING CONSOLES (LOC)

2.4.1 General

The LOC must consist of a remote microphone station incorporating a push-to-talk (PTT) hand-held microphone and system status indicators. The LOC must have the capability of being utilized to activate prerecorded messages. The unit must incorporate microphone override of any tone generation or recorded messages. The unit must be fully supervised from the FMCU. The housing for the LOC must not be lockable.[The LOC must have public address capability with the provision of a separate microphone. The PA paging function must not override any alarm or notification functions. The PA microphone must be [desktop][hand-held][_____] style. Hand-held microphones must be housed in a separate protective cabinet. The cabinet must be accessible without the use of a key. The location of the microphone[s] must be approved by the [_____] Designated Fire Protection Engineer (DFPE). Activation of the PA microphone must not initiate activation of visual notification appliances or LED text displays. The PA paging function must not override any alarm or notification functions.]

2.4.2 Multiple LOCs

When an installation has more than one LOC, the LOCs must be programmed to allow only one LOC to be available for paging or messaging at a time. Once one LOC becomes active, all other LOC's will have an indication that the system is busy (Amber Busy Light) and cannot be used at that time. This is to avoid two messages being given at the same time. It must be possible to override or lockout the LOC's from the FMCU.

2.5 AMPLIFIERS, PREAMPLIFIERS, TONE GENERATORS

Any amplifiers, preamplifiers, tone generators, [digitalized voice generators](#), and other hardware necessary for a complete, operational, textual audible circuit conforming to [NFPA 72](#) must be housed in a remote FMCU, terminal cabinet, or in the FMCU. Individual amplifiers must be 100 watts maximum.

2.5.1 Operation

The system must automatically operate and control all building speakers[except those installed in the stairs][and within elevator cabs]. [The speakers in the stairs[and elevator cabs] must operate only when the microphone is used to deliver live messages.]

2.5.2 Construction

Amplifiers must utilize computer grade solid state components and must be provided with output protection devices sufficient to protect the amplifier against any transient up to 10 times the highest rated voltage in the system.

2.5.3 Inputs

Equip each system with separate inputs for the tone generator, digitalized voice driver and control unit mounted microphone [Public Address Paging Function]. Microphone inputs must be of the low impedance, balanced line type. Both microphone and tone generator input must be operational on any amplifier.

2.5.4 Tone Generator

The tone generator must produce a three-pulse temporal pattern and must be constantly repeated until interrupted by either the digitalized voice message, the microphone input, or the alarm silence mode as specified. The tone generator must be single channel with an automatic backup generator per channel such that failure of the primary tone generator causes the backup generator to automatically take over the functions of the failed unit and also causes transfer of the common trouble relay. The tone generator must be provided with securely attached labels to identify the component as a tone generator and to identify the specific tone it produces.

2.5.5 Protection Circuits

Each amplifier must be constantly supervised for any condition that could render the amplifier inoperable at its maximum output. Failure of any component must cause illumination of a visual "amplifier trouble" indicator on the control unit, appropriate logging of the condition in the history log[and on the system printer], and other actions for trouble conditions as specified.

[2.6 VIDEO DISPLAY UNIT (VDU)

- a. The VDU must be the secondary operator-to-system interface for data retrieval, alarm annunciation, commands, and programming functions. The desk mounted VDU must consist of a LCD monitor and a keyboard. The VDU must have a [12][17][____]-inch minimum [touch]screen, capable of displaying 25 lines of 80 characters each. Communications with the FMCU must be supervised. Faults must be recorded in the history log[and on the printer]. Power required must be 120 VAC, 60 Hz from the same source as the FMCU.
- b. To eliminate confusion during an alarm situation, the screen must have dedicated areas for the following functions:
 - (1) Alarm and return to normal.
 - (2) Commands, reports, and programming.
 - (3) Time, day, and date.
- c. Use full English language throughout to describe system activity and instructions. Full English language descriptors defining system points must be 100 percent field programmable by factory trained personnel, alterable and user definable to accurately describe building areas.
- d. Alarms and other changes of status must be displayed in the screen area reserved for this information. Upon receipt of alarm, an audible

alarm must sound and the condition and point type must flash until acknowledged by the operator. Return to normal must also be annunciated and must require operator acknowledgment. The following information must be provided in full English:

- (1) Condition of device (alarm, trouble, or supervisory).
 - (2) Type of device (for example, manual pull, waterflow)
 - (3) Location of device plus numerical system address.
- e. The system must have multiple levels of priority for displaying alarms to conform with [UL 864](#). Priority levels must be as follows:
- (1) Level 1 - Mass Notification Signals
 - (2) Level 2 - Fire Alarm Signals
 - (3) Level 3 - Carbon Monoxide Alarm Signals
 - (4) Level 4 - Supervisory Signals
 - (5) Level 5 - Trouble Signals
- f. Provide the system with memory so that no alarm is lost. A highlighted message must advise the operator when unacknowledged alarms are in the system.
- g. Multiple levels of access must be provided for operators and supervisors via user-defined passwords. Provide the following functions for each level:
- (1) Operator level access functions:
 - (a) Display system directory, definable by device.
 - (b) Display status of an individual device.
 - (c) Manual command (alarm device with an associated command must use the same system address for both functions).
 - (d) Report generation, definable by device, output on the VDU[or printer], as desired by the operator.
 - (e) Activate building notification appliances.
 - (2) Supervisor level access functions:
 - (a) Reset time and date.
 - (b) Enable or disable event initiated programs[, printouts,] and initiators.
 - (c) Enable or disable individual devices and system components.
- h. The above supervisor level functions must not require computer programming skills. Changes to system programs must be [recorded on the printer and]maintained in the control unit as a trouble condition.

]2.7 REMOTE ANNUNCIATOR

[2.7.1 LCD Annunciator

Provide a [semi-recessed][flush] mounted annunciator that includes an LCD display. The display must indicate the device in trouble/alarm or any supervisory device. Display the device name, address[, and actual building location]. The remote annunciator must duplicate functions of the FMCU for message display, fire alarm, supervisory alarm, and trouble conditions, visual and audible notification, and system reset functions. Remote annunciator must require the use of a key for accessing the reset, control and other functions.

A building floor plan must be provided and mounted (behind Plexiglass or similar protective material) at the annunciator location. The floor plan must indicate all rooms by name and number including the locations of stairs and elevators. The floor plan must show all devices and their programmed address to facilitate identification of their physical location from the LCD display information.

][2.7.2 Graphic Annunciator

Graphic annunciator must be of the [interior][weatherproof] type, [flush][surface][pedestal]-mounted. Annunciator must be provided with the [building][room] floor plan, drawn to scale, with alarm lamps mounted to represent the location of [each concealed detector][each initiating device]. Annunciator graphic must also show the locations of the annunciator and control unit, and must have a "you are here" arrow showing its location. Orient building floor plan on graphic to location of person viewing the graphic(i.e., the direction the viewer is facing must be toward the top of the graphic display). Provide a North arrow.[Principal rooms and areas shown must be labeled with room numbers or titles.] Detectors mounted above ceilings, [on ceilings,]and beneath raised floors and different types of initiating devices must have different symbols or lamps of different colors for identification. Lamps must illuminate upon activation of corresponding device and must remain illuminated until the system is reset. Annunciator must have a lamp test switch.

2.7.2.1 Materials

Construct the graphic annunciator face plate of [smoked Plexiglas][non-glare matte finish][anodized bronze][anodized aluminum]. The face plate must be backlit with LEDs. Control equipment and wiring must be housed in a [recessed][semi-recessed][surface mounted] back box. The exposed portions of the back box must be [chrome plated][anodized bronze][anodized aluminum] without knockouts.

2.7.2.2 Programming

Where programming for the operation of the graphic annunciator is accomplished by a separate software program other than the software for the FMCU, the software program must not require reprogramming after loss of power. The software must be reprogrammable in the field.

][2.7.3 Printer

- a. Provide a system printer [with no stored memory] to record alarm, supervisory, and trouble conditions without loss of any signal or

signals. Printout must be by circuit, device, and function as provided in the FMCU. Printer must operate on a 120 VAC, 60 Hz power supply.

- b. The printer must have at least 80 characters per line and have a 96 ASCII character set. The printer must have a microprocessor-controlled, bi-directional, logic seeking head capable of printing 120 characters per second utilizing a 9 by 7 dot matrix print head. Printer must not contain internal software which is essential for proper operation.
- c. When the FMCU receives a signal, the alarm, supervisory, and trouble condition must be printed. The printout must include the type of signal, the circuit or device reporting, the date, and the time of the occurrence. The printer must differentiate alarm signals from other printed indications. When the system is reset, this condition must also be printed including the same information concerning device, location, date, and time. Provide a means to automatically print a list of existing alarm, supervisory, and trouble conditions in the system. If a printer is off-line when an alarm is received, the system must have a buffer to retain the data and it must be printed when the printer is restored to service. The printer must have an indicator to alert the operator that the paper has run out.

]2.8 MANUAL STATIONS

Provide metal or plastic, [semi-flush][flush][surface] mounted, [single][double]-action, addressable manual stations, that are not subject to operation by jarring or vibration. Stations must be equipped with screw terminals for each conductor. Stations that require the replacement of any portion of the device after activation are not permitted. Stations must be finished in red with molded raised lettering operating instructions of contrasting color. The use of a key must be required to reset the station.

2.9 SMOKE DETECTORS

2.9.1 Spot Type Detectors

Provide addressable [photoelectric][ionization][laser] smoke detectors as follows:

- a. Provide analog/addressable [photoelectric smoke detectors utilizing the photoelectric light scattering principle for operation in accordance with [UL 268](#)][smoke detectors that operate on the ionization principle and are actuated by the presence of visible or invisible products of combustion][laser smoke detectors utilizing laser diode and patented smoke sensing chamber, designed to amplify signals from smoke but diminish stray internal reflections and must, on command from the FMCU, send data to the control unit representing the analog level of smoke density]. Smoke detectors must be listed for use with the FMCU.
- b. Provide self-restoring type detectors that do not require any readjustment after actuation at the FMCU to restore them to normal operation. The detector must have a visual indicator to show actuation.
- c. Vibration must have no effect on the detector's operation. Protect

the detection chamber with a fine mesh metallic screen that prevents the entrance of insects or airborne materials. The screen must not inhibit the movement of smoke particles into the chamber.

- d. Provide twist lock bases [with sounder that produces a minimum of 90 dBA at 10 feet] with screw terminals for each conductor. The detectors must maintain contact with their bases without the use of springs.
- e. The detector address must identify the particular unit, its location within the system[, and its sensitivity setting]. Detectors must be of the low voltage type rated for use on a 24 VDC system.
- [f. Laser smoke detector must be listed for use with the FMCU. Detector must be able to achieve sensitivities from 0.02 percent-per-foot to 2 percent-per-foot obscuration.
- g. Laser smoke detector must provide point identification of the fire location through addressability, must experience no delay in response time due to smoke dilution or smoke transportation time, and must offer complete supervision of wiring and detector.]

[2.9.2 Projected Beam Smoke Detector

Detectors must consist of [combined transmitter and receiver unit] [separate transmitter and receiver units]. The transmitter unit must emit an infrared beam to the receiver unit [the use of a supplied reflector is required for the combined unit]. When the signal at the receiver falls below a preset threshold, the detector must initiate an alarm. The receiver must contain an LED status indicator that illuminates when an alarm condition exists. Long-term changes to the received signal caused by environmental variations must be automatically compensated. Detectors must incorporate features to assure that they are operational; a trouble signal must be initiated if the beam is obstructed for more than 3 seconds, the limits of the compensation circuit are reached, or the housing cover is removed. Detectors must have multiple sensitivity settings in order to meet UL listings for the different distances covered by the beam.

]2.9.3 Duct Smoke Detectors

Duct-mounted addressable photoelectric smoke detectors must consist of a smoke detector, as specified in paragraph Spot Type Detectors, mounted in a special housing fitted with duct sampling tubes. Detector circuitry must be mounted in a metallic or plastic enclosure exterior to the duct. [It is not permitted to cut the duct insulation to install the duct detector directly on the duct.] Detectors must be listed for operation over the complete range of air velocities, temperature and humidity expected at the detector when the air-handling system is operating. Detectors must be powered from the FMCU.

- a. Sampling tubes must run the full width of the duct. The duct detector package must conform to the requirements of NFPA 90A, UL 268A, and must be listed for use in air-handling systems. The control functions, operation, reset, and bypass must be controlled from the FMCU.
- b. Lights to indicate the operation and alarm condition must be visible and accessible with the unit installed and the cover in place. Remote

indicators must be provided where required by NFPA 72. Remote indicators as well as the affected fan units must be properly identified in etched plastic placards.

- c. Detectors must provide for control of auxiliary contacts that provide control, interlock, and shutdown functions specified in Section 23 09 00 to INSTRUMENTATION AND CONTROL FOR HVAC. Auxiliary contacts provide for this function must be located within 3 feet of the controlled circuit or appliance. The auxiliary contacts must be supplied by the fire alarm system manufacturer to ensure complete system compatibility.

[2.10 AIR SAMPLING SMOKE DETECTION SYSTEM

The [addressable] air sampling smoke system must consist of a detector assembly housing an integral aspiration fan, filter, laser-based detection chamber and control, output and supervision circuitry. [Each sampling point must be capable of being independently addressable.] The system must consist of a piping or tubing distribution network that runs from the detector assembly(s) to the protected area(s) and is supported by air sampling smoke detection system calculations from a computer-based design modeling tool. The system must include configurable alarm and trouble relay outputs for interface to other systems where required.

- a. System must be complete in all ways. It must include all engineering, and electrical installation, all detection and control equipment, auxiliary devices and controls, alarm interface, functional checkout and testing, training and all other operations necessary for a functional system.
- b. System base detectors and modules must each accommodate up to [40 addressable][_____] microbore sampling tubes where each tube has a sampling point at the end. Additional modules may be used to provide up to [20 addressable][_____] sampling holes per system.
- c. Program alarm thresholds to the following values unless the results of the pre-Government system tests indicate a clear need to change them. In the event that such a need is indicated, notify the Contracting Officer and provide complete documentation concerning the need to deviate from these values. Include within the deviation documentation request, information that complies with the paragraph entitled "Sensitivity Verification Test". Ensure initial threshold levels are approved prior to the Government test.
 - (1) Alarm Level 1: set ALERT at [_____] [0.0250] percent obscuration/foot
 - (2) Alarm Level 2: set PRE-ALARM at [_____] [0.0500] percent obscuration/foot
 - (3) Alarm Level 3: set FIRE 1 at [_____] [0.1000] percent obscuration/foot
 - (4) Alarm Level 4: set FIRE 2 at [_____] [0.2000] percent obscuration/foot
- d. All air sampling smoke detection devices and associated components must be new, standard products or the manufacturer's latest design and suitable to perform the functions intended.

- e. The laser detection chamber must be of the mass light scattering type and capable of detecting a wide range of smoke particle types of varying size. A particle counting method must be employed for the purposes of:
 - (1) Preventing large particles from affecting the true smoke reading.
 - (2) Monitoring contamination of the filter (for example, dust and dirt) to automatically notify when maintenance is required. The particle counting method must not be used for the purpose of smoke density measurement.
- f. Detector(s) must be self-monitoring for filter contamination and provide indication through system fault when replacement is necessary. Detectors which allow automatic reset of filter status upon removal and re-insertion are not permitted.
- g. Detector(s) must contain relays for alarm and fault conditions. The relays must be software programmable to the required functions.
- h. Detector(s) must permit configuration by programmers that are either integral to the system, portable or PC based.
- i. Detector(s) must allow programming of:
 - (1) Smoke threshold alarm levels; ALERT, PRE-ALARM, FIRE 1 and FIRE 2.
 - (2) Time delays. Ensure the display control unit contains individual adjustable alarm time delay features for each of the alarm threshold levels. Provide an adjustment range between 0 and 60 seconds. Program the alarm threshold time delays to 30 seconds for alarm levels 1 and 2, and 15 seconds for alarm levels 3 and 4.
 - (3) Faults, including airflow, detector, power, filter and network, as well as an indication of the urgency of the fault.
 - (4) Configuration of relay outputs for remote indication of alarm and fault conditions.
 - (5) General purpose input functionality.

]2.11 HEAT DETECTORS

2.11.1 Heat Detectors

Heat detectors must be analog/addressable and designed for detection of fire by [fixed temperature][combination fixed temperature and rate-of-rise principle][rate-compensating principle] in accordance with [UL 521](#). The alarm condition must be determined by comparing detector value with the stored values.. Detectors located in areas subject to moisture, exterior atmospheric conditions, or hazardous locations [as defined by [NFPA 70](#)][and][as indicated], must be types approved for such locations.

[2.11.1.1 Combination Fixed-Temperature and Rate-of-Rise Detectors

Detectors must be [surface][semi-flush] mounted in the [vertical][horizontal] orientation and supported independently of wiring connections. Detectors must be self-resetting. Detector must operate at

[135][194] degrees F. Detector must feature rate compensation. [Detectors rated to operate at 135 degrees F must not respond to momentary temperature fluctuations less than 30 degrees F per minute between 60 and 100 degrees F]. [Detectors rated to operate at 194 degrees F must not respond to momentary temperature fluctuations less than 50 degrees F per minute between 60 and 150 degrees F.] [The detector assembly must be [weatherproof][and][explosionproof].]

] [2.11.1.2 Rate Compensating Detectors

Detector backbox must be [surface][flush] mounted in the [vertical][horizontal] orientation and supported independently of wiring connections. Detectors must be self-restoring and hermetically sealed. [The detector assembly must be [weatherproof][and][explosionproof].]

] [2.11.1.3 Line-Type Fixed Temperature Detectors

Provide [thermostatic][or][thermistor] line-type heat detection cable [with weather-resistant outer covering] where indicated. Cable must be nominally rated for a temperature of [155][190][280] degrees F and must operate on fixed temperature principle only.

] [2.11.1.4 Fixed Temperature Detectors

Detectors must be [surface][semi-flush] mounted in the [vertical][horizontal] orientation and supported independently of wiring connections. Detectors must be self-restoring. The detectors must have a specific temperature setting [of [135][_____] degrees F][as shown]. [The detector assembly must be [weatherproof][and][explosionproof].]

] [2.12 FLAME DETECTORS

Detectors must be sensitive to the micron range best suited for their intended use. Detectors must operate over electrically supervised wiring circuits and the loss of power to the detector must result in a trouble signal. A self-test feature must be provided for each detector to be individually tested.

[2.12.1 Infrared (IR) Single Frequency Flame Detector

The detector must be sensitive in the range of [_____] to [_____] micrometers only.

] [2.12.2 Infrared (IR) Multi Frequency Flame Detector

The IR detector must consist of three or more IR sensors, each selected for a different IR frequency. The primary sensor must be sensitive in the range of [_____] to [_____] micrometers only. Secondary sensors are tuned to different IR wavelengths to null out the effect of black body radiation to the primary sensor.

] [2.12.3 Ultraviolet (UV) Flame Detectors

UV flame detector must be of the narrow band response type which operates on radiated ultraviolet energy and must be sensitive in the range of [_____] to [_____] micrometers only. The cone of vision must be 80 degrees or greater. Each detector must be completely insensitive to light sources in the visible frequency range.

][2.12.4 Combination UV/IR Flame Detector

The UV/IR detector must provide discrimination against false alarms by requiring both UV and IR flame detection before an alarm is sent. The UV sensor must be sensitive in the range of 0.185 to 0.265 micrometers only. The IR sensor must be sensitive in the range of [_____] to [_____] micrometers only. Detectors must be completely insensitive to light sources in the visible frequency range.

]]2.13 MULTI-CRITERIA DETECTORS

Multi-criteria detectors must contain [fixed temperature [_____] degrees F heat sensor], [rate-of-rise heat sensor], [photoelectric smoke detector], [_____] elements in a single housing.

]2.14 CARBON MONOXIDE DETECTOR

Analog/addressable carbon monoxide (CO) detectors must be listed to [UL 2075](#) and set to respond to the sensitivity limits of [UL 2034](#). Carbon monoxide detectors must be listed for use with fire alarm control units. Detectors must be [surface] [semi-flush] mounted in the [vertical][horizontal] orientation and supported independently of wiring connections. Detectors must be self-restoring. For FMCU with no listed compatible addressable CO detectors, provide listed 4-wire detectors. [Do not provide CO detectors with local alarms.] Detector must be provided with an LED status indicator.

- a. Where 4-wire CO detectors are necessary, each 4-wire CO detector must be individually monitored via addressable interface modules for alarm and off normal/trouble conditions (including loss of power to the individual detector). Power circuits for 4-wire CO detectors must be dedicated to powering the CO detectors only. Battery powered and 120 VAC powered detectors are prohibited.
- b. Wiring connections must be made by means of screw terminals and detectors must be equipped with trouble relays. Detectors must be able to mount a single-gang electrical box.
- c. A trouble condition at an individual CO detector must not affect any other CO detectors. CO detectors must be powered by the FMCU.
- d. Detectors must be provided with a means to test CO gas entry into the CO sensing cell.

2.15 ADDRESSABLE INTERFACE DEVICES

The initiating device being monitored must be configured as a [Class "A"][Class "B"] initiating device circuits. The module must be listed as compatible with the control unit. The module must provide address setting means compatible with the control unit's SLC supervision and store an internal identifying code. Monitor module must contain an integral LED that flashes each time the monitor module is polled and is visible through the device cover plate. Pull stations with a monitor module in a common backbox are not required to have an LED. [Existing fire alarm system initiating device circuits must be connected to a single module to supervise the circuit.] Modules must be listed for the environmental conditions in which they will be installed.

2.16 ADDRESSABLE CONTROL MODULES

The control module must be capable of operating as a relay (dry contact form C) for interfacing the control unit with other systems, and to control door holders or initiate elevator fire service. The module must be listed as compatible with the control unit. The indicating device or the external load being controlled must be configured as [Class B][Class A] notification appliance circuits. The system must be capable of supervising, audible, visual and dry contact circuits. The control module must have both an input and output address. The supervision must detect a short on the supervised circuit and must prevent power from being applied to the circuit. The control model must provide address setting means compatible with the control unit's SLC supervision and store an internal identifying code. The control module must contain an integral LED that flashes each time the control module is polled and is visible through the device cover plate. Control Modules must be listed for the environmental conditions in which they will be installed.

[2.17 ISOLATION MODULES

- a. Provide isolation modules to subdivide each signaling line circuit [into groups of not more than [20 addressable devices][_____]][each floor][in accordance with NFPA 72] between adjacent isolation modules.
- b. Isolation modules must provide short circuit isolation for signaling line circuit wiring.
- c. Power and communications must be supplied by the SLC and must report faults to the FMCU.
- d. After the wiring fault is repaired, the fault isolation modules must test the lines and automatically restore the connection.

]2.18 NOTIFICATION APPLIANCES

2.18.1 Audible Notification Appliances

Audible appliances must conform to the applicable requirements of UL 464. Appliances must be connected into notification appliance circuits. Surface mounted audible appliances must be painted [red][white][_____]. Recessed audible appliances must be installed with a grill that is painted [red][white][_____][with a factory finish to match the surface to which it is mounted].

2.18.1.1 Speakers

- a. Speakers must conform to the applicable requirements of UL 1480. Speakers must have six different sound output levels and operate with audio line input levels of 70.7 VRMs and 25 VRMs, by means of selectable tap settings. Interior speaker tap settings must include taps of 1/4, 1/2, 1, and 2 watt, at a minimum. Exterior speakers must also be multi-tapped with no more than 15 watt maximum setting. Speakers must incorporate a high efficiency speaker for maximum output at minimum power across a frequency range of 400 Hz to 4,000 Hz, and must have a sealed back construction. Speakers must be capable of installation on standard 4-inch square electrical boxes. Where speakers and strobes are provided in the same location, they may be combined into a single [wall mounted] unit. All inputs must be polarized for compatibility with standard reverse polarity supervision

of circuit wiring via the FMCU.

- b. Provide speaker mounting plates constructed of cold rolled steel having a minimum thickness of 16 gage or molded high impact plastic and equipped with mounting holes and other openings as needed for a complete installation. Fabrication marks and holes must be ground and finished to provide a smooth and neat appearance for each plate. Each plate must be primed and painted.
- c. Speakers must utilize screw terminals for termination of all field wiring.

2.18.2 Visual Notification Appliances

Visual notification appliances must conform to the applicable requirements of UL 1638, UL 1971 and conform to the Architectural Barriers Act (ABA). Visual Notification Appliances must have clear high intensity optic lens, xenon flash tubes, or light emitting diode (LED) and be marked "Alert" in letters of contrasting color. The light pattern must be disbursed so that it is visible above and below the strobe and from a 90 degree angle on both sides of the strobe. Strobe flash rate must be 1 flash per second and a minimum of [15][30][75][_____] candela based on the UL 1971 test. Strobe must be [surface][semi-flush] mounted.

2.18.3 Textual Display Signs

Textual display signs must be [LED][LCD flat panel][LED scrolling] and must not exceed 16 inches long by 6 inches high by 3 inches deep with a height necessary to meet the requirements of NFPA 72). The text display must spell out the word "EVACUATE" or "ANNOUNCEMENT" [and the remainder of the emergency instructions]as appropriate. The design of text display must be such that it cannot be read when not illuminated.

[LCD or LED scrolling text displays must meet the following requirements at a minimum:

- a. Two lines of information for high priority messaging.
- b. Minimum of 20 characters per line (40 total) displayed.
- c. Text must be no less than height requirements and color/contrast requirements of NFPA 72.
- d. 32K character memory.
- e. Display must be wall or ceiling mounted.
- f. Mounting brackets for a convenient wall/cubicle mount.
- [g. During non-emergency periods, display date and time.]
- h. The system must interface with the textual display sign control panel to activate the proper message.]

2.19 ELECTRIC POWER

2.19.1 Primary Power

Power must be [120][_____] VAC [50][60] Hz service for the FMCU from the

AC service to the building in accordance with NFPA 72.

2.20 SECONDARY POWER SUPPLY

Provide for system operation in the event of primary power source failure. Transfer from normal to auxiliary (secondary) power or restoration from auxiliary to normal power must be automatic and must not cause transmission of a false alarm.

2.20.1 Batteries

Provide sealed, maintenance-free, [sealed lead acid][lead-calcium][gel cell] batteries as the source for emergency power to the FMCU. Batteries must contain suspended electrolyte. The battery system must be maintained in a fully charged condition by means of a solid state battery charger. Provide an automatic transfer switch to transfer the load to the batteries in the event of the failure of primary power.

2.20.1.1 Capacity

Battery size must be the greater of the following two capacities. This capacity applies to every control unit associated with this system, including supplemental notification appliance circuit panels, auxiliary power supply panels, fire alarm transmitters, and Base-wide mass notification transceivers. When determining the required capacity under alarm condition, visual notification appliances must include both textual and non-textual type appliances.

- a. Sufficient capacity to operate the fire alarm system under supervisory and trouble conditions, including audible trouble signal devices for 48 hours and audible and visual signal devices under alarm conditions for an additional 15 minutes.
- b. Sufficient capacity to operate the mass notification for 60 minutes after loss of AC power.

2.20.1.2 Battery Power Calculations

- a. Verify that battery capacity exceeds supervisory and alarm power requirements for the criteria noted in the paragraph "Capacity" above.
 - (1) Substantiate the battery calculations for alarm and supervisory power requirements. Include ampere-hour requirements for each system component and each control unit component, and compliance with UL 864.
 - (2) Provide complete battery calculations for both the alarm and supervisory power requirements. Submit ampere-hour requirements for each system component with the calculations.
 - (3) Provide voltage drop calculations to indicate that sufficient voltage is available for proper operation of the system and all components. Calculations must be performed using the minimum rated voltage of each component.
- b. For battery calculations assume a starting voltage of 24 VDC for starting the calculations to size the batteries. Calculate the required Amp-Hours for the specified standby time, and then calculate the required Amp-Hours for the specified alarm time. Using 20.4 VDC

as starting voltage, perform a voltage drop calculation for circuits containing device and/or appliances remote from the power sources.

2.20.2 Battery Chargers

Provide a solid state, fully automatic, variable charging rate battery charger. The charger must be capable of providing 120 percent of the connected system load and must maintain the batteries at full charge. In the event the batteries are fully discharged (20.4 Volts dc), the charger must recharge the batteries back to 95 percent of full charge within 48 hours after a single discharge cycle as described in paragraph CAPACITY above. Provide pilot light to indicate when batteries are manually placed on a high rate of charge as part of the unit assembly if a high rate switch is provided.

2.21 SURGE PROTECTIVE DEVICES

Surge protective devices must be provided to suppress all voltage transients which might damage fire alarm control unit components. Systems having circuits located outdoors, communications equipment must be protected against surges induced on any signaling line circuit. Cables and conductors, that serve as communications links, must have surge protection circuits installed at each end. The surge protective device must wire in series to the power supply of the protected equipment with screw terminations. Line voltage surge arrester must be installed directly adjacent to the power panel where the FMCU breaker is located.

- a. Surge protective devices for nominal 120 VAC must be [UL 1449](#) listed with a maximum 500 volt suppression level and have a maximum response time of 5 nanoseconds. The surge protective device must also meet [IEEE C62.41.1](#) and [IEEE C62.41.2](#) category B tests for surge capacity. The surge protective device must feature multi-stage construction and be provided with a long-life indicator lamp (either light emitting diode or neon) which extinguishes upon failure of protected components. Any unit fusing must be externally accessible.
- b. Surge protective devices for nominal 24 VAC, fire alarm telephone dialer, or ethernet connection must be [UL 497B](#) listed, meet [IEEE C62.41.1](#) and have a maximum response time of 1-nanosecond. The surge protective device must feature multi-stage construction and be self-resetting. The surge protective device must be a base and plug style. The base assembly must have screw terminals for fire [alarm wiring](#). The base assembly must accept "plug-in" surge protective module.
- c. All surge protective devices (SPD) must be the standard product of a single manufacturer and be equal or better than the following:
 - (1) For 120 VAC nominal line voltage: [UL 1449](#) and [UL 1283](#) listed, series connected 120 VAC, 20A rated, surge protective device in a NEMA 4x enclosure. Minimum 50,000 amp surge current rating with EMI/RFI filtering and a dry contact circuit for remote monitoring of surge protection status.
 - (2) For 24-volt nominal line voltage: [UL 497B](#) listed, series connected low voltage, 24-volt, 5A rated, loop circuit protector, base and replaceable module.
 - (3) For alarm telephone dialers: [UL 497A](#) listed, series connected,

130-volt, 150 mA rated with self-resetting fuse, dialer circuit protector with modular plug and play.

- (4) For IP-DACTS: [UL 497B](#) listed, series connected, 6.4-volt, 1.5A rated with 20 kA/pair surge current, data network protector with modular plug and play.

2.22 WIRING

Provide wiring materials under this section as specified in Section [26 20 00 INTERIOR DISTRIBUTION SYSTEM](#) with the additions and modifications specified herein.

2.22.1 Alarm Wiring

IDC and SLC wiring must be [fiber optic][or][solid copper] cable in accordance with the manufacturers requirements. Copper signaling line circuits and initiating device circuit field wiring must be No. [14][16][18][_____] AWG size conductors at a minimum. Visual notification appliance circuit conductors, that contain audible alarm appliances, must be copper No. 14 AWG size conductors at a minimum. Speaker circuits must be copper No. [16][_____] AWG size twisted and shielded conductors at a minimum. [Wiring for textual notification appliance circuits must be in accordance with manufacturer's requirements but must be supervised by the FMCU.] Wire size must be sufficient to prevent voltage drop problems. Circuits operating at 24 VDC must not operate at less than the listed voltages for the detectors and/or appliances. Power wiring, operating at 120 VAC minimum, must be a minimum No. 12 AWG solid copper having similar insulation. Acceptable power-limited cables are FPL, FPLR or FPLP as appropriate with red colored covering. Nonpower-limited cables must comply with [NFPA 70](#).

2.23 INTERFACE TO THE BASE-WIDE MASS NOTIFICATION NETWORK

[2.23.1 Fiber Optic

The fiber optic transceiver must be fully compatible with EIA standards for RS-232, RS-422 and RS-485 at data rates from 0 (DC) to 2.1 mbps (200 kbps for RS-232) in the low speed mode or from 10 kbps to 10 mbps in the high-speed mode. The fiber optic transceiver must be capable of simplex or full duplex asynchronous transmissions in both point-to-point systems and drop-and-repeat data networks. The fiber optic transceiver must be user configurable for the protocol, speed and mode of operation required. The fiber optic transceiver must be installed as a [stand-alone][card-cage] unit. The fiber optic transceiver must operate on [Multi-mode][Single-mode] fiber optic cable. The fiber optic transceiver must be supplied with [ST][or][FCPC] type optical connectors. Cabling: as specified in Section [27 10 00 BUILDING TELECOMMUNICATIONS CABLING SYSTEM](#).

]2.23.2 Radio

The [mass notification transceiver](#) must be bi-direction and meet all the requirements of paragraph, RADIO TRANSMITTER AND INTERFACE PANELS as specified in this Specification Section. The transceiver utilized in the mass notification system must be capable of the following:

- a. Communication with the central control/monitoring system to provide supervision of communication link and status changes are reported by

automatic and manual poll/reply/acknowledge routines.

- b. All monitored points/status changes are transmitted immediately and at programmed intervals until acknowledged by the central control/monitoring system.
- c. Each transceiver must transmits a unique identity code as part of all messages; the code is set by the user at the transceiver.

] [2.23.3 Telephone

A modem must be provided for communication with the central control/monitoring system. The modem must be 56k, compatible with data mode V.90, utilizing Hayes compatible command codes. The modem must be capable of auto dialing a preset number based on preprogrammed events. The modem must auto answer and provide a secure password protection system. Cabling: as specified in Section 27 10 00 BUILDING TELECOMMUNICATIONS CABLING SYSTEM.

] [2.23.4 Secure Radio System

2.23.4.1 Communications Network

The communications network provides two-way signals between central control units and autonomous control units (in individual building systems), and should include redundant (primary and backup) communication links. The system must incorporate technology to prevent easy interruption of the radio traffic for MNS alerting.

2.23.4.2 Radio Frequency Communications

Use of radio frequency-type communications systems must comply with National Telecommunications and Information Administration (NTIA) requirements. The systems must be designed to minimize the potential for interference, jamming, eavesdropping, and spoofing.

2.23.4.3 Licensed Radio Frequency Systems

An approved DD Form 1494 for the system is required prior to operation.

] 2.24 AUTOMATIC FIRE ALARM TRANSMITTERS

[2.24.1 Radio Transmitter and Interface Panels

Transmitters must be compatible with proprietary supervising station receiving equipment. Each radio alarm transmitter must be the manufacturer's recognized commercial product, completely assembled, wired, factory tested, and delivered ready for installation and operation. Transmitters must be provided in accordance with applicable portions of NFPA 72, Federal Communications Commission (FCC) 47 CFR 90 and Federal Communications Commission (FCC) 47 CFR 15. Transmitter electronics module must be contained within the physical housing as an integral, removable assembly. The proprietary supervising station receiving equipment is [_____] and the transmitter must be fully compatible with this equipment. At the contractor's option, and if listed, the transmitter may be housed in the same control unit as the FMCU. The transmitter must be narrowband radio, with FCC certification for narrowband operation and meets the requirements of the NTIA (National Telecommunications and Information Administration) Manual of Regulations and Procedures for Federal Frequency

Management.

2.24.1.1 Operation

Operate each transmitter from 120-volt ac power. In the event of 120-volt ac power loss, the transmitter must automatically switch to battery operation. Switchover must be accomplished with no interruption of protective service, and must automatically transmit a trouble message. Upon restoration of ac power, transfer back to normal ac power supply must also be automatic.

2.24.1.2 Battery Power

Transmitter standby battery capacity must provide sufficient power to operate the transmitter in a normal standby status for a minimum of 72 hours and be capable of transmitting alarms during that period.

2.24.1.3 Transmitter Housing

Use NEMA Type 1 for housing. The housing must contain a lock that is keyed [identical to the fire alarm system for the building][identical to radio alarm transmitter housings on the Installation]. Radio alarm transmitter housing must be factory painted with a suitable priming coat and not less than two coats of a hard, durable weatherproof enamel.

2.24.1.4 Antenna

Antenna must be [omnidirectional, coaxial, halfwave dipole antennas][_____] for radio alarm transmitters with a driving point impedance to match transmitter output. The antenna and antenna mounts must be corrosion resistant and designed to withstand wind velocities of 100 mph. Do not mount antennas to any portion of the building roofing system. Protect the antenna from physical damage.

] [2.24.2 Digital Alarm Communicator Transmitter (DACT)

Provide DACT that is compatible with the existing supervising station fire alarm system. Transmitter must have a means to transmit alarm, supervisory, and trouble conditions via a single transmitter. Transmitter must have a source of power for operation that conforms to NFPA 72. Transmitter must be capable of initiating a test signal daily at any selected time. Transmitter must be arranged to seize telephone circuits in accordance with NFPA 72.

] 2.24.3 Signals to Be Transmitted to the Base Receiving Station

The following signals must be sent to the base receiving station:

- [a. Sprinkler waterflow]
- [b. Manual pull stations]
- [c. Smoke detectors]
- [d. Duct smoke detectors]
- [e. Sleeping room smoke detectors]
- [f. Carbon monoxide detectors]

- [g. Heat detectors]
- [h. Fire extinguishing system]
- [i. Sprinkler valve supervision]
- [j. Fire pump running]
- [k. Fire pump supervision]
- [l. Water supply level and temperature]
- [m. Combustion engine drive fire pump running
 - (1) Selector switch in position than automatic
 - (2) Engine over-speed
 - (3) Low fuel
 - (4) Low battery
 - (5) Engine trouble (for example, low oil, over temp)]

2.25 SYSTEM MONITORING

2.25.1 Valves

Each valve affecting the proper operation of a fire protection system, including automatic sprinkler control valves, [standpipe control valves,] sprinkler service entrance valve, [valves at fire pumps,] isolating valves for pressure type waterflow or supervision switches, and valves at backflow preventers, whether supplied under this contract or existing, must be electrically monitored to ensure its proper position. Provide each tamper switch with a separate address[, unless they are within the same room, then a maximum of five can use the same address].

[2.25.2 High/Low [Air][Nitrogen] Supervisory Switches

Provide monitoring of high and low supervisory [air][nitrogen] for [dry pipe][and][preaction] systems. Each air supervisory switch must have a separate address. Switches must be listed extinguishing system attachments. The device must contain double pole, double throw contacts. Operation of the switch must cause a supervisory signal to be transmitted to the FMCU when [air][nitrogen] pressure in the system monitored sprinkler system increases more than 5 psi above the normal system pressure or drops halfway from the normal pressure to the tripping point.

]2.25.3 Room Low Temperature Supervisory Switch

Provide [monitoring of the]listed supervisory air temperature switch for the [fire pump][sprinkler riser] room[s]. Switch must cause a supervisory signal to be transmitted to the FMCU whenever the temperature in the room drops to below 40 degrees F. Device must reset when temperature rises above 40 degrees F.

] [2.25.4 Electromagnetic Door Holders

Electromagnetic holding devices must operate on [120 VAC][24 VDC], and require not more than [3][_____] watts of power to develop 25 psi of holding force. Under normal conditions, the magnets must attract and hold the doors open. Operation must be fail safe with no moving parts. Electromagnetic door hold-open devices must not be required to be held open during building power failure. The device must be listed based on UL 228 tests.

] 2.26 ENVIRONMENTAL ENCLOSURES OR GUARDS

Environmental enclosures must be provided to permit fire alarm/mass notification components to be used in areas that exceed the environmental limits of the listing. The enclosure must be listed for the device or appliance as either a manufactured part number or as a listed compatible accessory for the component is currently listed. Guards required to deter mechanical damage must be either a listed manufactured part or a listed accessory for the category of the initiating device or notification appliance.

[2.27 FIREFIGHTER TELEPHONE COMMUNICATION SYSTEM

2.27.1 General

Provide a firefighter telephone communication system with complete, common talk, closed circuits. The system must include, but not be limited to, a master control station mounted in the fire alarm control unit, a power supply and standby battery system, and remote telephone stations.

2.27.2 Features

The system must include the following features:

- a. A master control station which must provide power, supervision, and control for wiring, components, and circuits. The act of lifting any remote telephone hand set from its cradle must cause both a visual and audible signal to annunciate at the master control station. Removing the hand set at the master control station and depressing a button at the remote telephone hand set must cause the automatic silencing of the audible signal.
- b. Communication between the master control station hand set and any/or all remote hand sets must require the depressing of a push-to-talk switch located on any/all remote hand sets. During the time that the master control hand set is removed from its cradle it must be possible to communicate between five remote hand sets and the master control station.
- c. Hand sets must be able to monitor any conversation in progress and join the conversation by pressing the push-to-talk button. It must not be possible to communicate between two or more remote hand sets with the master control station hand set in its cradle.
- d. The master control station hand set must be red in color and equipped with a 5-foot long strain-relieved coiled cord.
- e. The master control station must monitor wire and connections for any opens, shorts, or grounds which would render the system inoperable or

unintelligible.

- f. The master control station must be equipped with a silencing switch and ring-back feature such that any audible trouble signal can be silenced and must be so indicated by the lighting of an amber LED. Once any trouble condition has been corrected, the amber LED must be extinguished.
- g. The master control station must be equipped with a separate, LED annunciated switch for each telephone circuit. In addition, LEDs must provide for the annunciation of operating and supervisory power.
- h. The loss of operating or supervisory power must cause an audible and visual indication at the master control station and must also cause the fire alarm trouble signal to sound on the FMCU.
- i. Switches, LEDs, and controls must be fully labeled.

2.27.3 Handsets

Handsets must have the following features:

- a. Provide [surface][flush] mounted remote telephone stations.
- b. Each station must be equipped with a hinged door that is magnetically locked.
- c. Each hand set must be permanently wired in place with a coiled cord.
- d. Each hand set must be red high-impact cyclac and must be equipped with a push-to-talk switch which, when operated, must signal the master control station and a switch-equipped, storage cradle.
- e. Provide operating and supervising power from the same supply circuit(s) utilized for the FMCU.

]PART 3 EXECUTION

3.1 VERIFYING ACTUAL FIELD CONDITIONS

Before commencing work, examine all adjoining work on which the contractor's work is in any way dependent for perfect workmanship according to the intent of this specification section, and report to the Contracting Officer's Representative any condition which prevents performance of first class work. No "waiver of responsibility" for incomplete, inadequate or defective adjoining work will be considered unless notice has been filed before submittal of a proposal.

3.2 INSTALLATION

3.2.1 Fire Alarm and Mass Notification Control Unit (FMCU)

Locate the FMCU [where indicated on the drawings][_____]. [Recess][Semi-recess][Surface mount] the enclosure with the top of the cabinet 6 feet above the finished floor or center the cabinet at [5][_____] feet, whichever is lower. Conductor terminations must be labeled and a drawing containing conductors, their labels, their circuits, and their interconnection must be permanently mounted in the FMCU. Locate the document storage cabinet adjacent to the FMCU unless the Contracting

Officer directs otherwise.

3.2.2 Battery Cabinets

When batteries will not fit in the FMCU, locate battery cabinets below or adjacent to the FMCU. Battery cabinets must be installed at an accessible location when standing at floor level. Battery cabinets must not be installed lower than 12 inches above finished floor, measured to the bottom of the cabinet, nor higher than 36 inches above the floor, measured to the top of the cabinet. Installing batteries above drop ceilings or in inaccessible locations is prohibited. Battery cabinets must be large enough to accommodate batteries and also to allow ample gutter space for interconnection of control units as well as field wiring. The cabinet must be provided in a sturdy steel housing, complete with back box, hinged steel door with cylinder lock, and surface mounting provisions. The cabinet must be identified by an engraved phenolic resin nameplate. Lettering on the nameplate must indicate the control unit(s) the batteries power and must not be less than 1-inch high.

3.2.3 Manual Stations

Locate manual stations as required by NFPA 72 [and as indicated on the drawings]. Mount stations so they are located no farther than [5] [_____] feet from the exit door they serve, measured horizontally. Manual stations must be mounted at [42][44][_____] inches measured to the operating handle.

3.2.4 Notification Appliances

- a. Locate notification appliance devices [as required by NFPA 72][where indicated][and to meet the intelligibility requirements]. Where more than two visual notification appliances are located in the same room or corridor or field of view, provide synchronized operation. Devices must use screw terminals for all field wiring.[Audible and visual notification appliances mounted in acoustical ceiling tiles must be centered in the tiles plus or minus 2 inches.].
- b. Audible and visual notification appliances mounted on the exterior of the building, within unconditioned spaces, or in the vicinity of showers must be listed weatherproof appliances installed on weatherproof backboxes.
- c. Speakers must not be located in close proximity to the FMCU or LOC so as to cause feedback when the microphone is in use.

3.2.5 Smoke and Heat Detectors

Locate detectors [as required by NFPA 72 and their listing][as indicated on the drawings] on a 4-inch mounting box. Install heat detectors not less than 4 inches from a side wall to the near edge. Heat detectors located on the wall must have the top of the detector at least 4 inches below the ceiling, but not more than 12 inches below the ceiling. Smoke detectors are permitted to be on the wall no lower than 12 inches from the ceiling with no minimum distance from the ceiling.[In raised floor spaces, install the smoke detectors to protect [225 square feet per detector][____].] Install smoke detectors no closer than 3 feet from air handling supply diffusers. Detectors installed in acoustical ceiling tiles must be centered in the tiles plus or minus 2 inches.

3.2.6 Carbon Monoxide Detectors

Locate detectors [as required by NFPA 72 and their listings][as indicated on the drawings] on a 4-inch mounting box.[Carbon monoxide detectors must be installed separate from smoke and/or heat detectors.]

[3.2.7 Air Sampling Smoke Detector

Locate air sampling smoke detectors in accordance with the manufacturer's instructions. Air sampling smoke detectors must be installed as follows:

a. Air Sampling Smoke Detector Assembly:

- (1) Detector assembly must be mounted to a wall at a height between 48 to 60 inches to top of detector measured above the finished floor.
- (2) Mounting must be in a fully accessible and visible location.
- (3) Mounting or attachment to site equipment, cable trays, movable walls, other equipment or equipment supports is not permitted.
- (4) Piping network insertion into the detector inlet must not be glued.
- (5) Air sampling smoke detector assembly must be installed in accordance with this specification section and the manufacturer's installation and instruction manuals.
- (6) Flexible tubing for termination of the sampling pipe network into detector inlet is not permitted unless allowed by its listing.
- (7) Provide red background with white lettering labels that are plastic or phenolic type with a minimum of 0.25-inch block lettering to indicate detector and zone. For example: "AIR SAMPLING SOME DETECTOR No. 1-1 No. 5".
- (8) Provide a typeset printed or typewritten instruction card mounted behind a Lexan plastic or glass cover in a stainless steel or aluminum frame. Install the frame in a conspicuous location observable from the ASD panel. The card must show those steps to be taken by an operator when a signal is received as well as the functional operation of the system under all conditions, normal, alarm, supervisory, and trouble. The instructions must be approved by the Contracting Officer before being posted.

b. Pipe and Sampling Tube Mounting:

- (1) The pipe and sampling tubing detection network must be mounted as per the design and manufacturer's specification. The hardware used for mounting will depend upon the design and site requirements.
- (2) To minimize flexing, pipes must be secured every 5 feet.
- (3) Pipes must be suspended between 1 and 4 inches below the ceiling. In areas with a suspended ceiling, the pipe network must be installed above the ceiling utilizing the manufacturer's capillary sample port supported by the ceiling.
- (4) The sampling tubes must be of the same length or use the

manufacturer's guidelines to run tubes of the required lengths.

- (5) When installing a pipe network in areas subject to high temperature fluctuations allow for the contraction and expansion of pipes.
- (6) Where expansion or contraction of pipes is likely either after installation or on a continuous basis, do not place pipe clips adjacent to couplings and socket unions as these may interfere with the movement of the pipe.
- (7) No bends are permitted within the first 18 inches from the detector inlet.
- (8) The routing of the piping and sample tube network must be coordinated with potential obstructions, including cable trays, grounding bars, and HVAC ductwork.
- (9) All changes in direction must be made with standard elbows or tees.
- (10) All joints must be air-tight and made by using solvent cement, except at the entry to the detector assembly. Refer to ASTM F402.
- (11) All pipes must be supported by mechanical hangers attached to the structure of the building. Not more than 1-foot of pipe must extend beyond the last hanger of each sampling pipe. The final installation must result in no noticeable deflection in the piping network.
- (12) Attachment of air sampling pipes to cable trays, "gray iron", and telecommunications equipment is prohibited.
- (13) Clearly label pipe network to distinguish the pipe from other facility pipe work or protective cabling enclosures. For example: "SMOKE DETECTION SAMPLING TUBE - DO NOT DISTURB". In open rooms and exposed areas, provide labels at no greater than 20-foot intervals. Provide labels every 10 feet where piping is installed above suspended ceilings and every 2 feet, centered in the floor panels, where piping is installed within the raised floor cavity.
- (14) Placement of the sampling tube must take into consideration appropriate sampling point locations and spacing.

c. Air Sampling Points:

- (1) Open area ceiling sampling points must be oriented downward and must be within 1 to 4 inches below the underside of the ceiling above where the ceiling is smooth.
- (2) Label all air sampling points with a round red label, each with a center hole to match the diameter of the drilled sampling point. For example: "AIR SAMPLING POINT DIA 0.125 INCHES". Indicate fractional dimensions in decimal format with a minimum of three decimal places.

]3.2.8 Graphic Annunciator

Locate the graphic annunciator as shown on the drawings. Mount the annunciator, with the top 6 feet above the finished floor or center the

annunciator at [5][_____] feet, whichever is lower.

]3.2.9 LCD REMOTE Annunciator

Locate the LCD annunciator as shown on the drawings. Mount the annunciator, with the top 6 feet above the finished floor or center the annunciator at [5][_____] feet, whichever is lower.

[3.2.10 Electromagnetic Door Holder Release

Doors must be held open at a minimum of 90 degrees so as not to impede egress from the space. Mount the armature portion on the door and have an adjusting screw for seating the angle of the contact plate. Wall-mount the electromagnetic release, with a total horizontal projection not exceeding 4 inches. Ensure all doors release to close upon first stage (pre-discharge) alarm. Electrical supervision of wiring external of control unit for magnetic door holding circuits is not required.

]3.2.11 Firefighter Telephones

Mount telephone[hand sets][jacks] on the wall in each stair at each floor landing, in each emergency generator room, in each fire pump room, in each elevator machine room, in each elevator lobby, and in each elevator cab 4 feet above the finished floor.

]3.2.12 Local Operating Console (LOC)

Locate the LOC(s) as required by NFPA 72 and as indicated. Mount the console so that the top message button and microphone is no higher than 4 feet above the floor and the bottom (lowest) message button and microphone is at least 3 feet above the finished floor.

3.2.13 Ceiling Bridges

Provide ceiling bridges for ceiling-mounted appliances. Ceiling bridges must be as recommended/required by the manufacturer of the ceiling-mounted notification appliance.

3.3 SYSTEM FIELD WIRING

3.3.1 Wiring within Cabinets, Enclosures, and Boxes

Provide wiring installed in a neat and workmanlike manner and installed parallel with or at right angles to the sides and back of any box, enclosure, or cabinet. Conductors that are terminated, spliced, or otherwise interrupted in any enclosure, cabinet, mounting, or junction box must be connected to screw-type terminal blocks. Mark each terminal in accordance with the wiring diagrams of the system. The use of wire nuts or similar devices is prohibited. Wiring to conform with NFPA 70.

Indicate the following in the wiring diagrams:

- a. Point-to-point wiring diagrams showing the points of connection and terminals used for electrical field connections in the system, including interconnections between the equipment or systems that are supervised or controlled by the system. Diagrams must show connections from field devices to the FMCU and remote fire alarm/mass notification control units, initiating circuits, switches, relays and terminals.

- b. Complete riser diagrams indicating the wiring sequence of devices and their connections to the control equipment. Include a color code schedule for the wiring. Include floor plans showing the locations of devices and equipment.

3.3.2 Terminal Cabinets

Provide a terminal cabinet at the base of any circuit riser, on each floor at each riser, and where indicated on the drawings. Terminal size must be appropriate for the size of the wiring to be connected. Conductor terminations must be labeled and a drawing containing conductors, their labels, their circuits, and their interconnection must be permanently mounted in the terminal cabinet. Minimum size is 8 inches by 8 inches. Only screw-type terminals are permitted. Provide an identification label, that displays "FIRE ALARM TERMINAL CABINET" with 2-inch lettering, on the front of the terminal cabinet.

3.3.3 Alarm Wiring

- a. Voltages must not be mixed in any junction box, housing or device, except those containing power supplies and control relays.
- b. Utilize shielded wiring where recommended by the manufacturer. For shielded wiring, ground the shield at only one point, in or adjacent to the FMCU.
- c. [Pigtail or T-tap connections to signal line circuits, initiating device circuits, supervisory alarm circuits, and notification appliance circuits are prohibited.][T-tapping using screw terminal blocks is allowed for Class "B" signaling line circuits.]
- d. Color coding is required for circuits and must be maintained throughout the circuit. Conductors used for the same functions must be similarly color coded. Conform wiring to NFPA 70.
- e. Pull all conductors splice free. The use of wire nuts, crimped connectors, or twisting of conductors is prohibited. Where splices are unavoidable, the location of the junction box or pull box where they occur must be identified on the as-built drawings. The number and location of splices must be subject to approval by the [_____] Designated Fire Protection Engineer (DFPE).

3.3.4 Back Boxes and Conduit

In addition to the requirements of Section 26 20 00 INTERIOR DISTRIBUTION SYSTEM, provide all wiring in rigid metal conduit or intermediate metal conduit unless specifically indicated otherwise. Minimum conduit size must be 3/4-inch in diameter. Do not use electrical non-metallic tubing (ENT) or flexible non-metallic tubing and associated fittings.

- a. Galvanized rigid steel (GRS) conduit must be utilized where exposed to weather, where subject to physical damage, and where exposed on exterior of buildings. Intermediate metal conduit (IMC) may be used in lieu of GRS as allowed by NFPA 70.
- b. Electrical metallic tubing (EMT) is permitted above suspended ceilings or exposed where not subject to physical damage. Do not use EMT underground, encased in concrete, mortar, or grout, in hazardous

locations, where exposed to physical damage, outdoors or in fire pump rooms. Use die-cast compression connectors.

- c. For rigid metallic conduit (RMC), only threaded type fitting are permitted for wet or damp locations.
- d. Flexible metal conduit is permitted for initiating device circuits 6 feet in length or less. Flexible metal conduit is prohibited for notification appliance circuits and signaling line circuits. Use liquid tight flexible metal conduit in damp and wet locations.
- e. Schedule 40 (minimum) polyvinyl chloride (PVC) is permitted where conduit is routed underground or underground below floor slabs. Convert non-metallic conduit, other than PVC Schedule 40 or 80, to plastic-coated rigid, or IMC, steel conduit before turning up through floor slab.
- f. Exterior wall penetrations must be weathertight. Conduit must be sealed to prevent the infiltration of moisture.
- [g. For Class "A" or "X" circuits with conductor lengths of 10 feet or less, the conductors must be permitted to be installed in the same raceway in accordance with NFPA 72.]

3.3.5 Conductor Terminations

Labeling of conductors at terminal blocks in terminal cabinets, FMCU[, and remote FMCU] and the LOC must be provided at each conductor connection. Each conductor or cable must have a shrink-wrap label to provide a unique and specific designation. Each terminal cabinet, FMCU, and remote FMCU must contain a laminated drawing that indicates each conductor, its label, circuit, and terminal. The laminated drawing must be neat, using 12 point lettering minimum size, and mounted within each cabinet, control unit, or unit so that it does not interfere with the wiring or terminals. Maintain existing color code scheme where connecting to existing equipment.

[3.4 DISCONNECTION AND REMOVAL OF EXISTING SYSTEM

Maintain existing fire alarm/mass notification equipment fully operational until the new equipment has been tested and accepted by the Contracting Officer. As new equipment is installed, label it "NOT IN SERVICE" until the new equipment is accepted. Once the new system is completed, tested, and accepted by the Government, it must be placed in service and connected to the supervising station. Remove tags from new equipment and tag the existing equipment "NOT IN SERVICE" until removed from the building.

- a. After acceptance of the new system by the Contracting Officer, remove existing equipment not connected to the new system, remove unused exposed conduit, and restore damaged surfaces. Remove the material from the site and dispose.
- b. Disconnect and remove the existing fire alarm/mass notification and smoke detection systems where indicated and elsewhere in the specification.
- c. Control units and fire alarm devices and appliances disconnected and removed must be turned over to the Contracting Officer.
- d. Properly dispose of fire alarm outlet and junction boxes, wiring,

conduit, supports, and other such items.

3.5 CONNECTION OF NEW SYSTEM

The following new system connections must be made during the last phase of construction, at the beginning of the pre-Government tests. New system connections must include:

- a. Connection of new relays to existing magnetic door hold-open devices.
- b. Connection of new elevator recall relays to existing wiring and conduit.
- c. Connection of new system transmitter to existing installation fire reporting system.

Once these connections are made, system must be left energized. Report immediately to the Contracting Officer, coordination and field problems resulting from the connection of the above components.

]3.6 FIRESTOPPING

Provide firestopping for holes at conduit penetrations through floor slabs, fire-rated walls, partitions with fire-rated doors, corridor walls, and vertical service shafts in accordance with Section 07 84 00 FIRESTOPPING.

3.7 PAINTING

- a. In unfinished areas (including areas above drop ceilings), paint all exposed electrical conduit (serving fire alarm equipment), fire alarm conduit, surface metal raceway, junction boxes and covers red. In lieu of painting conduit, the contractor may utilize red conduit with a factory applied finish.
- b. In finished areas, paint exposed electrical conduit (serving fire alarm equipment), fire alarm conduit, surface metal raceways, junction boxes, and electrical boxes to match adjacent finishes. The inside cover of the junction box must be identified as "Fire Alarm" and the conduit must have painted red bands 3/4-inch wide at 10-foot centers and at each side of a floor, wall, or ceiling penetration.
- c. Painting must comply with Section 09 90 00 PAINTS AND COATINGS.

3.8 FIELD QUALITY CONTROL

3.8.1 Test Procedures

Submit detailed test procedures, prepared and signed by the NICET Level [III][or] [IV] Fire Alarm Technician, and the representative of the installing company, [and reviewed by the QFPE] [60][_____] days prior to performing system tests. Detailed test procedures must list all components of the installed system such as initiating devices and circuits, notification appliances and circuits, signaling line devices and circuits, control devices/equipment, batteries, transmitting and receiving equipment, power sources/supply, annunciators, special hazard equipment, emergency communication equipment, interface equipment, and surge protective devices. Test procedures must include sequence of testing, time estimate for each test, and sample test data forms. The test data

forms must be in a check-off format (pass/fail with space to add applicable test data; similar to the forma in [NFPA 72](#) and [NFPA 4](#).) The test procedures and accompanying test data forms must be used for the pre-Government testing and the Government testing. The test data forms must record the test results and must:

- a. Identify the NFPA Class of all Initiating Device Circuits (IDC), and Notification Appliance Circuits (NAC), Voice Notification System Circuits (NAC Audio), and Signaling Line Circuits (SLC).
- b. Identify each test required by [NFPA 72](#) Test Methods and required test herein to be performed on each component, and describe how these tests must be performed.
- c. Identify each component and circuit as to type, location within the facility, and unique identity within the installed system. Provide necessary floor plan sheets showing each component location, test location, and alphanumeric identity.
- d. Identify all test equipment and personnel required to perform each test (including equipment necessary for smoke detector testing. The use of magnets is not permitted.
- e. Provide space to identify the date and time of each test. Provide space to identify the names and signatures of the individuals conducting and witnessing each test.

3.8.2 Pre-Government Testing

3.8.2.1 Verification of Compliant Installation

Conduct inspections and tests to ensure that devices and circuits are functioning properly. Tests must meet the requirements of paragraph entitled "Minimum System Tests" as required by [NFPA 72](#). The contractor and an authorized representative from each supplier of equipment must be in attendance at the pre-Government testing to make necessary adjustments. After inspection and testing is complete, provide a signed [Verification of Compliant Installation](#) letter by the QFPE that the installation is complete, compliant with the specification and fully operable. The letter must include the names and titles of the witnesses to the pre-Government tests. Provide all completion documentation as required by [NFPA 72](#) including all referenced annex sections and the test reports noted below.

- a. [NFPA 72](#) Record of Completion.
- b. [NFPA 72](#) Record of Inspection and Testing.
- c. Fire Alarm and Emergency Communication System Inspection and Testing Form.
- d. Audibility test results with marked-up test floor plans.
- e. Intelligibility test results with marked-up floor plans.
- f. Documentation that all tests identified in the paragraph "Minimum System Tests" are complete.

3.8.2.2 Request for Government Final Test

When the verification of compliant installation has been completed, submit a formal request for Government final test to the [_____] [Designated Fire Protection Engineer (DFPE)] [Contracting Officer's Representative (COR)]. Government final testing will not be scheduled until the DFPE has received copies of the request for Government final testing and Verification of Compliant Installation letter with all required reports. Government final testing will not be performed until after the connections to the installation-wide fire reporting system [and the installation-wide mass notification system have] been completed and tested to confirm communications are fully functional. Submit request for test at least [15][_____] calendar days prior to the requested test date.

3.8.3 Correction of Deficiencies

If equipment was found to be defective or non-compliant with contract requirements, perform corrective actions and repeat the tests. Tests must be conducted and repeated if necessary until the system has been demonstrated to comply with all contract requirements.

3.8.4 Government Final Tests

The tests must be performed in accordance with the approved test procedures in the presence of the DFPE. Furnish instruments and personnel required for the tests. The following must be provided at the job site for Government Final Testing:

- a. The manufacturer's technical representative.
- [b. The contractor's Qualified Fire Protection Engineer (QFPE).]
- c. Marked-up red line drawings of the system as actually installed.
- d. Loop resistance test results.
- e. Complete program printout including input/output addresses.
- f. Copy of pre-Government Test Certificate, test procedures and completed test data forms.
- g. Audibility test results with marked-up floor plans.
- h. Intelligibility test results with marked-up floor plans.

Government Final Tests will be witnessed by the [_____] [Designated Fire Protection Engineer] [Contracting Officer's Representative (COR)] [, Qualified Fire Protection Engineer (QFPE)]. At this time, any and all required tests noted in the paragraph "Minimum System Tests" must be repeated at their discretion.

3.9 MINIMUM SYSTEM TESTS

3.9.1 System Tests

Test the system in accordance with the procedures outlined in NFPA 72. The required tests are as follows:

- a. Loop Resistance Tests: Measure and record the resistance of each

circuit with each pair of conductors in the circuit short-circuited at the farthest point from the circuit origin. The tests must be witnessed by the Contracting Officer and test results recorded for use at the final Government test.

- b. Verify the absence of unwanted voltages between circuit conductors and ground. The tests must be accomplished at the pre-Government test with results available at the final system test.
- c. Verify that the control unit is in the normal condition as detailed in the manufacturer's O&M manual.
- d. Test each initiating device and notification appliance and circuit for proper operation and response at the control unit. Smoke detectors must be tested in accordance with manufacturer's recommended calibrated test method. Use of magnets is prohibited. Testing of duct smoke detectors must comply with the requirements of NFPA 72 except disconnect at least 20 percent of devices. If there is a failure at these devices, then supervision must be tested at each device.
- e. Carbon Monoxide Detector Tests: Carbon monoxide detectors must be tested in accordance with NFPA 72 and the manufacturer's recommended calibrated test method.
- f. Test the system for specified functions in accordance with the contract drawings and specifications and the manufacturer's O&M manual.
- g. Test both primary power and secondary power. Verify, by test, the secondary power system is capable of operating the system for the time period and in the manner specified.
- h. Determine that the system is operable under trouble conditions as specified.
- i. Visually inspect wiring.
- j. Test the battery charger and batteries.
- k. Verify that software control and data files have been entered or programmed into the FMCU. Hard copy records of the software must be provided to the Contracting Officer.
- l. Verify that red-line drawings are accurate.
- m. Measure the current in circuits to ensure there is the calculated spare capacity for the circuits.
- n. Measure voltage readings for circuits to ensure that voltage drop is not excessive.
- o. Disconnect the verification feature for smoke detectors during tests to minimize the amount of smoke needed to activate the sensor. Testing of smoke detectors must be conducted using real smoke or the use of canned smoke which is permitted.
- p. Measure the voltage drop at the most remote appliance (based on wire length) on each notification appliance circuit.
- q. Verify the documentation cabinet is installed and contains all

as-built shop drawings, product data sheets, design calculations, site-specific software data package, and all documentation required by paragraph titled "Test Reports".

3.9.2 Audibility Tests

Sound pressure levels from audible notification appliances must be a minimum of 15 dBa over ambient with a maximum of 110 dBa in any occupiable area. The provisions for audible notification (audibility and intelligibility) must be met with doors, fire shutters, movable partitions, and similar devices closed.

3.9.3 Intelligibility Tests

Intelligibility testing of the System must be accomplished in accordance with NFPA 72 for Voice Evacuation Systems, and ASA S3.2. Following are the specific requirements for intelligibility tests:

- a. Intelligibility Requirements: Verify intelligibility by measurement after installation.
- b. Ensure that a CIS value greater than the required minimum value is provided in each area where building occupants typically could be found. The minimum required value for CIS is [.7][.8]. Rounding of values is permitted.
- c. Areas of the building provided with hard wall and ceiling surfaces (such as metal or concrete) that are found to cause excessive sound reflections may be permitted to have a CIS score less than the minimum required value if approved by the DFPE, and if building occupants in these areas can determine that a voice signal is being broadcast and they must walk no more than 33 feet to find a location with at least the minimum required CIS value within the same area.
- d. Areas of the building where occupants are not expected to be normally present are permitted to have a CIS score less than the minimum required value if personnel can determine that a voice signal is being broadcast and they must walk no more than 50 feet to a location with at least the minimum required CIS value within the same area.
- e. Take measurements near the head level applicable for most personnel in the space under normal conditions (e.g., standing, sitting, sleeping, as appropriate).
- f. The distance the occupant must walk to the location meeting the minimum required CIS value must be measured on the floor or other walking surface as follows:
 - (1) Along the centerline of the natural path of travel, starting from any point subject to occupancy with less than the minimum required CIS value.
 - (2) Curving around any corners or obstructions, with a 12 inches clearance there from.
 - (3) Terminating directly below the location where the minimum required CIS value has been obtained.

Use commercially available test instrumentation to measure intelligibility

as specified by [NFPA 72](#) as applicable. Use the mean value of at least three readings to compute the intelligibility score at each test location.

3.10 SYSTEM ACCEPTANCE

Following acceptance of the system, as-built drawings and O&M manuals must be delivered to the Contracting Officer for review and acceptance. The drawings must show the system as installed, including deviations from both the project drawings and the approved shop drawings. These drawings must be submitted within two weeks after the final Government test of the system. At least one set of as-built (marked-up) drawings must be provided at the time of, or prior to the Final Government Test.

- [a. The drawings must be prepared electronically and sized no less than the contract drawings.][Furnish one set of CDs or DVDs containing software back-up and CAD based drawings in latest version of [MicroStation] [AutoCAD,]DXF and portable document formats of as-built drawings and schematics.]
- b. Include complete wiring diagrams showing connections between devices and equipment, both factory and field wired.
- c. Include a riser diagram and drawings showing the as-built location of devices and equipment.
- d. Provide [Operation and Maintenance \(O&M\) Instructions](#).

[In existing buildings, the transfer of devices from the existing system to the new system and the permission to begin demolition of the old fire alarm system will not be permitted until the as-built drawings and O&M manuals are received.]

3.11 INSTRUCTION OF GOVERNMENT EMPLOYEES

3.11.1 Instructor

Provide the services of an instructor, who has received specific training from the manufacturer for the training of other persons regarding the operation, inspection, testing, and maintenance of the system provided. The instructor must train the Government employees designated by the Contracting Officer, in the care, adjustment, maintenance, and operation of the fire alarm system. The instructor must be thoroughly familiar with all parts of this installation. The instructor must be trained in operating theory as well as in practical O&M work. Submit the instructors information and qualifications including the training history.

3.11.2 Required Instruction Time

Provide [8][16][_____] hours of instruction after final acceptance of the system. The instruction must be given during regular working hours on such dates and times selected by the Contracting Officer. The instruction may be divided into two or more periods at the discretion of the Contracting Officer. The training must allow for rescheduling for unforeseen maintenance and/or fire department responses.

[3.11.2.1 Technical Training

Equipment manufacturer or a factory representative must provide [1][3][_____] days of on site[and 5 days of technical training to the

Government at the manufacturing facility]. Training must allow for classroom instruction as well as individual hands on programming, troubleshooting and diagnostics exercises.[Factory training must occur within [6][12][_____] months of system acceptance.]

]3.11.3 Technical Training Manual

Provide, in manual format, lesson plans, operating instructions, maintenance procedures, and training data for the training courses. The operations training must familiarize designated government personnel with proper operation of the installed system. The maintenance training course must provide the designated government personnel adequate knowledge required to diagnose, repair, maintain, and expand functions inherent to the system.

3.12 EXTRA MATERIALS

3.12.1 Repair Service/Replacement Parts

Repair services and replacement parts for the system must be available for a period of 10 years after the date of final acceptance of this work by the Contracting Officer. During the warranty period, the service technician must be on-site within 24 hours after notification. All repairs must be completed within 24 hours of arrival on-site.

During the warranty period, the installing fire alarm contractor is responsible for conducting all required testing and maintenance in accordance with the requirements and recommended practices of [NFPA 72](#) and the system manufacturer[s]. Installing fire alarm contractor is NOT responsible for any damage resulting from abuse, misuse, or neglect of equipment by the end user.

3.12.2 Spare Parts

Spare parts furnished must be directly interchangeable with the corresponding components of the installed system[s]. Spare parts must be suitably packaged and identified by nameplate, tagging, or stamping. Spare parts must be delivered to the Contracting Officer at the time of the Government testing and must be accompanied by an inventory list.

3.12.3 [Document Storage Cabinet](#)

Upon completion of the project, but prior to project close-out, place in the document storage cabinet copies of the following record documentation:

- a. As-built shop drawings
- b. Product data sheets
- c. Design calculations
- d. Site-specific software data package
- e. All documentation required by SD-06.

-- End of Section --

SECTION 31 05 19

GEOTEXTILE
08/08

PART 1 GENERAL

1.1 REFERENCES

The publications listed below form a part of this specification to the extent referenced. The publications are referred to within the text by the basic designation only.

AMERICAN ASSOCIATION OF STATE HIGHWAY AND TRANSPORTATION
OFFICIALS (AASHTO)

AASHTO M 288 Class 1 Woven Geotextile

ASTM INTERNATIONAL (ASTM)

- ASTM D4354 (2012) Sampling of Geosynthetics for Testing
- ASTM D4355/D4355M (2014) Deterioration of Geotextiles from Exposure to Light, Moisture and Heat in a Xenon-Arc Type Apparatus
- ASTM D4491/D4491M (2017) Standard Test Methods for Water Permeability of Geotextiles by Permittivity
- ASTM D4533/D4533M (2015) Standard Test Method for Trapezoid Tearing Strength of Geotextiles
- ASTM D4632/D4632M (2015a) Grab Breaking Load and Elongation of Geotextiles
- ASTM D4751 (2016) Standard Test Method for Determining Apparent Opening Size of a Geotextile
- ASTM D4759 (2011; R 2018) Standard Practice for Determining the Specification Conformance of Geosynthetics
- ASTM D4873/D4873M (2017) Standard Guide for Identification, Storage, and Handling of Geosynthetic Rolls and Samples
- ASTM D6241 (2014) Standard Test Method for the Static Puncture Strength of Geotextiles and Geotextile-Related Products Using a 50-mm Probe

1.2 SUBMITTALS

Government approval is required for submittals with a "G" designation; submittals not having a "G" designation are for Contractor Quality Control